

---

# **NI Modular Instruments Python API Documentation**

***Release 1.0.0***

**National Instruments**

**Jun 08, 2018**



<b>1</b>	<b>Intro</b>	<b>1</b>
<b>2</b>	<b>Installation</b>	<b>3</b>
<b>3</b>	<b>Contributing</b>	<b>5</b>
<b>4</b>	<b>Support / Feedback</b>	<b>7</b>
<b>5</b>	<b>Bugs / Feature Requests</b>	<b>9</b>
<b>6</b>	<b>Documentation</b>	<b>11</b>
6.1	Additional Documentation . . . . .	11
<b>7</b>	<b>License</b>	<b>13</b>
7.1	nidepower module . . . . .	13
7.1.1	Installation . . . . .	13
7.1.2	Usage . . . . .	13
7.1.3	API Reference . . . . .	14
7.1.3.1	nidepower.Session . . . . .	14
7.1.3.2	Enums . . . . .	114
7.1.3.3	Exceptions and Warnings . . . . .	119
7.1.3.4	Examples . . . . .	120
7.2	nidmm module . . . . .	123
7.2.1	Installation . . . . .	123
7.2.2	Usage . . . . .	123
7.2.3	API Reference . . . . .	123
7.2.3.1	nidmm.Session . . . . .	123
7.2.3.2	Enums . . . . .	179
7.2.3.3	Exceptions and Warnings . . . . .	186
7.2.3.4	Examples . . . . .	187
7.3	nifgen module . . . . .	190
7.3.1	Installation . . . . .	190
7.3.2	Usage . . . . .	191
7.3.3	API Reference . . . . .	191
7.3.3.1	nifgen.Session . . . . .	191
7.3.3.2	Enums . . . . .	280
7.3.3.3	Exceptions and Warnings . . . . .	286

	7.3.3.4	Examples	287
7.4		niscope module	290
	7.4.1	Installation	290
	7.4.2	Usage	290
	7.4.3	API Reference	293
	7.4.3.1	niscope.Session	293
	7.4.3.2	Enums	367
	7.4.3.3	Exceptions and Warnings	373
	7.4.3.4	Examples	374
7.5		niswitch module	378
	7.5.1	Installation	378
	7.5.2	Usage	378
	7.5.3	API Reference	379
	7.5.3.1	niswitch.Session	379
	7.5.3.2	Enums	417
	7.5.3.3	Exceptions and Warnings	423
	7.5.3.4	Examples	424
7.6		nimodinst module	428
	7.6.1	Installation	428
	7.6.2	Usage	428
	7.6.3	API Reference	428
	7.6.3.1	nimodinst.Session	428
	7.6.3.2	Exceptions and Warnings	433
	7.6.3.3	Examples	434
<b>8</b>		<b>Indices and tables</b>	<b>435</b>
		<b>Python Module Index</b>	<b>437</b>

# CHAPTER 1

---

## Intro

---

**nimi-python** is a collection of Python modules that provide an interface to the underlying NI driver. Currently, the following drivers are supported:

- NI-DCPower (Python module: nidcpower)
- NI-DMM (Python module: nidmm)
- NI-FGEN (Python module: nifgen)
- NI-SCOPE (Python module: niscscope)
- NI-SWITCH (Python module: niswitch)
- NI-ModInst (Python module: nimodinst)

**nimi-python** supports all the Operating Systems supported by the underlying driver.

**nimi-python** supports Python 2.7, 3.4 and later using CPython or PyPy.



## CHAPTER 2

---

### Installation

---

Driver specific installation instructions can be found on Read The Docs:

- [nidcpower](#)
- [nidmm](#)
- [nifgen](#)
- [niscopes](#)
- [niswitch](#)
- [nimodinst](#)





## CHAPTER 3

---

### Contributing

---

We welcome contributions! You can clone the project repository, build it, and install it by [following these instructions](#).



## CHAPTER 4

---

Support / Feedback

---

The packages included in **nimi-python** package are supported by NI. For support, open a request through the NI support portal at [ni.com](https://ni.com).



## CHAPTER 5

---

### Bugs / Feature Requests

---

To report a bug or submit a feature request specific to NI Modular Instruments Python bindings (nimi-python), please use the [GitHub issues page](#).

Fill in the issue template as completely as possible and we will respond as soon as we can.

For hardware support or any other questions not specific to this GitHub project, please visit [NI Community Forums](<https://forums.ni.com/>).



## CHAPTER 6

---

### Documentation

---

Documentation is available [here](#).

### 6.1 Additional Documentation

Refer to your driver documentation for device-specific information and detailed API documentation.





**nimi-python** is licensed under an MIT-style license (see [LICENSE](#)). Other incorporated projects may be licensed under different licenses. All licenses allow for non-commercial and commercial use.

## 7.1 nidcpower module

### 7.1.1 Installation

As a prerequisite to using the **nidcpower** module, you must install the NI-DCPower runtime on your system. Visit [ni.com/downloads](http://ni.com/downloads) to download the driver runtime for your devices.

The **nimi-python** modules (i.e. for **NI-DCPower**) can be installed with **pip**:

```
$ python -m pip install nidcpower~=1.0.0
```

Or **easy\_install** from **setuptools**:

```
$ python -m easy_install nidcpower
```

### 7.1.2 Usage

The following is a basic example of using the **nidcpower** module to open a session to a Source Meter Unit and measure voltage and current.

```
import nidcpower
# Configure the session.

with nidcpower.Session('dev1') as session:
    session.measure_record_length = 20
    session.measure_record_length_is_finite = True
    session.measure_when = nidcpower.MeasureWhen.AUTOMATICALLY_AFTER_SOURCE_COMPLETE
```

(continues on next page)

(continued from previous page)

```

session.voltage_level = 5.0

session.commit()
print('Effective measurement rate: {0} S/s'.format(session.measure_record_delta_
→time / 1))

samples_acquired = 0
print(' #      Voltage      Current      In Compliance')
row_format = '{0:3d}:   {1:8.6f}   {2:8.6f}   {3}'
with session.initiate():
    while samples_acquired < 20:
        measurements = session.fetch_multiple(count=session.fetch_backlog)
        samples_acquired += len(measurements)
        for i in range(len(measurements)):
            print(row_format.format(i, measurements[i].voltage, measurements[i].
→current, measurements[i].in_compliance))

```

Additional examples for NI-DCPower are located in `src/nidcpower/examples/` directory.

## 7.1.3 API Reference

### 7.1.3.1 nidcpower.Session

**class** `nidcpower.Session` (*self, resource\_name, channels=None, reset=False, options={}*)

Creates and returns a new NI-DCPower session to the power supply or SMU specified in **resource name** to be used in all subsequent NI-DCPower method calls. With this method, you can optionally set the initial state of the following session properties:

- `nidcpower.Session.simulate`
- `nidcpower.Session.driver_setup`

After calling this method, the session will be in the Uncommitted state. Refer to the [Programming States](#) topic for details about specific software states.

To place the device in a known start-up state when creating a new session, set **reset** to True. This action is equivalent to using the `nidcpower.Session.reset()` method immediately after initializing the session.

To open a session and leave the device in its existing configuration without passing through a transitional output state, set **reset** to False. Then configure the device as in the previous session, changing only the desired settings, and then call the `nidcpower.Session.initiate()` method.

#### Related Topics:

#### [Programming States](#)

#### Parameters

- **resource\_name** (*str*) – Specifies the **resourceName** assigned by Measurement & Automation Explorer (MAX), for example “PXI1Slot3” where “PXI1Slot3” is an instrument’s **resourceName**. **resourceName** can also be a logical IVI name.
- **channels** (*str*) – Specifies which output channel(s) to include in a new session. Specify multiple channels by using a channel list or a channel range. A channel list is a comma (,) separated sequence of channel names (for example, 0,2 specifies channels 0 and 2). A channel range is a lower bound channel followed by a hyphen (-) or colon (:) followed by an upper bound channel (for example, 0-2 specifies channels 0, 1, and 2). In the Running state, multiple output channel configurations are performed sequentially based on the order

specified in this parameter. If you do not specify any channels, by default all channels on the device are included in the session.

- **reset** (*bool*) – Specifies whether to reset the device during the initialization procedure.
- **options** (*str*) – Specifies the initial value of certain properties for the session. The syntax for **options** is a dictionary of properties with an assigned value. For example:

```
{ 'simulate': False }
```

You do not have to specify a value for all the properties. If you do not specify a value for a property, the default value is used.

Advanced Example: { 'simulate': True, 'driver\_setup': { 'Model': '<model number>', 'BoardType': '<type>' } }

Property	Default
range_check	True
query_instrument_status	False
cache	True
simulate	False
record_value_coersions	False
driver_setup	{ }

## Properties

Property	Datatype
<i>aperture_time</i>	float
<i>aperture_time_units</i>	<i>ApertureTimeUnits</i>
<i>auto_zero</i>	<i>AutoZero</i>
<i>auxiliary_power_source_available</i>	bool
<i>channel_count</i>	int
<i>compliance_limit_symmetry</i>	<i>ComplianceLimitSymmetry</i>
<i>current_compensation_frequency</i>	float
<i>current_gain_bandwidth</i>	float
<i>current_level</i>	float
<i>current_level_autorange</i>	bool
<i>current_level_range</i>	float
<i>current_limit</i>	float
<i>current_limit_autorange</i>	bool
<i>current_limit_high</i>	float
<i>current_limit_low</i>	float
<i>current_limit_range</i>	float
<i>current_pole_zero_ratio</i>	float
<i>dc_noise_rejection</i>	<i>DCNoiseRejection</i>
<i>digital_edge_measure_trigger_input_terminal</i>	str
<i>digital_edge_pulse_trigger_input_terminal</i>	str
<i>digital_edge_sequence_advance_trigger_input_terminal</i>	str
<i>digital_edge_source_trigger_input_terminal</i>	str
<i>digital_edge_start_trigger_input_terminal</i>	str
<i>driver_setup</i>	str
<i>exported_measure_trigger_output_terminal</i>	str
<i>exported_pulse_trigger_output_terminal</i>	str
<i>exported_sequence_advance_trigger_output_terminal</i>	str

Continued on next page

Table 1 – continued from previous page

Property	Datatype
<code>exported_source_trigger_output_terminal</code>	str
<code>exported_start_trigger_output_terminal</code>	str
<code>fetch_backlog</code>	int
<code>instrument_firmware_revision</code>	str
<code>instrument_manufacturer</code>	str
<code>instrument_model</code>	str
<code>interlock_input_open</code>	bool
<code>io_resource_descriptor</code>	str
<code>logical_name</code>	str
<code>measure_buffer_size</code>	int
<code>measure_complete_event_delay</code>	float in seconds or datetime.timedelta
<code>measure_complete_event_output_terminal</code>	str
<code>measure_complete_event_pulse_polarity</code>	<i>Polarity</i>
<code>measure_complete_event_pulse_width</code>	float
<code>measure_record_delta_time</code>	float in seconds or datetime.timedelta
<code>measure_record_length</code>	int
<code>measure_record_length_is_finite</code>	bool
<code>measure_trigger_type</code>	<i>TriggerType</i>
<code>measure_when</code>	<i>MeasureWhen</i>
<code>output_capacitance</code>	<i>OutputCapacitance</i>
<code>output_connected</code>	bool
<code>output_enabled</code>	bool
<code>output_function</code>	<i>OutputFunction</i>
<code>output_resistance</code>	float
<code>overranging_enabled</code>	bool
<code>ovp_enabled</code>	bool
<code>ovp_limit</code>	float
<code>power_line_frequency</code>	float
<code>power_source</code>	<i>PowerSource</i>
<code>power_source_in_use</code>	<i>PowerSourceInUse</i>
<code>pulse_bias_current_level</code>	float
<code>pulse_bias_current_limit</code>	float
<code>pulse_bias_current_limit_high</code>	float
<code>pulse_bias_current_limit_low</code>	float
<code>pulse_bias_delay</code>	float
<code>pulse_bias_voltage_level</code>	float
<code>pulse_bias_voltage_limit</code>	float
<code>pulse_bias_voltage_limit_high</code>	float
<code>pulse_bias_voltage_limit_low</code>	float
<code>pulse_complete_event_output_terminal</code>	str
<code>pulse_complete_event_pulse_polarity</code>	<i>Polarity</i>
<code>pulse_complete_event_pulse_width</code>	float
<code>pulse_current_level</code>	float
<code>pulse_current_level_range</code>	float
<code>pulse_current_limit</code>	float
<code>pulse_current_limit_high</code>	float
<code>pulse_current_limit_low</code>	float
<code>pulse_current_limit_range</code>	float
<code>pulse_off_time</code>	float in seconds or datetime.timedelta

Continued on next page

Table 1 – continued from previous page

Property	Datatype
<code>pulse_on_time</code>	float in seconds or <code>datetime.timedelta</code>
<code>pulse_trigger_type</code>	<i>TriggerType</i>
<code>pulse_voltage_level</code>	float
<code>pulse_voltage_level_range</code>	float
<code>pulse_voltage_limit</code>	float
<code>pulse_voltage_limit_high</code>	float
<code>pulse_voltage_limit_low</code>	float
<code>pulse_voltage_limit_range</code>	float
<code>query_instrument_status</code>	bool
<code>ready_for_pulse_trigger_event_output_terminal</code>	str
<code>ready_for_pulse_trigger_event_pulse_polarity</code>	<i>Polarity</i>
<code>ready_for_pulse_trigger_event_pulse_width</code>	float
<code>reset_average_before_measurement</code>	bool
<code>samples_to_average</code>	int
<code>self_calibration_persistence</code>	<i>SelfCalibrationPersistence</i>
<code>sense</code>	<i>Sense</i>
<code>sequence_advance_trigger_type</code>	<i>TriggerType</i>
<code>sequence_engine_done_event_output_terminal</code>	str
<code>sequence_engine_done_event_pulse_polarity</code>	<i>Polarity</i>
<code>sequence_engine_done_event_pulse_width</code>	float
<code>sequence_iteration_complete_event_output_terminal</code>	str
<code>sequence_iteration_complete_event_pulse_polarity</code>	<i>Polarity</i>
<code>sequence_iteration_complete_event_pulse_width</code>	float
<code>sequence_loop_count</code>	int
<code>sequence_loop_count_is_finite</code>	bool
<code>simulate</code>	bool
<code>source_complete_event_output_terminal</code>	str
<code>source_complete_event_pulse_polarity</code>	<i>Polarity</i>
<code>source_complete_event_pulse_width</code>	float
<code>source_delay</code>	float in seconds or <code>datetime.timedelta</code>
<code>source_mode</code>	<i>SourceMode</i>
<code>source_trigger_type</code>	<i>TriggerType</i>
<code>specific_driver_description</code>	str
<code>specific_driver_prefix</code>	str
<code>specific_driver_revision</code>	str
<code>specific_driver_vendor</code>	str
<code>start_trigger_type</code>	<i>TriggerType</i>
<code>supported_instrument_models</code>	str
<code>transient_response</code>	<i>TransientResponse</i>
<code>voltage_compensation_frequency</code>	float
<code>voltage_gain_bandwidth</code>	float
<code>voltage_level</code>	float
<code>voltage_level_autorange</code>	bool
<code>voltage_level_range</code>	float
<code>voltage_limit</code>	float
<code>voltage_limit_autorange</code>	bool
<code>voltage_limit_high</code>	float
<code>voltage_limit_low</code>	float
<code>voltage_limit_range</code>	float

Continued on next page

Table 1 – continued from previous page

Property	Datatype
<code>voltage_pole_zero_ratio</code>	float

**Public methods**

Method name
<code>abort()</code>
<code>commit()</code>
<code>configure_aperture_time()</code>
<code>disable()</code>
<code>fetch_multiple()</code>
<code>get_channel_name()</code>
<code>get_ext_cal_last_date_and_time()</code>
<code>get_ext_cal_last_temp()</code>
<code>get_ext_cal_recommended_interval()</code>
<code>get_self_cal_last_date_and_time()</code>
<code>get_self_cal_last_temp()</code>
<code>lock()</code>
<code>measure()</code>
<code>measure_multiple()</code>
<code>query_in_compliance()</code>
<code>query_max_current_limit()</code>
<code>query_max_voltage_level()</code>
<code>query_min_current_limit()</code>
<code>query_output_state()</code>
<code>read_current_temperature()</code>
<code>reset()</code>
<code>reset_device()</code>
<code>reset_with_defaults()</code>
<code>self_cal()</code>
<code>self_test()</code>
<code>send_software_edge_trigger()</code>
<code>set_sequence()</code>
<code>unlock()</code>
<code>wait_for_event()</code>

**Properties****aperture\_time**

`nidcpower.Session.aperture_time`

Specifies the measurement aperture time for the channel configuration. Aperture time is specified in the units set by the `nidcpower.Session.aperture_time_units` property. for information about supported devices. Refer to the Aperture Time topic in the NI DC Power Supplies and SMUs Help for more information about how to configure your measurements and for information about valid values. Default Value: 0.01666666 seconds

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].aperture_time = var
var = session.channels[0,1].aperture_time
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Aperture Time**
- C Attribute: **NIDCPOWER\_ATTR\_APERTURE\_TIME**

## aperture\_time\_units

`nidcpower.Session.aperture_time_units`

Specifies the units of the `nidcpower.Session.aperture_time` property for the channel configuration. for information about supported devices. Refer to the Aperture Time topic in the NI DC Power Supplies and SMUs Help for more information about how to configure your measurements and for information about valid values. Default Value: `SECONDS`

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].aperture_time_units = var
var = session.channels[0,1].aperture_time_units
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.ApertureTimeUnits</code>
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Aperture Time Units**
  - C Attribute: **NIDCPOWER\_ATTR\_APERTURE\_TIME\_UNITS**
- 

## auto\_zero

`nidcpower.Session.auto_zero`

Specifies the auto-zero method to use on the device. Refer to the NI PXI-4132 Measurement Configuration and Timing and Auto Zero topics for more information about how to configure your measurements. Default Value: The default value for the NI PXI-4132 is *ON*. The default value for all other devices is *OFF*, which is the only supported value for these devices.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].auto_zero = var
var = session.channels[0,1].auto_zero
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.AutoZero</code>
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Auto Zero**
  - C Attribute: **NIDCPOWER\_ATTR\_AUTO\_ZERO**
- 

## auxiliary\_power\_source\_available

`nidcpower.Session.auxiliary_power_source_available`

Indicates whether an auxiliary power source is connected to the device. A value of False may indicate that the auxiliary input fuse has blown. Refer to the Detecting Internal/Auxiliary Power topic in the NI DC Power Supplies and SMUs Help for more information about internal and auxiliary power. power source to generate power. Use the `nidcpower.Session.power_source_in_use` property to retrieve this information.

---

**Note:** This property does not necessarily indicate if the device is using the auxiliary

---



The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Advanced:Auxiliary Power Source Available**
  - C Attribute: **NIDCPOWER\_ATTR\_AUXILIARY\_POWER\_SOURCE\_AVAILABLE**
- 

## channel\_count

`nidcpower.Session.channel_count`

Indicates the number of channels that NI-DCPower supports for the instrument that was chosen when the current session was opened. For channel-based properties, the IVI engine maintains a separate cache value for each channel.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Capabilities:Channel Count**
  - C Attribute: **NIDCPOWER\_ATTR\_CHANNEL\_COUNT**
- 

## compliance\_limit\_symmetry

`nidcpower.Session.compliance_limit_symmetry`

Specifies whether compliance limits for current generation and voltage generation for the device are applied symmetrically about 0 V and 0 A or asymmetrically with respect to 0 V and 0 A. When set to **Symmetric**, voltage limits and current limits are set using a single property with a positive value. The resulting range is bounded by this positive value and its opposite. When set to **Asymmetric**, you must separately set a limit high and a limit low using distinct properties. For asymmetric limits, the range bounded by the limit high and limit low must include zero. **Default Value:** Symmetric  
**Related Topics:** [Compliance Ranges](#) [Changing Ranges](#) [Overranging](#)

---

**Note:** Refer to [Supported Properties by Device](#) for information about supported devices.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].compliance_limit_symmetry = var
var = session.channels[0,1].compliance_limit_symmetry
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.ComplianceLimitSymmetry</code>
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Compliance Limit Symmetry**
- C Attribute: **NIDCPOWER\_ATTR\_COMPLIANCE\_LIMIT\_SYMMETRY**

## current\_compensation\_frequency

`nidcpower.Session.current_compensation_frequency`

The frequency at which a pole-zero pair is added to the system when the channel is in Constant Current mode. for information about supported devices. Default Value: Determined by the value of the *NORMAL* setting of the `nidcpower.Session.transient_response` property.

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_compensation_frequency = var
var = session.channels[0,1].current_compensation_frequency
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Custom Transient Response:Current:Compensation Frequency**
  - C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_COMPENSATION\_FREQUENCY**
- 

## current\_gain\_bandwidth

`nidcpower.Session.current_gain_bandwidth`

The frequency at which the unloaded loop gain extrapolates to 0 dB in the absence of additional poles and zeroes. This property takes effect when the channel is in Constant Current mode. for information about supported devices. Default Value: Determined by the value of the *NORMAL* setting of the `nidcpower.Session.transient_response` property.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_gain_bandwidth = var
var = session.channels[0,1].current_gain_bandwidth
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Custom Transient Response:Current:Gain Bandwidth**
  - C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_GAIN\_BANDWIDTH**
- 

## current\_level

`nidcpower.Session.current_level`

Specifies the current level, in amps, that the device attempts to generate on the specified channel(s). This property is applicable only if the `nidcpower.Session.output_function` property is set to *DC\_CURRENT*. `nidcpower.Session.output_enabled` property for more information about enabling the output channel. Valid Values: The valid values for this property are defined by the values to which the `nidcpower.Session.current_level_range` property is set.

---

**Note:** The channel must be enabled for the specified current level to take effect. Refer to the

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_level = var
var = session.channels[0,1].current_level
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Current:Current Level**
  - C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_LEVEL**
- 

## current\_level\_autorange

### `nidcpower.Session.current_level_autorange`

Specifies whether NI-DCPower automatically selects the current level range based on the desired current level for the specified channels. If you set this property to *ON*, NI-DCPower ignores any changes you make to the `nidcpower.Session.current_level_range` property. If you change the `nidcpower.Session.current_level_autorange` property from *ON* to *OFF*, NI-DCPower retains the last value the `nidcpower.Session.current_level_range` property was set to (or the default value if the property was never set) and uses that value as the current level range. Query the `nidcpower.Session.current_level_range` property by using the `nidcpower.Session._get_attribute_vi_int32()` method for information about which range NI-DCPower automatically selects. The `nidcpower.Session.current_level_autorange` property is applicable only if the `nidcpower.Session.output_function` property is set to *DC\_CURRENT*. Default Value: *OFF*

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_level_autorange = var
var = session.channels[0,1].current_level_autorange
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Current:Current Level Autorange**
- C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_LEVEL\_AUTORANGE**

## current\_level\_range

### `nidcpower.Session.current_level_range`

Specifies the current level range, in amps, for the specified channel(s). The range defines the valid value to which the current level can be set. Use the `nidcpower.Session.current_level_autorange` property to enable automatic selection of the current level range. The `nidcpower.Session.current_level_range` property is applicable only if the `nidcpower.Session.output_function` property is set to `DC_CURRENT`. `nidcpower.Session.output_enabled` property for more information about enabling the output channel. For valid ranges, refer to the Ranges topic for your device in the NI DC Power Supplies and SMUs Help.

**Note:** The channel must be enabled for the specified current level range to take effect. Refer to the

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_level_range = var
var = session.channels[0,1].current_level_range
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Current:Current Level Range**

- C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_LEVEL\_RANGE**

## current\_limit

`nidcpower.Session.current_limit`

Specifies the current limit, in amps, that the output cannot exceed when generating the desired voltage level on the specified channel(s). This property is applicable only if the `nidcpower.Session.output_function` property is set to `DC_VOLTAGE` and the `nidcpower.Session.compliance_limit_symmetry` property is set to `NIDCPOWER_VAL_SYMMETRIC`. `nidcpower.Session.output_enabled` property for more information about enabling the output channel. Valid Values: The valid values for this property are defined by the values to which `nidcpower.Session.current_limit_range` property is set.

---

**Note:** The channel must be enabled for the specified current limit to take effect. Refer to the

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_limit = var
var = session.channels[0,1].current_limit
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Voltage:Current Limit**
  - C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_LIMIT**
- 

## current\_limit\_autorange

`nidcpower.Session.current_limit_autorange`

Specifies whether NI-DCPower automatically selects the current limit range based on the de-

sired current limit for the specified channel(s). If you set this property to *ON*, NI-DCPower ignores any changes you make to the `nidcpower.Session.current_limit_range` property. If you change this property from *ON* to *OFF*, NI-DCPower retains the last value the `nidcpower.Session.current_limit_range` property was set to (or the default value if the property was never set) and uses that value as the current limit range. Query the `nidcpower.Session.current_limit_range` property by using the `nidcpower.Session._get_attribute_vi_int32()` method for information about which range NI-DCPower automatically selects. The `nidcpower.Session.current_limit_autorange` property is applicable only if the `nidcpower.Session.output_function` property is set to *DC\_VOLTAGE*. Default Value: *OFF*

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_limit_autorange = var
var = session.channels[0,1].current_limit_autorange
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Voltage:Current Limit Autorange**
- C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_LIMIT\_AUTORANGE**

## current\_limit\_high

### `nidcpower.Session.current_limit_high`

Specifies the maximum current, in amps, that the output can produce when generating the desired voltage on the specified channel(s). This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **DC Voltage**. You must also specify a *Current Limit Low* `<p:py:meth:'nidcpower.Session.CurrentLimitLow.html'>__` to complete the asymmetric range. **Valid Values:** [1% of Current Limit Range `<p:py:meth:'nidcpower.Session.CurrentLimitRange.html'>__`, Current Limit Range `<p:py:meth:'nidcpower.Session.CurrentLimitRange.html'>__`] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled*

<p:py:meth: 'nidcpower.Session.OverrangingEnabled.html'>\_\_ property is set to TRUE.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_limit_high = var
var = session.channels[0,1].current_limit_high
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Voltage:Current Limit High**
  - C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_LIMIT\_HIGH**
- 

## current\_limit\_low

`nidcpower.Session.current_limit_low`

Specifies the minimum current, in amps, that the output can produce when generating the desired voltage on the specified channel(s). This property is applicable only if the *Compliance Limit Symmetry* <p:py:meth: 'nidcpower.Session.ComplianceLimitSymmetry.html'>\_\_ property is set to **Asymmetric** and the *Output Method* <p:py:meth: 'nidcpower.Session.OutputFunction.html'>\_\_ property is set to **DC Voltage**. You must also specify a *Current Limit High* <p:py:meth: 'nidcpower.Session.CurrentLimitHigh.html'>\_\_ to complete the asymmetric range. **Valid Values:** [-Current Limit Range <p:py:meth: 'nidcpower.Session.CurrentLimitRange.html'>\_\_, -1% of Current Limit Range <p:py:meth: 'nidcpower.Session.CurrentLimitRange.html'>\_\_] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* <p:py:meth: 'nidcpower.Session.OverrangingEnabled.html'>\_\_ property is set to TRUE.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_limit_low = var
var = session.channels[0,1].current_limit_low
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Voltage:Current Limit Low**
  - C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_LIMIT\_LOW**
- 

## current\_limit\_range

### `nidcpower.Session.current_limit_range`

Specifies the current limit range, in amps, for the specified channel(s). The range defines the valid value to which the current limit can be set. Use the `nidcpower.Session.current_limit_autorange` property to enable automatic selection of the current limit range. The `nidcpower.Session.current_limit_range` property is applicable only if the `nidcpower.Session.output_function` property is set to `DC_VOLTAGE`. `nidcpower.Session.output_enabled` property for more information about enabling the output channel. For valid ranges, refer to the Ranges topic for your device in the NI DC Power Supplies and SMUs Help.

---

**Note:** The channel must be enabled for the specified current limit to take effect. Refer to the

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_limit_range = var
var = session.channels[0,1].current_limit_range
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Voltage:Current Limit Range**
  - C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_LIMIT\_RANGE**
- 

## current\_pole\_zero\_ratio

`nidcpower.Session.current_pole_zero_ratio`

The ratio of the pole frequency to the zero frequency when the channel is in Constant Current mode. for information about supported devices. Default Value: Determined by the value of the [NORMAL](#) setting of the `nidcpower.Session.transient_response` property.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].current_pole_zero_ratio = var
var = session.channels[0,1].current_pole_zero_ratio
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Custom Transient Response:Current:Pole-Zero Ratio**
  - C Attribute: **NIDCPOWER\_ATTR\_CURRENT\_POLE\_ZERO\_RATIO**
-

## dc\_noise\_rejection

### `nidcpower.Session.dc_noise_rejection`

Determines the relative weighting of samples in a measurement. Refer to the NI PXIe-4140/4141 DC Noise Rejection, NI PXIe-4142/4143 DC Noise Rejection, or NI PXIe-4144/4145 DC Noise Rejection topic in the NI DC Power Supplies and SMUs Help for more information about noise rejection. for information about supported devices. Default Value: *NORMAL*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.DCNoiseRejection
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Advanced:DC Noise Rejection**
  - C Attribute: **NIDCPower\_ATTR\_DC\_NOISE\_REJECTION**
- 

## digital\_edge\_measure\_trigger\_input\_terminal

### `nidcpower.Session.digital_edge_measure_trigger_input_terminal`

Specifies the input terminal for the Measure trigger. This property is used only when the `nidcpower.Session.measure_trigger_type` property is set to *DIGITAL\_EDGE*. for this property. You can specify any valid input terminal for this property. Valid terminals are listed in Measurement & Automation Explorer under the Device Routes tab. Input terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0. The input terminal can also be a terminal from another device. For example, you can set the input terminal on Dev1 to be /Dev2/SourceCompleteEvent.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Measure Trigger:Digital Edge:Input Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_DIGITAL\_EDGE\_MEASURE\_TRIGGER\_INPUT\_TERMINAL**
- 

### digital\_edge\_pulse\_trigger\_input\_terminal

`nidcpower.Session.digital_edge_pulse_trigger_input_terminal`

Specifies the input terminal for the Pulse trigger. This property is used only when the `nidcpower.Session.pulse_trigger_type` property is set to digital edge. You can specify any valid input terminal for this property. Valid terminals are listed in Measurement & Automation Explorer under the Device Routes tab. Input terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0. The input terminal can also be a terminal from another device. For example, you can set the input terminal on Dev1 to be /Dev2/SourceCompleteEvent.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Pulse Trigger:Digital Edge:Input Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_DIGITAL\_EDGE\_PULSE\_TRIGGER\_INPUT\_TERMINAL**
- 

### digital\_edge\_sequence\_advance\_trigger\_input\_terminal

`nidcpower.Session.digital_edge_sequence_advance_trigger_input_terminal`

Specifies the input terminal for the Sequence Advance trigger. Use this property only when the `nidcpower.Session.sequence_advance_trigger_type` property is set to `DIGITAL_EDGE`. the NI DC Power Supplies and SMUs Help for information about supported devices. You can specify any valid input terminal for this property. Valid terminals are listed in Measurement & Automation Explorer under the Device Routes tab. Input terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0. The input terminal can also be a terminal from another device. For example, you can set the input terminal on Dev1 to be /Dev2/SourceCompleteEvent.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic in

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Sequence Advance Trigger:Digital Edge:Input Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_DIGITAL\_EDGE\_SEQUENCE\_ADVANCE\_TRIGGER\_INPUT\_TERMINAL**
- 

### digital\_edge\_source\_trigger\_input\_terminal

`nidcpower.Session.digital_edge_source_trigger_input_terminal`

Specifies the input terminal for the Source trigger. Use this property only when the `nidcpower.Session.source_trigger_type` property is set to `DIGITAL_EDGE`. for information about supported devices. You can specify any valid input terminal for this property. Valid terminals are listed in Measurement & Automation Explorer under the Device Routes tab. Input terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0. The input terminal can also be a terminal from another device. For example, you can set the input terminal on Dev1 to be /Dev2/SourceCompleteEvent.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Source Trigger:Digital Edge:Input Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_DIGITAL\_EDGE\_SOURCE\_TRIGGER\_INPUT\_TERMINAL**
- 

### digital\_edge\_start\_trigger\_input\_terminal

`nidcpower.Session.digital_edge_start_trigger_input_terminal`

Specifies the input terminal for the Start trigger. Use this property only when the `nidcpower.Session.start_trigger_type` property is set to `DIGITAL_EDGE`. for information about supported devices. You can specify any valid input terminal for this property. Valid terminals are

listed in Measurement & Automation Explorer under the Device Routes tab. Input terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0. The input terminal can also be a terminal from another device. For example, you can set the input terminal on Dev1 to be /Dev2/SourceCompleteEvent.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Start Trigger:Digital Edge:Input Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_DIGITAL\_EDGE\_START\_TRIGGER\_INPUT\_TERMINAL**
- 

## driver\_setup

### `nidcpower.Session.driver_setup`

Indicates the Driver Setup string that you specified when initializing the driver. Some cases exist where you must specify the instrument driver options at initialization time. An example of this case is specifying a particular device model from among a family of devices that the driver supports. This property is useful when simulating a device. You can specify the driver-specific options through the DriverSetup keyword in the optionsString parameter in the `nidcpower.Session.__init__()` method or through the IVI Configuration Utility. You can specify driver-specific options through the DriverSetup keyword in the optionsString parameter in the `nidcpower.Session.__init__()` method. If you do not specify a Driver Setup string, this property returns an empty string.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:Driver Setup**
  - C Attribute: **NIDCPOWER\_ATTR\_DRIVER\_SETUP**
-

## exported\_measure\_trigger\_output\_terminal

`nidcpower.Session.exported_measure_trigger_output_terminal`

Specifies the output terminal for exporting the Measure trigger. Refer to the Device Routes tab in Measurement & Automation Explorer for a list of the terminals available on your device. for information about supported devices. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Measure Trigger:Export Output Terminal**
  - C Attribute: **NIDCPower\_ATTR\_EXPORTED\_MEASURE\_TRIGGER\_OUTPUT\_TERMINAL**
- 

## exported\_pulse\_trigger\_output\_terminal

`nidcpower.Session.exported_pulse_trigger_output_terminal`

Specifies the output terminal for exporting the Pulse trigger. Refer to the Device Routes tab in Measurement & Automation Explorer for a list of the terminals available on your device. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Pulse Trigger:Export Output Terminal**

- C Attribute: `NIDCPOWER_ATTR_EXPORTED_PULSE_TRIGGER_OUTPUT_TERMINAL`
- 

### `exported_sequence_advance_trigger_output_terminal`

`nidcpower.Session.exported_sequence_advance_trigger_output_terminal`

Specifies the output terminal for exporting the Sequence Advance trigger. Refer to the Device Routes tab in Measurement & Automation Explorer for a list of the terminals available on your device. for information about supported devices. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Sequence Advance Trigger:Export Output Terminal**
  - C Attribute: `NIDCPOWER_ATTR_EXPORTED_SEQUENCE_ADVANCE_TRIGGER_OUTPUT_TERMINAL`
- 

### `exported_source_trigger_output_terminal`

`nidcpower.Session.exported_source_trigger_output_terminal`

Specifies the output terminal for exporting the Source trigger. Refer to the Device Routes tab in MAX for a list of the terminals available on your device. for information about supported devices. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No



---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Source Trigger:Export Output Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_EXPORTED\_SOURCE\_TRIGGER\_OUTPUT\_TERMINAL**
- 

## exported\_start\_trigger\_output\_terminal

`nidcpower.Session.exported_start_trigger_output_terminal`

Specifies the output terminal for exporting the Start trigger. Refer to the Device Routes tab in Measurement & Automation Explorer (MAX) for a list of the terminals available on your device. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0. for information about supported devices.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Start Trigger:Export Output Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_EXPORTED\_START\_TRIGGER\_OUTPUT\_TERMINAL**
- 

## fetch\_backlog

`nidcpower.Session.fetch_backlog`

Returns the number of measurements acquired that have not been fetched yet.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Fetch Backlog**

- C Attribute: **NIDCPOWER\_ATTR\_FETCH\_BACKLOG**
- 

## instrument\_firmware\_revision

`nidcpower.Session.instrument_firmware_revision`

Contains the firmware revision information for the device you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Firmware Revision**
  - C Attribute: **NIDCPOWER\_ATTR\_INSTRUMENT\_FIRMWARE\_REVISION**
- 

## instrument\_manufacturer

`nidcpower.Session.instrument_manufacturer`

Contains the name of the manufacturer for the device you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Manufacturer**
  - C Attribute: **NIDCPOWER\_ATTR\_INSTRUMENT\_MANUFACTURER**
- 

## instrument\_model

`nidcpower.Session.instrument_model`

Contains the model number or name of the device that you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Model**
  - C Attribute: **NIDCPOWER\_ATTR\_INSTRUMENT\_MODEL**
- 

## interlock\_input\_open

`nidcpower.Session.interlock_input_open`

Indicates whether the safety interlock circuit is open. Refer to the Safety Interlock topic in the NI DC Power Supplies and SMUs Help for more information about the safety interlock circuit, about supported devices.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Advanced:Interlock Input Open**
  - C Attribute: **NIDCPOWER\_ATTR\_INTERLOCK\_INPUT\_OPEN**
- 

## io\_resource\_descriptor

`nidcpower.Session.io_resource_descriptor`

Indicates the resource descriptor NI-DCPower uses to identify the physical device. If you initialize NI-DCPower with a logical name, this property contains the resource descriptor that corresponds to the entry in the IVI Configuration utility. If you initialize NI-DCPower with the resource descriptor, this property contains that value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:Resource Descriptor**
  - C Attribute: **NIDCPower\_ATTR\_IO\_RESOURCE\_DESCRIPTOR**
- 

## logical\_name

### `nidcpower.Session.logical_name`

Contains the logical name you specified when opening the current IVI session. You can pass a logical name to the `nidcpower.Session.__init__()` method. The IVI Configuration utility must contain an entry for the logical name. The logical name entry refers to a method section in the IVI Configuration file. The method section specifies a physical device and initial user options.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:Logical Name**
  - C Attribute: **NIDCPower\_ATTR\_LOGICAL\_NAME**
- 

## measure\_buffer\_size

### `nidcpower.Session.measure_buffer_size`

Specifies the number of samples that the active channel measurement buffer can hold. The default value is the maximum number of samples that a device is capable of recording in one second. for information about supported devices. Valid Values: 1000 to 2147483647 Default Value: Varies by device. Refer to Supported Properties by Device topic in the NI DC Power Supplies and SMUs Help for more information about default values.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Advanced:Measure Buffer Size**
  - C Attribute: **NIDCPOWER\_ATTR\_MEASURE\_BUFFER\_SIZE**
- 

## measure\_complete\_event\_delay

`nidcpower.Session.measure_complete_event_delay`

Specifies the amount of time to delay the generation of the Measure Complete event, in seconds. for information about supported devices. Valid Values: 0 to 167 seconds Default Value: The NI PXI-4132 and NI PXIe-4140/4141/4142/4143/4144/4145/4154 supports values from 0 seconds to 167 seconds.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Measure Complete Event:Event Delay**
  - C Attribute: **NIDCPOWER\_ATTR\_MEASURE\_COMPLETE\_EVENT\_DELAY**
- 

## measure\_complete\_event\_output\_terminal

`nidcpower.Session.measure_complete_event_output_terminal`

Specifies the output terminal for exporting the Measure Complete event. for information about supported devices. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Measure Complete Event:Output Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_MEASURE\_COMPLETE\_EVENT\_OUTPUT\_TERMINAL**
- 

### **measure\_complete\_event\_pulse\_polarity**

`nidcpower.Session.measure_complete_event_pulse_polarity`

Specifies the behavior of the Measure Complete event. for information about supported devices.  
Default Value: *HIGH*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.Polarity
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Measure Complete Event:Pulse:Polarity**
  - C Attribute: **NIDCPOWER\_ATTR\_MEASURE\_COMPLETE\_EVENT\_PULSE\_POLARITY**
- 

### **measure\_complete\_event\_pulse\_width**

`nidcpower.Session.measure_complete_event_pulse_width`

Specifies the width of the Measure Complete event, in seconds. The minimum event pulse width value for PXI devices is 150 ns, and the minimum event pulse width value for PXI Express devices is 250 ns. The maximum event pulse width value for all devices is 1.6 microseconds. for information about supported devices. Valid Values: 1.5e-7 to 1.6e-6 Default Value: The default value for PXI devices is 150 ns. The default value for PXI Express devices is 250 ns.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Measure Complete Event:Pulse:Width**
  - C Attribute: **NIDCPOWER\_ATTR\_MEASURE\_COMPLETE\_EVENT\_PULSE\_WIDTH**
- 

## measure\_record\_delta\_time

`nidcpower.Session.measure_record_delta_time`

Queries the amount of time, in seconds, between the start of two consecutive measurements in a measure record. Only query this property after the desired measurement settings are committed. for information about supported devices. two measurements and the rest would differ.

---

**Note:** This property is not available when Auto Zero is configured to Once because the amount of time between the first

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Measure Record Delta Time**
  - C Attribute: **NIDCPOWER\_ATTR\_MEASURE\_RECORD\_DELTA\_TIME**
- 

## measure\_record\_length

`nidcpower.Session.measure_record_length`

Specifies how many measurements compose a measure record. When this property is set to a value greater than 1, the `nidcpower.Session.measure_when` property must be set to `AUTOMATICALLY_AFTER_SOURCE_COMPLETE` or `ON_MEASURE_TRIGGER`. for information about supported devices. Valid Values: 1 to 16,777,216 Default Value: 1

---

**Note:** This property is not available in a session involving multiple channels.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Measure Record Length**
  - C Attribute: **NIDCPower\_ATTR\_MEASURE\_RECORD\_LENGTH**
- 

## measure\_record\_length\_is\_finite

`nidcpower.Session.measure_record_length_is_finite`

Specifies whether to take continuous measurements. Call the `nidcpower.Session.abort()` method to stop continuous measurements. When this property is set to False and the `nidcpower.Session.source_mode` property is set to `SINGLE_POINT`, the `nidcpower.Session.measure_when` property must be set to `AUTOMATICALLY_AFTER_SOURCE_COMPLETE` or `ON_MEASURE_TRIGGER`. When this property is set to False and the `nidcpower.Session.source_mode` property is set to `SEQUENCE`, the `nidcpower.Session.measure_when` property must be set to `ON_MEASURE_TRIGGER`. for information about supported devices. Default Value: True

---

**Note:** This property is not available in a session involving multiple channels.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Measure Record Length Is Finite**
  - C Attribute: **NIDCPower\_ATTR\_MEASURE\_RECORD\_LENGTH\_IS\_FINITE**
-



## measure\_trigger\_type

`nidcpower.Session.measure_trigger_type`

Specifies the behavior of the Measure trigger. for information about supported devices. Default Value: *DIGITAL\_EDGE*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.TriggerType
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Measure Trigger:Trigger Type**
  - C Attribute: **NIDCPOWER\_ATTR\_MEASURE\_TRIGGER\_TYPE**
- 

## measure\_when

`nidcpower.Session.measure_when`

Specifies when the measure unit should acquire measurements. Unless this property is configured to *ON\_MEASURE\_TRIGGER*, the `nidcpower.Session.measure_trigger_type` property is ignored. Refer to the Acquiring Measurements topic in the NI DC Power Supplies and SMUs Help for more information about how to configure your measurements. Default Value: If the `nidcpower.Session.source_mode` property is set to *SINGLE\_POINT*, the default value is *ON\_DEMAND*. This value supports only the `nidcpower.Session.measure()` method and `nidcpower.Session.measure_multiple()` method. If the `nidcpower.Session.source_mode` property is set to *SEQUENCE*, the default value is *AUTOMATICALLY\_AFTER\_SOURCE\_COMPLETE*. This value supports only the `nidcpower.Session.fetch_multiple()` method.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.MeasureWhen
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Advanced:Measure When**
  - C Attribute: **NIDCPOWER\_ATTR\_MEASURE\_WHEN**
-

## output\_capacitance

### `nidcpower.Session.output_capacitance`

Specifies whether to use a low or high capacitance on the output for the specified channel(s). for information about supported devices. Refer to the NI PXI-4130 Output Capacitance Selection topic in the NI DC Power Supplies and SMUs Help for more information about capacitance.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].output_capacitance = var
var = session.channels[0,1].output_capacitance
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.OutputCapacitance</code>
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Output Capacitance**
  - C Attribute: **NIDCPOWER\_ATTR\_OUTPUT\_CAPACITANCE**
- 

## output\_connected

### `nidcpower.Session.output_connected`

Specifies whether the output relay is connected (closed) or disconnected (open). The `nidcpower.Session.output_enabled` property does not change based on this property; they are independent of each other. about supported devices. Set this property to False to disconnect the output terminal from the output. to the output terminal might discharge unless the relay is disconnected. Excessive connecting and disconnecting of the output can cause premature wear on the relay. Default Value: True

---

**Note:** Only disconnect the output when disconnecting is necessary for your application. For example, a battery connected

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can

specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].output_connected = var
var = session.channels[0,1].output_connected
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Output Connected**
- C Attribute: **NIDCPOWER\_ATTR\_OUTPUT\_CONNECTED**

## output\_enabled

### `nidcpower.Session.output_enabled`

Specifies whether the output is enabled (True) or disabled (False). Depending on the value you specify for the `nidcpower.Session.output_function` property, you also must set the voltage level or current level in addition to enabling the output the `nidcpower.Session.initiate()` method. Refer to the Programming States topic in the NI DC Power Supplies and SMUs Help for more information about NI-DCPower programming states. Default Value: The default value is True if you use the `nidcpower.Session.__init__()` method to open the session. Otherwise the default value is False, including when you use a calibration session or the deprecated programming model.

**Note:** If the session is in the Committed or Uncommitted states, enabling the output does not take effect until you call

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the `set/get` will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].output_enabled = var
var = session.channels[0,1].output_enabled
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Output Enabled**
  - C Attribute: **NIDCPOWER\_ATTR\_OUTPUT\_ENABLED**
- 

## output\_function

### nidcpower.Session.output\_function

Configures the method to generate on the specified channel(s). When *DC\_VOLTAGE* is selected, the device generates the desired voltage level on the output as long as the output current is below the current limit. You can use the following properties to configure the channel when *DC\_VOLTAGE* is selected: *nidcpower.Session.voltage\_level* *nidcpower.Session.current\_limit* *nidcpower.Session.current\_limit\_high* *nidcpower.Session.current\_limit\_low* *nidcpower.Session.voltage\_level\_range* *nidcpower.Session.current\_limit\_range*. When *DC\_CURRENT* is selected, the device generates the desired current level on the output as long as the output voltage is below the voltage limit. You can use the following properties to configure the channel when *DC\_CURRENT* is selected: *nidcpower.Session.current\_level* *nidcpower.Session.voltage\_limit* *nidcpower.Session.voltage\_limit\_high* *nidcpower.Session.voltage\_limit\_low* *nidcpower.Session.current\_level\_range* *nidcpower.Session.voltage\_limit\_range*. Default Value: *DC\_VOLTAGE*

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the *nidcpower.Session* object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an *nidcpower.Session* repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].output_function = var
var = session.channels[0,1].output_function
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.OutputFunction
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Output Function**

- C Attribute: **NIDCPOWER\_ATTR\_OUTPUT\_FUNCTION**
- 

## output\_resistance

### `nidcpower.Session.output_resistance`

Specifies the output resistance that the device attempts to generate for the specified channel(s). This property is available only when you set the `nidcpower.Session.output_function` property on a support device. Refer to a supported device's topic about output resistance for more information about selecting an output resistance. about supported devices. Default Value: 0.0

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic for information

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].output_resistance = var
var = session.channels[0,1].output_resistance
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Output Resistance**
  - C Attribute: **NIDCPOWER\_ATTR\_OUTPUT\_RESISTANCE**
- 

## overranging\_enabled

### `nidcpower.Session.overranging_enabled`

Specifies whether NI-DCPower allows setting the voltage level, current level, voltage limit and current limit outside the device specification limits. True means that overranging is enabled. Refer to the Ranges topic in the NI DC Power Supplies and SMUs Help for more information about overranging. Default Value: False

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Overranging Enabled**
  - C Attribute: **NIDCPOWER\_ATTR\_OVERRANGING\_ENABLED**
- 

## ovp\_enabled

`nidcpower.Session.ovp_enabled`

Enables (True) or disables (False) overvoltage protection (OVP). Refer to the Output Overvoltage Protection topic in the NI DC Power Supplies and SMUs Help for more information about overvoltage protection. for information about supported devices. Default Value: False

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:OVP Enabled**
  - C Attribute: **NIDCPOWER\_ATTR\_OVP\_ENABLED**
- 

## ovp\_limit

`nidcpower.Session.ovp_limit`

Determines the voltage limit, in volts, beyond which overvoltage protection (OVP) engages. for information about supported devices. Valid Values: 2 V to 210 V Default Value: 210 V

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:OVP Limit**
  - C Attribute: **NIDCPOWER\_ATTR\_OVP\_LIMIT**
- 

## power\_line\_frequency

`nidcpower.Session.power_line_frequency`

Specifies the power line frequency for specified channel(s). NI-DCPower uses this value to select a timebase for setting the `nidcpower.Session.aperture_time` property in power line cycles (PLCs). in the NI DC Power Supplies and SMUs Help for information about supported devices. Default Value: NIDCPOWER\_VAL\_60\_HERTZ

---

**Note:** This property is not supported by all devices. Refer to the Supported Properties by Device topic

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].power_line_frequency = var
var = session.channels[0,1].power_line_frequency
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Power Line Frequency**

- C Attribute: **NIDCPOWER\_ATTR\_POWER\_LINE\_FREQUENCY**
- 

## power\_source

`nidcpower.Session.power_source`

Specifies the power source to use. NI-DCPower switches the power source used by the device to the specified value. Default Value: *AUTOMATIC* is set to *AUTOMATIC*. However, if the session is in the Committed or Uncommitted state when you set this property, the power source selection only occurs after you call the `nidcpower.Session.initiate()` method.

---

**Note:** Automatic selection is not persistent and occurs only at the time this property

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.PowerSource
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Advanced:Power Source**
  - C Attribute: **NIDCPOWER\_ATTR\_POWER\_SOURCE**
- 

## power\_source\_in\_use

`nidcpower.Session.power_source_in_use`

Indicates whether the device is using the internal or auxiliary power source to generate power.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.PowerSourceInUse
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Advanced:Power Source In Use**
  - C Attribute: **NIDCPOWER\_ATTR\_POWER\_SOURCE\_IN\_USE**
-



## pulse\_bias\_current\_level

`nidcpower.Session.pulse_bias_current_level`

Specifies the pulse bias current level, in amps, that the device attempts to generate on the specified channel(s) during the off phase of a pulse. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_CURRENT`. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.pulse_current_level_range` property.

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_bias_current_level = var
var = session.channels[0,1].pulse_bias_current_level
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Bias Current Level**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_CURRENT\_LEVEL**

## pulse\_bias\_current\_limit

`nidcpower.Session.pulse_bias_current_limit`

Specifies the pulse bias current limit, in amps, that the output cannot exceed when generating the desired pulse bias voltage on the specified channel(s) during the off phase of a pulse. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_VOLTAGE`. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.pulse_current_limit_range` property.

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_bias_current_limit = var
var = session.channels[0,1].pulse_bias_current_limit
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Bias Current Limit**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_CURRENT\_LIMIT**

## pulse\_bias\_current\_limit\_high

### `nidcpower.Session.pulse_bias_current_limit_high`

Specifies the maximum current, in amps, that the output can produce when generating the desired pulse voltage on the specified channel(s) during the *off* phase of a pulse. This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **Pulse Voltage**. You must also specify a *Pulse Bias Current Limit Low* `<p:py:meth:'nidcpower.Session.PulseBiasCurrentLimitLow.html'>__` to complete the asymmetric range. **Valid Values:** [1% of *Pulse Current Limit Range* `<p:py:meth:'nidcpower.Session.PulseCurrentLimitRange.html'>__`, *Pulse Current Limit Range* `<p:py:meth:'nidcpower.Session.PulseCurrentLimitRange.html'>__`] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to TRUE or if the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to a pulsing method.

**Note:** One or more of the referenced methods are not in the Python API for this driver.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nid-`

cpower.Session object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an nidcpower.Session repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_bias_current_limit_high = var
var = session.channels[0,1].pulse_bias_current_limit_high
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Bias Current Limit High**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_CURRENT\_LIMIT\_HIGH**

## pulse\_bias\_current\_limit\_low

### nidcpower.Session.pulse\_bias\_current\_limit\_low

Specifies the minimum current, in amps, that the output can produce when generating the desired pulse voltage on the specified channel(s) during the *off* phase of a pulse. This property is applicable only if the *Compliance Limit Symmetry* [<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>\\_\\_](#) property is set to **Asymmetric** and the *Output Method* [<p:py:meth:'nidcpower.Session.OutputFunction.html'>\\_\\_](#) property is set to **Pulse Voltage**. You must also specify a *Pulse Bias Current Limit High* [<p:py:meth:'nidcpower.Session.PulseBiasCurrentLimitHigh.html'>\\_\\_](#) to complete the asymmetric range. **Valid Values:** [\[-Pulse Current Limit Range <p:py:meth:'nidcpower.Session.PulseCurrentLimitRange.html'>\\_\\_](#), -1% of *Pulse Current Limit Range* [<p:py:meth:'nidcpower.Session.PulseCurrentLimitRange.html'>\\_\\_](#)] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* [<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>\\_\\_](#) property is set to TRUE or if the *Output Method* [<p:py:meth:'nidcpower.Session.OutputFunction.html'>\\_\\_](#) property is set to a pulsing method.

**Note:** One or more of the referenced methods are not in the Python API for this driver.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the nidcpower.Session object, then the set/get will use all repeated capabilities in the session. You can

specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].pulse_bias_current_limit_low = var
var = session.channels[0,1].pulse_bias_current_limit_low
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Bias Current Limit Low**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_CURRENT\_LIMIT\_LOW**
- 

## **pulse\_bias\_delay**

`nidcpower.Session.pulse_bias_delay`

Determines when, in seconds, the device generates the Pulse Complete event after generating the off level of a pulse. Valid Values: 0 to 167 seconds Default Value: 16.67 milliseconds

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the `set/get` will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].pulse_bias_delay = var
var = session.channels[0,1].pulse_bias_delay
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Pulse Bias Delay**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_DELAY**

## pulse\_bias\_voltage\_level

`nidcpower.Session.pulse_bias_voltage_level`

Specifies the pulse bias voltage level, in volts, that the device attempts to generate on the specified channel(s) during the off phase of a pulse. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_VOLTAGE`. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.pulse_voltage_level_range` property.

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_bias_voltage_level = var
var = session.channels[0,1].pulse_bias_voltage_level
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Bias Voltage Level**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_VOLTAGE\_LEVEL**

## pulse\_bias\_voltage\_limit

`nidcpower.Session.pulse_bias_voltage_limit`

Specifies the pulse voltage limit, in volts, that the output cannot exceed when generating the desired current on the specified channel(s) during the off phase of a pulse. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_CURRENT`. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.pulse_voltage_limit_range` property.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

---

```
session.channels[0,1].pulse_bias_voltage_limit = var
var = session.channels[0,1].pulse_bias_voltage_limit
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Bias Voltage Limit**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_VOLTAGE\_LIMIT**
- 

## pulse\_bias\_voltage\_limit\_high

### `nidcpower.Session.pulse_bias_voltage_limit_high`

Specifies the maximum voltage, in volts, that the output can produce when generating the desired pulse current on the specified channel(s) during the *off* phase of a pulse. This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **Pulse Current**. You must also specify a *Pulse Bias Voltage Limit Low* `<p:py:meth:'nidcpower.Session.PulseBiasVoltageLimitLow.html'>__` to complete the asymmetric range. **Valid Values:** [1% of *Pulse Voltage Limit Range* `<p:py:meth:'nidcpower.Session.PulseVoltageLimitRange.html'>__`, *Pulse Voltage Limit Range* `<p:py:meth:'nidcpower.Session.PulseVoltageLimitRange.html'>__`] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

---

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to TRUE or if the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to a pulsing method.

---

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_bias_voltage_limit_high = var
var = session.channels[0,1].pulse_bias_voltage_limit_high
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Bias Voltage Limit High**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_VOLTAGE\_LIMIT\_HIGH**
- 

## pulse\_bias\_voltage\_limit\_low

`nidcpower.Session.pulse_bias_voltage_limit_low`

Specifies the minimum voltage, in volts, that the output can produce when generating the desired pulse current on the specified channel(s) during the *off* phase of a pulse. This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **Pulse Current**. You must also specify a *Pulse Bias Voltage Limit High* `<p:py:meth:'nidcpower.Session.PulseBiasVoltageLimitHigh.html'>__` to complete the asymmetric range. **Valid Values:** `<p:py:meth:'nidcpower.Session.PulseVoltageLimitRange.html'>__`, -1% of *Pulse Voltage Limit Range* `<p:py:meth:'nidcpower.Session.PulseVoltageLimitRange.html'>__` The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

---

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to TRUE or if the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to a pulsing method.

---

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_bias_voltage_limit_low = var
var = session.channels[0,1].pulse_bias_voltage_limit_low
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Bias Voltage Limit Low**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_BIAS\_VOLTAGE\_LIMIT\_LOW**
- 

## pulse\_complete\_event\_output\_terminal

`nidcpower.Session.pulse_complete_event_output_terminal`

Specifies the output terminal for exporting the Pulse Complete event. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, `/Dev1/PXI_Trig0`, or with the shortened terminal name, `PXI_Trig0`. Default Value:The default value for PXI Express devices is 250 ns.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Pulse Complete Event:Output Terminal**



- C Attribute: `NIDCPOWER_ATTR_PULSE_COMPLETE_EVENT_OUTPUT_TERMINAL`
- 

### `pulse_complete_event_pulse_polarity`

`nidcpower.Session.pulse_complete_event_pulse_polarity`

Specifies the behavior of the Pulse Complete event. Default Value: `HIGH`

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.Polarity</code>
Permissions	<code>read-write</code>
Channel Based	<code>False</code>
Resettable	<code>No</code>

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Pulse Complete Event:Pulse:Polarity**
  - C Attribute: `NIDCPOWER_ATTR_PULSE_COMPLETE_EVENT_PULSE_POLARITY`
- 

### `pulse_complete_event_pulse_width`

`nidcpower.Session.pulse_complete_event_pulse_width`

Specifies the width of the Pulse Complete event, in seconds. The minimum event pulse width value for PXI Express devices is 250 ns. The maximum event pulse width value for PXI Express devices is 1.6 microseconds. Default Value: The default value for PXI Express devices is 250 ns.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>float</code>
Permissions	<code>read-write</code>
Channel Based	<code>False</code>
Resettable	<code>No</code>

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Pulse Complete Event:Pulse:Width**
- C Attribute: `NIDCPOWER_ATTR_PULSE_COMPLETE_EVENT_PULSE_WIDTH`

## pulse\_current\_level

`nidcpower.Session.pulse_current_level`

Specifies the pulse current level, in amps, that the device attempts to generate on the specified channel(s) during the on phase of a pulse. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_CURRENT`. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.pulse_current_level_range` property.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_current_level = var
var = session.channels[0,1].pulse_current_level
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Current Level**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_CURRENT\_LEVEL**
- 

## pulse\_current\_level\_range

`nidcpower.Session.pulse_current_level_range`

Specifies the pulse current level range, in amps, for the specified channel(s). The range defines the valid values to which you can set the pulse current level and pulse bias current level. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_CURRENT`. For valid ranges, refer to the ranges topic for your device in the NI DC Power Supplies and SMUs Help.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

---

```
session.channels[0,1].pulse_current_level_range = var
var = session.channels[0,1].pulse_current_level_range
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Current Level Range**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_CURRENT\_LEVEL\_RANGE**
- 

## pulse\_current\_limit

`nidcpower.Session.pulse_current_limit`

Specifies the pulse current limit, in amps, that the output cannot exceed when generating the desired pulse voltage on the specified channel(s) during the on phase of a pulse. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_VOLTAGE` and the `nidcpower.Session.compliance_limit_symmetry` property is set to `NIDCPOWER_VAL_SYMMETRIC`. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.pulse_current_limit_range` property.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can

---

specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].pulse_current_limit = var
var = session.channels[0,1].pulse_current_limit
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Current Limit**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_CURRENT\_LIMIT**

## pulse\_current\_limit\_high

### `nidcpower.Session.pulse_current_limit_high`

Specifies the maximum current, in amps, that the output can produce when generating the desired pulse voltage on the specified channel(s) during the *on* phase of a pulse. This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **Pulse Voltage**. You must also specify a *Pulse Current Limit Low* `<p:py:meth:'nidcpower.Session.PulseCurrentLimitLow.html'>__` to complete the asymmetric range. **Valid Values:** [1% of *Pulse Current Limit Range* `<p:py:meth:'nidcpower.Session.PulseCurrentLimitRange.html'>__`, *Pulse Current Limit Range* `<p:py:meth:'nidcpower.Session.PulseCurrentLimitRange.html'>__`] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to **TRUE** or if the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to a pulsing method.

**Note:** One or more of the referenced methods are not in the Python API for this driver.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the `set/get` will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].pulse_current_limit_high = var
var = session.channels[0,1].pulse_current_limit_high
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Current Limit High**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_CURRENT\_LIMIT\_HIGH**

## pulse\_current\_limit\_low

`nidcpower.Session.pulse_current_limit_low`

Specifies the minimum current, in amps, that the output can produce when generating the desired pulse voltage on the specified channel(s) during the *on* phase of a pulse. This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **Pulse Voltage**. You must also specify a *Pulse Current Limit High* `<p:py:meth:'nidcpower.Session.PulseCurrentLimitHigh.html'>__` to complete the asymmetric range. **Valid Values:** `<p:py:meth:'nidcpower.Session.PulseCurrentLimitRange.html'>__`, -1% of *Pulse Current Limit Range* `<p:py:meth:'nidcpower.Session.PulseCurrentLimitRange.html'>__` The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to TRUE or if the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to a pulsing method.

**Note:** One or more of the referenced methods are not in the Python API for this driver.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_current_limit_low = var
var = session.channels[0,1].pulse_current_limit_low
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Current Limit Low**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_CURRENT\_LIMIT\_LOW**
- 

## pulse\_current\_limit\_range

`nidcpower.Session.pulse_current_limit_range`

Specifies the pulse current limit range, in amps, for the specified channel(s). The range defines the valid values to which you can set the pulse current limit and pulse bias current limit. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_VOLTAGE`. For valid ranges, refer to the ranges topic for your device in the NI DC Power Supplies and SMUs Help.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_current_limit_range = var
var = session.channels[0,1].pulse_current_limit_range
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Current Limit Range**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_CURRENT\_LIMIT\_RANGE**

## pulse\_off\_time

`nidcpower.Session.pulse_off_time`

Determines the length, in seconds, of the off phase of a pulse. Valid Values: 10 microseconds to 167 seconds Default Value: 34 milliseconds

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_off_time = var
var = session.channels[0,1].pulse_off_time
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Pulse Off Time**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_OFF\_TIME**

## pulse\_on\_time

`nidcpower.Session.pulse_on_time`

Determines the length, in seconds, of the on phase of a pulse. Valid Values: 10 microseconds to 167 seconds Default Value: 34 milliseconds

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_on_time = var
var = session.channels[0,1].pulse_on_time
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Pulse On Time**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_ON\_TIME**
- 

## **pulse\_trigger\_type**

`nidcpower.Session.pulse_trigger_type`

Specifies the behavior of the Pulse trigger. Default Value: *NONE*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TriggerType</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Pulse Trigger:Trigger Type**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_TRIGGER\_TYPE**
-



## pulse\_voltage\_level

### `nidcpower.Session.pulse_voltage_level`

Specifies the pulse current limit, in amps, that the output cannot exceed when generating the desired pulse voltage on the specified channel(s) during the on phase of a pulse. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_VOLTAGE`. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.pulse_current_limit_range` property.

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_voltage_level = var
var = session.channels[0,1].pulse_voltage_level
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Voltage Level**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_VOLTAGE\_LEVEL**

## pulse\_voltage\_level\_range

### `nidcpower.Session.pulse_voltage_level_range`

Specifies the pulse voltage level range, in volts, for the specified channel(s). The range defines the valid values at which you can set the pulse voltage level and pulse bias voltage level. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_VOLTAGE`. For valid ranges, refer to the ranges topic for your device in the NI DC Power Supplies and SMUs Help.

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_voltage_level_range = var
var = session.channels[0,1].pulse_voltage_level_range
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Voltage:Pulse Voltage Level Range**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_VOLTAGE\_LEVEL\_RANGE**

## pulse\_voltage\_limit

### `nidcpower.Session.pulse_voltage_limit`

Specifies the pulse voltage limit, in volts, that the output cannot exceed when generating the desired pulse current on the specified channel(s) during the on phase of a pulse. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_CURRENT` and the `nidcpower.Session.compliance_limit_symmetry` property is set to `NIDCPOWER_VAL_SYMMETRIC`. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.pulse_voltage_limit_range` property.

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_voltage_limit = var
var = session.channels[0,1].pulse_voltage_limit
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Voltage Limit**
- C Attribute: **NIDCPOWER\_ATTR\_PULSE\_VOLTAGE\_LIMIT**

## pulse\_voltage\_limit\_high

`nidcpower.Session.pulse_voltage_limit_high`

Specifies the maximum voltage, in volts, that the output can produce when generating the desired pulse current on the specified channel(s) during the *on* phase of a pulse. This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **Pulse Current**. You must also specify a *Pulse Voltage Limit Low* `<p:py:meth:'nidcpower.Session.PulseVoltageLimitLow.html'>__` to complete the asymmetric range. **Valid Values:** [1% of *Pulse Voltage Limit Range* `<p:py:meth:'nidcpower.Session.PulseVoltageLimitRange.html'>__`, *Pulse Voltage Limit Range* `<p:py:meth:'nidcpower.Session.PulseVoltageLimitRange.html'>__`] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to TRUE or if the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to a pulsing method.

**Note:** One or more of the referenced methods are not in the Python API for this driver.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_voltage_limit_high = var
var = session.channels[0,1].pulse_voltage_limit_high
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Voltage Limit High**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_VOLTAGE\_LIMIT\_HIGH**
- 

## pulse\_voltage\_limit\_low

`nidcpower.Session.pulse_voltage_limit_low`

Specifies the minimum voltage, in volts, that the output can produce when generating the desired pulse current on the specified channel(s) during the *on* phase of a pulse. This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **Pulse Current**. You must also specify a *Pulse Voltage Limit High* `<p:py:meth:'nidcpower.Session.PulseVoltageLimitHigh.html'>__` to complete the asymmetric range. **Valid Values:** `<p:py:meth:'nidcpower.Session.PulseVoltageLimitRange.html'>__`, -1% of *Pulse Voltage Limit Range* `<p:py:meth:'nidcpower.Session.PulseVoltageLimitRange.html'>__` The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

---

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to TRUE or if the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to a pulsing method.

---



---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_voltage_limit_low = var
var = session.channels[0,1].pulse_voltage_limit_low
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Voltage Limit Low**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_VOLTAGE\_LIMIT\_LOW**
- 

## pulse\_voltage\_limit\_range

`nidcpower.Session.pulse_voltage_limit_range`

Specifies the pulse voltage limit range, in volts, for the specified channel(s). The range defines the valid values to which you can set the pulse voltage limit and pulse bias voltage limit. This property is applicable only if the `nidcpower.Session.output_function` property is set to `PULSE_CURRENT`. For valid ranges, refer to the ranges topic for your device in the NI DC Power Supplies and SMUs Help.

---

**Note:** The channel must be enabled for the specified current limit to take effect. Refer to the `nidcpower.Session.output_enabled` property for more information about enabling the output channel.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].pulse_voltage_limit_range = var
var = session.channels[0,1].pulse_voltage_limit_range
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Pulse Current:Pulse Voltage Limit Range**
  - C Attribute: **NIDCPOWER\_ATTR\_PULSE\_VOLTAGE\_LIMIT\_RANGE**
-

## query\_instrument\_status

### `nidcpower.Session.query_instrument_status`

Specifies whether NI-DCPower queries the device status after each operation. Querying the device status is useful for debugging. After you validate your program, you can set this property to False to disable status checking and maximize performance. NI-DCPower ignores status checking for particular properties regardless of the setting of this property. Use the `nidcpower.Session.__init__()` method to override this value. Default Value: True

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes>User Options:Query Instrument Status**
  - C Attribute: **NIDCPOWER\_ATTR\_QUERY\_INSTRUMENT\_STATUS**
- 

## ready\_for\_pulse\_trigger\_event\_output\_terminal

### `nidcpower.Session.ready_for_pulse_trigger_event_output_terminal`

Specifies the output terminal for exporting the Ready For Pulse Trigger event. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Ready For Pulse Trigger Event:Output Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_READY\_FOR\_PULSE\_TRIGGER\_EVENT\_OUTPUT\_TERMINAL**
-

## ready\_for\_pulse\_trigger\_event\_pulse\_polarity

`nidcpower.Session.ready_for_pulse_trigger_event_pulse_polarity`

Specifies the behavior of the Ready For Pulse Trigger event. Default Value: *HIGH*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.Polarity
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Ready For Pulse Trigger Event:Pulse:Polarity**
  - C Attribute: **NIDCPower\_ATTR\_READY\_FOR\_PULSE\_TRIGGER\_EVENT\_PULSE\_POLARITY**
- 

## ready\_for\_pulse\_trigger\_event\_pulse\_width

`nidcpower.Session.ready_for_pulse_trigger_event_pulse_width`

Specifies the width of the Ready For Pulse Trigger event, in seconds. The minimum event pulse width value for PXI Express devices is 250 ns. The maximum event pulse width value for all devices is 1.6 microseconds. Default Value: The default value for PXI Express devices is 250 ns

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information about supported devices.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Ready For Pulse Trigger Event:Pulse:Width**
  - C Attribute: **NIDCPower\_ATTR\_READY\_FOR\_PULSE\_TRIGGER\_EVENT\_PULSE\_WIDTH**
-

## reset\_average\_before\_measurement

### `nidcpower.Session.reset_average_before_measurement`

Specifies whether the measurement returned from any measurement call starts with a new measurement call (True) or returns a measurement that has already begun or completed(False). for information about supported devices. When you set the `nidcpower.Session.samples_to_average` property in the Running state, the output channel measurements might move out of synchronization. While NI-DCPower automatically synchronizes measurements upon the initialization of a session, you can force a synchronization in the running state before you run the `nidcpower.Session.measure_multiple()` method. To force a synchronization in the running state, set this property to True, and then run the `nidcpower.Session.measure_multiple()` method, specifying all channels in the channel name parameter. You can set the `nidcpower.Session.reset_average_before_measurement` property to False after the `nidcpower.Session.measure_multiple()` method completes. Default Value: True

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].reset_average_before_measurement = var
var = session.channels[0,1].reset_average_before_measurement
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Advanced:Reset Average Before Measurement**
  - C Attribute: **NIDCPOWER\_ATTR\_RESET\_AVERAGE\_BEFORE\_MEASUREMENT**
- 

## samples\_to\_average

### `nidcpower.Session.samples_to_average`

Specifies the number of samples to average when you take a measurement. Increasing the number of samples to average decreases measurement noise but increases the time required to take a measurement. Refer to the NI PXI-4110, NI PXI-4130, NI PXI-4132, or NI PXIe-4154 Averaging topic for optional property settings to improve immunity to certain noise types, or refer to the



NI PXIe-4140/4141 DC Noise Rejection, NI PXIe-4142/4143 DC Noise Rejection, or NI PXIe-4144/4145 DC Noise Rejection topic for information about improving noise immunity for those devices. Default Value: NI PXI-4110 or NI PXI-4130—10 NI PXI-4132—1 NI PXIe-4112—1 NI PXIe-4113—1 NI PXIe-4140/4141—1 NI PXIe-4142/4143—1 NI PXIe-4144/4145—1 NI PXIe-4154—500

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].samples_to_average = var
var = session.channels[0,1].samples_to_average
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Samples To Average**
- C Attribute: **NIDCPOWER\_ATTR\_SAMPLES\_TO\_AVERAGE**

## self\_calibration\_persistence

### `nidcpower.Session.self_calibration_persistence`

Specifies whether the values calculated during self-calibration should be written to hardware to be used until the next self-calibration or only used until the `nidcpower.Session.reset_device()` method is called or the machine is powered down. This property affects the behavior of the `nidcpower.Session.self_cal()` method. When set to `KEEP_IN_MEMORY`, the values calculated by the `nidcpower.Session.self_cal()` method are used in the existing session, as well as in all further sessions until you call the `nidcpower.Session.reset_device()` method or restart the machine. When you set this property to `WRITE_TO_EEPROM`, the values calculated by the `nidcpower.Session.self_cal()` method are written to hardware and used in the existing session and in all subsequent sessions until another call to the `nidcpower.Session.self_cal()` method is made. about supported devices. Default Value: `KEEP_IN_MEMORY`

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device for information

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.SelfCalibrationPersistence
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Advanced:Self-Calibration Persistence**
  - C Attribute: **NIDCPOWER\_ATTR\_SELF\_CALIBRATION\_PERSISTENCE**
- 

## sense

### `nidcpower.Session.sense`

Selects either local or remote sensing of the output voltage for the specified channel(s). Refer to the Local and Remote Sense topic in the NI DC Power Supplies and SMUs Help for more information about sensing voltage on supported channels and about devices that support local and/or remote sensing. Default Value: The default value is *LOCAL* if the device supports local sense. Otherwise, the default and only supported value is *REMOTE*.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].sense = var
var = session.channels[0,1].sense
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.Sense
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Measurement:Sense**
  - C Attribute: **NIDCPOWER\_ATTR\_SENSE**
- 

## sequence\_advance\_trigger\_type

### `nidcpower.Session.sequence_advance_trigger_type`

Specifies the behavior of the Sequence Advance trigger. for information about supported devices.

Default Value: *NONE*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.TriggerType
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Sequence Advance Trigger:Trigger Type**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_ADVANCE\_TRIGGER\_TYPE**
- 

## sequence\_engine\_done\_event\_output\_terminal

`nidcpower.Session.sequence_engine_done_event_output_terminal`

Specifies the output terminal for exporting the Sequence Engine Done Complete event. for information about supported devices. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Sequence Engine Done Event:Output Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_ENGINE\_DONE\_EVENT\_OUTPUT\_TERMINAL**
- 

## sequence\_engine\_done\_event\_pulse\_polarity

`nidcpower.Session.sequence_engine_done_event_pulse_polarity`

Specifies the behavior of the Sequence Engine Done event. for information about supported devices.  
Default Value: *HIGH*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.Polarity
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Sequence Engine Done Event:Pulse:Polarity**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_ENGINE\_DONE\_EVENT\_PULSE\_POLARITY**
- 

## sequence\_engine\_done\_event\_pulse\_width

`nidcpower.Session.sequence_engine_done_event_pulse_width`

Specifies the width of the Sequence Engine Done event, in seconds. The minimum event pulse width value for PXI devices is 150 ns, and the minimum event pulse width value for PXI Express devices is 250 ns. The maximum event pulse width value for all devices is 1.6 microseconds. for information about supported devices. Valid Values: 1.5e-7 to 1.6e-6 seconds Default Value: The default value for PXI devices is 150 ns. The default value for PXI Express devices is 250 ns.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Sequence Engine Done Event:Pulse:Width**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_ENGINE\_DONE\_EVENT\_PULSE\_WIDTH**
- 

## sequence\_iteration\_complete\_event\_output\_terminal

`nidcpower.Session.sequence_iteration_complete_event_output_terminal`

Specifies the output terminal for exporting the Sequence Iteration Complete event. for information about supported devices. Output terminals can be specified in one of two ways. If the device is

named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Sequence Iteration Complete Event:Output Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_ITERATION\_COMPLETE\_EVENT\_OUTPUT\_TERMINAL**
- 

### sequence\_iteration\_complete\_event\_pulse\_polarity

`nidcpower.Session.sequence_iteration_complete_event_pulse_polarity`

Specifies the behavior of the Sequence Iteration Complete event. for information about supported devices. Default Value: *HIGH*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.Polarity
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Sequence Iteration Complete Event:Pulse:Polarity**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_ITERATION\_COMPLETE\_EVENT\_PULSE\_POLARITY**
- 

### sequence\_iteration\_complete\_event\_pulse\_width

`nidcpower.Session.sequence_iteration_complete_event_pulse_width`

Specifies the width of the Sequence Iteration Complete event, in seconds. The minimum event pulse width value for PXI devices is 150 ns, and the minimum event pulse width value for PXI Express devices is 250 ns. The maximum event pulse width value for all devices is 1.6 microseconds. the NI

DC Power Supplies and SMUs Help for information about supported devices. Valid Values: 1.5e-7 to 1.6e-6 seconds Default Value: The default value for PXI devices is 150 ns. The default value for PXI Express devices is 250 ns.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic in

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Sequence Iteration Complete Event:Pulse:Width**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_ITERATION\_COMPLETE\_EVENT\_PULSE\_WIDTH**
- 

## sequence\_loop\_count

`nidcpower.Session.sequence_loop_count`

Specifies the number of times a sequence is run after initiation. Refer to the Sequence Source Mode topic in the NI DC Power Supplies and SMUs Help for more information about the sequence loop count. for information about supported devices. When the `nidcpower.Session.sequence_loop_count_is_finite` property is set to False, the `nidcpower.Session.sequence_loop_count` property is ignored. Valid Range: 1 to 134217727 Default Value: 1

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Sequence Loop Count**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_LOOP\_COUNT**
-

## sequence\_loop\_count\_is\_finite

`nidcpower.Session.sequence_loop_count_is_finite`

Specifies whether a sequence should repeat indefinitely. Refer to the Sequence Source Mode topic in the NI DC Power Supplies and SMUs Help for more information about infinite sequencing. `nidcpower.Session.sequence_loop_count_is_finite` property is set to False, the `nidcpower.Session.sequence_loop_count` property is ignored. Default Value: True

---

**Note:** This property is not supported by all devices. When the

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Sequence Loop Count Is Finite**
  - C Attribute: **NIDCPOWER\_ATTR\_SEQUENCE\_LOOP\_COUNT\_IS\_FINITE**
- 

## simulate

`nidcpower.Session.simulate`

Specifies whether to simulate NI-DCPower I/O operations. True specifies that operation is simulated. Default Value: False

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:User Options:Simulate**
  - C Attribute: **NIDCPOWER\_ATTR\_SIMULATE**
- 

## source\_complete\_event\_output\_terminal

`nidcpower.Session.source_complete_event_output_terminal`

Specifies the output terminal for exporting the Source Complete event. for information about sup-

ported devices. Output terminals can be specified in one of two ways. If the device is named Dev1 and your terminal is PXI\_Trig0, you can specify the terminal with the fully qualified terminal name, /Dev1/PXI\_Trig0, or with the shortened terminal name, PXI\_Trig0.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Source Complete Event:Output Terminal**
  - C Attribute: **NIDCPOWER\_ATTR\_SOURCE\_COMPLETE\_EVENT\_OUTPUT\_TERMINAL**
- 

### source\_complete\_event\_pulse\_polarity

`nidcpower.Session.source_complete_event_pulse_polarity`

Specifies the behavior of the Source Complete event. for information about supported devices.  
Default Value: *HIGH*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.Polarity
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Source Complete Event:Pulse:Polarity**
  - C Attribute: **NIDCPOWER\_ATTR\_SOURCE\_COMPLETE\_EVENT\_PULSE\_POLARITY**
- 

### source\_complete\_event\_pulse\_width

`nidcpower.Session.source_complete_event_pulse_width`

Specifies the width of the Source Complete event, in seconds. for information about supported devices. The minimum event pulse width value for PXI devices is 150 ns, and the minimum event



pulse width value for PXI Express devices is 250 ns. The maximum event pulse width value for all devices is 1.6 microseconds Valid Values: 1.5e-7 to 1.6e-6 seconds Default Value: The default value for PXI devices is 150 ns. The default value for PXI Express devices is 250 ns.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Source Complete Event:Pulse:Width**
  - C Attribute: **NIDCPOWER\_ATTR\_SOURCE\_COMPLETE\_EVENT\_PULSE\_WIDTH**
- 

## source\_delay

`nidcpower.Session.source_delay`

Determines when, in seconds, the device generates the Source Complete event, potentially starting a measurement if the `nidcpower.Session.measure_when` property is set to `AUTOMATICALLY_AFTER_SOURCE_COMPLETE`. Refer to the Single Point Source Mode and Sequence Source Mode topics for more information. Valid Values: 0 to 167 seconds Default Value: 0.01667 seconds

---

**Note:** Refer to Supported Properties by Device for information about supported devices.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].source_delay = var
var = session.channels[0,1].source_delay
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Advanced:Source Delay**
  - C Attribute: **NIDCPOWER\_ATTR\_SOURCE\_DELAY**
- 

## source\_mode

`nidcpower.Session.source_mode`

Specifies whether to run a single output point or a sequence. Refer to the Single Point Source Mode and Sequence Source Mode topics in the NI DC Power Supplies and SMUs Help for more information about source modes. Default value: *SINGLE\_POINT*

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.SourceMode
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Source Mode**
  - C Attribute: **NIDCPOWER\_ATTR\_SOURCE\_MODE**
- 

## source\_trigger\_type

`nidcpower.Session.source_trigger_type`

Specifies the behavior of the Source trigger. for information about supported devices. Default Value: *NONE*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.TriggerType
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Source Trigger:Trigger Type**
  - C Attribute: **NIDCPOWER\_ATTR\_SOURCE\_TRIGGER\_TYPE**
-

## specific\_driver\_description

`nidcpower.Session.specific_driver_description`

Contains a brief description of the specific driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Description**
  - C Attribute: **NIDCPower\_ATTR\_SPECIFIC\_DRIVER\_DESCRIPTION**
- 

## specific\_driver\_prefix

`nidcpower.Session.specific_driver_prefix`

Contains the prefix for NI-DCPower. The name of each user-callable method in NI-DCPower begins with this prefix.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Driver Prefix**
  - C Attribute: **NIDCPower\_ATTR\_SPECIFIC\_DRIVER\_PREFIX**
- 

## specific\_driver\_revision

`nidcpower.Session.specific_driver_revision`

Contains additional version information about NI-DCPower.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Revision**
  - C Attribute: **NIDCPower\_ATTR\_SPECIFIC\_DRIVER\_REVISION**
- 

### `specific_driver_vendor`

`nidcpower.Session.specific_driver_vendor`

Contains the name of the vendor that supplies NI-DCPower.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Driver Vendor**
  - C Attribute: **NIDCPower\_ATTR\_SPECIFIC\_DRIVER\_VENDOR**
- 

### `start_trigger_type`

`nidcpower.Session.start_trigger_type`

Specifies the behavior of the Start trigger. for information about supported devices. Default Value: *NONE*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TriggerType</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Start Trigger:Trigger Type**
  - C Attribute: **NIDCPOWER\_ATTR\_START\_TRIGGER\_TYPE**
- 

## supported\_instrument\_models

`nidcpower.Session.supported_instrument_models`

Contains a comma-separated (,) list of supported NI-DCPower device models.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Capabilities:Supported Instrument Models**
  - C Attribute: **NIDCPOWER\_ATTR\_SUPPORTED\_INSTRUMENT\_MODELS**
- 

## transient\_response

`nidcpower.Session.transient_response`

Specifies the transient response. Refer to the Transient Response topic in the NI DC Power Supplies and SMUs Help for more information about transient response. for information about supported devices. Default Value: *NORMAL*

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].transient_response = var
var = session.channels[0,1].transient_response
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.TransientResponse
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Transient Response**
  - C Attribute: **NIDCPOWER\_ATTR\_TRANSIENT\_RESPONSE**
- 

## voltage\_compensation\_frequency

`nidcpower.Session.voltage_compensation_frequency`

The frequency at which a pole-zero pair is added to the system when the channel is in Constant Voltage mode. for information about supported devices. Default value: Determined by the value of the *NORMAL* setting of the `nidcpower.Session.transient_response` property.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_compensation_frequency = var
var = session.channels[0,1].voltage_compensation_frequency
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Custom Transient Response:Voltage:Compensation Frequency**
  - C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_COMPENSATION\_FREQUENCY**
-

## voltage\_gain\_bandwidth

### `nidcpower.Session.voltage_gain_bandwidth`

The frequency at which the unloaded loop gain extrapolates to 0 dB in the absence of additional poles and zeroes. This property takes effect when the channel is in Constant Voltage mode. for information about supported devices. Default Value: Determined by the value of the [NORMAL](#) setting of the `nidcpower.Session.transient_response` property.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_gain_bandwidth = var
var = session.channels[0,1].voltage_gain_bandwidth
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Custom Transient Response:Voltage:Gain Bandwidth**
  - C Attribute: **NIDCPower\_ATTR\_VOLTAGE\_GAIN\_BANDWIDTH**
- 

## voltage\_level

### `nidcpower.Session.voltage_level`

Specifies the voltage level, in volts, that the device attempts to generate on the specified channel(s). This property is applicable only if the `nidcpower.Session.output_function` property is set to `DC_VOLTAGE`. `nidcpower.Session.output_enabled` property for more information about enabling the output channel. Valid Values: The valid values for this property are defined by the values you specify for the `nidcpower.Session.voltage_level_range` property.

---

**Note:** The channel must be enabled for the specified voltage level to take effect. Refer to the

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_level = var
var = session.channels[0,1].voltage_level
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Voltage:Voltage Level**
- C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_LEVEL**

## voltage\_level\_autorange

`nidcpower.Session.voltage_level_autorange`

Specifies whether NI-DCPower automatically selects the voltage level range based on the desired voltage level for the specified channel(s). If you set this property to *ON*, NI-DCPower ignores any changes you make to the `nidcpower.Session.voltage_level_range` property. If you change the `nidcpower.Session.voltage_level_autorange` property from *ON* to *OFF*, NI-DCPower retains the last value the `nidcpower.Session.voltage_level_range` property was set to (or the default value if the property was never set) and uses that value as the voltage level range. Query the `nidcpower.Session.voltage_level_range` property by using the `nidcpower.Session._get_attribute_vi_int32()` method for information about which range NI-DCPower automatically selects. The `nidcpower.Session.voltage_level_autorange` property is applicable only if the `nidcpower.Session.output_function` property is set to *DC\_VOLTAGE*. Default Value: *OFF*

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_level_autorange = var
var = session.channels[0,1].voltage_level_autorange
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No



---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Voltage:Voltage Level Autorange**
  - C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_LEVEL\_AUTORANGE**
- 

## voltage\_level\_range

`nidcpower.Session.voltage_level_range`

Specifies the voltage level range, in volts, for the specified channel(s). The range defines the valid values to which the voltage level can be set. Use the `nidcpower.Session.voltage_level_autorange` property to enable automatic selection of the voltage level range. The `nidcpower.Session.voltage_level_range` property is applicable only if the `nidcpower.Session.output_function` property is set to `DC_VOLTAGE`. `nidcpower.Session.output_enabled` property for more information about enabling the output channel. For valid ranges, refer to the Ranges topic for your device in the NI DC Power Supplies and SMUs Help.

---

**Note:** The channel must be enabled for the specified voltage level range to take effect. Refer to the

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_level_range = var
var = session.channels[0,1].voltage_level_range
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Voltage:Voltage Level Range**
  - C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_LEVEL\_RANGE**
- 

## voltage\_limit

`nidcpower.Session.voltage_limit`

Specifies the voltage limit, in volts, that the output cannot exceed when generating the desired current level on the specified channels. This property is applicable

only if the `nidcpower.Session.output_function` property is set to `DC_CURRENT` and the `nidcpower.Session.compliance_limit_symmetry` property is set to `NIDCPower_VAL_SYMMETRIC`. `nidcpower.Session.output_enabled` property for more information about enabling the output channel. Valid Values: The valid values for this property are defined by the values to which the `nidcpower.Session.voltage_limit_range` property is set.

---

**Note:** The channel must be enabled for the specified current level to take effect. Refer to the

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_limit = var
var = session.channels[0,1].voltage_limit
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Current:Voltage Limit**
  - C Attribute: **NIDCPower\_ATTR\_VOLTAGE\_LIMIT**
- 

## voltage\_limit\_autorange

`nidcpower.Session.voltage_limit_autorange`

Specifies whether NI-DCPower automatically selects the voltage limit range based on the desired voltage limit for the specified channel(s). If this property is set to `ON`, NI-DCPower ignores any changes you make to the `nidcpower.Session.voltage_limit_range` property. If you change the `nidcpower.Session.voltage_limit_autorange` property from `ON` to `OFF`, NI-DCPower retains the last value the `nidcpower.Session.voltage_limit_range` property was set to (or the default value if the property was never set) and uses that value as the voltage limit range. Query the `nidcpower.Session.voltage_limit_range` property by using the `nidcpower.Session._get_attribute_vi_int32()` method to find out which range NI-DCPower automatically selects. The `nidcpower.Session`.

`voltage_limit_autorange` property is applicable only if the `nidcpower.Session.output_function` property is set to `DC_CURRENT`. Default Value: `OFF`

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_limit_autorange = var
var = session.channels[0,1].voltage_limit_autorange
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Current:Voltage Limit Autorange**
- C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_LIMIT\_AUTORANGE**

## voltage\_limit\_high

`nidcpower.Session.voltage_limit_high`

Specifies the maximum voltage, in volts, that the output can produce when generating the desired current on the specified channel(s). This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **DC Current**. You must also specify a *Voltage Limit Low* `<p:py:meth:'nidcpower.Session.VoltageLimitLow.html'>__` to complete the asymmetric range. **Valid Values:** [1% of Voltage Limit Range `<p:py:meth:'nidcpower.Session.VoltageLimitRange.html'>__`, Voltage Limit Range `<p:py:meth:'nidcpower.Session.VoltageLimitRange.html'>__`] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to **TRUE**.

**Note:** One or more of the referenced methods are not in the Python API for this driver.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can

specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].voltage_limit_high = var
var = session.channels[0,1].voltage_limit_high
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Current:Voltage Limit High**
  - C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_LIMIT\_HIGH**
- 

## voltage\_limit\_low

`nidcpower.Session.voltage_limit_low`

Specifies the minimum voltage, in volts, that the output can produce when generating the desired current on the specified channel(s). This property is applicable only if the *Compliance Limit Symmetry* `<p:py:meth:'nidcpower.Session.ComplianceLimitSymmetry.html'>__` property is set to **Asymmetric** and the *Output Method* `<p:py:meth:'nidcpower.Session.OutputFunction.html'>__` property is set to **DC Current**. You must also specify a *Voltage Limit High* `<p:py:meth:'nidcpower.Session.VoltageLimitHigh.html'>__` to complete the asymmetric range. **Valid Values:** [-*Voltage Limit Range* `<p:py:meth:'nidcpower.Session.VoltageLimitRange.html'>__`, -1% of *Voltage Limit Range* `<p:py:meth:'nidcpower.Session.VoltageLimitRange.html'>__`] The range bounded by the limit high and limit low must include zero. **Default Value:** Refer to [Supported Properties by Device](#) for the default value by device. **Related Topics:** [Ranges Changing Ranges Overranging](#)

---

**Note:** The limit may be extended beyond the selected limit range if the *Overranging Enabled* `<p:py:meth:'nidcpower.Session.OverrangingEnabled.html'>__` property is set to **TRUE**.

---



---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the `set/get` will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].voltage_limit_low = var
var = session.channels[0,1].voltage_limit_low
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Current:Voltage Limit Low**
  - C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_LIMIT\_LOW**
- 

## voltage\_limit\_range

`nidcpower.Session.voltage_limit_range`

Specifies the voltage limit range, in volts, for the specified channel(s). The range defines the valid values to which the voltage limit can be set. Use the `nidcpower.Session.voltage_limit_autorange` property to enable automatic selection of the voltage limit range. The `nidcpower.Session.voltage_limit_range` property is applicable only if the `nidcpower.Session.output_function` property is set to `DC_CURRENT`. `nidcpower.Session.output_enabled` property for more information about enabling the output channel. For valid ranges, refer to the Ranges topic for your device in the NI DC Power Supplies and SMUs Help.

---

**Note:** The channel must be enabled for the specified voltage limit range to take effect. Refer to the

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_limit_range = var
var = session.channels[0,1].voltage_limit_range
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:DC Current:Voltage Limit Range**
  - C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_LIMIT\_RANGE**
- 

## voltage\_pole\_zero\_ratio

`nidcpower.Session.voltage_pole_zero_ratio`

The ratio of the pole frequency to the zero frequency when the channel is in Constant Voltage mode. for information about supported devices. Default value: Determined by the value of the [NORMAL](#) setting of the `nidcpower.Session.transient_response` property.

---

**Note:** This property is not supported by all devices. Refer to Supported Properties by Device topic

---

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `nidcpower.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].voltage_pole_zero_ratio = var
var = session.channels[0,1].voltage_pole_zero_ratio
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Source:Custom Transient Response:Voltage:Pole-Zero Ratio**
  - C Attribute: **NIDCPOWER\_ATTR\_VOLTAGE\_POLE\_ZERO\_RATIO**
- 

## Methods

### abort

`nidcpower.Session.abort()`

Transitions the NI-DCPower session from the Running state to the Committed state. If a sequence is running, it is stopped. Any configuration methods called after this method are not applied until the `nidcpower.Session.initiate()` method is called. If power output is enabled when you call the `nidcpower.Session.abort()` method, the output channels remain in their current state and continue providing power.

Use the `nidcpower.Session.ConfigureOutputEnabled()` method to disable power output on a per channel basis. Use the `nidcpower.Session.reset()` method to disable output on all channels.

Refer to the [Programming States](#) topic in the *NI DC Power Supplies and SMUs Help* for information about the specific NI-DCPower software states.

#### Related Topics:

[Programming States](#)

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

## commit

`nidcpower.Session.commit()`

Applies previously configured settings to the device. Calling this method moves the NI-DCPower session from the Uncommitted state into the Committed state. After calling this method, modifying any property reverts the NI-DCPower session to the Uncommitted state. Use the `nidcpower.Session.initiate()` method to transition to the Running state. Refer to the [Programming States](#) topic in the *NI DC Power Supplies and SMUs Help* for details about the specific NI-DCPower software states.

#### Related Topics:

[Programming States](#)

## configure\_aperture\_time

`nidcpower.Session.configure_aperture_time(aperture_time, units=nidcpower.ApertureTimeUnits.SECONDS)`

Configures the aperture time on the specified channel(s).

The supported values depend on the **units**. Refer to the *Aperture Time* topic for your device in the *NI DC Power Supplies and SMUs Help* for more information. In general, devices support discrete **apertureTime** values, and if you configure **apertureTime** to some unsupported value, NI-DCPower coerces it up to the next supported value.

Refer to the *Measurement Configuration and Timing* or *DC Noise Rejection* topic for your device in the *NI DC Power Supplies and SMUs Help* for more information about how to configure your measurements.

#### Related Topics:

[Aperture Time](#)

---

**Note:** This method is not supported on all devices. Refer to [Supported Methods by Device](#) for more information about supported devices.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].configure_aperture_time(aperture_time,
↳units=nidcpower.ApertureTimeUnits.SECONDS)
```

### Parameters

- **aperture\_time** (*float*) – Specifies the aperture time. Refer to the *Aperture Time* topic for your device in the *NI DC Power Supplies and SMUs Help* for more information.
- **units** (*nidcpower.ApertureTimeUnits*) – Specifies the units for **apertureTime**. **Defined Values:**

<i>SECONDS</i> (1028)	Specifies seconds.
<i>POWER_LINE_CYCLES</i> (1029)	Specifies Power Line Cycles.

### disable

```
nidcpower.Session.disable()
```

This method performs the same actions as the `nidcpower.Session.reset()` method, except that this method also immediately sets the `nidcpower.Session.output_enabled` property to False.

This method opens the output relay on devices that have an output relay.

### fetch\_multiple

```
nidcpower.Session.fetch_multiple(count, timeout=datetime.timedelta(seconds=1.0))
```

Returns a list of named tuples (Measurement) that were previously taken and are stored in the NI-DCPower buffer. This method should not be used when the `nidcpower.Session.measure_when` property is set to `ON_DEMAND`. You must first call `nidcpower.Session.initiate()` before calling this method.

Fields in Measurement:

- **voltage** (float)
- **current** (float)
- **in\_compliance** (bool)

**Note:** This method is not supported on all devices. Refer to [Supported Methods by Device](#) for more information about supported devices.

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].fetch_multiple(count, timeout=datetime.
↳timedelta(seconds=1.0))
```



### Parameters

- **count** (*int*) – Specifies the number of measurements to fetch.
- **timeout** (*float in seconds or datetime.timedelta*) – Specifies the maximum time allowed for this method to complete. If the method does not complete within this time interval, NI-DCPower returns an error.

---

**Note:** When setting the timeout interval, ensure you take into account any triggers so that the timeout interval is long enough for your application.

---

**Return type** list of Measurement

### Returns

List of named tuples with fields:

- **voltage** (float)
- **current** (float)
- **in\_compliance** (bool)

## get\_channel\_name

`nidcpower.Session.get_channel_name(index)`

Retrieves the output **channelName** that corresponds to the requested **index**. Use the `nidcpower.Session.channel_count` property to determine the upper bound of valid values for **index**.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].get_channel_name(index)
```

---

**Parameters** **index** (*int*) – Specifies which output channel name to return. The index values begin at 1.

## get\_ext\_cal\_last\_date\_and\_time

`nidcpower.Session.get_ext_cal_last_date_and_time()`

Returns the date and time of the last successful calibration.

**Return type** `datetime.datetime`

**Returns** Indicates date and time of the last calibration.

## get\_ext\_cal\_last\_temp

`nidcpower.Session.get_ext_cal_last_temp()`

Returns the onboard **temperature** of the device, in degrees Celsius, during the last successful external calibration.

**Return type** `float`

**Returns** Returns the onboard **temperature** of the device, in degrees Celsius, during the last successful external calibration.

### `get_ext_cal_recommended_interval`

`nidcpower.Session.get_ext_cal_recommended_interval()`

Returns the recommended maximum interval, in **months**, between external calibrations.

**Return type** `datetime.timedelta`

**Returns** Specifies the recommended maximum interval, in **months**, between external calibrations.

### `get_self_cal_last_date_and_time`

`nidcpower.Session.get_self_cal_last_date_and_time()`

Returns the date and time of the oldest successful self-calibration from among the channels in the session.

---

**Note:** This method is not supported on all devices.

---

**Return type** `datetime.datetime`

**Returns** Returns the date and time the device was last calibrated.

### `get_self_cal_last_temp`

`nidcpower.Session.get_self_cal_last_temp()`

Returns the onboard temperature of the device, in degrees Celsius, during the oldest successful self-calibration from among the channels in the session.

For example, if you have a session using channels 1 and 2, and you perform a self-calibration on channel 1 with a device temperature of 25 degrees Celsius at 2:00, and a self-calibration was performed on channel 2 at 27 degrees Celsius at 3:00 on the same day, this method returns 25 for the **temperature** parameter.

---

**Note:** This method is not supported on all devices. Refer to [Supported Methods by Device](#) for more information about supported devices.

---

**Return type** `float`

**Returns** Returns the onboard **temperature** of the device, in degrees Celsius, during the oldest successful calibration.

## lock

`nidcpower.Session.lock()`

Obtains a multithread lock on the device session. Before doing so, the software waits until all other execution threads release their locks on the device session.

Other threads may have obtained a lock on this session for the following reasons:

- The application called the `nidcpower.Session.lock()` method.
- A call to NI-DCPower locked the session.
- After a call to the `nidcpower.Session.lock()` method returns successfully, no other threads can access the device session until you call the `nidcpower.Session.unlock()` method or exit out of the with block when using lock context manager.
- Use the `nidcpower.Session.lock()` method and the `nidcpower.Session.unlock()` method around a sequence of calls to instrument driver methods if you require that the device retain its settings through the end of the sequence.

You can safely make nested calls to the `nidcpower.Session.lock()` method within the same thread. To completely unlock the session, you must balance each call to the `nidcpower.Session.lock()` method with a call to the `nidcpower.Session.unlock()` method.

One method for ensuring there are the same number of unlock method calls as there is lock calls is to use lock as a context manager

```
with nidcpower.Session('dev1') as session:
    with session.lock():
        # Calls to session within a single lock context
```

The first *with* block ensures the session is closed regardless of any exceptions raised

The second *with* block ensures that unlock is called regardless of any exceptions raised

**Return type** context manager

**Returns** When used in a *with* statement, `nidcpower.Session.lock()` acts as a context manager and unlock will be called when the *with* block is exited

## measure

`nidcpower.Session.measure(measurement_type)`

Returns the measured value of either the voltage or current on the specified output channel. Each call to this method blocks other method calls until the hardware returns the **measurement**. To measure multiple output channels, use the `nidcpower.Session.measure_multiple()` method.

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].measure(measurement_type)
```

**Parameters** `measurement_type` (`nidcpower.MeasurementTypes`) – Specifies whether a voltage or current value is measured. **Defined Values:**

<i>VOLTAGE</i> (1)	The device measures voltage.
<i>CURRENT</i> (0)	The device measures current.

**Return type** float

**Returns** Returns the value of the measurement, either in volts for voltage or amps for current.

## measure\_multiple

`nidcpower.Session.measure_multiple()`

Returns a list of named tuples (Measurement) containing the measured voltage and current values on the specified output channel(s). Each call to this method blocks other method calls until the measurements are returned from the device. The order of the measurements returned in the array corresponds to the order on the specified output channel(s).

Fields in Measurement:

- **voltage** (float)
- **current** (float)
- **in\_compliance** (bool) - Always None

---

**Note:** This method is not supported on all devices. Refer to [Supported Methods by Device](#) for more information about supported devices.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].measure_multiple()
```

---

**Return type** list of Measurement

**Returns**

List of named tuples with fields:

- **voltage** (float)
- **current** (float)
- **in\_compliance** (bool) - Always None

## query\_in\_compliance

`nidcpower.Session.query_in_compliance()`

Queries the specified output device to determine if it is operating at the [compliance](#) limit.

The compliance limit is the current limit when the output method is set to [DC\\_VOLTAGE](#). If the output is operating at the compliance limit, the output reaches the current limit before the desired

voltage level. Refer to the `nidcpower.Session.ConfigureOutputFunction()` method and the `nidcpower.Session.ConfigureCurrentLimit()` method for more information about output method and current limit, respectively.

The compliance limit is the voltage limit when the output method is set to `DC_CURRENT`. If the output is operating at the compliance limit, the output reaches the voltage limit before the desired current level. Refer to the `nidcpower.Session.ConfigureOutputFunction()` method and the `nidcpower.Session.ConfigureVoltageLimit()` method for more information about output method and voltage limit, respectively.

#### Related Topics:

[Compliance](#)

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].query_in_compliance()
```

---

**Return type** `bool`

**Returns** Returns whether the device output channel is in compliance.

### query\_max\_current\_limit

`nidcpower.Session.query_max_current_limit(voltage_level)`

Queries the maximum current limit on an output channel if the output channel is set to the specified `voltageLevel`.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].query_max_current_limit(voltage_level)
```

---

**Parameters** `voltage_level` (*float*) – Specifies the voltage level to use when calculating the `maxCurrentLimit`.

**Return type** `float`

**Returns** Returns the maximum current limit that can be set with the specified `voltageLevel`.

## query\_max\_voltage\_level

`nidcpower.Session.query_max_voltage_level(current_limit)`

Queries the maximum voltage level on an output channel if the output channel is set to the specified **currentLimit**.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].query_max_voltage_level(current_limit)
```

---

**Parameters** **current\_limit** (*float*) – Specifies the current limit to use when calculating the **maxVoltageLevel**.

**Return type** *float*

**Returns** Returns the maximum voltage level that can be set on an output channel with the specified **currentLimit**.

## query\_min\_current\_limit

`nidcpower.Session.query_min_current_limit(voltage_level)`

Queries the minimum current limit on an output channel if the output channel is set to the specified **voltageLevel**.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].query_min_current_limit(voltage_level)
```

---

**Parameters** **voltage\_level** (*float*) – Specifies the voltage level to use when calculating the **minCurrentLimit**.

**Return type** *float*

**Returns** Returns the minimum current limit that can be set on an output channel with the specified **voltageLevel**.

## query\_output\_state

`nidcpower.Session.query_output_state(output_state)`

Queries the specified output channel to determine if the output channel is currently in the state specified by **outputState**.

**Related Topics:**

[Compliance](#)

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].query_output_state(output_state)
```

**Parameters** `output_state` (*`nidcpower.OutputStates`*) – Specifies the output state of the output channel that is being queried. **Defined Values:**

<i><code>VOLTAGE</code></i> (0)	The device maintains a constant voltage by adjusting the current.
<i><code>CURRENT</code></i> (1)	The device maintains a constant current by adjusting the voltage.

**Return type** `bool`

**Returns** Returns whether the device output channel is in the specified output state.

## read\_current\_temperature

```
nidcpower.Session.read_current_temperature()
```

Returns the current onboard **temperature**, in degrees Celsius, of the device.

**Return type** `float`

**Returns** Returns the onboard **temperature**, in degrees Celsius, of the device.

## reset

```
nidcpower.Session.reset()
```

Resets the device to a known state. This method disables power generation, resets session properties to their default values, commits the session properties, and leaves the session in the Uncommitted state. Refer to the [Programming States](#) topic for more information about NI-DCPower software states.

## reset\_device

```
nidcpower.Session.reset_device()
```

Resets the device to a known state. The method disables power generation, resets session properties to their default values, clears errors such as overtemperature and unexpected loss of auxiliary power, commits the session properties, and leaves the session in the Uncommitted state. This method also performs a hard reset on the device and driver software. This method has the same functionality as using `reset` in Measurement & Automation Explorer. Refer to the [Programming States](#) topic for more information about NI-DCPower software states.

This will also open the output relay on devices that have an output relay.

## reset\_with\_defaults

`nidcpower.Session.reset_with_defaults()`

Resets the device to a known state. This method disables power generation, resets session properties to their default values, commits the session properties, and leaves the session in the [Running](#) state. In addition to exhibiting the behavior of the `nidcpower.Session.reset()` method, this method can assign user-defined default values for configurable properties from the IVI configuration.

## self\_cal

`nidcpower.Session.self_cal()`

Performs a self-calibration upon the specified channel(s).

This method disables the output, performs several internal calculations, and updates calibration values. The updated calibration values are written to the device hardware if the `nidcpower.Session.self_calibration_persistence` property is set to `WRITE_TO_EEPROM`. Refer to the `nidcpower.Session.self_calibration_persistence` property topic for more information about the settings for this property.

When calling `nidcpower.Session.self_cal()` with the PXIe-4162/4163, specify all channels of your PXIe-4162/4163 with the `channelName` input. You cannot self-calibrate a subset of PXIe-4162/4163 channels.

Refer to the [Self-Calibration](#) topic for more information about this method.

### Related Topics:

[Self-Calibration](#)

---

**Note:** This method is not supported on all devices. Refer to [Supported Methods by Device](#) for more information about supported devices.

---

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].self_cal()
```

---

## self\_test

`nidcpower.Session.self_test()`

Performs the device self-test routine and returns the test result(s). Calling this method implicitly calls the `nidcpower.Session.reset()` method.

When calling `nidcpower.Session.self_test()` with the PXIe-4162/4163, specify all channels of your PXIe-4162/4163 with the `channels` input of `nidcpower.Session.__init__()`. You cannot self test a subset of PXIe-4162/4163 channels.

Raises `SelfTestError` on self test failure. Properties on exception object:

- `code` - failure code from driver



- message - status message from driver

Self-Test Code	Description
0	Self test passed.
1	Self test failed.

## send\_software\_edge\_trigger

`nidcpower.Session.send_software_edge_trigger(trigger)`

Asserts the specified trigger. This method can override an external edge trigger.

### Related Topics:

[Triggers](#)

---

**Note:** This method is not supported on all devices. Refer to [Supported Methods by Device](#) for more information about supported devices.

---

**Parameters** `trigger` (`nidcpower.SendSoftwareEdgeTriggerType`) – Specifies which trigger to assert. **Defined Values:**

NIDCPower_VAL_START_TRIGGER (1034)	Asserts the Start trigger.
NIDCPower_VAL_SOURCE_TRIGGER (1035)	Asserts the Source trigger.
NIDCPower_VAL_MEASURE_TRIGGER (1036)	Asserts the Measure trigger.
NIDCPower_VAL_SEQUENCE_ADVANCE_TRIGGER (1037)	Asserts the Sequence Advance trigger.
NIDCPower_VAL_PULSE_TRIGGER (1053)	Asserts the Pulse trigger.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## set\_sequence

`nidcpower.Session.set_sequence(values, source_delays)`

Configures a series of voltage or current outputs and corresponding source delays. The source mode must be set to [Sequence](#) for this method to take effect.

Refer to the [Configuring the Source Unit](#) topic in the *NI DC Power Supplies and SMUs Help* for more information about how to configure your device.

Use this method in the Uncommitted or Committed programming states. Refer to the [Programming States](#) topic in the *NI DC Power Supplies and SMUs Help* for more information about NI-DCPower programming states.

---

**Note:** This method is not supported on all devices. Refer to [Supported Methods by Device](#) for more information about supported devices.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nidcpower.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nidcpower.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].set_sequence(values, source_delays)
```

---

#### Parameters

- **values** (*list of float*) – Specifies the series of voltage levels or current levels, depending on the configured [output method](#). **Valid values:** The valid values for this parameter are defined by the voltage level range or current level range.
- **source\_delays** (*list of float*) – Specifies the source delay that follows the configuration of each value in the sequence. **Valid Values:** The valid values are between 0 and 167 seconds.

### unlock

```
nidcpower.Session.unlock()
```

Releases a lock that you acquired on an device session using `nidcpower.Session.lock()`. Refer to `nidcpower.Session.unlock()` for additional information on session locks.

### wait\_for\_event

```
nidcpower.Session.wait_for_event(event_id, timeout=datetime.timedelta(seconds=10.0))
```

Waits until the device has generated the specified event.

The session monitors whether each type of event has occurred at least once since the last time this method or the `nidcpower.Session.initiate()` method were called. If an event has only been generated once and you call this method successively, the method times out. Individual events must be generated between separate calls of this method.

---

**Note:** Refer to [Supported Methods by Device](#) for more information about supported devices.

---

#### Parameters

- **event\_id** (`nidcpower.Event`) – Specifies which event to wait for. **Defined Values:**

NIDCPOWER_VAL_SOURCE_COMPLETE_EVENT (1030)	Waits for the Source Complete event.
NIDCPOWER_VAL_MEASURE_COMPLETE_EVENT (1031)	Waits for the Measure Complete event.
NIDCPOWER_VAL_SEQUENCE_ITERATION_COMPLETE_EVENT (1032)	Waits for the Sequence Iteration Complete event.
NIDCPOWER_VAL_SEQUENCE_ENGINE_DONE_EVENT (1033)	Waits for the Sequence Engine Done event.
NIDCPOWER_VAL_PULSE_COMPLETE_EVENT (1051)	Waits for the Pulse Complete event.
NIDCPOWER_VAL_READY_FOR_PULSE_TRIGGER_EVENT (1052)	Waits for the Ready for Pulse Trigger event.

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

- **timeout** (*float in seconds or `datetime.timedelta`*) – Specifies the maximum time allowed for this method to complete, in seconds. If the method does not complete within this time interval, NI-DCPower returns an error.

**Note:** When setting the timeout interval, ensure you take into account any triggers so that the timeout interval is long enough for your application.

## Properties

Property	Datatype
<code>nidcpower.Session.aperture_time</code>	float
<code>nidcpower.Session.aperture_time_units</code>	ApertureTimeUnits
<code>nidcpower.Session.auto_zero</code>	AutoZero
<code>nidcpower.Session.auxiliary_power_source_available</code>	bool
<code>nidcpower.Session.channel_count</code>	int
<code>nidcpower.Session.compliance_limit_symmetry</code>	ComplianceLimitSymmetry
<code>nidcpower.Session.current_compensation_frequency</code>	float
<code>nidcpower.Session.current_gain_bandwidth</code>	float
<code>nidcpower.Session.current_level</code>	float
<code>nidcpower.Session.current_level_autorange</code>	bool
<code>nidcpower.Session.current_level_range</code>	float
<code>nidcpower.Session.current_limit</code>	float
<code>nidcpower.Session.current_limit_autorange</code>	bool
<code>nidcpower.Session.current_limit_high</code>	float
<code>nidcpower.Session.current_limit_low</code>	float
<code>nidcpower.Session.current_limit_range</code>	float
<code>nidcpower.Session.current_pole_zero_ratio</code>	float
<code>nidcpower.Session.dc_noise_rejection</code>	DCNoiseRejection
<code>nidcpower.Session.digital_edge_measure_trigger_input_terminal</code>	str
<code>nidcpower.Session.digital_edge_pulse_trigger_input_terminal</code>	str

Continued on

Table 2 – continued from previous page

Property	Datatype
<code>nidcpower.Session.digital_edge_sequence_advance_trigger_input_terminal</code>	str
<code>nidcpower.Session.digital_edge_source_trigger_input_terminal</code>	str
<code>nidcpower.Session.digital_edge_start_trigger_input_terminal</code>	str
<code>nidcpower.Session.driver_setup</code>	str
<code>nidcpower.Session.exported_measure_trigger_output_terminal</code>	str
<code>nidcpower.Session.exported_pulse_trigger_output_terminal</code>	str
<code>nidcpower.Session.exported_sequence_advance_trigger_output_terminal</code>	str
<code>nidcpower.Session.exported_source_trigger_output_terminal</code>	str
<code>nidcpower.Session.exported_start_trigger_output_terminal</code>	str
<code>nidcpower.Session.fetch_backlog</code>	int
<code>nidcpower.Session.instrument_firmware_revision</code>	str
<code>nidcpower.Session.instrument_manufacturer</code>	str
<code>nidcpower.Session.instrument_model</code>	str
<code>nidcpower.Session.interlock_input_open</code>	bool
<code>nidcpower.Session.io_resource_descriptor</code>	str
<code>nidcpower.Session.logical_name</code>	str
<code>nidcpower.Session.measure_buffer_size</code>	int
<code>nidcpower.Session.measure_complete_event_delay</code>	float in seconds or datetime
<code>nidcpower.Session.measure_complete_event_output_terminal</code>	str
<code>nidcpower.Session.measure_complete_event_pulse_polarity</code>	Polarity
<code>nidcpower.Session.measure_complete_event_pulse_width</code>	float
<code>nidcpower.Session.measure_record_delta_time</code>	float in seconds or datetime
<code>nidcpower.Session.measure_record_length</code>	int
<code>nidcpower.Session.measure_record_length_is_finite</code>	bool
<code>nidcpower.Session.measure_trigger_type</code>	TriggerType
<code>nidcpower.Session.measure_when</code>	MeasureWhen
<code>nidcpower.Session.output_capacitance</code>	OutputCapacitance
<code>nidcpower.Session.output_connected</code>	bool
<code>nidcpower.Session.output_enabled</code>	bool
<code>nidcpower.Session.output_function</code>	OutputFunction
<code>nidcpower.Session.output_resistance</code>	float
<code>nidcpower.Session.overranging_enabled</code>	bool
<code>nidcpower.Session.ovp_enabled</code>	bool
<code>nidcpower.Session.ovp_limit</code>	float
<code>nidcpower.Session.power_line_frequency</code>	float
<code>nidcpower.Session.power_source</code>	PowerSource
<code>nidcpower.Session.power_source_in_use</code>	PowerSourceInUse
<code>nidcpower.Session.pulse_bias_current_level</code>	float
<code>nidcpower.Session.pulse_bias_current_limit</code>	float
<code>nidcpower.Session.pulse_bias_current_limit_high</code>	float
<code>nidcpower.Session.pulse_bias_current_limit_low</code>	float
<code>nidcpower.Session.pulse_bias_delay</code>	float
<code>nidcpower.Session.pulse_bias_voltage_level</code>	float
<code>nidcpower.Session.pulse_bias_voltage_limit</code>	float
<code>nidcpower.Session.pulse_bias_voltage_limit_high</code>	float
<code>nidcpower.Session.pulse_bias_voltage_limit_low</code>	float
<code>nidcpower.Session.pulse_complete_event_output_terminal</code>	str
<code>nidcpower.Session.pulse_complete_event_pulse_polarity</code>	Polarity
<code>nidcpower.Session.pulse_complete_event_pulse_width</code>	float

Continued on

Table 2 – continued from previous page

Property	Datatype
<code>nidcpower.Session.pulse_current_level</code>	float
<code>nidcpower.Session.pulse_current_level_range</code>	float
<code>nidcpower.Session.pulse_current_limit</code>	float
<code>nidcpower.Session.pulse_current_limit_high</code>	float
<code>nidcpower.Session.pulse_current_limit_low</code>	float
<code>nidcpower.Session.pulse_current_limit_range</code>	float
<code>nidcpower.Session.pulse_off_time</code>	float in seconds or datetime
<code>nidcpower.Session.pulse_on_time</code>	float in seconds or datetime
<code>nidcpower.Session.pulse_trigger_type</code>	TriggerType
<code>nidcpower.Session.pulse_voltage_level</code>	float
<code>nidcpower.Session.pulse_voltage_level_range</code>	float
<code>nidcpower.Session.pulse_voltage_limit</code>	float
<code>nidcpower.Session.pulse_voltage_limit_high</code>	float
<code>nidcpower.Session.pulse_voltage_limit_low</code>	float
<code>nidcpower.Session.pulse_voltage_limit_range</code>	float
<code>nidcpower.Session.query_instrument_status</code>	bool
<code>nidcpower.Session.ready_for_pulse_trigger_event_output_terminal</code>	str
<code>nidcpower.Session.ready_for_pulse_trigger_event_pulse_polarity</code>	Polarity
<code>nidcpower.Session.ready_for_pulse_trigger_event_pulse_width</code>	float
<code>nidcpower.Session.reset_average_before_measurement</code>	bool
<code>nidcpower.Session.samples_to_average</code>	int
<code>nidcpower.Session.self_calibration_persistence</code>	SelfCalibrationPersistence
<code>nidcpower.Session.sense</code>	Sense
<code>nidcpower.Session.sequence_advance_trigger_type</code>	TriggerType
<code>nidcpower.Session.sequence_engine_done_event_output_terminal</code>	str
<code>nidcpower.Session.sequence_engine_done_event_pulse_polarity</code>	Polarity
<code>nidcpower.Session.sequence_engine_done_event_pulse_width</code>	float
<code>nidcpower.Session.sequence_iteration_complete_event_output_terminal</code>	str
<code>nidcpower.Session.sequence_iteration_complete_event_pulse_polarity</code>	Polarity
<code>nidcpower.Session.sequence_iteration_complete_event_pulse_width</code>	float
<code>nidcpower.Session.sequence_loop_count</code>	int
<code>nidcpower.Session.sequence_loop_count_is_finite</code>	bool
<code>nidcpower.Session.simulate</code>	bool
<code>nidcpower.Session.source_complete_event_output_terminal</code>	str
<code>nidcpower.Session.source_complete_event_pulse_polarity</code>	Polarity
<code>nidcpower.Session.source_complete_event_pulse_width</code>	float
<code>nidcpower.Session.source_delay</code>	float in seconds or datetime
<code>nidcpower.Session.source_mode</code>	SourceMode
<code>nidcpower.Session.source_trigger_type</code>	TriggerType
<code>nidcpower.Session.specific_driver_description</code>	str
<code>nidcpower.Session.specific_driver_prefix</code>	str
<code>nidcpower.Session.specific_driver_revision</code>	str
<code>nidcpower.Session.specific_driver_vendor</code>	str
<code>nidcpower.Session.start_trigger_type</code>	TriggerType
<code>nidcpower.Session.supported_instrument_models</code>	str
<code>nidcpower.Session.transient_response</code>	TransientResponse
<code>nidcpower.Session.voltage_compensation_frequency</code>	float
<code>nidcpower.Session.voltage_gain_bandwidth</code>	float
<code>nidcpower.Session.voltage_level</code>	float

Continued on

Table 2 – continued from previous page

Property	Datatype
<code>nidcpower.Session.voltage_level_autorange</code>	bool
<code>nidcpower.Session.voltage_level_range</code>	float
<code>nidcpower.Session.voltage_limit</code>	float
<code>nidcpower.Session.voltage_limit_autorange</code>	bool
<code>nidcpower.Session.voltage_limit_high</code>	float
<code>nidcpower.Session.voltage_limit_low</code>	float
<code>nidcpower.Session.voltage_limit_range</code>	float
<code>nidcpower.Session.voltage_pole_zero_ratio</code>	float

## Methods

Method name
<code>nidcpower.Session.abort()</code>
<code>nidcpower.Session.commit()</code>
<code>nidcpower.Session.configure_aperture_time()</code>
<code>nidcpower.Session.disable()</code>
<code>nidcpower.Session.fetch_multiple()</code>
<code>nidcpower.Session.get_channel_name()</code>
<code>nidcpower.Session.get_ext_cal_last_date_and_time()</code>
<code>nidcpower.Session.get_ext_cal_last_temp()</code>
<code>nidcpower.Session.get_ext_cal_recommended_interval()</code>
<code>nidcpower.Session.get_self_cal_last_date_and_time()</code>
<code>nidcpower.Session.get_self_cal_last_temp()</code>
<code>nidcpower.Session.lock()</code>
<code>nidcpower.Session.measure()</code>
<code>nidcpower.Session.measure_multiple()</code>
<code>nidcpower.Session.query_in_compliance()</code>
<code>nidcpower.Session.query_max_current_limit()</code>
<code>nidcpower.Session.query_max_voltage_level()</code>
<code>nidcpower.Session.query_min_current_limit()</code>
<code>nidcpower.Session.query_output_state()</code>
<code>nidcpower.Session.read_current_temperature()</code>
<code>nidcpower.Session.reset()</code>
<code>nidcpower.Session.reset_device()</code>
<code>nidcpower.Session.reset_with_defaults()</code>
<code>nidcpower.Session.self_cal()</code>
<code>nidcpower.Session.self_test()</code>
<code>nidcpower.Session.send_software_edge_trigger()</code>
<code>nidcpower.Session.set_sequence()</code>
<code>nidcpower.Session.unlock()</code>
<code>nidcpower.Session.wait_for_event()</code>

### 7.1.3.2 Enums

Enums used in NI-DCPower

## ApertureTimeUnits

```
class nidcpower.ApertureTimeUnits
```

### SECONDS

Specifies aperture time in seconds.

### POWER\_LINE\_CYCLES

Specifies aperture time in power line cycles (PLCs).

## AutoZero

```
class nidcpower.AutoZero
```

### OFF

Disables auto zero.

### ON

Makes zero conversions for every measurement.

### ONCE

Makes zero conversions following the first measurement after initiating the device. The device uses these zero conversions for the preceding measurement and future measurements until the device is reinitiated.

## ComplianceLimitSymmetry

```
class nidcpower.ComplianceLimitSymmetry
```

### SYMMETRIC

Compliance limits are specified symmetrically about 0.

### ASYMMETRIC

Compliance limits can be specified asymmetrically with respect to 0.

## DCNoiseRejection

```
class nidcpower.DCNoiseRejection
```

### SECOND\_ORDER

Second-order rejection of DC noise.

### NORMAL

Normal rejection of DC noise.

## Event

```
class nidcpower.Event
```

### SOURCE\_COMPLETE

**MEASURE\_COMPLETE**  
**SEQUENCE\_ITERATION\_COMPLETE**  
**SEQUENCE\_ENGINE\_DONE**  
**PULSE\_COMPLETE**  
**READY\_FOR\_PULSE\_TRIGGER**

## MeasureWhen

**class** `nidcpower.MeasureWhen`

**AUTOMATICALLY\_AFTER\_SOURCE\_COMPLETE**  
 Acquires a measurement after each Source Complete event completes.

**ON\_DEMAND**  
 Acquires a measurement when the `nidcpower.Session.measure()` method or `nidcpower.Session.measure_multiple()` method is called.

**ON\_MEASURE\_TRIGGER**  
 Acquires a measurement when a Measure trigger is received.

## MeasurementTypes

**class** `nidcpower.MeasurementTypes`

**CURRENT**  
 The device measures current.

**VOLTAGE**  
 The device measures voltage.

## OutputCapacitance

**class** `nidcpower.OutputCapacitance`

**LOW**  
 Output Capacitance is low.

**HIGH**  
 Output Capacitance is high.

## OutputFunction

**class** `nidcpower.OutputFunction`

**DC\_VOLTAGE**  
 Sets the output method to DC voltage.

**DC\_CURRENT**  
 Sets the output method to DC current.



**PULSE\_VOLTAGE**

Sets the output method to pulse voltage.

**PULSE\_CURRENT**

Sets the output method to pulse current.

## OutputStates

```
class nidcpower.OutputStates
```

**VOLTAGE**

The device maintains a constant voltage by adjusting the current

**CURRENT**

The device maintains a constant current by adjusting the voltage.

## Polarity

```
class nidcpower.Polarity
```

**HIGH**

A high pulse occurs when the event is generated. The exported signal is low level both before and after the event is generated.

**LOW**

A low pulse occurs when the event is generated. The exported signal is high level both before and after the event is generated.

## PowerSource

```
class nidcpower.PowerSource
```

**INTERNAL**

Uses the PXI chassis power source.

**AUXILIARY**

Uses the auxiliary power source connected to the device.

**AUTOMATIC**

Uses the auxiliary power source if it is available; otherwise uses the PXI chassis power source.

## PowerSourceInUse

```
class nidcpower.PowerSourceInUse
```

**INTERNAL**

Uses the PXI chassis power source.

#### **AUXILIARY**

Uses the auxiliary power source connected to the device. Only the NI PXI-4110, NI PXIe-4112, NI PXIe-4113, and NI PXI-4130 support this value. This is the only supported value for the NI PXIe-4112 and NI PXIe-4113.

### **SelfCalibrationPersistence**

```
class nidcpower.SelfCalibrationPersistence
```

#### **KEEP\_IN\_MEMORY**

Keep new self calibration values in memory only.

#### **WRITE\_TO\_EEPROM**

Write new self calibration values to hardware.

### **SendSoftwareEdgeTriggerType**

```
class nidcpower.SendSoftwareEdgeTriggerType
```

#### **START**

#### **SOURCE**

#### **MEASURE**

#### **SEQUENCE\_ADVANCE**

#### **PULSE**

### **Sense**

```
class nidcpower.Sense
```

#### **LOCAL**

Local sensing is selected.

#### **REMOTE**

Remote sensing is selected.

### **SourceMode**

```
class nidcpower.SourceMode
```

#### **SINGLE\_POINT**

The source unit applies a single source configuration.

#### **SEQUENCE**

The source unit applies a list of voltage or current configurations sequentially.

## TransientResponse

**class** `nidcpower.TransientResponse`

### **NORMAL**

The output responds to changes in load at a normal speed.

### **FAST**

The output responds to changes in load quickly.

### **SLOW**

The output responds to changes in load slowly.

### **CUSTOM**

The output responds to changes in load based on specified values.

## TriggerType

**class** `nidcpower.TriggerType`

### **NONE**

No trigger is configured.

### **DIGITAL\_EDGE**

The data operation starts when a digital edge is detected.

### **SOFTWARE\_EDGE**

The data operation starts when a software trigger occurs.

## 7.1.3.3 Exceptions and Warnings

### DriverError

**exception** `nidcpower.DriverError`

An error originating from the NI-DCPower driver

### UnsupportedConfigurationError

**exception** `nidcpower.UnsupportedConfigurationError`

An error due to using this module in an unsupported platform.

### DriverNotInstalledError

**exception** `nidcpower.DriverNotInstalledError`

An error due to using this module without the driver runtime installed.

### InvalidRepeatedCapabilityError

**exception** `nidcpower.InvalidRepeatedCapabilityError`

An error due to an invalid character in a repeated capability

## SelfTestError

**exception** `nidcpower.SelfTestError`  
 An error due to a failed self-test

## DriverWarning

**exception** `nidcpower.DriverWarning`  
 A warning originating from the NI-DCPower driver

### 7.1.3.4 Examples

#### `nidcpower_measure_record.py`

Listing 1: (`nidcpower_measure_record.py`)

```

1  #!/usr/bin/python
2
3  import argparse
4  import nidcpower
5  import sys
6
7
8  def example(resource_name, channels, options, voltage, length):
9      with nidcpower.Session(resource_name=resource_name, channels=channels,
10         ↪options=options) as session:
11
12         # Configure the session.
13         session.measure_record_length = length
14         session.measure_record_length_is_finite = True
15         session.measure_when = nidcpower.MeasureWhen.AUTOMATICALLY_AFTER_SOURCE_
16         ↪COMPLETE
17         session.voltage_level = voltage
18
19         session.commit()
20         print('Effective measurement rate: {0} S/s'.format(session.measure_record_
21         ↪delta_time / 1))
22
23         samples_acquired = 0
24         print(' #      Voltage      Current      In Compliance')
25         row_format = '{0:3d}:    {1:8.6f}    {2:8.6f}    {3}'
26         with session.initiate():
27             while samples_acquired < length:
28                 measurements = session.fetch_multiple(count=session.fetch_backlog)
29                 samples_acquired += len(measurements)
30                 for i in range(len(measurements)):
31                     print(row_format.format(i, measurements[i].voltage,
32                     ↪measurements[i].current, measurements[i].in_compliance))
33
34 def _main(argv):
35     parser = argparse.ArgumentParser(description='Outputs the specified voltage, then_
36     ↪takes the specified number of voltage and current readings.', formatter_
37     ↪class=argparse.ArgumentDefaultsHelpFormatter)

```

(continues on next page)

(continued from previous page)

```

33     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
↳ name of a National Instruments SMU')
34     parser.add_argument('-c', '--channels', default='0', help='Channel(s) to use')
35     parser.add_argument('-l', '--length', default='20', type=int, help='Measure_
↳ record length')
36     parser.add_argument('-v', '--voltage', default=5.0, type=float, help='Voltage_
↳ level (V)')
37     parser.add_argument('-op', '--option-string', default='', type=str, help='Option_
↳ string')
38     args = parser.parse_args(argv)
39     example(args.resource_name, args.channels, args.option_string, args.voltage, args.
↳ length)
40
41
42 def main():
43     _main(sys.argv[1:])
44
45
46 def test_example():
47     options = {'simulate': True, 'driver_setup': {'Model': '4162', 'BoardType': 'PXIe
↳ ', }, }
48     example('PXI1Slot2', '0', options, 5.0, 20)
49
50
51 def test_main():
52     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:4162; BoardType:PXIe
↳ ', ]
53     _main(cmd_line)
54
55
56 if __name__ == '__main__':
57     main()
58
59

```

## nidcpower\_source\_delay\_measure.py

Listing 2: (nidcpower\_source\_delay\_measure.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import datetime
5  import nidcpower
6  import sys
7
8
9  def print_fetched_measurements(measurements):
10     print('          Voltage : {:f} V'.format(measurements[0].voltage))
11     print('          Current: {:f} A'.format(measurements[0].current))
12     print('          In compliance: {0}'.format(measurements[0].in_compliance))
13
14
15 def example(resource_name, channels, options, voltage1, voltage2, delay):

```

(continues on next page)

(continued from previous page)

```

16     timeout = datetime.timedelta(seconds=(delay + 1.0))
17
18     with nidcpower.Session(resource_name=resource_name, channels=channels,
19 ↪options=options) as session:
20
21         # Configure the session.
22         session.source_mode = nidcpower.SourceMode.SINGLE_POINT
23         session.output_function = nidcpower.OutputFunction.DC_VOLTAGE
24         session.current_limit = .06
25         session.voltage_level_range = 5.0
26         session.current_limit_range = .06
27         session.source_delay = datetime.timedelta(seconds=delay)
28         session.measure_when = nidcpower.MeasureWhen.AUTOMATICALLY_AFTER_SOURCE_
29 ↪COMPLETE
30         session.voltage_level = voltage1
31
32         with session.initiate():
33             print('Voltage 1:')
34             print_fetched_measurements(session.fetch_multiple(count=1,
35 ↪timeout=timeout))
36             session.voltage_level = voltage2 # on-the-fly set
37             print('Voltage 2:')
38             print_fetched_measurements(session.fetch_multiple(count=1,
39 ↪timeout=timeout))
40             session.output_enabled = False
41
42 def _main(argv):
43     parser = argparse.ArgumentParser(description='Outputs voltage 1, waits for source_
44 ↪delay, and then takes a measurement. Then orepeat with voltage 2.', formatter_
45 ↪class=argparse.ArgumentDefaultsHelpFormatter)
46     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
47 ↪name of a National Instruments SMU')
48     parser.add_argument('-c', '--channels', default='0', help='Channel(s) to use')
49     parser.add_argument('-v1', '--voltage1', default=1.0, type=float, help='Voltage_
50 ↪level 1 (V)')
51     parser.add_argument('-v2', '--voltage2', default=2.0, type=float, help='Voltage_
52 ↪level 2 (V)')
53     parser.add_argument('-d', '--delay', default=0.05, type=float, help='Source delay_
54 ↪(s)')
55     parser.add_argument('-op', '--option-string', default='', type=str, help='Option_
56 ↪string')
57     args = parser.parse_args(argv)
58     example(args.resource_name, args.channels, args.option_string, args.voltage1,
59 ↪args.voltage2, args.delay)
60
61 def main():
62     _main(sys.argv[1:])
63
64 def test_main():
65     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:4162; BoardType:PXIe
66 ↪', ]
67     _main(cmd_line)

```

(continues on next page)

(continued from previous page)

```

60 def test_example():
61     options = {'simulate': True, 'driver_setup': {'Model': '4162', 'BoardType': 'PXIe
    ↪', }, }, }
62     example('PXI1Slot2', '0', options, 1.0, 2.0, 0.05)
63
64
65 if __name__ == '__main__':
66     main()
67
68

```

## 7.2 nidmm module

### 7.2.1 Installation

As a prerequisite to using the `nidmm` module, you must install the NI-DMM runtime on your system. Visit [ni.com/downloads](https://ni.com/downloads) to download the driver runtime for your devices.

The `nimi-python` modules (i.e. for **NI-DMM**) can be installed with `pip`:

```
$ python -m pip install nidmm~=1.0.0
```

Or `easy_install` from `setuptools`:

```
$ python -m easy_install nidmm
```

### 7.2.2 Usage

The following is a basic example of using the **nidmm** module to open a session to a DMM and perform a 5.5 digits of resolution voltage measurement in the 10 V range.

```

import nidmm
with nidmm.Session("Dev1") as session:
    session.configureMeasurementDigits(nidmm.Function.DC_VOLTS, 10, 5.5)
    print("Measurement: " + str(session.read()))

```

Additional examples for NI-DMM are located in `src/nidmm/examples/` directory.

### 7.2.3 API Reference

#### 7.2.3.1 nidmm.Session

**class** `nidmm.Session` (*self*, *resource\_name*, *id\_query=False*, *reset\_device=False*, *options={}*)

This method completes the following tasks:

- Creates a new IVI instrument driver session and, optionally, sets the initial state of the following session properties: `nidmm.Session.range_check`, `nidmm.Session.QUERY_INSTR_STATUS`, `nidmm.Session.cache`, `nidmm.Session.simulate`, `nidmm.Session.record_coercions`.

- Opens a session to the device you specify for the **Resource\_Name** parameter. If the **ID\_Query** parameter is set to True, this method queries the instrument ID and checks that it is valid for this instrument driver.
- If the **Reset\_Device** parameter is set to True, this method resets the instrument to a known state. Sends initialization commands to set the instrument to the state necessary for the operation of the instrument driver.
- Returns a ViSession handle that you use to identify the instrument in all subsequent instrument driver method calls.

---

**Note:** One or more of the referenced properties are not in the Python API for this driver.

---

### Parameters

- **resource\_name** (*str*) –

**Caution:** All IVI names for the **Resource\_Name**, such as logical names or virtual names, are case-sensitive. If you use logical names, driver session names, or virtual names in your program, you must make sure that the name you use matches the name in the IVI Configuration Store file exactly, without any variations in the case of the characters in the name.

Contains the **resource\_name** of the device to initialize. The **resource\_name** is assigned in Measurement & Automation Explorer (MAX). Refer to [Related Documentation](#) for the *NI Digital Multimeters Getting Started Guide* for more information about configuring and testing the DMM in MAX.

Valid Syntax:

- NI-DAQmx name
  - DAQ::NI-DAQmx name[::INSTR]
  - DAQ::Traditional NI-DAQ device number[::INSTR]
  - IVI logical name
- **id\_query** (*bool*) – Verifies that the device you initialize is one that the driver supports. NI-DMM automatically performs this query, so setting this parameter is not necessary. Defined Values:

True (default)	1	Perform ID Query
False	0	Skip ID Query

- **reset\_device** (*bool*) – Specifies whether to reset the instrument during the initialization procedure. Defined Values:

True (default)	1	Reset Device
False	0	Don't Reset

- **options** (*str*) – Specifies the initial value of certain properties for the session. The syntax for **options** is a dictionary of properties with an assigned value. For example:



```
{ 'simulate': False }
```

You do not have to specify a value for all the properties. If you do not specify a value for a property, the default value is used.

Advanced Example: { 'simulate': True, 'driver\_setup': { 'Model': '<model number>', 'BoardType': '<type>' } }

Property	Default
range_check	True
query_instrument_status	False
cache	True
simulate	False
record_value_coersions	False
driver_setup	{}

## Properties

Property	Datatype
<i>ac_max_freq</i>	float
<i>ac_min_freq</i>	float
<i>adc_calibration</i>	<i>ADCCalibration</i>
<i>aperture_time</i>	float
<i>aperture_time_units</i>	<i>ApertureTimeUnits</i>
<i>auto_range_value</i>	float
<i>auto_zero</i>	<i>AutoZero</i>
<i>buffer_size</i>	int
<i>cable_comp_type</i>	<i>CableCompensationType</i>
<i>channel_count</i>	int
<i>current_source</i>	float
<i>dc_bias</i>	bool
<i>dc_noise_rejection</i>	<i>DCNoiseRejection</i>
<i>driver_setup</i>	str
<i>freq_voltage_auto_range</i>	float
<i>freq_voltage_range</i>	float
<i>function</i>	<i>Function</i>
<i>input_resistance</i>	float
<i>instrument_firmware_revision</i>	str
<i>instrument_manufacturer</i>	str
<i>instrument_model</i>	str
<i>instrument_product_id</i>	int
<i>io_resource_descriptor</i>	str
<i>lc_calculation_model</i>	<i>LCCalculationModel</i>
<i>lc_number_meas_to_average</i>	int
<i>logical_name</i>	str
<i>meas_complete_dest</i>	<i>MeasurementCompleteDest</i>
<i>number_of_averages</i>	int
<i>offset_comp_ohms</i>	bool
<i>open_cable_comp_conductance</i>	float
<i>open_cable_comp_susceptance</i>	float
<i>operation_mode</i>	<i>OperationMode</i>
<i>powerline_freq</i>	float

Continued on next page

Table 3 – continued from previous page

Property	Datatype
<i>range</i>	float
<i>resolution_absolute</i>	float
<i>resolution_digits</i>	float
<i>sample_count</i>	int
<i>sample_interval</i>	float in seconds or datetime.timedelta
<i>sample_trigger</i>	<i>SampleTrigger</i>
<i>serial_number</i>	str
<i>settle_time</i>	float in seconds or datetime.timedelta
<i>short_cable_comp_reactance</i>	float
<i>short_cable_comp_resistance</i>	float
<i>simulate</i>	bool
<i>specific_driver_description</i>	str
<i>specific_driver_major_version</i>	int
<i>specific_driver_minor_version</i>	int
<i>specific_driver_revision</i>	str
<i>specific_driver_vendor</i>	str
<i>supported_instrument_models</i>	str
<i>temp_rtd_a</i>	float
<i>temp_rtd_b</i>	float
<i>temp_rtd_c</i>	float
<i>temp_rtd_res</i>	float
<i>temp_rtd_type</i>	<i>RTDType</i>
<i>temp_tc_fixed_ref_junc</i>	float
<i>temp_tc_ref_junc_type</i>	<i>ThermocoupleReferenceJunctionType</i>
<i>temp_tc_type</i>	<i>ThermocoupleType</i>
<i>temp_thermistor_a</i>	float
<i>temp_thermistor_b</i>	float
<i>temp_thermistor_c</i>	float
<i>temp_thermistor_type</i>	<i>ThermistorType</i>
<i>temp_transducer_type</i>	<i>TransducerType</i>
<i>trigger_count</i>	int
<i>trigger_delay</i>	float in seconds or datetime.timedelta
<i>trigger_source</i>	<i>TriggerSource</i>
<i>waveform_coupling</i>	<i>WaveformCoupling</i>
<i>waveform_points</i>	int
<i>waveform_rate</i>	float

## Public methods

Method name
<i>abort()</i>
<i>configure_measurement_absolute()</i>
<i>configure_measurement_digits()</i>
<i>configure_multi_point()</i>
<i>configure_rtd_custom()</i>
<i>configure_rtd_type()</i>
<i>configure_thermistor_custom()</i>
<i>configure_thermocouple()</i>
<i>configure_trigger()</i>

Continued on next page

Table 4 – continued from previous page

Method name
<code>configure_waveform_acquisition()</code>
<code>disable()</code>
<code>fetch()</code>
<code>fetch_multi_point()</code>
<code>fetch_waveform()</code>
<code>fetch_waveform_into()</code>
<code>get_cal_date_and_time()</code>
<code>get_dev_temp()</code>
<code>get_ext_cal_recommended_interval()</code>
<code>get_last_cal_temp()</code>
<code>get_self_cal_supported()</code>
<code>lock()</code>
<code>perform_open_cable_comp()</code>
<code>perform_short_cable_comp()</code>
<code>read()</code>
<code>read_multi_point()</code>
<code>read_status()</code>
<code>read_waveform()</code>
<code>reset()</code>
<code>reset_with_defaults()</code>
<code>self_cal()</code>
<code>self_test()</code>
<code>send_software_trigger()</code>
<code>unlock()</code>

## Properties

### ac\_max\_freq

`nidmm.Session.ac_max_freq`

Specifies the maximum frequency component of the input signal for AC measurements. This property is used only for error checking and verifies that the value of this parameter is less than the maximum frequency of the device. This property affects the DMM only when you set the `nidmm.Session.method` property to AC measurements. The valid range is 1 Hz-300 kHz for the NI 4070/4071/4072, 10 Hz-100 kHz for the NI 4065, and 20 Hz-25 kHz for the NI 4050 and NI 4060.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Max Frequency**
- C Attribute: **NIDMM\_ATTR\_AC\_MAX\_FREQ**

## ac\_min\_freq

`nidmm.Session.ac_min_freq`

Specifies the minimum frequency component of the input signal for AC measurements. This property affects the DMM only when you set the `nidmm.Session.method` property to AC measurements. The valid range is 1 Hz-300 kHz for the NI 4070/4071/4072, 10 Hz-100 kHz for the NI 4065, and 20 Hz-25 kHz for the NI 4050 and NI 4060.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Min Frequency**
  - C Attribute: **NIDMM\_ATTR\_AC\_MIN\_FREQ**
- 

## adc\_calibration

`nidmm.Session.adc_calibration`

For the NI 4070/4071/4072 only, specifies the ADC calibration mode.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.ADCCalibration
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:ADC Calibration**
  - C Attribute: **NIDMM\_ATTR\_ADC\_CALIBRATION**
- 

## aperture\_time

`nidmm.Session.aperture_time`

Specifies the measurement aperture time for the current configuration. Aperture time is specified in units set by `nidmm.Session.aperture_time_units`. To override the default aperture, set this property to the desired aperture time after calling `nidmm.Session.ConfigureMeasurement()`. To return to the default, set this property to `NIDMM_VAL_APERTURE_TIME_AUTO` (-1). On the NI 4070/4071/4072, the minimum aperture

time is 8.89 usec, and the maximum aperture time is 149 sec. Any number of powerline cycles (PLCs) within the minimum and maximum ranges is allowed on the NI 4070/4071/4072. On the NI 4065 the minimum aperture time is 333  $\mu$ s, and the maximum aperture time is 78.2 s. If setting the number of averages directly, the total measurement time is aperture time X the number of averages, which must be less than 72.8 s. The aperture times allowed are 333  $\mu$ s, 667  $\mu$ s, or multiples of 1.11 ms—for example 1.11 ms, 2.22 ms, 3.33 ms, and so on. If you set an aperture time other than 333  $\mu$ s, 667  $\mu$ s, or multiples of 1.11 ms, the value will be coerced up to the next supported aperture time. On the NI 4060, when the powerline frequency is 60 Hz, the PLCs allowed are 1 PLC, 6 PLC, 12 PLC, and 120 PLC. When the powerline frequency is 50 Hz, the PLCs allowed are 1 PLC, 5 PLC, 10 PLC, and 100 PLC.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Advanced:Aperture Time**
  - C Attribute: **NIDMM\_ATTR\_APERTURE\_TIME**
- 

## aperture\_time\_units

`nidmm.Session.aperture_time_units`

Specifies the units of aperture time for the current configuration. The NI 4060 does not support an aperture time set in seconds.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.ApertureTimeUnits
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Advanced:Aperture Time Units**
- C Attribute: **NIDMM\_ATTR\_APERTURE\_TIME\_UNITS**

## auto\_range\_value

`nidmm.Session.auto_range_value`

Specifies the value of the range. If auto ranging, shows the actual value of the active range. The value of this property is set during a read operation.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Auto Range Value**
  - C Attribute: **NIDMM\_ATTR\_AUTO\_RANGE\_VALUE**
- 

## auto\_zero

`nidmm.Session.auto_zero`

Specifies the AutoZero mode. The NI 4050 is not supported.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.AutoZero
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Auto Zero**
  - C Attribute: **NIDMM\_ATTR\_AUTO\_ZERO**
- 

## buffer\_size

`nidmm.Session.buffer_size`

Size in samples of the internal data buffer. Maximum is 134,217,727 (0X7FFFFFFF) samples. When set to NIDMM\_VAL\_BUFFER\_SIZE\_AUTO (-1), NI-DMM chooses the buffer size.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Multi Point Acquisition:Advanced:Buffer Size**
  - C Attribute: **NIDMM\_ATTR\_BUFFER\_SIZE**
- 

## cable\_comp\_type

`nidmm.Session.cable_comp_type`

For the NI 4072 only, the type of cable compensation that is applied to the current capacitance or inductance measurement for the current range. Changing the method or the range through this property or through `nidmm.Session.configure_measurement_digits()` resets the value of this property to the default value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.CableCompensationType</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Capacitance and Inductance:Cable Compensation Type**
  - C Attribute: **NIDMM\_ATTR\_CABLE\_COMP\_TYPE**
- 

## channel\_count

`nidmm.Session.channel_count`

Indicates the number of channels that the specific instrument driver supports. For each property for which the `IVI_VAL_MULTI_CHANNEL` flag property is set, the IVI engine maintains a separate cache value for each channel.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Capabilities:Channel Count**
  - C Attribute: **NIDMM\_ATTR\_CHANNEL\_COUNT**
- 

## current\_source

`nidmm.Session.current_source`

Specifies the current source provided during diode measurements. The NI 4050 and NI 4060 are not supported.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Current Source**
  - C Attribute: **NIDMM\_ATTR\_CURRENT\_SOURCE**
- 

## dc\_bias

`nidmm.Session.dc_bias`

For the NI 4072 only, controls the available DC bias for capacitance measurements.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:



- LabVIEW Property: **Configuration:Measurement Options:Capacitance and Inductance:Advanced:DC Bias**
  - C Attribute: **NIDMM\_ATTR\_DC\_BIAS**
- 

## dc\_noise\_rejection

`nidmm.Session.dc_noise_rejection`

Specifies the DC noise rejection mode. The NI 4050 and NI 4060 are not supported.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.DCNoiseRejection
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:DC Noise Rejection**
  - C Attribute: **NIDMM\_ATTR\_DC\_NOISE\_REJECTION**
- 

## driver\_setup

`nidmm.Session.driver_setup`

This property indicates the Driver Setup string that the user specified when initializing the driver. Some cases exist where the end-user must specify instrument driver options at initialization time. An example of this is specifying a particular instrument model from among a family of instruments that the driver supports. This is useful when using simulation. The end-user can specify driver-specific options through the DriverSetup keyword in the optionsString parameter to the niDMM Init With Options.vi. If the user does not specify a Driver Setup string, this property returns an empty string.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes>User Options:Driver Setup**
  - C Attribute: **NIDMM\_ATTR\_DRIVER\_SETUP**
-

## freq\_voltage\_auto\_range

`nidmm.Session.freq_voltage_auto_range`

For the NI 4070/4071/4072 only, specifies the value of the frequency voltage range. If Auto Ranging, shows the actual value of the active frequency voltage range. If not Auto Ranging, the value of this property is the same as that of `nidmm.Session.freq_voltage_range`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Frequency Voltage Auto Range Value**
  - C Attribute: **NIDMM\_ATTR\_FREQ\_VOLTAGE\_AUTO\_RANGE**
- 

## freq\_voltage\_range

`nidmm.Session.freq_voltage_range`

Specifies the maximum amplitude of the input signal for frequency measurements.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Frequency Voltage Range**
  - C Attribute: **NIDMM\_ATTR\_FREQ\_VOLTAGE\_RANGE**
- 

## function

`nidmm.Session.function`

Specifies the measurement method. Refer to the `nidmm.Session.method` topic in the NI Digital Multimeters Help for device-specific information. If you are setting this property directly, you must also set the `nidmm.Session.operation_mode` property, which controls whether the DMM takes standard single or multipoint measurements, or acquires a waveform. If you are

programming properties directly, you must set the `nidmm.Session.operation_mode` property before setting other configuration properties. If the `nidmm.Session.operation_mode` property is set to `WAVEFORM`, the only valid method types are `WAVEFORM_VOLTAGE` and `WAVEFORM_CURRENT`. Set the `nidmm.Session.operation_mode` property to `IVIDMM` to set all other method values.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.Function
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Function**
  - C Attribute: **NIDMM\_ATTR\_FUNCTION**
- 

## input\_resistance

`nidmm.Session.input_resistance`

Specifies the input resistance of the instrument. The NI 4050 and NI 4060 are not supported.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Input Resistance**
  - C Attribute: **NIDMM\_ATTR\_INPUT\_RESISTANCE**
- 

## instrument\_firmware\_revision

`nidmm.Session.instrument_firmware_revision`

A string containing the instrument firmware revision number.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Instrument Firmware Revision**
  - C Attribute: **NIDMM\_ATTR\_INSTRUMENT\_FIRMWARE\_REVISION**
- 

## instrument\_manufacturer

`nidmm.Session.instrument_manufacturer`

A string containing the manufacturer of the instrument.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Instrument Manufacturer**
  - C Attribute: **NIDMM\_ATTR\_INSTRUMENT\_MANUFACTURER**
- 

## instrument\_model

`nidmm.Session.instrument_model`

A string containing the instrument model.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Instrument Model**
  - C Attribute: **NIDMM\_ATTR\_INSTRUMENT\_MODEL**
- 

## instrument\_product\_id

`nidmm.Session.instrument_product_id`

The PCI product ID.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Instrument Product ID**
  - C Attribute: **NIDMM\_ATTR\_INSTRUMENT\_PRODUCT\_ID**
- 

## io\_resource\_descriptor

`nidmm.Session.io_resource_descriptor`

A string containing the resource descriptor of the instrument.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:I/O Resource Descriptor**
  - C Attribute: **NIDMM\_ATTR\_IO\_RESOURCE\_DESCRIPTOR**
- 

## lc\_calculation\_model

`nidmm.Session.lc_calculation_model`

For the NI 4072 only, specifies the type of algorithm that the measurement processing uses for capacitance and inductance measurements.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.LCCalculationModel
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Capacitance and Inductance:Advanced:Calculation Model**
  - C Attribute: **NIDMM\_ATTR\_LC\_CALCULATION\_MODEL**
- 

### lc\_number\_meas\_to\_average

`nidmm.Session.lc_number_meas_to_average`

For the NI 4072 only, specifies the number of LC measurements that are averaged to produce one reading.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Capacitance and Inductance:Number of LC Measurements To Average**
  - C Attribute: **NIDMM\_ATTR\_LC\_NUMBER\_MEAS\_TO\_AVERAGE**
- 

### logical\_name

`nidmm.Session.logical_name`

A string containing the logical name of the instrument.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:Logical Name**
  - C Attribute: **NIDMM\_ATTR\_LOGICAL\_NAME**
- 

## meas\_complete\_dest

`nidmm.Session.meas_complete_dest`

Specifies the destination of the measurement complete (MC) signal. The NI 4050 is not supported. To determine which values are supported by each device, refer to the LabWindows/CVI Trigger Routing section in the NI Digital Multimeters Help.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.MeasurementCompleteDest</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Trigger:Measurement Complete Dest**
  - C Attribute: **NIDMM\_ATTR\_MEAS\_COMPLETE\_DEST**
- 

## number\_of\_averages

`nidmm.Session.number_of_averages`

Specifies the number of averages to perform in a measurement. For the NI 4070/4071/4072, applies only when the aperture time is not set to AUTO and Auto Zero is ON. The default is 1. The NI 4050 and NI 4060 are not supported.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Advanced:Number Of Averages**
  - C Attribute: **NIDMM\_ATTR\_NUMBER\_OF\_AVERAGES**
-

## offset\_comp\_ohms

`nidmm.Session.offset_comp_ohms`

For the NI 4070/4071/4072 only, enables or disables offset compensated ohms.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Offset Compensated Ohms**
  - C Attribute: **NIDMM\_ATTR\_OFFSET\_COMP\_OHMS**
- 

## open\_cable\_comp\_conductance

`nidmm.Session.open_cable_comp_conductance`

For the NI 4072 only, specifies the active part (conductance) of the open cable compensation. The valid range is any real number greater than 0. The default value (-1.0) indicates that compensation has not taken place. Changing the method or the range through this property or through `nidmm.Session.configure_measurement_digits()` resets the value of this property to the default value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Capacitance and Inductance:Open Cable Compensation Values:Conductance**
  - C Attribute: **NIDMM\_ATTR\_OPEN\_CABLE\_COMP\_CONDUCTANCE**
- 

## open\_cable\_comp\_susceptance

`nidmm.Session.open_cable_comp_susceptance`

For the NI 4072 only, specifies the reactive part (susceptance) of the open cable compensation. The valid range is any real number greater than 0. The default value (-1.0) indicates that compensation has not taken place. Changing the method or the range through this property or through



`nidmm.Session.configure_measurement_digits()` resets the value of this property to the default value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Capacitance and Inductance:Open Cable Compensation Values:Susceptance**
- C Attribute: **NIDMM\_ATTR\_OPEN\_CABLE\_COMP\_SUSCEPTANCE**

## operation\_mode

`nidmm.Session.operation_mode`

Specifies how the NI 4065 and NI 4070/4071/4072 acquire data. When you call `nidmm.Session.configure_measurement_digits()`, NI-DMM sets this property to `IVIDMM`. When you call `nidmm.Session.configure_waveform_acquisition()`, NI-DMM sets this property to `WAVEFORM`. If you are programming properties directly, you must set this property before setting other configuration properties.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.OperationMode
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Advanced:Operation Mode**
- C Attribute: **NIDMM\_ATTR\_OPERATION\_MODE**

## powerline\_freq

`nidmm.Session.powerline_freq`

Specifies the powerline frequency. The NI 4050 and NI 4060 use this value to select an aperture time to reject powerline noise by selecting the appropriate internal sample clock and filter. The NI 4065 and NI 4070/4071/4072 use this value to select a timebase for setting the `nidmm.Session.aperture_time` property in powerline cycles (PLCs). After configuring powerline frequency, set the `nidmm.Session.aperture_time_units` property to PLCs. When setting the `nidmm.Session.aperture_time` property, select the number of PLCs for the powerline frequency.

For example, if powerline frequency = 50 Hz (or 20ms) and aperture time in PLCs = 5, then aperture time in Seconds = 20ms \* 5 PLCs = 100 ms. Similarly, if powerline frequency = 60 Hz (or 16.667 ms) and aperture time in PLCs = 6, then aperture time in Seconds = 16.667 ms \* 6 PLCs = 100 ms.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Powerline Frequency**
  - C Attribute: **NIDMM\_ATTR\_POWERLINE\_FREQ**
- 

## range

### `nidmm.Session.range`

Specifies the measurement range. Use positive values to represent the absolute value of the maximum expected measurement. The value is in units appropriate for the current value of the `nidmm.Session.method` property. For example, if `nidmm.Session.method` is set to `NIDMM_VAL_VOLTS`, the units are volts. The NI 4050 and NI 4060 only support Auto Range when the trigger and sample trigger is set to IMMEDIATE. `NIDMM_VAL_AUTO_RANGE_ON` -1.0 NI-DMM performs an Auto Range before acquiring the measurement. `NIDMM_VAL_AUTO_RANGE_OFF` -2.0 NI-DMM sets the Range to the current `nidmm.Session.auto_range_value` and uses this range for all subsequent measurements until the measurement configuration is changed. `NIDMM_VAL_AUTO_RANGE_ONCE` -3.0 NI-DMM performs an Auto Range before acquiring the next measurement. The `nidmm.Session.auto_range_value` is stored and used for all subsequent measurements until the measurement configuration is changed.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Range**
- C Attribute: **NIDMM\_ATTR\_RANGE**

## resolution\_absolute

### `nidmm.Session.resolution_absolute`

Specifies the measurement resolution in absolute units. Setting this property to higher values increases the measurement accuracy. Setting this property to lower values increases the measurement speed. NI-DMM ignores this property for capacitance and inductance measurements on the NI 4072. To achieve better resolution for such measurements, use the `nidmm.Session.lc_number_meas_to_average` property.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Absolute Resolution**
  - C Attribute: **NIDMM\_ATTR\_RESOLUTION\_ABSOLUTE**
- 

## resolution\_digits

### `nidmm.Session.resolution_digits`

Specifies the measurement resolution in digits. Setting this property to higher values increases the measurement accuracy. Setting this property to lower values increases the measurement speed. NI-DMM ignores this property for capacitance and inductance measurements on the NI 4072. To achieve better resolution for such measurements, use the `nidmm.Session.lc_number_meas_to_average` property.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Digits Resolution**
  - C Attribute: **NIDMM\_ATTR\_RESOLUTION\_DIGITS**
-

## sample\_count

`nidmm.Session.sample_count`

Specifies the number of measurements the DMM takes each time it receives a trigger in a multiple point acquisition.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Multi Point Acquisition:Sample Count**
  - C Attribute: **NIDMM\_ATTR\_SAMPLE\_COUNT**
- 

## sample\_interval

`nidmm.Session.sample_interval`

Specifies the amount of time in seconds the DMM waits between measurement cycles. This property only applies when the `nidmm.Session.sample_trigger` property is set to INTERVAL. On the NI 4060, the value for this property is used as the settling time. When this property is set to 0, the NI 4060 does not settle between measurement cycles. The onboard timing resolution is 1  $\mu$ s on the NI 4060. The NI 4065 and NI 4070/4071/4072 use the value specified in this property as additional delay. On the NI 4065 and NI 4070/4071/4072, the onboard timing resolution is 34.72 ns and the valid range is 0-149 s. Only positive values are valid when setting the sample interval. The NI 4050 is not supported.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Multi Point Acquisition:Sample Interval**
  - C Attribute: **NIDMM\_ATTR\_SAMPLE\_INTERVAL**
- 

## sample\_trigger

`nidmm.Session.sample_trigger`

Specifies the sample trigger source. To determine which values are supported by each device, refer

to the LabWindows/CVI Trigger Routing section in the NI Digital Multimeters Help.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.SampleTrigger
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Multi Point Acquisition:Sample Trigger**
  - C Attribute: **NIDMM\_ATTR\_SAMPLE\_TRIGGER**
- 

## serial\_number

`nidmm.Session.serial_number`

A string containing the serial number of the instrument. This property corresponds to the serial number label that is attached to most products.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Instrument Serial Number**
  - C Attribute: **NIDMM\_ATTR\_SERIAL\_NUMBER**
- 

## settle\_time

`nidmm.Session.settle_time`

Specifies the settling time in seconds. To override the default settling time, set this property. To return to the default, set this property to `NIDMM_VAL_SETTLE_TIME_AUTO` (-1). The NI 4050 and NI 4060 are not supported.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Advanced:Settle Time**
  - C Attribute: **NIDMM\_ATTR\_SETTLE\_TIME**
- 

### **short\_cable\_comp\_reactance**

`nidmm.Session.short_cable_comp_reactance`

For the NI 4072 only, represents the reactive part (reactance) of the short cable compensation. The valid range is any real number greater than 0. The default value (-1) indicates that compensation has not taken place. Changing the method or the range through this property or through `nidmm.Session.configure_measurement_digits()` resets the value of this property to the default value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Capacitance and Inductance:Short Cable Compensation Values:Reactance**
  - C Attribute: **NIDMM\_ATTR\_SHORT\_CABLE\_COMP\_REACTANCE**
- 

### **short\_cable\_comp\_resistance**

`nidmm.Session.short_cable_comp_resistance`

For the NI 4072 only, represents the active part (resistance) of the short cable compensation. The valid range is any real number greater than 0. The default value (-1) indicates that compensation has not taken place. Changing the method or the range through this property or through `nidmm.Session.configure_measurement_digits()` resets the value of this property to the default value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Capacitance and Inductance:Short Cable Compensation Values:Resistance**
  - C Attribute: **NIDMM\_ATTR\_SHORT\_CABLE\_COMP\_RESISTANCE**
- 

## simulate

### `nidmm.Session.simulate`

Specifies whether or not to simulate instrument driver I/O operations. If simulation is enabled, instrument driver methods perform range checking and call IVI Get and Set methods, but they do not perform instrument I/O. For output parameters that represent instrument data, the instrument driver methods return calculated values. The default value is False (0). Use the `nidmm.Session.__init__()` method to override this setting. Simulate can only be set within the `InitWithOptions` method. The property value cannot be changed outside of the method.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:User Options:Simulate**
  - C Attribute: **NIDMM\_ATTR\_SIMULATE**
- 

## specific\_driver\_description

### `nidmm.Session.specific_driver_description`

A string containing a description of the specific driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Specific Driver Identification:Specific Driver Description**
  - C Attribute: **NIDMM\_ATTR\_SPECIFIC\_DRIVER\_DESCRIPTION**
- 

### **specific\_driver\_major\_version**

`nidmm.Session.specific_driver_major_version`

Returns the major version number of this instrument driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Version Info:Specific Driver Major Version**
  - C Attribute: **NIDMM\_ATTR\_SPECIFIC\_DRIVER\_MAJOR\_VERSION**
- 

### **specific\_driver\_minor\_version**

`nidmm.Session.specific_driver_minor_version`

The minor version number of this instrument driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Version Info:Specific Driver Minor Version**
  - C Attribute: **NIDMM\_ATTR\_SPECIFIC\_DRIVER\_MINOR\_VERSION**
-



## specific\_driver\_revision

`nidmm.Session.specific_driver_revision`

A string that contains additional version information about this specific instrument driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Version Info:Specific Driver Revision**
  - C Attribute: **NIDMM\_ATTR\_SPECIFIC\_DRIVER\_REVISION**
- 

## specific\_driver\_vendor

`nidmm.Session.specific_driver_vendor`

A string containing the vendor of the specific driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Specific Driver Identification:Specific Driver Vendor**
  - C Attribute: **NIDMM\_ATTR\_SPECIFIC\_DRIVER\_VENDOR**
- 

## supported\_instrument\_models

`nidmm.Session.supported_instrument_models`

A string containing the instrument models supported by the specific driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Specific Driver Capabilities:Supported Instrument Models**
  - C Attribute: **NIDMM\_ATTR\_SUPPORTED\_INSTRUMENT\_MODELS**
- 

## temp\_rtd\_a

`nidmm.Session.temp_rtd_a`

Specifies the Callendar-Van Dusen A coefficient for RTD scaling when the RTD Type property is set to Custom. The default value is 3.9083e-3 (Pt3851).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Resistance Temperature Detector:RTD A**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_RTD\_A**
- 

## temp\_rtd\_b

`nidmm.Session.temp_rtd_b`

Specifies the Callendar-Van Dusen B coefficient for RTD scaling when the RTD Type property is set to Custom. The default value is -5.775e-7(Pt3851).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Resistance Temperature Detector:RTD B**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_RTD\_B**
- 

## temp\_rtd\_c

`nidmm.Session.temp_rtd_c`

Specifies the Callendar-Van Dusen C coefficient for RTD scaling when the RTD Type property is set to Custom. The default value is -4.183e-12(Pt3851).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Resistance Temperature Detector:RTD C**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_RTD\_C**
- 

## temp\_rtd\_res

`nidmm.Session.temp_rtd_res`

Specifies the RTD resistance at 0 degrees Celsius. This applies to all supported RTDs, including custom RTDs. The default value is 100 (?).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Resistance Temperature Detector:RTD Resistance**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_RTD\_RES**
-

## temp\_rtd\_type

`nidmm.Session.temp_rtd_type`

Specifies the type of RTD used to measure temperature. The default value is `PT3851`. Refer to the `nidmm.Session.temp_rtd_type` topic in the NI Digital Multimeters Help for additional information about defined values.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.RTDType</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Resistance Temperature Detector:RTD Type**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_RTD\_TYPE**
- 

## temp\_tc\_fixed\_ref\_junc

`nidmm.Session.temp_tc_fixed_ref_junc`

Specifies the reference junction temperature when a fixed reference junction is used to take a thermocouple measurement. The default value is 25.0 (°C).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Thermocouple:Fixed Reference Junction**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_TC\_FIXED\_REF\_JUNC**
- 

## temp\_tc\_ref\_junc\_type

`nidmm.Session.temp_tc_ref_junc_type`

Specifies the type of reference junction to be used in the reference junction compensation of a thermocouple. The only supported value, `NIDMM_VAL_TEMP_REF_JUNC_FIXED`, is fixed.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.ThermocoupleReferenceJunctionType
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Thermocouple:Reference Junction Type** Op-
  - C Attribute: **NIDMM\_ATTR\_TEMP\_TC\_REF\_JUNC\_TYPE**
- 

## temp\_tc\_type

`nidmm.Session.temp_tc_type`

Specifies the type of thermocouple used to measure the temperature. The default value is `J`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.ThermocoupleType
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Thermocouple:Thermocouple Type** Op-
  - C Attribute: **NIDMM\_ATTR\_TEMP\_TC\_TYPE**
- 

## temp\_thermistor\_a

`nidmm.Session.temp_thermistor_a`

Specifies the Steinhart-Hart A coefficient for thermistor scaling when the Thermistor Type property is set to Custom. The default value is 0.0010295 (44006).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Thermistor:Thermistor A**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_THERMISTOR\_A**
- 

### temp\_thermistor\_b

`nidmm.Session.temp_thermistor_b`

Specifies the Steinhart-Hart B coefficient for thermistor scaling when the Thermistor Type property is set to Custom. The default value is 0.0002391 (44006).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Thermistor:Thermistor B**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_THERMISTOR\_B**
- 

### temp\_thermistor\_c

`nidmm.Session.temp_thermistor_c`

Specifies the Steinhart-Hart C coefficient for thermistor scaling when the Thermistor Type property is set to Custom. The default value is 1.568e-7 (44006).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Thermistor:Thermistor C**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_THERMISTOR\_C**
- 

## temp\_thermistor\_type

`nidmm.Session.temp_thermistor_type`

Specifies the type of thermistor used to measure the temperature. The default value is `THERMISTOR_44006`. Refer to the `nidmm.Session.temp_thermistor_type` topic in the NI Digital Multimeters Help for additional information about defined values.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.ThermistorType</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Thermistor:Thermistor Type**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_THERMISTOR\_TYPE**
- 

## temp\_transducer\_type

`nidmm.Session.temp_transducer_type`

Specifies the type of device used to measure the temperature. The default value is `NIDMM_VAL_4_THERMOCOUPLE`.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TransducerType</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Configuration:Measurement Options:Temperature:Transducer Type**
  - C Attribute: **NIDMM\_ATTR\_TEMP\_TRANSDUCER\_TYPE**
- 

## trigger\_count

`nidmm.Session.trigger_count`

Specifies the number of triggers the DMM receives before returning to the Idle state. This property can be set to any positive ViInt32 value for the NI 4065 and NI 4070/4071/4072. The NI 4050 and NI 4060 support this property being set to 1. Refer to the Multiple Point Acquisitions section of the NI Digital Multimeters Help for more information.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Multi Point Acquisition:Trigger Count**
  - C Attribute: **NIDMM\_ATTR\_TRIGGER\_COUNT**
- 

## trigger\_delay

`nidmm.Session.trigger_delay`

Specifies the time (in seconds) that the DMM waits after it has received a trigger before taking a measurement. The default value is AUTO DELAY (-1), which means that the DMM waits an appropriate settling time before taking the measurement. (-1) signifies that AUTO DELAY is on, and (-2) signifies that AUTO DELAY is off. The NI 4065 and NI 4070/4071/4072 use the value specified in this property as additional settling time. For the The NI 4065 and NI 4070/4071/4072, the valid range for Trigger Delay is AUTO DELAY (-1) or 0.0-149.0 seconds and the onboard timing resolution is 34.72 ns. On the NI 4060, if this property is set to 0, the DMM does not settle before taking the measurement. On the NI 4060, the valid range for AUTO DELAY (-1) is 0.0-12.0 seconds and the onboard timing resolution is 100 ms. When using the NI 4050, this property must be set to AUTO DELAY (-1). Use positive values to set the trigger delay in seconds. Valid Range: NIDMM\_VAL\_AUTO\_DELAY (-1.0), 0.0-12.0 seconds (NI 4060 only) Default Value: NIDMM\_VAL\_AUTO\_DELAY

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.



Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Trigger:Trigger Delay**
  - C Attribute: **NIDMM\_ATTR\_TRIGGER\_DELAY**
- 

## trigger\_source

### `nidmm.Session.trigger_source`

Specifies the trigger source. When `nidmm.Session._initiate()` is called, the DMM waits for the trigger specified with this property. After it receives the trigger, the DMM waits the length of time specified with the `nidmm.Session.trigger_delay` property. The DMM then takes a measurement. This property is not supported on the NI 4050. To determine which values are supported by each device, refer to the LabWindows/CVI Trigger Routing section in the NI Digital Multimeters Help.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TriggerSource</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Trigger:Trigger Source**
  - C Attribute: **NIDMM\_ATTR\_TRIGGER\_SOURCE**
- 

## waveform\_coupling

### `nidmm.Session.waveform_coupling`

For the NI 4070/4071/4072 only, specifies the coupling during a waveform acquisition.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.WaveformCoupling</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Waveform Acquisition:Waveform Coupling**
  - C Attribute: **NIDMM\_ATTR\_WAVEFORM\_COUPLING**
- 

## waveform\_points

`nidmm.Session.waveform_points`

For the NI 4070/4071/4072 only, specifies the number of points to acquire in a waveform acquisition.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Waveform Acquisition:Waveform Points**
  - C Attribute: **NIDMM\_ATTR\_WAVEFORM\_POINTS**
- 

## waveform\_rate

`nidmm.Session.waveform_rate`

For the NI 4070/4071/4072 only, specifies the rate of the waveform acquisition in Samples per second (S/s). The valid Range is 10.0-1,800,000 S/s. Values are coerced to the closest integer divisor of 1,800,000. The default value is 1,800,000.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Waveform Acquisition:Waveform Rate**
  - C Attribute: **NIDMM\_ATTR\_WAVEFORM\_RATE**
-

## Methods

### abort

```
nidmm.Session.abort()
```

Aborts a previously initiated measurement and returns the DMM to the Idle state.

### configure\_measurement\_absolute

```
nidmm.Session.configure_measurement_absolute(measurement_function, range,  
                                              resolution_absolute)
```

Configures the common properties of the measurement. These properties include `nidmm.Session.method`, `nidmm.Session.range`, and `nidmm.Session.resolution_absolute`.

#### Parameters

- **measurement\_function** (*nidmm.Function*) – Specifies the **measurement\_function** used to acquire the measurement. The driver sets `nidmm.Session.method` to this value.
- **range** (*float*) – Specifies the **range** for the method specified in the **Measurement\_Function** parameter. When frequency is specified in the **Measurement\_Function** parameter, you must supply the minimum frequency expected in the **range** parameter. For example, you must type in 100 Hz if you are measuring 101 Hz or higher. For all other methods, you must supply a **range** that exceeds the value that you are measuring. For example, you must type in 10 V if you are measuring 9 V. **range** values are coerced up to the closest input **range**. Refer to the [Devices Overview](#) for a list of valid ranges. The driver sets `nidmm.Session.range` to this value. The default is 0.02 V.

NIDMM_VAL_AUTO	1.0	NI-DMM performs an Auto Range before acquiring the measurement.
NIDMM_VAL_AUTO	2.0	NI-DMM sets the Range to the current <code>nidmm.Session.auto_range_value</code> and uses this range for all subsequent measurements until the measurement configuration is changed.
NIDMM_VAL_AUTO	3.0	NI-DMM performs an Auto Range before acquiring the measurement. The <code>nidmm.Session.auto_range_value</code> is stored and used for all subsequent measurements until the measurement configuration is changed.

**Note:** The NI 4050, NI 4060, and NI 4065 only support Auto Range when the trigger and sample trigger are set to IMMEDIATE.

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

- **resolution\_absolute** (*float*) – Specifies the absolute resolution for the measurement. NI-DMM sets `nidmm.Session.resolution_absolute` to

this value. This parameter is ignored when the **Range** parameter is set to `NIDMM_VAL_AUTO_RANGE_ON` (-1.0) or `NIDMM_VAL_AUTO_RANGE_ONCE` (-3.0). The default is 0.001 V.

---

**Note:** NI-DMM ignores this parameter for capacitance and inductance measurements on the NI 4072. To achieve better resolution for such measurements, use the `nidmm.Session.lc_number_meas_to_average` property.

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## configure\_measurement\_digits

`nidmm.Session.configure_measurement_digits` (*measurement\_function*, *range*, *resolution\_digits*)

Configures the common properties of the measurement. These properties include `nidmm.Session.method`, `nidmm.Session.range`, and `nidmm.Session.resolution_digits`.

### Parameters

- **measurement\_function** (*nidmm.Function*) – Specifies the **measurement\_function** used to acquire the measurement. The driver sets `nidmm.Session.method` to this value.
- **range** (*float*) – Specifies the range for the method specified in the **Measurement\_Function** parameter. When frequency is specified in the **Measurement\_Function** parameter, you must supply the minimum frequency expected in the **range** parameter. For example, you must type in 100 Hz if you are measuring 101 Hz or higher. For all other methods, you must supply a range that exceeds the value that you are measuring. For example, you must type in 10 V if you are measuring 9 V. range values are coerced up to the closest input range. Refer to the [Devices Overview](#) for a list of valid ranges. The driver sets `nidmm.Session.range` to this value. The default is 0.02 V.

<code>NIDMM_VAL_AUTO_RANGE_ON</code>	1.0	NI-DMM performs an Auto Range before acquiring the measurement.
<code>NIDMM_VAL_AUTO_RANGE_ONCE</code>	2.0	NI-DMM sets the Range to the current <code>nidmm.Session.auto_range_value</code> and uses this range for all subsequent measurements until the measurement configuration is changed.
<code>NIDMM_VAL_AUTO_RANGE_ALWAYS</code>	3.0	NI-DMM performs an Auto Range before acquiring the measurement. The <code>nidmm.Session.auto_range_value</code> is stored and used for all subsequent measurements until the measurement configuration is changed.

---

**Note:** The NI 4050, NI 4060, and NI 4065 only support Auto Range when the trigger and sample trigger are set to IMMEDIATE.

---

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

- **resolution\_digits** (*float*) – Specifies the resolution of the measurement in digits. The driver sets the [Devices Overview](#) for a list of valid ranges. The driver sets `nidmm.Session.resolution_digits` property to this value. This parameter is ignored when the **Range** parameter is set to `NIDMM_VAL_AUTO_RANGE_ON` (-1.0) or `NIDMM_VAL_AUTO_RANGE_ONCE` (-3.0). The default is 5½.

---

**Note:** NI-DMM ignores this parameter for capacitance and inductance measurements on the NI 4072. To achieve better resolution for such measurements, use the `nidmm.Session.lc_number_meas_to_average` property.

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## configure\_multi\_point

```
nidmm.Session.configure_multi_point(trigger_count, sample_count, sample_trigger=nidmm.SampleTrigger.IMMEDIATE,
                                     sample_interval=datetime.timedelta(seconds=-1))
```

Configures the properties for multipoint measurements. These properties include `nidmm.Session.trigger_count`, `nidmm.Session.sample_count`, `nidmm.Session.sample_trigger`, and `nidmm.Session.sample_interval`.

For continuous acquisitions, set `nidmm.Session.trigger_count` or `nidmm.Session.sample_count` to zero. For more information, refer to [Multiple Point Acquisitions, Triggering, and Using Switches](#).

### Parameters

- **trigger\_count** (*int*) – Sets the number of triggers you want the DMM to receive before returning to the Idle state. The driver sets `nidmm.Session.trigger_count` to this value. The default value is 1.
- **sample\_count** (*int*) – Sets the number of measurements the DMM makes in each measurement sequence initiated by a trigger. The driver sets `nidmm.Session.sample_count` to this value. The default value is 1.
- **sample\_trigger** (`nidmm.SampleTrigger`) – Specifies the **sample\_trigger** source you want to use. The driver sets `nidmm.Session.sample_trigger` to this value. The default is Immediate.

---

**Note:** To determine which values are supported by each device, refer to the [LabWindows/CVI Trigger Routing](#) section.

---

- **sample\_interval** (*float in seconds or datetime.timedelta*) – Sets the amount of time in seconds the DMM waits between measurement cycles. The driver sets `nidmm.Session.sample_interval` to this value. Specify a

sample interval to add settling time between measurement cycles or to decrease the measurement rate. **sample\_interval** only applies when the **Sample\_Trigger** is set to **INTERVAL**.

On the NI 4060, the **sample\_interval** value is used as the settling time. When sample interval is set to 0, the DMM does not settle between measurement cycles. The NI 4065 and NI 4070/4071/4072 use the value specified in **sample\_interval** as additional delay. The default value (-1) ensures that the DMM settles for a recommended time. This is the same as using an Immediate trigger.

---

**Note:** This property is not used on the NI 4080/4081/4082 and the NI 4050.

---

## configure\_rtd\_custom

```
nidmm.Session.configure_rtd_custom(rtd_a, rtd_b, rtd_c)
```

Configures the A, B, and C parameters for a custom RTD.

### Parameters

- **rtd\_a** (*float*) – Specifies the Callendar-Van Dusen A coefficient for RTD scaling when RTD Type parameter is set to Custom in the `nidmm.Session.configure_rtd_type()` method. The default is 3.9083e-3 (Pt3851)
- **rtd\_b** (*float*) – Specifies the Callendar-Van Dusen B coefficient for RTD scaling when RTD Type parameter is set to Custom in the `nidmm.Session.configure_rtd_type()` method. The default is -5.775e-7 (Pt3851).
- **rtd\_c** (*float*) – Specifies the Callendar-Van Dusen C coefficient for RTD scaling when RTD Type parameter is set to Custom in the `nidmm.Session.configure_rtd_type()` method. The default is -4.183e-12 (Pt3851).

## configure\_rtd\_type

```
nidmm.Session.configure_rtd_type(rtd_type, rtd_resistance)
```

Configures the RTD Type and RTD Resistance parameters for an RTD.

### Parameters

- **rtd\_type** (`nidmm.RTDType`) – Specifies the type of RTD used to measure the temperature resistance. NI-DMM uses this value to set the RTD Type property. The default is `PT3851`.

Enum	Standards	Ma- te- rial	TCR ( $\alpha$ )	Typ- ical $R_0$ ( $\Omega$ )	Notes	
Callendar- Van Dusen Coeffi- cient						
<i>PT3851</i>	IEC-751 DIN 43760 BS 1904 ASTM-E1137 EN-60751	Plat- inum	.00385	100 $\Omega$ 1000 $\Omega$	$A = 3.9083 \times 10^{-3}$ $B = -5.775 \times 10^{-7}$ $C = -4.183 \times 10^{-12}$	Most com- mon RTDs
<i>PT3750</i>	Low-cost ven- dor compliant RTD*	Plat- inum	.00375	1000 $\Omega$	$A = 3.81 \times 10^{-3}$ $B = -6.02 \times 10^{-7}$ $C = -6.0 \times 10^{-12}$	Low- cost RTD
<i>PT3916</i>	JISC 1604	Plat- inum	.00391	1600 $\Omega$	$A = 3.9739 \times 10^{-3}$ $B = -5.870 \times 10^{-7}$ $C = -4.4 \times 10^{-12}$	Used in primar- ily in Japan
<i>PT3920</i>	US Industrial Standard D- 100 American	Plat- inum	.00392	1000 $\Omega$	$A = 3.9787 \times 10^{-3}$ $B = -5.8686 \times 10^{-7}$ $C = -4.167 \times 10^{-12}$	Low- cost RTD
<i>PT3911</i>	US Indus- trial Standard American	Plat- inum	.00391	1100 $\Omega$	$A = 3.9692 \times 10^{-3}$ $B = -5.8495 \times 10^{-7}$ $C = -4.233 \times 10^{-12}$	Low- cost RTD
<i>PT3928</i>	ITS-90	Plat- inum	.00392	1000 $\Omega$	$A = 3.9888 \times 10^{-3}$ $B = -5.915 \times 10^{-7}$ $C = -3.85 \times 10^{-12}$	The defi- nition of temper- ature
*No stan- dard. Check the TCR.						

- **rtd\_resistance** (*float*) – Specifies the RTD resistance in ohms at 0 °C. NI-DMM uses this value to set the RTD Resistance property. The default is 100 ( $\Omega$ ).

## configure\_thermistor\_custom

```
nidmm.Session.configure_thermistor_custom(thermistor_a, thermistor_b, thermistor_c)
```

Configures the A, B, and C parameters for a custom thermistor.

### Parameters

- **thermistor\_a** (*float*) – Specifies the Steinhart-Hart A coefficient for thermistor scaling when Thermistor Type is set to Custom in the `nidmm.Session.ConfigureThermistorType()` method. The default is 1.0295e-3 (44006).

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

- **thermistor\_b** (*float*) – Specifies the Steinhart-Hart B coefficient for thermistor scaling when Thermistor Type is set to Custom in the `nidmm.Session.ConfigureThermistorType()` method. The default is 2.391e-4 (44006).

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

- **thermistor\_c** (*float*) – Specifies the Steinhart-Hart C coefficient for thermistor scaling when Thermistor Type is set to Custom in the `nidmm.Session.ConfigureThermistorType()` method. The default is 1.568e-7 (44006).

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

## configure\_thermocouple

```
nidmm.Session.configure_thermocouple(thermocouple_type, reference_junction_type=nidmm.ThermocoupleReferenceJunctionType.FIXED)
```

Configures the thermocouple type and reference junction type for a chosen thermocouple.

### Parameters

- **thermocouple\_type** (*nidmm.ThermocoupleType*) – Specifies the type of thermocouple used to measure the temperature. NI-DMM uses this value to set the Thermocouple Type property. The default is *J*.

<i>B</i>	Thermocouple type B
<i>E</i>	Thermocouple type E
<i>J</i>	Thermocouple type J
<i>K</i>	Thermocouple type K
<i>N</i>	Thermocouple type N
<i>R</i>	Thermocouple type R
<i>S</i>	Thermocouple type S
<i>T</i>	Thermocouple type T



- **reference\_junction\_type** (*nidmm.ThermocoupleReferenceJunctionType*) – Specifies the type of reference junction to be used in the reference junction compensation of a thermocouple measurement. NI-DMM uses this value to set the Reference Junction Type property. The only supported value is NIDMM\_VAL\_TEMP\_REF\_JUNC\_FIXED.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## configure\_trigger

`nidmm.Session.configure_trigger(trigger_source, trigger_delay=datetime.timedelta(seconds=-1))`

Configures the DMM **Trigger\_Source** and **Trigger\_Delay**. Refer to [Triggering](#) and [Using Switches](#) for more information.

### Parameters

- **trigger\_source** (*nidmm.TriggerSource*) – Specifies the **trigger\_source** that initiates the acquisition. The driver sets `nidmm.Session.trigger_source` to this value. Software configures the DMM to wait until `nidmm.Session.send_software_trigger()` is called before triggering the DMM.

---

**Note:** To determine which values are supported by each device, refer to the [LabWindows/CVI Trigger Routing](#) section.

---

- **trigger\_delay** (*float in seconds or datetime.timedelta*) – Specifies the time that the DMM waits after it has received a trigger before taking a measurement. The driver sets the `nidmm.Session.trigger_delay` property to this value. By default, **trigger\_delay** is NIDMM\_VAL\_AUTO\_DELAY (-1), which means the DMM waits an appropriate settling time before taking the measurement. On the NI 4060, if you set **trigger\_delay** to 0, the DMM does not settle before taking the measurement. The NI 4065 and NI 4070/4071/4072 use the value specified in **trigger\_delay** as additional settling time.

---

**Note:** When using the NI 4050, **Trigger\_Delay** must be set to NIDMM\_VAL\_AUTO\_DELAY (-1).

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## configure\_waveform\_acquisition

`nidmm.Session.configure_waveform_acquisition(measurement_function, range, rate, waveform_points)`

Configures the DMM for waveform acquisitions. This feature is supported on the NI 4080/4081/4082 and the NI 4070/4071/4072.

## Parameters

- **measurement\_function** (*nidmm.Function*) – Specifies the **measurement\_function** used in a waveform acquisition. The driver sets `nidmm.Session.method` to this value.

WAVEFORM_VOLTAGE (default)	1003	Voltage Waveform
WAVEFORM_CURRENT	1004	Current Waveform

- **range** (*float*) – Specifies the expected maximum amplitude of the input signal and sets the **range** for the **Measurement\_Function**. NI-DMM sets `nidmm.Session.range` to this value. **range** values are coerced up to the closest input **range**. The default is 10.0.

For valid ranges refer to the topics in [Devices](#).

Auto-ranging is not supported during waveform acquisitions.

- **rate** (*float*) – Specifies the **rate** of the acquisition in samples per second. NI-DMM sets `nidmm.Session.waveform_rate` to this value.

The valid **Rate** is 10.0–1,800,000 S/s. **rate** values are coerced to the closest integer divisor of 1,800,000. The default value is 1,800,000.

- **waveform\_points** (*int*) – Specifies the number of points to acquire before the waveform acquisition completes. NI-DMM sets `nidmm.Session.waveform_points` to this value.

To calculate the maximum and minimum number of waveform points that you can acquire in one acquisition, refer to the [Waveform Acquisition Measurement Cycle](#).

The default value is 500.

## disable

```
nidmm.Session.disable()
```

Places the instrument in a quiescent state where it has minimal or no impact on the system to which it is connected. If a measurement is in progress when this method is called, the measurement is aborted.

## fetch

```
nidmm.Session.fetch(maximum_time=datetime.timedelta(milliseconds=-1))
```

Returns the value from a previously initiated measurement. You must call `nidmm.Session._initiate()` before calling this method.

**Parameters** **maximum\_time** (*float in seconds or datetime.timedelta*) – Specifies the **maximum\_time** allowed for this method to complete in milliseconds. If the method does not complete within this time interval, the method returns the `NIDMM_ERROR_MAX_TIME_EXCEEDED` error code. This may happen if an external trigger has not been received, or if the specified timeout is not long enough for the acquisition to complete.

The valid range is 0–86400000. The default value is `NIDMM_VAL_TIME_LIMIT_AUTO` (-1). The DMM calculates the timeout automatically.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

**Return type** `float`

**Returns** The measured value returned from the DMM.

## fetch\_multi\_point

```
nidmm.Session.fetch_multi_point(array_size, maximum_time=datetime.timedelta(milliseconds=-1))
```

Returns an array of values from a previously initiated multipoint measurement. The number of measurements the DMM makes is determined by the values you specify for the **Trigger\_Count** and **Sample\_Count** parameters of `nidmm.Session.configure_multi_point()`. You must first call `nidmm.Session._initiate()` to initiate a measurement before calling this method.

### Parameters

- **array\_size** (`int`) – Specifies the number of measurements to acquire. The maximum number of measurements for a finite acquisition is the (**Trigger\_Count** x **Sample\_Count**) parameters in `nidmm.Session.configure_multi_point()`.

For continuous acquisitions, up to 100,000 points can be returned at once. The number of measurements can be a subset. The valid range is any positive `ViInt32`. The default value is 1.

- **maximum\_time** (`float in seconds or datetime.timedelta`) – Specifies the **maximum\_time** allowed for this method to complete in milliseconds. If the method does not complete within this time interval, the method returns the `NIDMM_ERROR_MAX_TIME_EXCEEDED` error code. This may happen if an external trigger has not been received, or if the specified timeout is not long enough for the acquisition to complete.

The valid range is 0–86400000. The default value is `NIDMM_VAL_TIME_LIMIT_AUTO` (-1). The DMM calculates the timeout automatically.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

### Return type

tuple (reading\_array, actual\_number\_of\_points)

WHERE

reading\_array (array.array("d")):

An array of measurement values.

---

**Note:** The size of the **Reading\_Array** must be at least the size that you specify for the **Array\_Size** parameter.

---

actual\_number\_of\_points (int):

Indicates the number of measured values actually retrieved from the DMM.

## fetch\_waveform

```
nidmm.Session.fetch_waveform(array_size, maximum_time=datetime.timedelta(milliseconds=-1))
```

For the NI 4080/4081/4082 and the NI 4070/4071/4072, returns an array of values from a previously initiated waveform acquisition. You must call `nidmm.Session._initiate()` before calling this method.

### Parameters

- **array\_size** (*int*) – Specifies the number of waveform points to return. You specify the total number of points that the DMM acquires in the **Waveform Points** parameter of `nidmm.Session.configure_waveform_acquisition()`. The default value is 1.
- **maximum\_time** (*float in seconds or datetime.timedelta*) – Specifies the **maximum\_time** allowed for this method to complete in milliseconds. If the method does not complete within this time interval, the method returns the `NIDMM_ERROR_MAX_TIME_EXCEEDED` error code. This may happen if an external trigger has not been received, or if the specified timeout is not long enough for the acquisition to complete.

The valid range is 0–86400000. The default value is `NIDMM_VAL_TIME_LIMIT_AUTO` (-1). The DMM calculates the timeout automatically.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

### Return type

tuple (waveform\_array, actual\_number\_of\_points)

WHERE

waveform\_array (array.array("d")):

**Waveform Array** is an array of measurement values stored in waveform data type.

actual\_number\_of\_points (int):

Indicates the number of measured values actually retrieved from the DMM.

## fetch\_waveform\_into

```
nidmm.Session.fetch_waveform_into(array_size, maximum_time=datetime.timedelta(milliseconds=-1))
```

For the NI 4080/4081/4082 and the NI 4070/4071/4072, returns an array of values from a previously initiated waveform acquisition. You must call `nidmm.Session._initiate()` before calling this method.

### Parameters

- **waveform\_array** (*numpy.array(dtype=numpy.float64)*) – **Waveform Array** is an array of measurement values stored in waveform data type.
- **maximum\_time** (*float in seconds or datetime.timedelta*) – Specifies the **maximum\_time** allowed for this method to complete in milliseconds. If the method does not complete within this time interval, the method returns the NIDMM\_ERROR\_MAX\_TIME\_EXCEEDED error code. This may happen if an external trigger has not been received, or if the specified timeout is not long enough for the acquisition to complete.

The valid range is 0–86400000. The default value is NIDMM\_VAL\_TIME\_LIMIT\_AUTO (-1). The DMM calculates the timeout automatically.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

### Return type

tuple (waveform\_array, actual\_number\_of\_points)

WHERE

waveform\_array (*numpy.array(dtype=numpy.float64)*):

**Waveform Array** is an array of measurement values stored in waveform data type.

actual\_number\_of\_points (*int*):

Indicates the number of measured values actually retrieved from the DMM.

## get\_cal\_date\_and\_time

`nidmm.Session.get_cal_date_and_time(cal_type)`

Returns the date and time of the last calibration performed.

---

**Note:** The NI 4050 and NI 4060 are not supported.

---

**Parameters** **cal\_type** (*int*) – Specifies the type of calibration performed (external or self-calibration).

NIDMM_VAL_INTERNAL_AREA (default)	0	Self-Calibration
NIDMM_VAL_EXTERNAL_AREA	1	External Calibration

---

**Note:** The NI 4065 does not support self-calibration.

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

**Return type** *datetime.datetime*

**Returns** Indicates date and time of the last calibration.

### get\_dev\_temp

`nidmm.Session.get_dev_temp(options='')`  
Returns the current **Temperature** of the device.

---

**Note:** The NI 4050 and NI 4060 are not supported.

---

**Parameters** `options` (*str*) – Reserved.

**Return type** `float`

**Returns** Returns the current **temperature** of the device.

### get\_ext\_cal\_recommended\_interval

`nidmm.Session.get_ext_cal_recommended_interval()`  
Returns the recommended interval between external recalibration in **Months**.

---

**Note:** The NI 4050 and NI 4060 are not supported.

---

**Return type** `datetime.timedelta`

**Returns** Returns the recommended number of **months** between external calibrations.

### get\_last\_cal\_temp

`nidmm.Session.get_last_cal_temp(cal_type)`  
Returns the **Temperature** during the last calibration procedure.

---

**Note:** The NI 4050 and NI 4060 are not supported.

---

**Parameters** `cal_type` (*int*) – Specifies the type of calibration performed (external or self-calibration).

NIDMM_VAL_INTERNAL_AREA (default)	0	Self-Calibration
NIDMM_VAL_EXTERNAL_AREA	1	External Calibration

---

**Note:** The NI 4065 does not support self-calibration.

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

**Return type** float

**Returns** Returns the **temperature** during the last calibration.

## get\_self\_cal\_supported

`nidmm.Session.get_self_cal_supported()`

Returns a Boolean value that expresses whether or not the DMM that you are using can perform self-calibration.

**Return type** bool

**Returns**

Returns whether Self Cal is supported for the device specified by the given session.

True	1	The DMM that you are using can perform self-calibration.
False	0	The DMM that you are using cannot perform self-calibration.

## lock

`nidmm.Session.lock()`

Obtains a multithread lock on the device session. Before doing so, the software waits until all other execution threads release their locks on the device session.

Other threads may have obtained a lock on this session for the following reasons:

- The application called the `nidmm.Session.lock()` method.
- A call to NI-DMM locked the session.
- After a call to the `nidmm.Session.lock()` method returns successfully, no other threads can access the device session until you call the `nidmm.Session.unlock()` method or exit out of the with block when using lock context manager.
- Use the `nidmm.Session.lock()` method and the `nidmm.Session.unlock()` method around a sequence of calls to instrument driver methods if you require that the device retain its settings through the end of the sequence.

You can safely make nested calls to the `nidmm.Session.lock()` method within the same thread. To completely unlock the session, you must balance each call to the `nidmm.Session.lock()` method with a call to the `nidmm.Session.unlock()` method.

One method for ensuring there are the same number of unlock method calls as there is lock calls is to use lock as a context manager

```
with nidmm.Session('dev1') as session:
    with session.lock():
        # Calls to session within a single lock context
```

The first *with* block ensures the session is closed regardless of any exceptions raised

The second *with* block ensures that unlock is called regardless of any exceptions raised

**Return type** context manager

**Returns** When used in a *with* statement, `nidmm.Session.lock()` acts as a context manager and unlock will be called when the *with* block is exited

## perform\_open\_cable\_comp

`nidmm.Session.perform_open_cable_comp()`

For the NI 4082 and NI 4072 only, performs the open cable compensation measurements for the current capacitance/inductance range, and returns open cable compensation **Conductance** and **Susceptance** values. You can use the return values of this method as inputs to `nidmm.Session.ConfigureOpenCableCompValues()`.

This method returns an error if the value of the `nidmm.Session.method` property is not set to CAPACITANCE (1005) or INDUCTANCE (1006).

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

### Return type

tuple (conductance, susceptance)

WHERE

conductance (float):

**conductance** is the measured value of open cable compensation **conductance**.

susceptance (float):

**susceptance** is the measured value of open cable compensation **susceptance**.

## perform\_short\_cable\_comp

`nidmm.Session.perform_short_cable_comp()`

Performs the short cable compensation measurements for the current capacitance/inductance range, and returns short cable compensation **Resistance** and **Reactance** values. You can use the return values of this method as inputs to `nidmm.Session.ConfigureShortCableCompValues()`.

This method returns an error if the value of the `nidmm.Session.method` property is not set to CAPACITANCE (1005) or INDUCTANCE (1006).

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

### Return type

tuple (resistance, reactance)

WHERE

resistance (float):

**resistance** is the measured value of short cable compensation **resistance**.

reactance (float):

**reactance** is the measured value of short cable compensation **reactance**.



## read

```
nidmm.Session.read(maximum_time=datetime.timedelta(milliseconds=-1))
```

Acquires a single measurement and returns the measured value.

**Parameters** **maximum\_time** (*float in seconds or `datetime.timedelta`*) – Specifies the **maximum\_time** allowed for this method to complete in milliseconds. If the method does not complete within this time interval, the method returns the `NIDMM_ERROR_MAX_TIME_EXCEEDED` error code. This may happen if an external trigger has not been received, or if the specified timeout is not long enough for the acquisition to complete.

The valid range is 0–86400000. The default value is `NIDMM_VAL_TIME_LIMIT_AUTO` (-1). The DMM calculates the timeout automatically.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

**Return type** `float`

**Returns** The measured value returned from the DMM.

## read\_multi\_point

```
nidmm.Session.read_multi_point(array_size, maximum_time=datetime.timedelta(milliseconds=-1))
```

Acquires multiple measurements and returns an array of measured values. The number of measurements the DMM makes is determined by the values you specify for the **Trigger\_Count** and **Sample\_Count** parameters in `nidmm.Session.configure_multi_point()`.

### Parameters

- **array\_size** (*int*) – Specifies the number of measurements to acquire. The maximum number of measurements for a finite acquisition is the (**Trigger\_Count** x **Sample\_Count**) parameters in `nidmm.Session.configure_multi_point()`.

For continuous acquisitions, up to 100,000 points can be returned at once. The number of measurements can be a subset. The valid range is any positive `ViInt32`. The default value is 1.

- **maximum\_time** (*float in seconds or `datetime.timedelta`*) – Specifies the **maximum\_time** allowed for this method to complete in milliseconds. If the method does not complete within this time interval, the method returns the `NIDMM_ERROR_MAX_TIME_EXCEEDED` error code. This may happen if an external trigger has not been received, or if the specified timeout is not long enough for the acquisition to complete.

The valid range is 0–86400000. The default value is `NIDMM_VAL_TIME_LIMIT_AUTO` (-1). The DMM calculates the timeout automatically.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

**Return type**

tuple (reading\_array, actual\_number\_of\_points)

WHERE

reading\_array (array.array("d")):

An array of measurement values.

---

**Note:** The size of the **Reading\_Array** must be at least the size that you specify for the **Array\_Size** parameter.

---

actual\_number\_of\_points (int):

Indicates the number of measured values actually retrieved from the DMM.

**read\_status**

`nidmm.Session.read_status()`

Returns measurement backlog and acquisition status. Use this method to determine how many measurements are available before calling `nidmm.Session.fetch()`, `nidmm.Session.fetch_multi_point()`, or `nidmm.Session.fetch_waveform()`.

---

**Note:** The NI 4050 is not supported.

---

**Return type**

tuple (acquisition\_backlog, acquisition\_status)

WHERE

acquisition\_backlog (int):

The number of measurements available to be read. If the backlog continues to increase, data is eventually overwritten, resulting in an error.

---

**Note:** On the NI 4060, the **Backlog** does not increase when autoranging. On the NI 4065, the **Backlog** does not increase when Range is set to AUTO RANGE ON (-1), or before the first point is fetched when Range is set to AUTO RANGE ONCE (-3). These behaviors are due to the autorange model of the devices.

---

acquisition\_status (`nidmm.AcquisitionStatus`):

Indicates status of the acquisition. The following table shows the acquisition states:

0	Running
1	Finished with backlog
2	Finished with no backlog
3	Paused
4	No acquisition in progress

## read\_waveform

```
nidmm.Session.read_waveform(array_size, maximum_time=datetime.timedelta(milliseconds=-1))
```

For the NI 4080/4081/4082 and the NI 4070/4071/4072, acquires a waveform and returns data as an array of values or as a waveform data type. The number of elements in the **Waveform\_Array** is determined by the values you specify for the **Waveform\_Points** parameter in `nidmm.Session.configure_waveform_acquisition()`.

### Parameters

- **array\_size** (*int*) – Specifies the number of waveform points to return. You specify the total number of points that the DMM acquires in the **Waveform\_Points** parameter of `nidmm.Session.configure_waveform_acquisition()`. The default value is 1.
- **maximum\_time** (*float in seconds or datetime.timedelta*) – Specifies the **maximum\_time** allowed for this method to complete in milliseconds. If the method does not complete within this time interval, the method returns the `NIDMM_ERROR_MAX_TIME_EXCEEDED` error code. This may happen if an external trigger has not been received, or if the specified timeout is not long enough for the acquisition to complete.

The valid range is 0–86400000. The default value is `NIDMM_VAL_TIME_LIMIT_AUTO` (-1). The DMM calculates the timeout automatically.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

### Return type

tuple (waveform\_array, actual\_number\_of\_points)

#### WHERE

waveform\_array (array.array("d")):

An array of measurement values.

---

**Note:** The size of the **Waveform\_Array** must be at least the size that you specify for the **Array\_Size** parameter.

---

actual\_number\_of\_points (int):

Indicates the number of measured values actually retrieved from the DMM.

## reset

```
nidmm.Session.reset()
```

Resets the instrument to a known state and sends initialization commands to the instrument. The initialization commands set instrument settings to the state necessary for the operation of the instrument driver.

## reset\_with\_defaults

`nidmm.Session.reset_with_defaults()`

Resets the instrument to a known state and sends initialization commands to the DMM. The initialization commands set the DMM settings to the state necessary for the operation of NI-DMM. All user-defined default values associated with a logical name are applied after setting the DMM.

## self\_cal

`nidmm.Session.self_cal()`

For the NI 4080/4081/4082 and the NI 4070/4071/4072, executes the self-calibration routine to maintain measurement accuracy.

---

**Note:** This method calls `nidmm.Session.reset()`, and any configurations previous to the call will be lost. All properties will be set to their default values after the call returns.

---

## self\_test

`nidmm.Session.self_test()`

Performs a self-test on the DMM to ensure that the DMM is functioning properly. Self-test does not calibrate the DMM. Zero indicates success.

On the NI 4080/4082 and NI 4070/4072, the error code 1013 indicates that you should check the fuse and replace it, if necessary.

Raises `SelfTestError` on self test failure. Properties on exception object:

- code - failure code from driver
- message - status message from driver

---

**Note:** Self-test does not check the fuse on the NI 4065, NI 4071, and NI 4081. Hence, even if the fuse is blown on the device, self-test does not return error code 1013.

---



---

**Note:** This method calls `nidmm.Session.reset()`, and any configurations previous to the call will be lost. All properties will be set to their default values after the call returns.

---

## send\_software\_trigger

`nidmm.Session.send_software_trigger()`

Sends a command to trigger the DMM. Call this method if you have configured either the `nidmm.Session.trigger_source` or `nidmm.Session.sample_trigger` properties. If the `nidmm.Session.trigger_source` and/or `nidmm.Session.sample_trigger` properties are set to `NIDMM_VAL_EXTERNAL` or `NIDMM_VAL_TTLn`, you can use this method to override the trigger source that you configured and trigger the device. The NI 4050 and NI 4060 are not supported.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## unlock

`nidmm.Session.unlock()`

Releases a lock that you acquired on an device session using `nidmm.Session.lock()`. Refer to `nidmm.Session.unlock()` for additional information on session locks.

## Properties

Property	Datatype
<code>nidmm.Session.ac_max_freq</code>	float
<code>nidmm.Session.ac_min_freq</code>	float
<code>nidmm.Session.adc_calibration</code>	ADCCalibration
<code>nidmm.Session.aperture_time</code>	float
<code>nidmm.Session.aperture_time_units</code>	ApertureTimeUnits
<code>nidmm.Session.auto_range_value</code>	float
<code>nidmm.Session.auto_zero</code>	AutoZero
<code>nidmm.Session.buffer_size</code>	int
<code>nidmm.Session.cable_comp_type</code>	CableCompensationType
<code>nidmm.Session.channel_count</code>	int
<code>nidmm.Session.current_source</code>	float
<code>nidmm.Session.dc_bias</code>	bool
<code>nidmm.Session.dc_noise_rejection</code>	DCNoiseRejection
<code>nidmm.Session.driver_setup</code>	str
<code>nidmm.Session.freq_voltage_auto_range</code>	float
<code>nidmm.Session.freq_voltage_range</code>	float
<code>nidmm.Session.function</code>	Function
<code>nidmm.Session.input_resistance</code>	float
<code>nidmm.Session.instrument_firmware_revision</code>	str
<code>nidmm.Session.instrument_manufacturer</code>	str
<code>nidmm.Session.instrument_model</code>	str
<code>nidmm.Session.instrument_product_id</code>	int
<code>nidmm.Session.io_resource_descriptor</code>	str
<code>nidmm.Session.lc_calculation_model</code>	LCCalculationModel
<code>nidmm.Session.lc_number_meas_to_average</code>	int
<code>nidmm.Session.logical_name</code>	str
<code>nidmm.Session.meas_complete_dest</code>	MeasurementCompleteDest
<code>nidmm.Session.number_of_averages</code>	int
<code>nidmm.Session.offset_comp_ohms</code>	bool
<code>nidmm.Session.open_cable_comp_conductance</code>	float
<code>nidmm.Session.open_cable_comp_susceptance</code>	float
<code>nidmm.Session.operation_mode</code>	OperationMode
<code>nidmm.Session.powerline_freq</code>	float
<code>nidmm.Session.range</code>	float
<code>nidmm.Session.resolution_absolute</code>	float

Continued on next page

Table 5 – continued from previous page

Property	Datatype
<code>nidmm.Session.resolution_digits</code>	float
<code>nidmm.Session.sample_count</code>	int
<code>nidmm.Session.sample_interval</code>	float in seconds or <code>datetime.timedelta</code>
<code>nidmm.Session.sample_trigger</code>	SampleTrigger
<code>nidmm.Session.serial_number</code>	str
<code>nidmm.Session.settle_time</code>	float in seconds or <code>datetime.timedelta</code>
<code>nidmm.Session.short_cable_comp_reactance</code>	float
<code>nidmm.Session.short_cable_comp_resistance</code>	float
<code>nidmm.Session.simulate</code>	bool
<code>nidmm.Session.specific_driver_description</code>	str
<code>nidmm.Session.specific_driver_major_version</code>	int
<code>nidmm.Session.specific_driver_minor_version</code>	int
<code>nidmm.Session.specific_driver_revision</code>	str
<code>nidmm.Session.specific_driver_vendor</code>	str
<code>nidmm.Session.supported_instrument_models</code>	str
<code>nidmm.Session.temp_rtd_a</code>	float
<code>nidmm.Session.temp_rtd_b</code>	float
<code>nidmm.Session.temp_rtd_c</code>	float
<code>nidmm.Session.temp_rtd_res</code>	float
<code>nidmm.Session.temp_rtd_type</code>	RTDType
<code>nidmm.Session.temp_tc_fixed_ref_junc</code>	float
<code>nidmm.Session.temp_tc_ref_junc_type</code>	ThermocoupleReferenceJunctionType
<code>nidmm.Session.temp_tc_type</code>	ThermocoupleType
<code>nidmm.Session.temp_thermistor_a</code>	float
<code>nidmm.Session.temp_thermistor_b</code>	float
<code>nidmm.Session.temp_thermistor_c</code>	float
<code>nidmm.Session.temp_thermistor_type</code>	ThermistorType
<code>nidmm.Session.temp_transducer_type</code>	TransducerType
<code>nidmm.Session.trigger_count</code>	int
<code>nidmm.Session.trigger_delay</code>	float in seconds or <code>datetime.timedelta</code>
<code>nidmm.Session.trigger_source</code>	TriggerSource
<code>nidmm.Session.waveform_coupling</code>	WaveformCoupling
<code>nidmm.Session.waveform_points</code>	int
<code>nidmm.Session.waveform_rate</code>	float

## Methods

Method name
<code>nidmm.Session.abort()</code>
<code>nidmm.Session.configure_measurement_absolute()</code>
<code>nidmm.Session.configure_measurement_digits()</code>
<code>nidmm.Session.configure_multi_point()</code>
<code>nidmm.Session.configure_rtd_custom()</code>
<code>nidmm.Session.configure_rtd_type()</code>
<code>nidmm.Session.configure_thermistor_custom()</code>
<code>nidmm.Session.configure_thermocouple()</code>
<code>nidmm.Session.configure_trigger()</code>
<code>nidmm.Session.configure_waveform_acquisition()</code>

Continued on next page

Table 6 – continued from previous page

Method name
<code>nidmm.Session.disable()</code>
<code>nidmm.Session.fetch()</code>
<code>nidmm.Session.fetch_multi_point()</code>
<code>nidmm.Session.fetch_waveform()</code>
<code>nidmm.Session.fetch_waveform_into()</code>
<code>nidmm.Session.get_cal_date_and_time()</code>
<code>nidmm.Session.get_dev_temp()</code>
<code>nidmm.Session.get_ext_cal_recommended_interval()</code>
<code>nidmm.Session.get_last_cal_temp()</code>
<code>nidmm.Session.get_self_cal_supported()</code>
<code>nidmm.Session.lock()</code>
<code>nidmm.Session.perform_open_cable_comp()</code>
<code>nidmm.Session.perform_short_cable_comp()</code>
<code>nidmm.Session.read()</code>
<code>nidmm.Session.read_multi_point()</code>
<code>nidmm.Session.read_status()</code>
<code>nidmm.Session.read_waveform()</code>
<code>nidmm.Session.reset()</code>
<code>nidmm.Session.reset_with_defaults()</code>
<code>nidmm.Session.self_cal()</code>
<code>nidmm.Session.self_test()</code>
<code>nidmm.Session.send_software_trigger()</code>
<code>nidmm.Session.unlock()</code>

### 7.2.3.2 Enums

Enums used in NI-DMM

#### ADCCalibration

**class** `nidmm.ADCCalibration`

##### **AUTO**

The DMM enables or disables ADC calibration for you.

##### **OFF**

The DMM does not compensate for changes to the gain.

##### **ON**

The DMM measures an internal reference to calculate the correct gain for the measurement.

#### AcquisitionStatus

**class** `nidmm.AcquisitionStatus`

##### **RUNNING**

Running

##### **FINISHED\_WITH\_BACKLOG**

Finished with **Backlog**

**FINISHED\_WITH\_NO\_BACKLOG**

Finished with no **Backlog**

**PAUSED**

Paused

**NO\_ACQUISITION\_IN\_PROGRESS**

No acquisition in progress

## ApertureTimeUnits

**class** `nidmm.ApertureTimeUnits`

**SECONDS**

Seconds

**POWER\_LINE\_CYCLES**

Powerline Cycles

## AutoZero

**class** `nidmm.AutoZero`

**AUTO**

The drivers chooses the AutoZero setting based on the configured method and resolution.

**OFF**

Disables AutoZero.

**ON**

The DMM internally disconnects the input signal following each measurement and takes a zero reading. It then subtracts the zero reading from the preceding reading.

**ONCE**

The DMM internally disconnects the input signal for the first measurement and takes a zero reading. It then subtracts the zero reading from the first reading and the following readings.

## CableCompensationType

**class** `nidmm.CableCompensationType`

**NONE**

No Cable Compensation

**OPEN**

Open Cable Compensation

**SHORT**

Short Cable Compensation

**OPEN\_AND\_SHORT**

Open and Short Cable Compensation



## DCNoiseRejection

```
class nidmm.DCNoiseRejection
```

### AUTO

The driver chooses the DC noise rejection setting based on the configured method and resolution.

### NORMAL

NI-DMM weighs all samples equally.

### SECOND\_ORDER

NI-DMM weighs the samples taken in the middle of the aperture time more than samples taken at the beginning and the end of the measurement using a triangular weighing method.

### HIGH\_ORDER

NI-DMM weighs the samples taken in the middle of the aperture time more than samples taken at the beginning and the end of the measurement using a bell-curve weighing method.

## Function

```
class nidmm.Function
```

### DC\_VOLTS

DC Voltage

### AC\_VOLTS

AC Voltage

### DC\_CURRENT

DC Current

### AC\_CURRENT

AC Current

### TWO\_WIRE\_RES

2-Wire Resistance

### FOUR\_WIRE\_RES

4-Wire Resistance

### FREQ

Frequency

### PERIOD

Period

### TEMPERATURE

NI 4065, and NI 4070/4071/4072 supported.

### AC\_VOLTS\_DC\_COUPLED

AC Voltage with DC Coupling

### DIODE

Diode

### WAVEFORM\_VOLTAGE

Waveform voltage

**WAVEFORM\_CURRENT**

Waveform current

**CAPACITANCE**

Capacitance

**INDUCTANCE**

Inductance

## LCCalculationModel

```
class nidmm.LCCalculationModel
```

**AUTO**

NI-DMM chooses the algorithm based on method and range

**SERIES**

NI-DMM uses the series impedance model to calculate capacitance and inductance

**PARALLEL**

NI-DMM uses the parallel admittance model to calculate capacitance and inductance

## MeasurementCompleteDest

```
class nidmm.MeasurementCompleteDest
```

**NONE**

No Trigger

**EXTERNAL**

AUX I/O Connector

**PXI\_TRIG0**

PXI Trigger Line 0

**PXI\_TRIG1**

PXI Trigger Line 1

**PXI\_TRIG2**

PXI Trigger Line 2

**PXI\_TRIG3**

PXI Trigger Line 3

**PXI\_TRIG4**

PXI Trigger Line 4

**PXI\_TRIG5**

PXI Trigger Line 5

**PXI\_TRIG6**

PXI Trigger Line 6

**PXI\_TRIG7**

PXI Trigger Line 7

**LBR\_TRIG0**

Internal Trigger Line of a PXI/SCXI Combination Chassis

## OperationMode

**class** `nidmm.OperationMode`

**IVIDMM**

IviDmm Mode

**WAVEFORM**

Waveform acquisition mode

## RTDType

**class** `nidmm.RTDType`

**CUSTOM**

Performs Callendar-Van Dusen RTD scaling with the user-specified A, B, and C coefficients.

**PT3750**

Performs scaling for a Pt 3750 RTD.

**PT3851**

Performs scaling for a Pt 3851 RTD.

**PT3911**

Performs scaling for a Pt 3911 RTD.

**PT3916**

Performs scaling for a Pt 3916 RTD.

**PT3920**

Performs scaling for a Pt 3920 RTD.

**PT3928**

Performs scaling for a Pt 3928 RTD.

## SampleTrigger

**class** `nidmm.SampleTrigger`

**IMMEDIATE**

No Trigger

**EXTERNAL**

AUX I/O Connector Trigger Line 0

**SOFTWARE\_TRIG**

Software Trigger

**INTERVAL**

Interval Trigger

**PXI\_TRIG0**

PXI Trigger Line 0

**PXI\_TRIG1**

PXI Trigger Line 1

**PXI\_TRIG2**  
PXI Trigger Line 2

**PXI\_TRIG3**  
PXI Trigger Line 3

**PXI\_TRIG4**  
PXI Trigger Line 4

**PXI\_TRIG5**  
PXI Trigger Line 5

**PXI\_TRIG6**  
PXI Trigger Line 6

**PXI\_TRIG7**  
PXI Trigger Line 7

**PXI\_STAR**  
PXI Star Trigger Line

**AUX\_TRIG1**  
AUX I/O Connector Trigger Line 1

**LBR\_TRIG1**  
Internal Trigger Line of a PXI/SCXI Combination Chassis

## ThermistorType

**class** `nidmm.ThermistorType`

**CUSTOM**  
Custom

**THERMISTOR\_44004**  
44004

**THERMISTOR\_44006**  
44006

**THERMISTOR\_44007**  
44007

## ThermocoupleReferenceJunctionType

**class** `nidmm.ThermocoupleReferenceJunctionType`

**FIXED**  
Thermocouple reference junction is fixed at the user-specified temperature.

## ThermocoupleType

**class** `nidmm.ThermocoupleType`

<b>B</b>	Thermocouple type B
<b>E</b>	Thermocouple type E
<b>J</b>	Thermocouple type J
<b>K</b>	Thermocouple type K
<b>N</b>	Thermocouple type N
<b>R</b>	Thermocouple type R
<b>S</b>	Thermocouple type S
<b>T</b>	Thermocouple type T

## TransducerType

```
class nidmm.TransducerType
```

<b>THERMOCOUPLE</b>	Thermocouple
<b>THERMISTOR</b>	Thermistor
<b>TWO_WIRE_RTD</b>	2-wire RTD
<b>FOUR_WIRE_RTD</b>	4-wire RTD

## TriggerSource

```
class nidmm.TriggerSource
```

<b>IMMEDIATE</b>	No Trigger
<b>EXTERNAL</b>	AUX I/O Connector Trigger Line 0
<b>SOFTWARE_TRIG</b>	Software Trigger
<b>PXI_TRIG0</b>	PXI Trigger Line 0
<b>PXI_TRIG1</b>	PXI Trigger Line 1

**PXI\_TRIG2**  
PXI Trigger Line 2

**PXI\_TRIG3**  
PXI Trigger Line 3

**PXI\_TRIG4**  
PXI Trigger Line 4

**PXI\_TRIG5**  
PXI Trigger Line 5

**PXI\_TRIG6**  
PXI Trigger Line 6

**PXI\_TRIG7**  
PXI Trigger Line 7

**PXI\_STAR**  
PXI Star Trigger Line

**AUX\_TRIG1**  
AUX I/O Connector Trigger Line 1

**LBR\_TRIG1**  
Internal Trigger Line of a PXI/SCXI Combination Chassis

## WaveformCoupling

**class** `nidmm.WaveformCoupling`

**AC**  
AC Coupled

**DC**  
DC Coupled

### 7.2.3.3 Exceptions and Warnings

#### DriverError

**exception** `nidmm.DriverError`  
An error originating from the NI-DMM driver

#### UnsupportedConfigurationError

**exception** `nidmm.UnsupportedConfigurationError`  
An error due to using this module in an unsupported platform.

#### DriverNotInstalledError

**exception** `nidmm.DriverNotInstalledError`  
An error due to using this module without the driver runtime installed.

## InvalidRepeatedCapabilityError

**exception** `nidmm.InvalidRepeatedCapabilityError`

An error due to an invalid character in a repeated capability

## SelfTestError

**exception** `nidmm.SelfTestError`

An error due to a failed self-test

## DriverWarning

**exception** `nidmm.DriverWarning`

A warning originating from the NI-DMM driver

### 7.2.3.4 Examples

#### `nidmm_fetch_waveform.py`

Listing 3: (`nidmm_fetch_waveform.py`)

```

1  #!/usr/bin/python
2
3  import argparse
4  import nidmm
5  import sys
6  import time
7
8
9  def example(resource_name, options, function, range, points, rate):
10     with nidmm.Session(resource_name=resource_name, options=options) as session:
11         session.configure_waveform_acquisition(measurement_function=nidmm.
12         ↪Function[function], range=range, rate=rate, waveform_points=points)
13         with session.initiate():
14             while True:
15                 time.sleep(0.1)
16                 backlog, acquisition_state = session.read_status()
17                 if acquisition_state == nidmm.AcquisitionStatus.FINISHED_WITH_NO_
18                 ↪BACKLOG:
19                     break
20                 measurements = session.fetch_waveform(array_size=backlog)
21                 print(measurements)
22
23 def _main(argv):
24     parser = argparse.ArgumentParser(description='Performs a waveform acquisition_
25     ↪using the NI-DMM API.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)
26     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
27     ↪name of a National Instruments Digital Multimeter.')
28     parser.add_argument('-f', '--function', default='WAVEFORM_VOLTAGE', choices=nidmm.
29     ↪Function.__members__.keys(), type=str.upper, help='Measurement function.')
30     parser.add_argument('-r', '--range', default=10, type=float, help='Measurement_
31     ↪range.')

```

(continues on next page)

(continued from previous page)

```

27     parser.add_argument('-p', '--points', default=10, type=int, help='Specifies the
↳ number of points to acquire before the waveform acquisition completes.')
28     parser.add_argument('-s', '--rate', default=1000, type=int, help='Specifies the
↳ rate of the acquisition in samples per second.')
29     parser.add_argument('-op', '--option-string', default='', type=str, help='Option
↳ string')
30     args = parser.parse_args(argv)
31     example(args.resource_name, args.option_string, args.function, args.range, args.
↳ points, args.rate)
32
33
34 def main():
35     _main(sys.argv[1:])
36
37
38 def test_example():
39     options = {'simulate': True, 'driver_setup': {'Model': '4082', 'BoardType': 'PXIe
↳ ', }, }
40     example('PXI1Slot2', options, 'WAVEFORM_VOLTAGE', 10, 10, 1000)
41
42
43 def test_main():
44     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:4082; BoardType:PXIe
↳ ', ]
45     _main(cmd_line)
46
47
48 if __name__ == '__main__':
49     main()
50
51

```

## nidmm\_measurement.py

Listing 4: (nidmm\_measurement.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import nidmm
5  import sys
6
7
8  def example(resource_name, option_string, function, range, digits):
9      with nidmm.Session(resource_name=resource_name, options=option_string) as session:
10         session.configure_measurement_digits(measurement_function=nidmm.
↳ Function[function], range=range, resolution_digits=digits)
11         print(session.read())
12
13
14 def _main(argv):
15     supported_functions = list(nidmm.Function.__members__.keys())
16     parser = argparse.ArgumentParser(description='Performs a single measurement using
↳ the NI-DMM API.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)

```

(continues on next page)



(continued from previous page)

```

17     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
↳ name of a National Instruments Digital Multimeter.')
18     parser.add_argument('-f', '--function', default=supported_functions[0],
↳ choices=supported_functions, type=str.upper, help='Measurement function.')
19     parser.add_argument('-r', '--range', default=10, type=float, help='Measurement_
↳ range.')
20     parser.add_argument('-d', '--digits', default=6.5, type=float, help='Digits of_
↳ resolution for the measurement.')
21     parser.add_argument('-op', '--option-string', default='', type=str, help='Option_
↳ string')
22     args = parser.parse_args(argv)
23     example(args.resource_name, args.option_string, args.function, args.range, args.
↳ digits)
24
25
26 def main():
27     _main(sys.argv[1:])
28
29
30 def test_example():
31     options = {'simulate': True, 'driver_setup': {'Model': '4082', 'BoardType': 'PXIe
↳ ', }, }
32     example('PXI1Slot2', options, 'DC_VOLTS', 10, 6.5)
33
34
35 def test_main():
36     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:4082; BoardType:PXIe
↳ ', ]
37     _main(cmd_line)
38
39
40 if __name__ == '__main__':
41     main()
42
43

```

## nidmm\_multi\_point\_measurement.py

Listing 5: (nidmm\_multi\_point\_measurement.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import nidmm
5  import sys
6
7
8  def example(resource_name, options, function, range, digits, samples, triggers):
9      with nidmm.Session(resource_name=resource_name, options=options) as session:
10         session.configure_measurement_digits(measurement_function=nidmm.
↳ Function[function], range=range, resolution_digits=digits)
11         session.configure_multi_point(trigger_count=triggers, sample_count=samples)
12         measurements = session.read_multi_point(array_size=samples)
13         print('Measurements: ', measurements)

```

(continues on next page)

(continued from previous page)

```

14
15
16 def _main(argv):
17     parser = argparse.ArgumentParser(description='Performs a multipoint measurement_
↳ using the NI-DMM API.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)
18     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
↳ name of a National Instruments Digital Multimeter.')
19     parser.add_argument('-f', '--function', default='DC_VOLTS', choices=nidmm.
↳ Function.__members__.keys(), type=str.upper, help='Measurement function.')
20     parser.add_argument('-r', '--range', default=10, type=float, help='Measurement_
↳ range.')
21     parser.add_argument('-d', '--digits', default=6.5, type=float, help='Digits of_
↳ resolution for the measurement.')
22     parser.add_argument('-s', '--samples', default=10, type=int, help='The number of_
↳ measurements the DMM makes.')
23     parser.add_argument('-t', '--triggers', default=1, type=int, help='Sets the_
↳ number of triggers you want the DMM to receive before returning to the Idle state.')
24     parser.add_argument('-op', '--option-string', default='', type=str, help='Option_
↳ string')
25     args = parser.parse_args(argv)
26     example(args.resource_name, args.option_string, args.function, args.range, args.
↳ digits, args.samples, args.triggers)
27
28
29 def main():
30     _main(sys.argv[1:])
31
32
33 def test_example():
34     options = {'simulate': True, 'driver_setup': {'Model': '4082', 'BoardType': 'PXIe
↳ ', }, }
35     example('PXI1Slot2', options, 'DC_VOLTS', 10, 6.5, 10, 1)
36
37
38 def test_main():
39     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:4082; BoardType:PXIe
↳ ', ]
40     _main(cmd_line)
41
42
43 if __name__ == '__main__':
44     main()
45
46
47

```

## 7.3 nifgen module

### 7.3.1 Installation

As a prerequisite to using the nifgen module, you must install the NI-FGEN runtime on your system. Visit [ni.com/downloads](https://ni.com/downloads) to download the driver runtime for your devices.

The nimi-python modules (i.e. for **NI-FGEN**) can be installed with `pip`:

```
$ python -m pip install nifgen~=1.0.0
```

Or `easy_install` from `setuptools`:

```
$ python -m easy_install nifgen
```

## 7.3.2 Usage

The following is a basic example of using the **nifgen** module to open a session to a Function Generator and generate a sine wave for 5 seconds.

```
import nifgen
import time
with nifgen.Session("Dev1") as session:
    session.output_mode = nifgen.OutputMode.FUNC
    session.configure_standard_waveform(waveform=nifgen.Waveform.SINE, amplitude=1.0,
    frequency=10000000, dc_offset=0.0, start_phase=0.0)
    with session.initiate():
        time.sleep(5)
```

Additional examples for NI-FGEN are located in `src/nifgen/examples/` directory.

## 7.3.3 API Reference

### 7.3.3.1 nifgen.Session

**class** `nifgen.Session` (*self*, *resource\_name*, *channel\_name=None*, *reset\_device=False*, *options={}*)

Creates and returns a new NI-FGEN session to the specified channel of a waveform generator that is used in all subsequent NI-FGEN method calls.

#### Parameters

- **resource\_name** (*str*) –

**Caution:** Traditional NI-DAQ and NI-DAQmx device names are not case-sensitive. However, all IVI names, such as logical names, are case-sensitive. If you use logical names, driver session names, or virtual names in your program, you must ensure that the name you use matches the name in the IVI Configuration Store file exactly, without any variations in the case of the characters.

Specifies the resource name of the device to initialize.

For Traditional NI-DAQ devices, the syntax is `DAQ::n`, where *n* is the device number assigned by MAX, as shown in Example 1.

For NI-DAQmx devices, the syntax is just the device name specified in MAX, as shown in Example 2. Typical default names for NI-DAQmx devices in MAX are `Dev1` or `PXI1Slot1`. You can rename an NI-DAQmx device by right-clicking on the name in MAX and entering a new name.

An alternate syntax for NI-DAQmx devices consists of `DAQ::NI-DAQmx device name`, as shown in Example 3. This naming convention allows for the use of an NI-DAQmx device in an application that was originally designed for a Traditional NI-DAQ device. For example, if the application expects `DAQ::1`, you can rename the NI-DAQmx device to 1 in MAX and pass in `DAQ::1` for the resource name, as shown in Example 4.

If you use the `DAQ::n` syntax and an NI-DAQmx device name already exists with that same name, the NI-DAQmx device is matched first.

You can also pass in the name of an IVI logical name or an IVI virtual name configured with the IVI Configuration utility, as shown in Example 5. A logical name identifies a particular virtual instrument. A virtual name identifies a specific device and specifies the initial settings for the session.

Ex-ample #	Device Type	Syntax	Variable
1	Traditional NI-DAQ device	<code>DAQ::I</code>	( <i>I</i> = device number)
2	NI-DAQmx device	<code>myDAQmxDevice</code>	( <i>myDAQmxDevice</i> = device name)
3	NI-DAQmx device	<code>DAQ::myDAQmxDevice</code>	( <i>myDAQmxDevice</i> = device name)
4	NI-DAQmx device	<code>DAQ::2</code>	( <i>2</i> = device name)
5	IVI logical name or IVI virtual name	<code>myLogicalName</code>	( <i>myLogicalName</i> = name)

- **channel\_name** (*str*) – Specifies the channel that this VI uses.

**Default Value:** “0”

- **reset\_device** (*bool*) – Specifies whether you want to reset the device during the initialization procedure. True specifies that the device is reset and performs the same method as the `nifgen.Session.Reset()` method.

**\*\*Defined Values\*\***

**Default Value:** False

True	Reset device
False	Do not reset device

- **options** (*str*) – Specifies the initial value of certain properties for the session. The syntax for **options** is a dictionary of properties with an assigned value. For example:

```
{ 'simulate': False }
```

You do not have to specify a value for all the properties. If you do not specify a value for a property, the default value is used.

Advanced Example: { 'simulate': True, 'driver\_setup': { 'Model': '<model number>', 'BoardType': '<type>' } }

Property	Default
range_check	True
query_instrument_status	False
cache	True
simulate	False
record_value_coersions	False
driver_setup	{}

### Properties

Property	Datatype
<i>all_marker_events_latched_status</i>	int
<i>all_marker_events_live_status</i>	int
<i>analog_data_mask</i>	int
<i>analog_filter_enabled</i>	bool
<i>analog_path</i>	<i>AnalogPath</i>
<i>analog_static_value</i>	int
<i>arb_gain</i>	float
<i>arb_marker_position</i>	int
<i>arb_offset</i>	float
<i>arb_repeat_count</i>	int
<i>arb_sample_rate</i>	float
<i>arb_sequence_handle</i>	int
<i>arb_waveform_handle</i>	int
<i>aux_power_enabled</i>	bool
<i>bus_type</i>	<i>BusType</i>
<i>channel_count</i>	int
<i>channel_delay</i>	float
<i>clock_mode</i>	<i>ClockMode</i>
<i>common_mode_offset</i>	float
<i>data_marker_events_count</i>	int
<i>data_marker_event_data_bit_number</i>	int
<i>data_marker_event_level_polarity</i>	<i>DataMarkerEventLevelPolarity</i>
<i>data_marker_event_output_terminal</i>	str
<i>data_transfer_block_size</i>	int
<i>data_transfer_maximum_bandwidth</i>	float
<i>data_transfer_maximum_in_flight_reads</i>	int
<i>data_transfer_preferred_packet_size</i>	int
<i>digital_data_mask</i>	int
<i>digital_edge_script_trigger_edge</i>	<i>ScriptTriggerDigitalEdgeEdge</i>
<i>digital_edge_script_trigger_source</i>	str
<i>digital_edge_start_trigger_edge</i>	<i>StartTriggerDigitalEdgeEdge</i>
<i>digital_edge_start_trigger_source</i>	str
<i>digital_filter_enabled</i>	bool
<i>digital_filter_interpolation_factor</i>	float
<i>digital_gain</i>	float
<i>digital_pattern_enabled</i>	bool
<i>digital_static_value</i>	int
<i>done_event_output_terminal</i>	str
<i>driver_setup</i>	str

Continued on next page

Table 7 – continued from previous page

Property	Datatype
<i>exported_onboard_reference_clock_output_terminal</i>	str
<i>exported_reference_clock_output_terminal</i>	str
<i>exported_sample_clock_divisor</i>	int
<i>exported_sample_clock_output_terminal</i>	str
<i>exported_sample_clock_timebase_divisor</i>	int
<i>exported_sample_clock_timebase_output_terminal</i>	str
<i>exported_script_trigger_output_terminal</i>	str
<i>exported_start_trigger_output_terminal</i>	str
<i>external_clock_delay_binary_value</i>	int
<i>external_sample_clock_multiplier</i>	float
<i>file_transfer_block_size</i>	int
<i>filter_correction_frequency</i>	float
<i>flatness_correction_enabled</i>	bool
<i>fpga_bitfile_path</i>	str
<i>freq_list_duration_quantum</i>	float
<i>freq_list_handle</i>	int
<i>func_amplitude</i>	float
<i>func_buffer_size</i>	int
<i>func_dc_offset</i>	float
<i>func_duty_cycle_high</i>	float
<i>func_frequency</i>	float
<i>func_max_buffer_size</i>	int
<i>func_start_phase</i>	float
<i>func_waveform</i>	<i>Waveform</i>
<i>idle_behavior</i>	<i>IdleBehavior</i>
<i>idle_value</i>	int
<i>instrument_firmware_revision</i>	str
<i>instrument_manufacturer</i>	str
<i>instrument_model</i>	str
<i>io_resource_descriptor</i>	str
<i>load_impedance</i>	float
<i>logical_name</i>	str
<i>major_version</i>	int
<i>marker_events_count</i>	int
<i>marker_event_output_terminal</i>	str
<i>max_freq_list_duration</i>	float
<i>max_freq_list_length</i>	int
<i>max_loop_count</i>	int
<i>max_num_freq_lists</i>	int
<i>max_num_sequences</i>	int
<i>max_num_waveforms</i>	int
<i>max_sequence_length</i>	int
<i>max_waveform_size</i>	int
<i>memory_size</i>	int
<i>minor_version</i>	int
<i>min_freq_list_duration</i>	float
<i>min_freq_list_length</i>	int
<i>min_sequence_length</i>	int
<i>min_waveform_size</i>	int

Continued on next page

Table 7 – continued from previous page

Property	Datatype
<code>module_revision</code>	str
<code>output_enabled</code>	bool
<code>output_impedance</code>	float
<code>output_mode</code>	<i>OutputMode</i>
<code>ready_for_start_event_output_terminal</code>	str
<code>reference_clock_source</code>	<i>ReferenceClockSource</i>
<code>ref_clock_frequency</code>	float
<code>sample_clock_source</code>	<i>SampleClockSource</i>
<code>sample_clock_timebase_rate</code>	float
<code>sample_clock_timebase_source</code>	<i>SampleClockTimebaseSource</i>
<code>script_to_generate</code>	str
<code>script_triggers_count</code>	int
<code>script_trigger_type</code>	<i>ScriptTriggerType</i>
<code>serial_number</code>	str
<code>simulate</code>	bool
<code>specific_driver_description</code>	str
<code>specific_driver_revision</code>	str
<code>specific_driver_vendor</code>	str
<code>started_event_output_terminal</code>	str
<code>start_trigger_type</code>	<i>StartTriggerType</i>
<code>streaming_space_available_in_waveform</code>	int
<code>streaming_waveform_handle</code>	int
<code>streaming_waveform_name</code>	str
<code>streaming_write_timeout</code>	float in seconds or <code>datetime.timedelta</code>
<code>supported_instrument_models</code>	str
<code>terminal_configuration</code>	<i>TerminalConfiguration</i>
<code>trigger_mode</code>	<i>TriggerMode</i>
<code>wait_behavior</code>	<i>WaitBehavior</i>
<code>wait_value</code>	int
<code>waveform_quantum</code>	int

**Public methods**

Method name
<code>abort()</code>
<code>allocate_named_waveform()</code>
<code>allocate_waveform()</code>
<code>clear_arb_memory()</code>
<code>clear_arb_sequence()</code>
<code>clear_freq_list()</code>
<code>clear_user_standard_waveform()</code>
<code>commit()</code>
<code>configure_arb_sequence()</code>
<code>configure_arb_waveform()</code>
<code>configure_custom_fir_filter_coefficients()</code>
<code>configure_freq_list()</code>
<code>configure_standard_waveform()</code>
<code>create_advanced_arb_sequence()</code>
<code>create_arb_sequence()</code>

Continued on next page

Table 8 – continued from previous page

Method name
<code>create_freq_list()</code>
<code>create_waveform_from_file_f64()</code>
<code>create_waveform_from_file_il6()</code>
<code>create_waveform_numpy()</code>
<code>define_user_standard_waveform()</code>
<code>delete_script()</code>
<code>delete_waveform()</code>
<code>disable()</code>
<code>get_ext_cal_last_date_and_time()</code>
<code>get_ext_cal_last_temp()</code>
<code>get_ext_cal_recommended_interval()</code>
<code>get_hardware_state()</code>
<code>get_self_cal_last_date_and_time()</code>
<code>get_self_cal_last_temp()</code>
<code>get_self_cal_supported()</code>
<code>is_done()</code>
<code>lock()</code>
<code>query_arb_seq_capabilities()</code>
<code>query_arb_wfm_capabilities()</code>
<code>query_freq_list_capabilities()</code>
<code>read_current_temperature()</code>
<code>reset()</code>
<code>reset_device()</code>
<code>reset_with_defaults()</code>
<code>self_cal()</code>
<code>self_test()</code>
<code>send_software_edge_trigger()</code>
<code>set_next_write_position()</code>
<code>unlock()</code>
<code>wait_until_done()</code>
<code>write_script()</code>
<code>write_waveform()</code>

## Properties

### `all_marker_events_latched_status`

`nifgen.Session.all_marker_events_latched_status`

Returns a bit field of the latched status of all Marker Events. Write 0 to this property to clear the latched status of all Marker Events.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes



---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Marker:Advanced:All Marker Events Latched Status**
  - C Attribute: **NIFGEN\_ATTR\_ALL\_MARKER\_EVENTS\_LATCHED\_STATUS**
- 

### **all\_marker\_events\_live\_status**

`nifgen.Session.all_marker_events_live_status`

Returns a bit field of the live status of all Marker Events.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Marker:Advanced:All Marker Events Live Status**
  - C Attribute: **NIFGEN\_ATTR\_ALL\_MARKER\_EVENTS\_LIVE\_STATUS**
- 

### **analog\_data\_mask**

`nifgen.Session.analog_data_mask`

Specifies the mask to apply to the analog output. The masked data is replaced with the data in `nifgen.Session.analog_static_value`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Data Mask:Analog Data Mask**
  - C Attribute: **NIFGEN\_ATTR\_ANALOG\_DATA\_MASK**
-

## analog\_filter\_enabled

### `nifgen.Session.analog_filter_enabled`

Controls whether the signal generator applies to an analog filter to the output signal. This property is valid in arbitrary waveform, arbitrary sequence, and script modes. This property can also be used in standard method and frequency list modes for user-defined waveforms.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Filters:Analog Filter Enabled**
  - C Attribute: **NIFGEN\_ATTR\_ANALOG\_FILTER\_ENABLED**
- 

## analog\_path

### `nifgen.Session.analog_path`

Specifies the analog signal path that should be used. The main path allows you to configure gain, offset, analog filter status, output impedance, and output enable. The main path has two amplifier options, high- and low-gain. The direct path presents a much smaller gain range, and you cannot adjust offset or the filter status. The direct path also provides a smaller output range but also lower distortion. NI-FGEN normally chooses the amplifier based on the user-specified gain.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.AnalogPath</code>
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Analog Path**
  - C Attribute: **NIFGEN\_ATTR\_ANALOG\_PATH**
- 

## analog\_static\_value

### `nifgen.Session.analog_static_value`

Specifies the static value that replaces data masked by `nifgen.Session.analog_data_mask`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Data Mask:Analog Static Value**
  - C Attribute: **NIFGEN\_ATTR\_ANALOG\_STATIC\_VALUE**
- 

## arb\_gain

`nifgen.Session.arb_gain`

Specifies the factor by which the signal generator scales the arbitrary waveform data. When you create arbitrary waveforms, you must first normalize the data points to the range -1.0 to +1.0. Use this property to scale the arbitrary waveform to other ranges. For example, when you set this property to 2.0, the output signal ranges from -2.0 V to +2.0 V. Use this property when `nifgen.Session.output_mode` is set to *ARB* or *SEQ*.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Gain**
  - C Attribute: **NIFGEN\_ATTR\_ARB\_GAIN**
- 

## arb\_marker\_position

`nifgen.Session.arb_marker_position`

Specifies the position for a marker to be asserted in the arbitrary waveform. This property defaults to -1 when no marker position is specified. Use this property when `nifgen.Session.output_mode` is set to *ARB*. Use `nifgen.Session.ExportSignal()` to export the marker signal.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

**Tip:** This property can use repeated capabilities (markers). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.markers[0,1].arb_marker_position = var
var = session.markers[0,1].arb_marker_position
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Arbitrary Waveform Mode:Marker Position**
  - C Attribute: **NIFGEN\_ATTR\_ARB\_MARKER\_POSITION**
- 

## arb\_offset

### `nifgen.Session.arb_offset`

Specifies the value that the signal generator adds to the arbitrary waveform data. When you create arbitrary waveforms, you must first normalize the data points to the range -1.0 to +1.0. Use this property to shift the arbitrary waveform range. For example, when you set this property to 1.0, the output signal ranges from 2.0 V to 0.0 V. Use this property when `nifgen.Session.output_mode` is set to *ARB* or *SEQ*. Units: Volts

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Offset**
  - C Attribute: **NIFGEN\_ATTR\_ARB\_OFFSET**
-

## arb\_repeat\_count

### `nifgen.Session.arb_repeat_count`

Specifies number of times to repeat the arbitrary waveform when the `triggerMode` parameter of `nifgen.Session.ConfigureTriggerMode()` is set to *SINGLE* or *STEPPED*. This property is ignored if the `triggerMode` parameter is set to *CONTINUOUS* or *BURST*. Use this property when `nifgen.Session.output_mode` is set to *ARB*. When used during streaming, this property specifies the number of times to repeat the streaming waveform (the onboard memory allocated for streaming). For more information about streaming, refer to the Streaming topic.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Arbitrary Waveform Mode:Repeat Count**
  - C Attribute: **NIFGEN\_ATTR\_ARB\_REPEAT\_COUNT**
- 

## arb\_sample\_rate

### `nifgen.Session.arb_sample_rate`

Specifies the rate at which the signal generator outputs the points in arbitrary waveforms. Use this property when `nifgen.Session.output_mode` is set to *ARB* or *SEQ*. Units: Samples/s

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock:Rate**
  - C Attribute: **NIFGEN\_ATTR\_ARB\_SAMPLE\_RATE**
- 

## arb\_sequence\_handle

### `nifgen.Session.arb_sequence_handle`

This channel-based property identifies which sequence the signal generator produces. You can

create multiple sequences using `nifgen.Session.create_arb_sequence()`. `nifgen.Session.create_arb_sequence()` returns a handle that you can use to identify the particular sequence. To configure the signal generator to produce a particular sequence, set this property to the sequence handle. Use this property only when `nifgen.Session.output_mode` is set to `SEQ`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Arbitrary Sequence Mode:Arbitrary Sequence Handle**
  - C Attribute: **NIFGEN\_ATTR\_ARB\_SEQUENCE\_HANDLE**
- 

## arb\_waveform\_handle

`nifgen.Session.arb_waveform_handle`

Selects which arbitrary waveform the signal generator produces. You can create multiple arbitrary waveforms using one of the following niFgen Create Waveform methods: `nifgen.Session.create_waveform()` `nifgen.Session.create_waveform()` `nifgen.Session.create_waveform_from_file_i16()` `nifgen.Session.create_waveform_from_file_f64()` `nifgen.Session.CreateWaveformFromFileHWS()` These methods return a handle that you can use to identify the particular waveform. To configure the signal generator to produce a particular waveform, set this property to the waveform handle. Use this property only when `nifgen.Session.output_mode` is set to `ARB`.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Arbitrary Waveform Mode:Arbitrary Waveform Handle**
- C Attribute: **NIFGEN\_ATTR\_ARB\_WAVEFORM\_HANDLE**

## aux\_power\_enabled

`nifgen.Session.aux_power_enabled`

Controls the specified auxiliary power pin. Setting this property to TRUE energizes the auxiliary power when the session is committed. When this property is FALSE, the power pin of the connector outputs no power.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Advanced:AUX Power Enabled**
  - C Attribute: **NIFGEN\_ATTR\_AUX\_POWER\_ENABLED**
- 

## bus\_type

`nifgen.Session.bus_type`

The bus type of the signal generator.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.BusType
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Bus Type**
  - C Attribute: **NIFGEN\_ATTR\_BUS\_TYPE**
- 

## channel\_count

`nifgen.Session.channel_count`

Returns the number of channels that the specific instrument driver supports. For each property for which `IVI_VAL_MULTI_CHANNEL` is set, the IVI Engine maintains a separate cache value for each channel.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Driver Capabilities:Channel Count**
  - C Attribute: **NIFGEN\_ATTR\_CHANNEL\_COUNT**
- 

## channel\_delay

`nifgen.Session.channel_delay`

Specifies, in seconds, the delay to apply to the analog output of the channel specified by the channel string. You can use the channel delay to configure the timing relationship between channels on a multichannel device. Values for this property can be zero or positive. A value of zero indicates that the channels are aligned. A positive value delays the analog output by the specified number of seconds.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Channel Delay**
  - C Attribute: **NIFGEN\_ATTR\_CHANNEL\_DELAY**
- 

## clock\_mode

`nifgen.Session.clock_mode`

Controls which clock mode is used for the signal generator. For signal generators that support it, this property allows switching the sample clock to High-Resolution mode. When in Divide-Down mode, the sample rate can only be set to certain frequencies, based on dividing down the update clock. However, in High-Resolution mode, the sample rate may be set to any value.

The following table lists the characteristics of this property.



Characteristic	Value
Datatype	enums.ClockMode
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock:Mode**
  - C Attribute: **NIFGEN\_ATTR\_CLOCK\_MODE**
- 

### common\_mode\_offset

`nifgen.Session.common_mode_offset`

Specifies, in volts, the value the signal generator adds to or subtracts from the arbitrary waveform data. This property applies only when you set the `nifgen.Session.terminal_configuration` property to `DIFFERENTIAL`. Common mode offset is applied to the signals generated at each differential output terminal.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Common Mode Offset**
  - C Attribute: **NIFGEN\_ATTR\_COMMON\_MODE\_OFFSET**
- 

### data\_marker\_events\_count

`nifgen.Session.data_marker_events_count`

Returns the number of Data Marker Events supported by the device.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Data Marker Events Count**
  - C Attribute: **NIFGEN\_ATTR\_DATA\_MARKER\_EVENTS\_COUNT**
- 

### **data\_marker\_event\_data\_bit\_number**

`nifgen.Session.data_marker_event_data_bit_number`

Specifies the bit number to assign to the Data Marker Event.

---

**Tip:** This property can use repeated capabilities (markers). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.markers[0,1].data_marker_event_data_bit_number = var
var = session.markers[0,1].data_marker_event_data_bit_number
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Data Marker:Data Bit Number**
  - C Attribute: **NIFGEN\_ATTR\_DATA\_MARKER\_EVENT\_DATA\_BIT\_NUMBER**
- 

### **data\_marker\_event\_level\_polarity**

`nifgen.Session.data_marker_event_level_polarity`

Specifies the output polarity of the Data marker event.

---

**Tip:** This property can use repeated capabilities (markers). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.markers[0,1].data_marker_event_level_polarity = var
var = session.markers[0,1].data_marker_event_level_polarity
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.DataMarkerEventLevelPolarity
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Data Marker:Level:Active Level**
  - C Attribute: **NIFGEN\_ATTR\_DATA\_MARKER\_EVENT\_LEVEL\_POLARITY**
- 

## data\_marker\_event\_output\_terminal

`nifgen.Session.data_marker_event_output_terminal`

Specifies the destination terminal for the Data Marker Event.

---

**Tip:** This property can use repeated capabilities (markers). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.markers[0,1].data_marker_event_output_terminal = var
var = session.markers[0,1].data_marker_event_output_terminal
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Data Marker:Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_DATA\_MARKER\_EVENT\_OUTPUT\_TERMINAL**
- 

## data\_transfer\_block\_size

`nifgen.Session.data_transfer_block_size`

The number of samples at a time to download to onboard memory. Useful when the total data to be transferred to onboard memory is large.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform>Data Transfer>Data Transfer Block Size**
  - C Attribute: **NIFGEN\_ATTR\_DATA\_TRANSFER\_BLOCK\_SIZE**
- 

### **data\_transfer\_maximum\_bandwidth**

`nifgen.Session.data_transfer_maximum_bandwidth`

Specifies the maximum amount of bus bandwidth (in bytes per second) to use for data transfers. The signal generator limits data transfer speeds on the PCIe bus to the value you specify for this property. Set this property to optimize bus bandwidth usage for multi-device streaming applications by preventing the signal generator from consuming all of the available bandwidth on a PCI express link when waveforms are being written to the onboard memory of the device.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform>Data Transfer:Maximum Bandwidth**
  - C Attribute: **NIFGEN\_ATTR\_DATA\_TRANSFER\_MAXIMUM\_BANDWIDTH**
- 

### **data\_transfer\_maximum\_in\_flight\_reads**

`nifgen.Session.data_transfer_maximum_in_flight_reads`

Specifies the maximum number of concurrent PCI Express read requests the signal generator can issue. When transferring data from computer memory to device onboard memory across the PCI Express bus, the signal generator can issue multiple memory reads at the same time. In general, the larger the number of read requests, the more efficiently the device uses the bus because the multiple read requests keep the data flowing, even in a PCI Express topology that has high latency due to PCI Express switches in the data path. Most NI devices can issue a large number of read requests (typically 8 or 16). By default, this property is set to the highest value the signal generator supports. If other devices in your system cannot tolerate long data latencies, it may be helpful to decrease the number of in-flight read requests the NI signal generator issues. This helps to reduce the amount of data the signal generator reads at one time.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform>Data Transfer:Advanced:Maximum In-Flight Read Requests**
  - C Attribute: **NIFGEN\_ATTR\_DATA\_TRANSFER\_MAXIMUM\_IN\_FLIGHT\_READS**
- 

### `data_transfer_preferred_packet_size`

`nifgen.Session.data_transfer_preferred_packet_size`

Specifies the preferred size of the data field in a PCI Express read request packet. In general, the larger the packet size, the more efficiently the device uses the bus. By default, NI signal generators use the largest packet size allowed by the system. However, due to different system implementations, some systems may perform better with smaller packet sizes. Recommended values for this property are powers of two between 64 and 512. In some cases, the signal generator generates packets smaller than the preferred size you set with this property. You cannot change this property while the device is generating a waveform. If you want to change the device configuration, call the `nifgen.Session.abort()` method or wait for the generation to complete.

---

**Note:** :

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform>Data Transfer:Advanced:Preferred Packet Size**
  - C Attribute: **NIFGEN\_ATTR\_DATA\_TRANSFER\_PREFERRED\_PACKET\_SIZE**
- 

### `digital_data_mask`

`nifgen.Session.digital_data_mask`

Specifies the mask to apply to the output on the digital connector. The masked data is replaced with the data in `nifgen.Session.digital_static_value`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output>Data Mask:Digital Data Mask**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_DATA\_MASK**
- 

### **digital\_edge\_script\_trigger\_edge**

`nifgen.Session.digital_edge_script_trigger_edge`

Specifies the active edge for the Script trigger. This property is used when `nifgen.Session.script_trigger_type` is set to Digital Edge.

---

**Tip:** This property can use repeated capabilities (script\_triggers). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.script_triggers[0,1].digital_edge_script_trigger_edge = var
var = session.script_triggers[0,1].digital_edge_script_trigger_edge
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.ScriptTriggerDigitalEdgeEdge
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Script:Digital Edge:Edge**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_EDGE\_SCRIPT\_TRIGGER\_EDGE**
- 

### **digital\_edge\_script\_trigger\_source**

`nifgen.Session.digital_edge_script_trigger_source`

Specifies the source terminal for the Script trigger. This property is used when `nifgen.Session.script_trigger_type` is set to Digital Edge.

---

**Tip:** This property can use repeated capabilities (`script_triggers`). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.script_triggers[0,1].digital_edge_script_trigger_source = var
var = session.script_triggers[0,1].digital_edge_script_trigger_source
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Script:Digital Edge:Source**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_EDGE\_SCRIPT\_TRIGGER\_SOURCE**
- 

### **digital\_edge\_start\_trigger\_edge**

`nifgen.Session.digital_edge_start_trigger_edge`

Specifies the active edge for the Start trigger. This property is used only when `nifgen.Session.start_trigger_type` is set to Digital Edge.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.StartTriggerDigitalEdgeEdge
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Start:Digital Edge:Edge**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_EDGE\_START\_TRIGGER\_EDGE**
- 

### **digital\_edge\_start\_trigger\_source**

`nifgen.Session.digital_edge_start_trigger_source`

Specifies the source terminal for the Start trigger. This property is used only when `nifgen.Session.start_trigger_type` is set to Digital Edge.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Start:Digital Edge:Source**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_EDGE\_START\_TRIGGER\_SOURCE**
- 

## **digital\_filter\_enabled**

`nifgen.Session.digital_filter_enabled`

Controls whether the signal generator applies a digital filter to the output signal. This property is valid in arbitrary waveform, arbitrary sequence, and script modes. This property can also be used in standard method and frequency list modes for user-defined waveforms.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Filters:Digital Filter Enabled**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_FILTER\_ENABLED**
- 

## **digital\_filter\_interpolation\_factor**

`nifgen.Session.digital_filter_interpolation_factor`

This property only affects the device when `nifgen.Session.digital_filter_enabled` is set to True. If you do not set this property directly, NI-FGEN automatically selects the maximum interpolation factor allowed for the current sample rate. Valid values are 2, 4, and 8.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No



---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Filters:Digital Filter Interpolation Factor**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_FILTER\_INTERPOLATION\_FACTOR**
- 

## digital\_gain

`nifgen.Session.digital_gain`

Specifies a factor by which the signal generator digitally multiplies generated data before converting it to an analog signal in the DAC. For a digital gain greater than 1.0, the product of digital gain times the generated data must be inside the range plus or minus 1.0 (assuming floating point data). If the product exceeds these limits, the signal generator clips the output signal, and an error results. Some signal generators support both digital gain and an analog gain (analog gain is specified with the `nifgen.Session.func_amplitude` property or the `nifgen.Session.arb_gain` property). Digital gain can be changed during generation without the glitches that may occur when changing analog gains, due to relay switching. However, the DAC output resolution is a method of analog gain, so only analog gain makes full use of the resolution of the DAC.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Digital Gain**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_GAIN**
- 

## digital\_pattern\_enabled

`nifgen.Session.digital_pattern_enabled`

Controls whether the signal generator generates a digital pattern of the output signal.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Advanced:Digital Pattern Enabled**

- C Attribute: **NIFGEN\_ATTR\_DIGITAL\_PATTERN\_ENABLED**
- 

## digital\_static\_value

`nifgen.Session.digital_static_value`

Specifies the static value that replaces data masked by `nifgen.Session.digital_data_mask`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Data Mask:Digital Static Value**
  - C Attribute: **NIFGEN\_ATTR\_DIGITAL\_STATIC\_VALUE**
- 

## done\_event\_output\_terminal

`nifgen.Session.done_event_output_terminal`

Specifies the destination terminal for the Done Event.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Done:Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_DONE\_EVENT\_OUTPUT\_TERMINAL**
- 

## driver\_setup

`nifgen.Session.driver_setup`

Specifies the driver setup portion of the option string that was passed into the `nifgen.Session.InitWithOptions()` method.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	0
Resettable	0

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIFGEN\_ATTR\_DRIVER\_SETUP**
- 

### **exported\_onboard\_reference\_clock\_output\_terminal**

`nifgen.Session.exported_onboard_reference_clock_output_terminal`

Specifies the terminal to which to export the Onboard Reference Clock.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Reference Clock:Onboard Reference Clock:Export Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_EXPORTED\_ONBOARD\_REFERENCE\_CLOCK\_OUTPUT\_TERMINAL**
- 

### **exported\_reference\_clock\_output\_terminal**

`nifgen.Session.exported_reference_clock_output_terminal`

Specifies the terminal to which to export the Reference Clock.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Reference Clock:Export Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_EXPORTED\_REFERENCE\_CLOCK\_OUTPUT\_TERMINAL**
- 

### **exported\_sample\_clock\_divisor**

`nifgen.Session.exported_sample_clock_divisor`

Specifies the factor by which to divide the Sample clock, also known as the Update clock, before it is exported. To export the Sample clock, use the `nifgen.Session.ExportSignal()` method or the `nifgen.Session.exported_sample_clock_output_terminal` property.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock:Exported Sample Clock Divisor**
  - C Attribute: **NIFGEN\_ATTR\_EXPORTED\_SAMPLE\_CLOCK\_DIVISOR**
- 

### **exported\_sample\_clock\_output\_terminal**

`nifgen.Session.exported_sample_clock_output_terminal`

Specifies the terminal to which to export the Sample Clock.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock:Export Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_EXPORTED\_SAMPLE\_CLOCK\_OUTPUT\_TERMINAL**
-

## exported\_sample\_clock\_timebase\_divisor

### `nifgen.Session.exported_sample_clock_timebase_divisor`

Specifies the factor by which to divide the sample clock timebase (board clock) before it is exported. To export the Sample clock timebase, use the `nifgen.Session.ExportSignal()` method or the `nifgen.Session.exported_sample_clock_timebase_output_terminal` property.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock Timebase:Exported Sample Clock Timebase Divisor**
  - C Attribute: **NIFGEN\_ATTR\_EXPORTED\_SAMPLE\_CLOCK\_TIMEBASE\_DIVISOR**
- 

## exported\_sample\_clock\_timebase\_output\_terminal

### `nifgen.Session.exported_sample_clock_timebase_output_terminal`

Specifies the terminal to which to export the Sample clock timebase. If you specify a divisor with the `nifgen.Session.exported_sample_clock_timebase_divisor` property, the Sample clock exported with the `nifgen.Session.exported_sample_clock_timebase_output_terminal` property is the value of the Sample clock timebase after it is divided-down. For a list of the terminals available on your device, refer to the Device Routes tab in MAX. To change the device configuration, call `nifgen.Session.abort()` or wait for the generation to complete.

---

**Note:** The signal generator must not be in the Generating state when you change this property.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock Timebase:Export Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_EXPORTED\_SAMPLE\_CLOCK\_TIMEBASE\_OUTPUT\_TERMINAL**
- 

## exported\_script\_trigger\_output\_terminal

`nifgen.Session.exported_script_trigger_output_terminal`

Specifies the output terminal for the exported Script trigger. Setting this property to an empty string means that when you commit the session, the signal is removed from that terminal and, if possible, the terminal is tristated.

---

**Tip:** This property can use repeated capabilities (script\_triggers). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.script_triggers[0,1].exported_script_trigger_output_terminal =   
↪var  
var = session.script_triggers[0,1].exported_script_trigger_output_  
↪terminal
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Script:Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_EXPORTED\_SCRIPT\_TRIGGER\_OUTPUT\_TERMINAL**
- 

## exported\_start\_trigger\_output\_terminal

`nifgen.Session.exported_start_trigger_output_terminal`

Specifies the destination terminal for exporting the Start trigger.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Start:Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_EXPORTED\_START\_TRIGGER\_OUTPUT\_TERMINAL**
- 

### external\_clock\_delay\_binary\_value

`nifgen.Session.external_clock_delay_binary_value`

Binary value of the external clock delay.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Advanced:External Clock Delay Binary Value**
  - C Attribute: **NIFGEN\_ATTR\_EXTERNAL\_CLOCK\_DELAY\_BINARY\_VALUE**
- 

### external\_sample\_clock\_multiplier

`nifgen.Session.external_sample_clock_multiplier`

Specifies a multiplication factor to use to obtain a desired sample rate from an external Sample clock. The resulting sample rate is equal to this factor multiplied by the external Sample clock rate. You can use this property to generate samples at a rate higher than your external clock rate. When using this property, you do not need to explicitly set the external clock rate.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Advanced:External Sample Clock Multiplier**
  - C Attribute: **NIFGEN\_ATTR\_EXTERNAL\_SAMPLE\_CLOCK\_MULTIPLIER**
-

## file\_transfer\_block\_size

`nifgen.Session.file_transfer_block_size`

The number of samples at a time to read from the file and download to onboard memory. Used in conjunction with the Create From File and Write From File methods.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform>Data Transfer:File Transfer Block Size**
  - C Attribute: **NIFGEN\_ATTR\_FILE\_TRANSFER\_BLOCK\_SIZE**
- 

## filter\_correction\_frequency

`nifgen.Session.filter_correction_frequency`

Controls the filter correction frequency of the analog filter. This property corrects for the ripples in the analog filter frequency response at the frequency specified. For standard waveform output, the filter correction frequency should be set to be the same as the frequency of the standard waveform. To have no filter correction, set this property to 0 Hz.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:5401/5411/5431:Filter Correction Frequency**
  - C Attribute: **NIFGEN\_ATTR\_FILTER\_CORRECTION\_FREQUENCY**
- 

## flatness\_correction\_enabled

`nifgen.Session.flatness_correction_enabled`

When True, the signal generator applies a flatness correction factor to the generated sine wave in order to ensure the same output power level at all frequencies. This property should be set to False when performing Flatness Calibration.

The following table lists the characteristics of this property.



Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Filters:Flatness Correction Enabled**
  - C Attribute: **NIFGEN\_ATTR\_FLATNESS\_CORRECTION\_ENABLED**
- 

## fpga\_bitfile\_path

`nifgen.Session.fpga_bitfile_path`

Gets the absolute file path to the bitfile loaded on the FPGA.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:FPGA Bitfile Path**
  - C Attribute: **NIFGEN\_ATTR\_FPGA\_BITFILE\_PATH**
- 

## freq\_list\_duration\_quantum

`nifgen.Session.freq_list_duration_quantum`

Returns the quantum of which all durations must be a multiple in a frequency list.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Frequency List Mode:Frequency List Duration Quantum**

- C Attribute: **NIFGEN\_ATTR\_FREQ\_LIST\_DURATION\_QUANTUM**
- 

## freq\_list\_handle

`nifgen.Session.freq_list_handle`

Sets which frequency list the signal generator produces. Create a frequency list using `nifgen.Session.create_freq_list()`. `nifgen.Session.create_freq_list()` returns a handle that you can use to identify the list.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Frequency List Mode:Frequency List Handle**
  - C Attribute: **NIFGEN\_ATTR\_FREQ\_LIST\_HANDLE**
- 

## func\_amplitude

`nifgen.Session.func_amplitude`

Controls the amplitude of the standard waveform that the signal generator produces. This value is the amplitude at the output terminal. For example, to produce a waveform ranging from -5.00 V to +5.00 V, set the amplitude to 10.00 V. set the Waveform parameter to *DC*. Units: Vpk-pk

---

**Note:** This parameter does not affect signal generator behavior when you

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Amplitude**
  - C Attribute: **NIFGEN\_ATTR\_FUNC\_AMPLITUDE**
-

## func\_buffer\_size

`nifgen.Session.func_buffer_size`

This property contains the number of samples used in the standard method waveform buffer. This property is only valid on devices that implement standard method mode in software, and is read-only for all other devices. implementation of Standard Method Mode on your device.

---

**Note:** Refer to the Standard Method Mode topic for more information on the

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Standard Function Mode:Buffer Size**
  - C Attribute: **NIFGEN\_ATTR\_FUNC\_BUFFER\_SIZE**
- 

## func\_dc\_offset

`nifgen.Session.func_dc_offset`

Controls the DC offset of the standard waveform that the signal generator produces. This value is the offset at the output terminal. The value is the offset from ground to the center of the waveform that you specify with the Waveform parameter. For example, to configure a waveform with an amplitude of 10.00 V to range from 0.00 V to +10.00 V, set DC Offset to 5.00 V. Units: volts

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:DC Offset**
  - C Attribute: **NIFGEN\_ATTR\_FUNC\_DC\_OFFSET**
-

## func\_duty\_cycle\_high

`nifgen.Session.func_duty_cycle_high`

Controls the duty cycle of the square wave the signal generator produces. Specify this property as a percentage of the time the square wave is high in a cycle. set the Waveform parameter to *SQUARE*. Units: Percentage of time the waveform is high

---

**Note:** This parameter only affects signal generator behavior when you

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Duty Cycle High**
  - C Attribute: **NIFGEN\_ATTR\_FUNC\_DUTY\_CYCLE\_HIGH**
- 

## func\_frequency

`nifgen.Session.func_frequency`

Controls the frequency of the standard waveform that the signal generator produces. Units: hertz (1) This parameter does not affect signal generator behavior when you set the Waveform parameter of the `nifgen.Session.configure_standard_waveform()` method to *DC*. (2) For *SINE*, the range is between 0 MHz and 16 MHz, but the range is between 0 MHz and 1 MHz for all other waveforms.

---

**Note:** :

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Standard Function Mode:Frequency**
  - C Attribute: **NIFGEN\_ATTR\_FUNC\_FREQUENCY**
-

## func\_max\_buffer\_size

### `nifgen.Session.func_max_buffer_size`

This property sets the maximum number of samples that can be used in the standard method waveform buffer. Increasing this value may increase the quality of the waveform. This property is only valid on devices that implement standard method mode in software, and is read-only for all other devices. implementation of Standard Method Mode on your device.

---

**Note:** Refer to the Standard Method Mode topic for more information on the

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Standard Function Mode:Maximum Buffer Size**
  - C Attribute: **NIFGEN\_ATTR\_FUNC\_MAX\_BUFFER\_SIZE**
- 

## func\_start\_phase

### `nifgen.Session.func_start_phase`

Controls horizontal offset of the standard waveform the signal generator produces. Specify this property in degrees of one waveform cycle. A start phase of 180 degrees means output generation begins halfway through the waveform. A start phase of 360 degrees offsets the output by an entire waveform cycle, which is identical to a start phase of 0 degrees. set the Waveform parameter to *DC*. Units: Degrees of one cycle

---

**Note:** This parameter does not affect signal generator behavior when you

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Start Phase**
  - C Attribute: **NIFGEN\_ATTR\_FUNC\_START\_PHASE**
-

## func\_waveform

`nifgen.Session.func_waveform`

This channel-based property specifies which standard waveform the signal generator produces. Use this property only when `nifgen.Session.output_mode` is set to `FUNC.SINE` - Sinusoid waveform `SQUARE` - Square waveform `TRIANGLE` - Triangle waveform `RAMP_UP` - Positive ramp waveform `RAMP_DOWN` - Negative ramp waveform `DC` - Constant voltage `NOISE` - White noise `USER` - User-defined waveform as defined with `nifgen.Session.define_user_standard_waveform()`

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.Waveform
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Waveform**
  - C Attribute: **NIFGEN\_ATTR\_FUNC\_WAVEFORM**
- 

## idle\_behavior

`nifgen.Session.idle_behavior`

Specifies the behavior of the output during the Idle state. The output can be configured to hold the last generated voltage before entering the Idle state or jump to the Idle Value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.IdleBehavior
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Advanced:Idle Behavior**
  - C Attribute: **NIFGEN\_ATTR\_IDLE\_BEHAVIOR**
- 

## idle\_value

`nifgen.Session.idle_value`

Specifies the value to generate in the Idle state. The Idle Behavior must be configured to jump to this value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Advanced:Idle Value**
  - C Attribute: **NIFGEN\_ATTR\_IDLE\_VALUE**
- 

## instrument\_firmware\_revision

`nifgen.Session.instrument_firmware_revision`

A string that contains the firmware revision information for the device that you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Instrument Identification:Firmware Revision**
  - C Attribute: **NIFGEN\_ATTR\_INSTRUMENT\_FIRMWARE\_REVISION**
- 

## instrument\_manufacturer

`nifgen.Session.instrument_manufacturer`

A string that contains the name of the device manufacturer you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Instrument Identification:Manufacturer**
  - C Attribute: **NIFGEN\_ATTR\_INSTRUMENT\_MANUFACTURER**
- 

## instrument\_model

`nifgen.Session.instrument_model`

A string that contains the model number or name of the device that you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Instrument Identification:Model**
  - C Attribute: **NIFGEN\_ATTR\_INSTRUMENT\_MODEL**
- 

## io\_resource\_descriptor

`nifgen.Session.io_resource_descriptor`

Indicates the resource descriptor that NI-FGEN uses to identify the physical device. If you initialize NI-FGEN with a logical name, this property contains the resource descriptor that corresponds to the entry in the IVI Configuration Utility. If you initialize NI-FGEN with the resource descriptor, this property contains that value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Advanced Session Information:Resource Descriptor**
  - C Attribute: **NIFGEN\_ATTR\_IO\_RESOURCE\_DESCRIPTOR**
-



## load\_impedance

### `nifgen.Session.load_impedance`

This channel-based property specifies the load impedance connected to the analog output of the channel. If you set this property to `NIFGEN_VAL_MATCHED_LOAD_IMPEDANCE` (-1.0), NI-FGEN assumes that the load impedance matches the output impedance. NI-FGEN compensates to give the desired peak-to-peak voltage amplitude or arbitrary gain (relative to 1 V).

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Load Impedance**
  - C Attribute: **NIFGEN\_ATTR\_LOAD\_IMPEDANCE**
- 

## logical\_name

### `nifgen.Session.logical_name`

A string containing the logical name that you specified when opening the current IVI session. You may pass a logical name to `nifgen.Session.init()` or `nifgen.Session.InitWithOptions()`. The IVI Configuration Utility must contain an entry for the logical name. The logical name entry refers to a virtual instrument section in the IVI Configuration file. The virtual instrument section specifies a physical device and initial user options.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Advanced Session Information:Logical Name**

- C Attribute: **NIFGEN\_ATTR\_LOGICAL\_NAME**
- 

## major\_version

`nifgen.Session.major_version`

Returns the major version number of NI-FGEN.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Obsolete:Major Version**
  - C Attribute: **NIFGEN\_ATTR\_MAJOR\_VERSION**
- 

## marker\_events\_count

`nifgen.Session.marker_events_count`

Returns the number of markers supported by the device. Use this property when `nifgen.Session.output_mode` is set to *SCRIPT*.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Marker Events Count**
  - C Attribute: **NIFGEN\_ATTR\_MARKER\_EVENTS\_COUNT**
- 

## marker\_event\_output\_terminal

`nifgen.Session.marker_event_output_terminal`

Specifies the destination terminal for the Marker Event.

---

**Tip:** This property can use repeated capabilities (markers). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.markers[0,1].marker_event_output_terminal = var
var = session.markers[0,1].marker_event_output_terminal
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Marker:Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_MARKER\_EVENT\_OUTPUT\_TERMINAL**
- 

## max\_freq\_list\_duration

`nifgen.Session.max_freq_list_duration`

Returns the maximum duration of any one step in the frequency list.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Frequency List Mode:Maximum Frequency List Duration**
  - C Attribute: **NIFGEN\_ATTR\_MAX\_FREQ\_LIST\_DURATION**
- 

## max\_freq\_list\_length

`nifgen.Session.max_freq_list_length`

Returns the maximum number of steps that can be in a frequency list.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Frequency List Mode:Maximum Frequency List Length**
  - C Attribute: **NIFGEN\_ATTR\_MAX\_FREQ\_LIST\_LENGTH**
- 

## max\_loop\_count

`nifgen.Session.max_loop_count`

Returns the maximum number of times that the signal generator can repeat a waveform in a sequence. Typically, this value is constant for the signal generator.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Arbitrary Sequence Mode:Max Loop Count**
  - C Attribute: **NIFGEN\_ATTR\_MAX\_LOOP\_COUNT**
- 

## max\_num\_freq\_lists

`nifgen.Session.max_num_freq_lists`

Returns the maximum number of frequency lists the signal generator allows.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Frequency List Mode:Maximum Number Of Frequency Lists**
  - C Attribute: **NIFGEN\_ATTR\_MAX\_NUM\_FREQ\_LISTS**
- 

### **max\_num\_sequences**

`nifgen.Session.max_num_sequences`

Returns the maximum number of arbitrary sequences that the signal generator allows. Typically, this value is constant for the signal generator.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Arbitrary Sequence Mode:Max Number of Sequences**
  - C Attribute: **NIFGEN\_ATTR\_MAX\_NUM\_SEQUENCES**
- 

### **max\_num\_waveforms**

`nifgen.Session.max_num_waveforms`

Returns the maximum number of arbitrary waveforms that the signal generator allows. Typically, this value is constant for the signal generator.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Capabilities:Max Number of Waveforms**
  - C Attribute: **NIFGEN\_ATTR\_MAX\_NUM\_WAVEFORMS**
-

## max\_sequence\_length

`nifgen.Session.max_sequence_length`

Returns the maximum number of arbitrary waveforms that the signal generator allows in a sequence. Typically, this value is constant for the signal generator.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Arbitrary Sequence Mode:Max Sequence Length**
  - C Attribute: **NIFGEN\_ATTR\_MAX\_SEQUENCE\_LENGTH**
- 

## max\_waveform\_size

`nifgen.Session.max_waveform_size`

Returns the size, in samples, of the largest waveform that can be created. This property reflects the space currently available, taking into account previously allocated waveforms and instructions.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Capabilities:Max Waveform Size**
  - C Attribute: **NIFGEN\_ATTR\_MAX\_WAVEFORM\_SIZE**
- 

## memory\_size

`nifgen.Session.memory_size`

The total amount of memory, in bytes, on the signal generator.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Memory Size**
  - C Attribute: **NIFGEN\_ATTR\_MEMORY\_SIZE**
- 

### minor\_version

`nifgen.Session.minor_version`

Returns the minor version number of NI-FGEN.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Obsolete:Minor Version**
  - C Attribute: **NIFGEN\_ATTR\_MINOR\_VERSION**
- 

### min\_freq\_list\_duration

`nifgen.Session.min_freq_list_duration`

Returns the minimum number of steps that can be in a frequency list.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Frequency List Mode:Minimum Frequency List Duration**

- C Attribute: **NIFGEN\_ATTR\_MIN\_FREQ\_LIST\_DURATION**
- 

## min\_freq\_list\_length

`nifgen.Session.min_freq_list_length`

Returns the minimum number of frequency lists that the signal generator allows.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Standard Function:Frequency List Mode:Minimum Frequency List Length**
  - C Attribute: **NIFGEN\_ATTR\_MIN\_FREQ\_LIST\_LENGTH**
- 

## min\_sequence\_length

`nifgen.Session.min_sequence_length`

Returns the minimum number of arbitrary waveforms that the signal generator allows in a sequence. Typically, this value is constant for the signal generator.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Arbitrary Sequence Mode:Min Sequence Length**
  - C Attribute: **NIFGEN\_ATTR\_MIN\_SEQUENCE\_LENGTH**
- 

## min\_waveform\_size

`nifgen.Session.min_waveform_size`

Returns the minimum number of points that the signal generator allows in an arbitrary waveform. Typically, this value is constant for the signal generator.



The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Capabilities:Min Waveform Size**
  - C Attribute: **NIFGEN\_ATTR\_MIN\_WAVEFORM\_SIZE**
- 

## module\_revision

`nifgen.Session.module_revision`

A string that contains the module revision for the device that you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Instrument Identification:Module Revision**
  - C Attribute: **NIFGEN\_ATTR\_MODULE\_REVISION**
- 

## output\_enabled

`nifgen.Session.output_enabled`

This channel-based property specifies whether the signal that the signal generator produces appears at the output connector.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Output Enabled**
  - C Attribute: **NIFGEN\_ATTR\_OUTPUT\_ENABLED**
- 

## output\_impedance

`nifgen.Session.output_impedance`

This channel-based property specifies the signal generator output impedance at the output connector. NI signal sources modules have an output impedance of 50 ohms and an optional 75 ohms on select modules. If the load impedance matches the output impedance, then the voltage at the signal output connector is at the needed level. The voltage at the signal output connector varies with load output impedance, up to doubling the voltage for a high-impedance load.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Output Impedance**
  - C Attribute: **NIFGEN\_ATTR\_OUTPUT\_IMPEDANCE**
- 

## output\_mode

`nifgen.Session.output_mode`

Sets which output mode the signal generator will use. The value you specify determines which methods and properties you use to configure the waveform the signal generator produces.

---

**Note:** The signal generator must not be in the Generating state when you change this property. To change the device configuration, call `nifgen.Session.abort()` or wait for the generation to complete.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.OutputMode
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Output Mode**
  - C Attribute: **NIFGEN\_ATTR\_OUTPUT\_MODE**
- 

### ready\_for\_start\_event\_output\_terminal

`nifgen.Session.ready_for_start_event_output_terminal`

Specifies the destination terminal for the Ready for Start Event.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Ready For Start:Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_READY\_FOR\_START\_EVENT\_OUTPUT\_TERMINAL**
- 

### reference\_clock\_source

`nifgen.Session.reference_clock_source`

Specifies the reference clock source used by the signal generator. The signal generator derives the frequencies and sample rates that it uses to generate waveforms from the source you specify. For example, when you set this property to `ClkIn`, the signal generator uses the signal it receives at the CLK IN front panel connector as the Reference clock. To change the device configuration, call `nifgen.Session.abort()` or wait for the generation to complete.

---

**Note:** The signal generator must not be in the Generating state when you change this property.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.ReferenceClockSource</code>
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Reference Clock:Source**

- C Attribute: **NIFGEN\_ATTR\_REFERENCE\_CLOCK\_SOURCE**
- 

## ref\_clock\_frequency

`nifgen.Session.ref_clock_frequency`

Sets the frequency of the signal generator reference clock. The signal generator uses the reference clock to derive frequencies and sample rates when generating output.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Reference Clock:Frequency**
  - C Attribute: **NIFGEN\_ATTR\_REF\_CLOCK\_FREQUENCY**
- 

## sample\_clock\_source

`nifgen.Session.sample_clock_source`

Specifies the Sample clock source. If you specify a divisor with the `nifgen.Session.exported_sample_clock_divisor` property, the Sample clock exported with the `nifgen.Session.exported_sample_clock_output_terminal` property is the value of the Sample clock after it is divided-down. For a list of the terminals available on your device, refer to the Device Routes tab in MAX. To change the device configuration, call `nifgen.Session.abort()` or wait for the generation to complete.

---

**Note:** The signal generator must not be in the Generating state when you change this property.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.SampleClockSource
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock:Source**
  - C Attribute: **NIFGEN\_ATTR\_SAMPLE\_CLOCK\_SOURCE**
-

## sample\_clock\_timebase\_rate

### `nifgen.Session.sample_clock_timebase_rate`

Specifies the Sample clock timebase rate. This property applies only to external Sample clock timebases. To change the device configuration, call `nifgen.Session.abort()` or wait for the generation to complete.

---

**Note:** The signal generator must not be in the Generating state when you change this property.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock Timebase:Rate**
  - C Attribute: **NIFGEN\_ATTR\_SAMPLE\_CLOCK\_TIMEBASE\_RATE**
- 

## sample\_clock\_timebase\_source

### `nifgen.Session.sample_clock_timebase_source`

Specifies the Sample Clock Timebase source. To change the device configuration, call the `nifgen.Session.abort()` method or wait for the generation to complete.

---

**Note:** The signal generator must not be in the Generating state when you change this property.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.SampleClockTimebaseSource
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocks:Sample Clock Timebase:Source**
  - C Attribute: **NIFGEN\_ATTR\_SAMPLE\_CLOCK\_TIMEBASE\_SOURCE**
-

## script\_to\_generate

### `nifgen.Session.script_to_generate`

Specifies which script the generator produces. To configure the generator to run a particular script, set this property to the name of the script. Use `nifgen.Session.write_script()` to create multiple scripts. Use this property when `nifgen.Session.output_mode` is set to `SCRIPT`.

---

**Note:** The signal generator must not be in the Generating state when you change this property. To change the device configuration, call `nifgen.Session.abort()` or wait for the generation to complete.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Script Mode:Script to Generate**
  - C Attribute: **NIFGEN\_ATTR\_SCRIPT\_TO\_GENERATE**
- 

## script\_triggers\_count

### `nifgen.Session.script_triggers_count`

Specifies the number of Script triggers supported by the device. Use this property when `nifgen.Session.output_mode` is set to `SCRIPT`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Script Triggers Count**
  - C Attribute: **NIFGEN\_ATTR\_SCRIPT\_TRIGGERS\_COUNT**
-

## script\_trigger\_type

`nifgen.Session.script_trigger_type`

Specifies the Script trigger type. Depending upon the value of this property, additional properties may need to be configured to fully configure the trigger.

**Tip:** This property can use repeated capabilities (`script_triggers`). If set or get directly on the `nifgen.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.script_triggers[0,1].script_trigger_type = var
var = session.script_triggers[0,1].script_trigger_type
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.ScriptTriggerType</code>
Permissions	read-write
Channel Based	False
Resettable	Yes

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Script:Trigger Type**
- C Attribute: **NIFGEN\_ATTR\_SCRIPT\_TRIGGER\_TYPE**

## serial\_number

`nifgen.Session.serial_number`

The signal generator's serial number.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>str</code>
Permissions	read only
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Serial Number**
- C Attribute: **NIFGEN\_ATTR\_SERIAL\_NUMBER**

## simulate

### `nifgen.Session.simulate`

Specifies whether to simulate NI-FGEN I/O operations. If simulation is enabled, NI-FGEN methods perform range checking and call `Ivi_GetAttribute` and `Ivi_SetAttribute`, but they do not perform device I/O. For output parameters that represent device data, NI-FGEN methods return calculated values. Default Value: False Use `nifgen.Session.InitWithOptions()` to override default value.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:User Options:Simulate**
  - C Attribute: **NIFGEN\_ATTR\_SIMULATE**
- 

## specific\_driver\_description

### `nifgen.Session.specific_driver_description`

Returns a brief description of NI-FGEN.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Driver Identification:Description**
  - C Attribute: **NIFGEN\_ATTR\_SPECIFIC\_DRIVER\_DESCRIPTION**
- 

## specific\_driver\_revision

### `nifgen.Session.specific_driver_revision`

A string that contains additional version information about NI-FGEN.



The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Driver Identification:Revision**
  - C Attribute: **NIFGEN\_ATTR\_SPECIFIC\_DRIVER\_REVISION**
- 

### **specific\_driver\_vendor**

`nifgen.Session.specific_driver_vendor`

A string that contains the name of the vendor that supplies NI-FGEN.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Driver Identification:Driver Vendor**
  - C Attribute: **NIFGEN\_ATTR\_SPECIFIC\_DRIVER\_VENDOR**
- 

### **started\_event\_output\_terminal**

`nifgen.Session.started_event_output_terminal`

Specifies the destination terminal for the Started Event.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Events:Started:Output Terminal**
  - C Attribute: **NIFGEN\_ATTR\_STARTED\_EVENT\_OUTPUT\_TERMINAL**
- 

## start\_trigger\_type

`nifgen.Session.start_trigger_type`

Specifies whether you want the Start trigger to be a Digital Edge, or Software trigger. You can also choose None as the value for this property.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.StartTriggerType</code>
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Start:Trigger Type**
  - C Attribute: **NIFGEN\_ATTR\_START\_TRIGGER\_TYPE**
- 

## streaming\_space\_available\_in\_waveform

`nifgen.Session.streaming_space_available_in_waveform`

Indicates the space available (in samples) in the streaming waveform for writing new data. During generation, this available space may be in multiple locations with, for example, part of the available space at the end of the streaming waveform and the rest at the beginning. In this situation, writing a block of waveform data the size of the total space available in the streaming waveform causes NI-FGEN to return an error, as NI-FGEN will not wrap the data from the end of the waveform to the beginning and cannot write data past the end of the waveform buffer. To avoid writing data past the end of the waveform, write new data to the waveform in a fixed size that is an integer divisor of the total size of the streaming waveform. Used in conjunction with the `nifgen.Session.streaming_waveform_handle` or `nifgen.Session.streaming_waveform_name` properties.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>int</code>
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Data Transfer:Streaming:Space Available in Streaming Waveform**

- C Attribute: **NIFGEN\_ATTR\_STREAMING\_SPACE\_AVAILABLE\_IN\_WAVEFORM**
- 

## streaming\_waveform\_handle

`nifgen.Session.streaming_waveform_handle`

Specifies the waveform handle of the waveform used to continuously stream data during generation. This property defaults to -1 when no streaming waveform is specified. Used in conjunction with `nifgen.Session.streaming_space_available_in_waveform`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform>Data Transfer:Streaming:Streaming Waveform Handle**
  - C Attribute: **NIFGEN\_ATTR\_STREAMING\_WAVEFORM\_HANDLE**
- 

## streaming\_waveform\_name

`nifgen.Session.streaming_waveform_name`

Specifies the name of the waveform used to continuously stream data during generation. This property defaults to // when no streaming waveform is specified. Use in conjunction with `nifgen.Session.streaming_space_available_in_waveform`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform>Data Transfer:Streaming:Streaming Waveform Name**
  - C Attribute: **NIFGEN\_ATTR\_STREAMING\_WAVEFORM\_NAME**
-

## streaming\_write\_timeout

`nifgen.Session.streaming_write_timeout`

Specifies the maximum amount of time allowed to complete a streaming write operation.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Data Transfer:Streaming:Streaming Write Timeout**
  - C Attribute: **NIFGEN\_ATTR\_STREAMING\_WRITE\_TIMEOUT**
- 

## supported\_instrument\_models

`nifgen.Session.supported_instrument_models`

Returns a model code of the device. For NI-FGEN versions that support more than one device, this property contains a comma-separated list of supported device models.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Instrument:Inherent IVI Attributes:Driver Capabilities:Supported Instrument Models**
  - C Attribute: **NIFGEN\_ATTR\_SUPPORTED\_INSTRUMENT\_MODELS**
- 

## terminal\_configuration

`nifgen.Session.terminal_configuration`

Specifies whether gain and offset values will be analyzed based on single-ended or differential operation.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.TerminalConfiguration
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Terminal Configuration**
  - C Attribute: **NIFGEN\_ATTR\_TERMINAL\_CONFIGURATION**
- 

## trigger\_mode

`nifgen.Session.trigger_mode`

Controls the trigger mode.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.TriggerMode
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggers:Trigger Mode**
  - C Attribute: **NIFGEN\_ATTR\_TRIGGER\_MODE**
- 

## wait\_behavior

`nifgen.Session.wait_behavior`

Specifies the behavior of the output while waiting for a script trigger or during a wait instruction. The output can be configured to hold the last generated voltage before waiting or jump to the Wait Value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.WaitBehavior
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Advanced:Wait Behavior**
  - C Attribute: **NIFGEN\_ATTR\_WAIT\_BEHAVIOR**
- 

## wait\_value

`nifgen.Session.wait_value`

Specifies the value to generate while waiting. The Wait Behavior must be configured to jump to this value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Output:Advanced:Wait Value**
  - C Attribute: **NIFGEN\_ATTR\_WAIT\_VALUE**
- 

## waveform\_quantum

`nifgen.Session.waveform_quantum`

The size of each arbitrary waveform must be a multiple of a quantum value. This property returns the quantum value that the signal generator allows. For example, when this property returns a value of 8, all waveform sizes must be a multiple of 8. Typically, this value is constant for the signal generator.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Arbitrary Waveform:Capabilities:Waveform Quantum**
  - C Attribute: **NIFGEN\_ATTR\_WAVEFORM\_QUANTUM**
-

## Methods

### abort

`nifgen.Session.abort()`

Aborts any previously initiated signal generation. Call the `nifgen.Session.initiate()` method to cause the signal generator to produce a signal again.

### allocate\_named\_waveform

`nifgen.Session.allocate_named_waveform(waveform_name, waveform_size)`

Specifies the size of a named waveform up front so that it can be allocated in onboard memory before loading the associated data. Data can then be loaded in smaller blocks with the niFgen Write (Binary16) Waveform methods.

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].allocate_named_waveform(waveform_name, waveform_
↪size)
```

#### Parameters

- **waveform\_name** (*str*) – Specifies the name to associate with the allocated waveform.
- **waveform\_size** (*int*) – Specifies the size of the waveform to allocate in samples.

**Default Value:** “4096”

### allocate\_waveform

`nifgen.Session.allocate_waveform(waveform_size)`

Specifies the size of a waveform so that it can be allocated in onboard memory before loading the associated data. Data can then be loaded in smaller blocks with the Write Binary 16 Waveform methods.

**Note:** The signal generator must not be in the Generating state when you call this method.

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].allocate_waveform(waveform_size)
```

**Parameters** `waveform_size` (*int*) – Specifies, in samples, the size of the waveform to allocate.

**Return type** `int`

**Returns** The handle that identifies the new waveform. This handle is used later when referring to this waveform.

### `clear_arb_memory`

```
nifgen.Session.clear_arb_memory()
```

Removes all previously created arbitrary waveforms, sequences, and scripts from the signal generator memory and invalidates all waveform handles, sequence handles, and waveform names.

---

**Note:** The signal generator must not be in the Generating state when you call this method.

---

### `clear_arb_sequence`

```
nifgen.Session.clear_arb_sequence(sequence_handle)
```

Removes a previously created arbitrary sequence from the signal generator memory and invalidates the sequence handle.

---

**Note:** The signal generator must not be in the Generating state when you call this method.

---

**Parameters** `sequence_handle` (*int*) – Specifies the handle of the arbitrary sequence that you want the signal generator to remove. You can create an arbitrary sequence using the `nifgen.Session.create_arb_sequence()` or `nifgen.Session.create_advanced_arb_sequence()` method. These methods return a handle that you use to identify the sequence.

**Defined Value:**

`NIFGEN_VAL_ALL_SEQUENCES`—Remove all sequences from the signal generator

**Default Value:** None

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

### `clear_freq_list`

```
nifgen.Session.clear_freq_list(frequency_list_handle)
```

Removes a previously created frequency list from the signal generator memory and invalidates the frequency list handle.



---

**Note:** The signal generator must not be in the Generating state when you call this method.

---

**Parameters** `frequency_list_handle` (*int*) – Specifies the handle of the frequency list you want the signal generator to remove. You create multiple frequency lists using `nifgen.Session.create_freq_list()`. `nifgen.Session.create_freq_list()` returns a handle that you use to identify each list. Specify a value of -1 to clear all frequency lists.

**Defined Value**

NIFGEN\_VAL\_ALL\_FLISTS—Remove all frequency lists from the signal generator.

**Default Value:** None

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## clear\_user\_standard\_waveform

`nifgen.Session.clear_user_standard_waveform()`  
Clears the user-defined waveform created by the `nifgen.Session.define_user_standard_waveform()` method.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].clear_user_standard_waveform()
```

---

## commit

`nifgen.Session.commit()`  
Causes a transition to the Committed state. This method verifies property values, reserves the device, and commits the property values to the device. If the property values are all valid, NI-FGEN sets the device hardware configuration to match the session configuration. This method does not support the NI 5401/5404/5411/5431 signal generators.

In the Committed state, you can load waveforms, scripts, and sequences into memory. If any properties are changed, NI-FGEN implicitly transitions back to the Idle state, where you can program all session properties before applying them to the device. This method has no effect if the device is already in the Committed or Generating state and returns a successful status value.

Calling this VI before the niFgen Initiate Generation VI is optional but has the following benefits:

- Routes are committed, so signals are exported or imported.
- Any Reference Clock and external clock circuits are phase-locked.

- A subsequent `nifgen.Session.initiate()` method can run faster because the device is already configured.

## configure\_arb\_sequence

`nifgen.Session.configure_arb_sequence(sequence_handle, gain, offset)`

Configures the signal generator properties that affect arbitrary sequence generation. Sets the `nifgen.Session.arb_sequence_handle`, `nifgen.Session.arb_gain`, and `nifgen.Session.arb_offset` properties.

---

**Note:** The signal generator must not be in the Generating state when you call this method.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

---

```
session.channels[0,1].configure_arb_sequence(sequence_handle, gain,
↪offset)
```

---

### Parameters

- **sequence\_handle** (*int*) – Specifies the handle of the arbitrary sequence that you want the signal generator to produce. NI-FGEN sets the `nifgen.Session.arb_sequence_handle` property to this value. You can create an arbitrary sequence using the `nifgen.Session.create_arb_sequence()` or `nifgen.Session.create_advanced_arb_sequence()` method. These methods return a handle that you use to identify the sequence.

**Default Value:** None

- **gain** (*float*) – Specifies the factor by which the signal generator scales the arbitrary waveforms in the sequence. When you create an arbitrary waveform, you must first normalize the data points to a range of  $-1.00$  to  $+1.00$ . You can use this parameter to scale the waveform to other ranges. The gain is applied before the offset is added.

For example, to configure the output signal to range from  $-2.00$  to  $+2.00$  V, set **gain** to `2.00`.

**Units:** unitless

**Default Value:** None

- **offset** (*float*) – Specifies the value the signal generator adds to the arbitrary waveform data. When you create arbitrary waveforms, you must first normalize the data points to a range of  $-1.00$  to  $+1.00$  V. You can use this parameter to shift the range of the arbitrary waveform. NI-FGEN sets the `nifgen.Session.arb_offset` property to this value.

For example, to configure the output signal to range from  $0.00$  to  $2.00$  V instead of  $-1.00$  to  $1.00$  V, set the offset to `1.00`.

**Units:** volts

**Default Value:** None

## configure\_arb\_waveform

`nifgen.Session.configure_arb_waveform(waveform_handle, gain, offset)`

Configures the properties of the signal generator that affect arbitrary waveform generation. Sets the `nifgen.Session.arb_waveform_handle`, `nifgen.Session.arb_gain`, and `nifgen.Session.arb_offset` properties.

---

**Note:** The signal generator must not be in the Generating state when you call this method.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].configure_arb_waveform(waveform_handle, gain,
↪offset)
```

---

### Parameters

- **waveform\_handle** (*int*) – Specifies the handle of the arbitrary waveform you want the signal generator to produce. NI-FGEN sets the `nifgen.Session.arb_waveform_handle` property to this value. You can create an arbitrary waveform using one of the following niFgen Create Waveform methods:

- `nifgen.Session.create_waveform()`
- `nifgen.Session.create_waveform()`
- `nifgen.Session.create_waveform_from_file_i16()`
- `nifgen.Session.create_waveform_from_file_f64()`
- `nifgen.Session.CreateWaveformFromFileHWS()`

These methods return a handle that you use to identify the waveform.

**Default Value:** None

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

- **gain** (*float*) – Specifies the factor by which the signal generator scales the arbitrary waveforms in the sequence. When you create an arbitrary waveform, you must first normalize the data points to a range of  $-1.00$  to  $+1.00$ . You can use this parameter to scale the waveform to other ranges. The gain is applied before the offset is added.

For example, to configure the output signal to range from  $-2.00$  to  $+2.00$  V, set **gain** to `2.00`.

**Units:** unitless

**Default Value:** None

- **offset** (*float*) – Specifies the value the signal generator adds to the arbitrary waveform data. When you create arbitrary waveforms, you must first normalize the data points to a range of –1.00 to +1.00 V. You can use this parameter to shift the range of the arbitrary waveform. NI-FGEN sets the `nifgen.Session.arb_offset` property to this value.

For example, to configure the output signal to range from 0.00 to 2.00 V instead of –1.00 to 1.00 V, set the offset to 1.00.

**Units:** volts

**Default Value:** None

## configure\_custom\_fir\_filter\_coefficients

`nifgen.Session.configure_custom_fir_filter_coefficients(coefficients_array)`

Sets the FIR filter coefficients used by the onboard signal processing block. The values are coerced to the closest settings achievable by the signal generator.

Refer to the *FIR Filter* topic for your device in the *NI Signal Generators Help* for more information about FIR filter coefficients. This method is supported only for the NI 5441.

---

**Note:** The signal generator must not be in the Generating state when you call this method.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].configure_custom_fir_filter_
    ↪coefficients(coefficients_array)
```

---

**Parameters** `coefficients_array` (*list of float*) – Specifies the array of data the onboard signal processor uses for the FIR filter coefficients. For the NI 5441, provide a symmetric array of 95 coefficients to this parameter. The array must have at least as many elements as the value that you specify in the **numberOfCoefficients** parameter in this method. The coefficients should range between –1.00 and +1.00.

## configure\_freq\_list

`nifgen.Session.configure_freq_list(frequency_list_handle, amplitude, dc_offset=0.0, start_phase=0.0)`

Configures the properties of the signal generator that affect frequency list generation (the `nifgen.Session.freq_list_handle`, `nifgen.Session.func_amplitude`, `nifgen.Session.func_dc_offset`, and `nifgen.Session.func_start_phase` properties).

---

**Note:** The signal generator must not be in the Generating state when you call this method.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result:

```
session.channels[0,1].configure_freq_list(frequency_list_handle,   
←amplitude, dc_offset=0.0, start_phase=0.0)
```

### Parameters

- **frequency\_list\_handle** (*int*) – Specifies the handle of the frequency list that you want the signal generator to produce. NI-FGEN sets the `nifgen.Session.freq_list_handle` property to this value. You can create a frequency list using the `nifgen.Session.create_freq_list()` method, which returns a handle that you use to identify the list. **Default Value:** None
- **amplitude** (*float*) – Specifies the amplitude of the standard waveform that you want the signal generator to produce. This value is the amplitude at the output terminal. NI-FGEN sets the `nifgen.Session.func_amplitude` property to this value.

For example, to produce a waveform ranging from –5.00 V to +5.00 V, set the amplitude to 10.00 V.

**Units:** peak-to-peak voltage

**Default Value:** None

---

**Note:** This parameter does not affect signal generator behavior when you set the **waveform** parameter of the `nifgen.Session.configure_standard_waveform()` method to *DC*.

---

- **dc\_offset** (*float*) – Specifies the DC offset of the standard waveform that you want the signal generator to produce. The value is the offset from ground to the center of the waveform you specify with the **waveform** parameter, observed at the output terminal. For example, to configure a waveform with an amplitude of 10.00 V to range from 0.00 V to +10.00 V, set the **dcOffset** to 5.00 V. NI-FGEN sets the `nifgen.Session.func_dc_offset` property to this value.

**Units:** volts

**Default Value:** None

- **start\_phase** (*float*) – Specifies the horizontal offset of the standard waveform you want the signal generator to produce. Specify this property in degrees of one waveform cycle. NI-FGEN sets the `nifgen.Session.func_start_phase` property to this value. A start phase of 180 degrees means output generation begins halfway through the waveform. A start phase of 360 degrees offsets the output by an entire waveform cycle, which is identical to a start phase of 0 degrees.

**Units:** degrees of one cycle

**Default Value:** None degrees

---

**Note:** This parameter does not affect signal generator behavior when you set the **waveform** parameter to *DC*.

---

## configure\_standard\_waveform

```
nifgen.Session.configure_standard_waveform(waveform, amplitude, frequency,
                                           dc_offset=0.0, start_phase=0.0)
```

Configures the following properties of the signal generator that affect standard waveform generation:

- *nifgen.Session.func\_waveform*
- *nifgen.Session.func\_amplitude*
- *nifgen.Session.func\_dc\_offset*
- *nifgen.Session.func\_frequency*
- *nifgen.Session.func\_start\_phase*

---

**Note:** You must call the `nifgen.Session.ConfigureOutputMode()` method with the **outputMode** parameter set to *FUNC* before calling this method.

---



---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].configure_standard_waveform(waveform, amplitude,
↪frequency, dc_offset=0.0, start_phase=0.0)
```

---

### Parameters

- **waveform** (*nifgen.Waveform*) – Specifies the standard waveform that you want the signal generator to produce. NI-FGEN sets the *nifgen.Session.func\_waveform* property to this value.

**\*\*Defined Values\*\***

**Default Value:** *SINE*

<code>SINE</code>	Specifies that the signal generator produces a sinusoid waveform.
<code>SQUARE</code>	Specifies that the signal generator produces a square waveform.
<code>TRIANGLE</code>	Specifies that the signal generator produces a triangle waveform.
<code>RAMP_UP</code>	Specifies that the signal generator produces a positive ramp waveform.
<code>RAMP_DOWN</code>	Specifies that the signal generator produces a negative ramp waveform.
<code>DC</code>	Specifies that the signal generator produces a constant voltage.
<code>NOISE</code>	Specifies that the signal generator produces white noise.
<code>USER</code>	Specifies that the signal generator produces a user-defined waveform as defined with the <code>nifgen.Session.define_user_standard_waveform()</code> method.

- **amplitude** (*float*) – Specifies the amplitude of the standard waveform that you want the signal generator to produce. This value is the amplitude at the output terminal. NI-FGEN sets the `nifgen.Session.func_amplitude` property to this value.

For example, to produce a waveform ranging from –5.00 V to +5.00 V, set the amplitude to 10.00 V.

**Units:** peak-to-peak voltage

**Default Value:** None

---

**Note:** This parameter does not affect signal generator behavior when you set the **waveform** parameter of the `nifgen.Session.configure_standard_waveform()` method to `DC`.

---

- **frequency** (*float*) –

Specifies the frequency of the standard waveform that you want the signal generator to produce. NI-FGEN sets the `nifgen.Session.func_frequency` property to this value.

**Units:** hertz

**Default Value:** None

---

**Note:** This parameter does not affect signal generator behavior when you set the **waveform** parameter of the `nifgen.Session.configure_standard_waveform()` method to `DC`.

---

- **dc\_offset** (*float*) – Specifies the DC offset of the standard waveform that you want the signal generator to produce. The value is the offset from ground to the center of the waveform you specify with the **waveform** parameter, observed at the output terminal. For example, to configure a waveform with an amplitude of 10.00 V to range from 0.00 V to +10.00 V, set the **dcOffset** to 5.00 V. NI-FGEN sets the `nifgen.Session.func_dc_offset` property to this value.

**Units:** volts

**Default Value:** None

- **start\_phase** (*float*) – Specifies the horizontal offset of the standard waveform that you want the signal generator to produce. Specify this parameter

in degrees of one waveform cycle. NI-FGEN sets the `nifgen.Session.func_start_phase` property to this value. A start phase of 180 degrees means output generation begins halfway through the waveform. A start phase of 360 degrees offsets the output by an entire waveform cycle, which is identical to a start phase of 0 degrees.

**Units:** degrees of one cycle

**Default Value:** 0.00

---

**Note:** This parameter does not affect signal generator behavior when you set the **waveform** parameter to `DC`.

---

## create\_advanced\_arb\_sequence

```
nifgen.Session.create_advanced_arb_sequence (waveform_handles_array,  
                                             loop_counts_array,          sam-  
                                             ple_counts_array=None,  
                                             marker_location_array=None)
```

Creates an arbitrary sequence from an array of waveform handles and an array of corresponding loop counts. This method returns a handle that identifies the sequence. You pass this handle to the `nifgen.Session.configure_arb_sequence()` method to specify what arbitrary sequence you want the signal generator to produce.

The `nifgen.Session.create_advanced_arb_sequence()` method extends on the `nifgen.Session.create_arb_sequence()` method by adding the ability to set the number of samples in each sequence step and to set marker locations.

An arbitrary sequence consists of multiple waveforms. For each waveform, you specify the number of times the signal generator produces the waveform before proceeding to the next waveform. The number of times to repeat a specific waveform is called the loop count.

---

**Note:** The signal generator must not be in the Generating state when you call this method. You must call the `nifgen.Session.ConfigureOutputMode()` method to set the **outputMode** parameter to `SEQ` before calling this method.

---

### Parameters

- **waveform\_handles\_array** (*list of int*) – Specifies the array of waveform handles from which you want to create a new arbitrary sequence. The array must have at least as many elements as the value that you specify in **sequenceLength**. Each **waveformHandlesArray** element has a corresponding **loopCountsArray** element that indicates how many times that waveform is repeated. You obtain waveform handles when you create arbitrary waveforms with the `nifgen.Session.allocate_waveform()` method or one of the following niFgen CreateWaveform methods:
  - `nifgen.Session.create_waveform()`
  - `nifgen.Session.create_waveform()`
  - `nifgen.Session.create_waveform_from_file_i16()`
  - `nifgen.Session.create_waveform_from_file_f64()`



– `nifgen.Session.CreateWaveformFromFileHWS()`

**Default Value:** None

- **loop\_counts\_array** (*list of int*) – Specifies the array of loop counts you want to use to create a new arbitrary sequence. The array must have at least as many elements as the value that you specify in the **sequenceLength** parameter. Each **loopCountsArray** element corresponds to a **waveformHandlesArray** element and indicates how many times to repeat that waveform. Each element of the **loopCountsArray** must be less than or equal to the maximum number of loop counts that the signal generator allows. You can obtain the maximum loop count from **maximumLoopCount** in the `nifgen.Session.query_arb_seq_capabilities()` method.

**Default Value:** None

- **sample\_counts\_array** (*list of int*) – Specifies the array of sample counts that you want to use to create a new arbitrary sequence. The array must have at least as many elements as the value you specify in the **sequenceLength** parameter. Each **sampleCountsArray** element corresponds to a **waveformHandlesArray** element and indicates the subset, in samples, of the given waveform to generate. Each element of the **sampleCountsArray** must be larger than the minimum waveform size, a multiple of the waveform quantum and no larger than the number of samples in the corresponding waveform. You can obtain these values by calling the `nifgen.Session.query_arb_wfm_capabilities()` method.

**Default Value:** None

- **marker\_location\_array** (*list of int*) – Specifies the array of marker locations to where you want a marker to be generated in the sequence. The array must have at least as many elements as the value you specify in the **sequenceLength** parameter. Each **markerLocationArray** element corresponds to a **waveformHandlesArray** element and indicates where in the waveform a marker is to generate. The marker location must be less than the size of the waveform the marker is in. The markers are coerced to the nearest marker quantum and the coerced values are returned in the **coercedMarkersArray** parameter.

If you do not want a marker generated for a particular sequence stage, set this parameter to `NIFGEN_VAL_NO_MARKER`.

**Defined Value:** `NIFGEN_VAL_NO_MARKER`

**Default Value:** None

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

### Return type

tuple (coerced\_markers\_array, sequence\_handle)

WHERE

coerced\_markers\_array (list of int):

Returns an array of all given markers that are coerced (rounded) to the nearest marker quantum. Not all devices coerce markers.

**Default Value:** None

`sequence_handle (int):`

Returns the handle that identifies the new arbitrary sequence. You can pass this handle to `nifgen.Session.configure_arb_sequence()` to generate the arbitrary sequence.

## `create_arb_sequence`

```
nifgen.Session.create_arb_sequence (waveform_handles_array,  
                                   loop_counts_array)
```

Creates an arbitrary sequence from an array of waveform handles and an array of corresponding loop counts. This method returns a handle that identifies the sequence. You pass this handle to the `nifgen.Session.configure_arb_sequence()` method to specify what arbitrary sequence you want the signal generator to produce.

An arbitrary sequence consists of multiple waveforms. For each waveform, you can specify the number of times that the signal generator produces the waveform before proceeding to the next waveform. The number of times to repeat a specific waveform is called the loop count.

---

**Note:** You must call the `nifgen.Session.ConfigureOutputMode()` method to set the **outputMode** parameter to `SEQ` before calling this method.

---

### Parameters

- **waveform\_handles\_array** (*list of int*) – Specifies the array of waveform handles from which you want to create a new arbitrary sequence. The array must have at least as many elements as the value that you specify in **sequenceLength**. Each **waveformHandlesArray** element has a corresponding **loopCountsArray** element that indicates how many times that waveform is repeated. You obtain waveform handles when you create arbitrary waveforms with the `nifgen.Session.allocate_waveform()` method or one of the following niFgen CreateWaveform methods:

- `nifgen.Session.create_waveform()`
- `nifgen.Session.create_waveform()`
- `nifgen.Session.create_waveform_from_file_i16()`
- `nifgen.Session.create_waveform_from_file_f64()`
- `nifgen.Session.CreateWaveformFromFileHWS()`

**Default Value:** None

- **loop\_counts\_array** (*list of int*) – Specifies the array of loop counts you want to use to create a new arbitrary sequence. The array must have at least as many elements as the value that you specify in the **sequenceLength** parameter. Each **loopCountsArray** element corresponds to a **waveformHandlesArray** element and indicates how many times to repeat that waveform. Each element of the **loopCountsArray** must be less than or equal to the maximum number of loop counts that the signal generator allows. You can obtain the maximum loop count from **maximumLoopCount** in the `nifgen.Session.query_arb_seq_capabilities()` method.

**Default Value:** None

**Return type** `int`

**Returns** Returns the handle that identifies the new arbitrary sequence. You can pass this handle to `nifgen.Session.configure_arb_sequence()` to generate the arbitrary sequence.

## create\_freq\_list

`nifgen.Session.create_freq_list(waveform, frequency_array, duration_array)`

Creates a frequency list from an array of frequencies (**frequencyArray**) and an array of durations (**durationArray**). The two arrays should have the same number of elements, and this value must also be the size of the **frequencyListLength**. The method returns a handle that identifies the frequency list (the **frequencyListHandle**). You can pass this handle to `nifgen.Session.configure_freq_list()` to specify what frequency list you want the signal generator to produce.

A frequency list consists of a list of frequencies and durations. The signal generator generates each frequency for the given amount of time and then proceeds to the next frequency. When the end of the list is reached, the signal generator starts over at the beginning of the list.

---

**Note:** The signal generator must not be in the Generating state when you call this method.

---

### Parameters

- **waveform** (`nifgen.Waveform`) – Specifies the standard waveform that you want the signal generator to produce. NI-FGEN sets the `nifgen.Session.func_waveform` property to this value.

**\*\*Defined Values\*\***

**Default Value:** `SINE`

<code>SINE</code>	Specifies that the signal generator produces a sinusoid waveform.
<code>SQUARE</code>	Specifies that the signal generator produces a square waveform.
<code>TRIANGLE</code>	Specifies that the signal generator produces a triangle waveform.
<code>RAMP_UP</code>	Specifies that the signal generator produces a positive ramp waveform.
<code>RAMP_DOWN</code>	Specifies that the signal generator produces a negative ramp waveform.
<code>DC</code>	Specifies that the signal generator produces a constant voltage.
<code>NOISE</code>	Specifies that the signal generator produces white noise.
<code>USER</code>	Specifies that the signal generator produces a user-defined waveform as defined with the <code>nifgen.Session.define_user_standard_waveform()</code> method.

- **frequency\_array** (`list of float`) – Specifies the array of frequencies to form the frequency list. The array must have at least as many elements as the value you specify in **frequencyListLength**. Each **frequencyArray** element has a corresponding **durationArray** element that indicates how long that frequency is repeated.

**Units:** hertz

**Default Value:** None

- **duration\_array** (`list of float`) – Specifies the array of durations to form the frequency list. The array must have at least as many elements as the value that

you specify in **frequencyListLength**. Each **durationArray** element has a corresponding **frequencyArray** element and indicates how long in seconds to generate the corresponding frequency.

**Units:** seconds

**Default Value:** None

**Return type** `int`

**Returns** Returns the handle that identifies the new frequency list. You can pass this handle to `nifgen.Session.configure_freq_list()` to generate the arbitrary sequence.

## create\_waveform\_from\_file\_f64

`nifgen.Session.create_waveform_from_file_f64(file_name, byte_order)`

This method takes the floating point double (F64) data from the specified file and creates an onboard waveform for use in Arbitrary Waveform or Arbitrary Sequence output mode. The **waveformHandle** returned by this method can later be used for setting the active waveform, changing the data in the waveform, building sequences of waveforms, or deleting the waveform when it is no longer needed.

---

**Note:** The F64 data must be between -1.0 and +1.0 V. Use the `nifgen.Session.digital_gain` property to generate different voltage outputs.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

---

```
session.channels[0,1].create_waveform_from_file_f64(file_name, byte_order)
```

---

## Parameters

- **file\_name** (*str*) – The full path and name of the file where the waveform data resides.
- **byte\_order** (*nifgen.ByteOrder*) – Specifies the byte order of the data in the file.

**\*\*Defined Values\*\***

**\*\*Default Value:\*\*** `LITTLE`

<code>LITTLE</code>	Little Endian Data—The least significant bit is stored at the lowest address, followed by the other bits, in order of increasing significance.
<code>BIG</code>	Big Endian Data—The most significant bit is stored at the lowest address, followed by the other bits, in order of decreasing significance.

---

**Note:** Data written by most applications in Windows (including LabWindows™/CVI™) is in Little Endian format. Data written to a file from LabVIEW is in Big Endian format by default on all platforms. Big Endian and Little Endian refer to the way data is stored in memory, which can differ on different processors.

---

**Return type** `int`

**Returns** The handle that identifies the new waveform. This handle is used later when referring to this waveform.

### create\_waveform\_from\_file\_i16

`nifgen.Session.create_waveform_from_file_i16(file_name, byte_order)`

Takes the binary 16-bit signed integer (I16) data from the specified file and creates an onboard waveform for use in Arbitrary Waveform or Arbitrary Sequence output mode. The **waveformHandle** returned by this method can later be used for setting the active waveform, changing the data in the waveform, building sequences of waveforms, or deleting the waveform when it is no longer needed.

---

**Note:** The I16 data (values between -32768 and +32767) is assumed to represent -1 to +1 V. Use the `nifgen.Session.digital_gain` property to generate different voltage outputs.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].create_waveform_from_file_i16(file_name, byte_order)
```

### Parameters

- **file\_name** (*str*) – The full path and name of the file where the waveform data resides.
- **byte\_order** (*nifgen.ByteOrder*) – Specifies the byte order of the data in the file.

**\*\*Defined Values\*\***

**\*\*Default Value:\*\*** `LITTLE`

<code>LITTLE</code>	Little Endian Data—The least significant bit is stored at the lowest address, followed by the other bits, in order of increasing significance.
<code>BIG</code>	Big Endian Data—The most significant bit is stored at the lowest address, followed by the other bits, in order of decreasing significance.

---

**Note:** Data written by most applications in Windows (including LabWindows™/CVI™) is in Little Endian format. Data written to a file from LabVIEW is in Big Endian format by default on all platforms. Big Endian and Little Endian refer to the way data is stored in memory, which can differ on different processors.

---

**Return type** `int`

**Returns** The handle that identifies the new waveform. This handle is used later when referring to this waveform.

### `create_waveform_numpy`

`nifgen.Session.create_waveform_numpy(waveform_data_array)`

Creates an onboard waveform for use in Arbitrary Waveform output mode or Arbitrary Sequence output mode.

---

**Note:** You must set `nifgen.Session.output_mode` to `ARB` or `SEQ` before calling this method.

---

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].create_waveform(waveform_data_array)
```

---

**Parameters** `waveform_data_array` (*list of float*) – Array of data for the new arbitrary waveform. This may be an iterable of float, or for best performance a `numpy.ndarray` of dtype `int16` or `float64`.

**Return type** `int`

**Returns** The handle that identifies the new waveform. This handle is used in other methods when referring to this waveform.

### `define_user_standard_waveform`

`nifgen.Session.define_user_standard_waveform(waveform_data_array)`

Defines a user waveform for use in either Standard Method or Frequency List output mode.

To select the waveform, set the **waveform** parameter to `USER` with either the `nifgen.Session.configure_standard_waveform()` or the `nifgen.Session.create_freq_list()` method.

The waveform data must be scaled between `-1.0` and `1.0`. Use the **amplitude** parameter in the `nifgen.Session.configure_standard_waveform()` method to generate different output voltages.

---

**Note:** You must call the `nifgen.Session.ConfigureOutputMode()` method to set the **outputMode** parameter to *FUNC* or *FREQ\_LIST* before calling this method.

---

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].define_user_standard_waveform(waveform_data_array)
```

---

**Parameters** **waveform\_data\_array** (*list of float*) – Specifies the array of data you want to use for the new arbitrary waveform. The array must have at least as many elements as the value that you specify in **waveformSize**.

You must normalize the data points in the array to be between  $-1.00$  and  $+1.00$ .

**Default Value:** None

## delete\_script

`nifgen.Session.delete_script(script_name)`

Deletes the specified script from onboard memory.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].delete_script(script_name)
```

---

**Parameters** **script\_name** (*str*) – Specifies the name of the script you want to delete. The script name appears in the text of the script following the script keyword.

## delete\_waveform

`nifgen.Session.delete_waveform(waveform_name_or_handle)`

Removes a previously created arbitrary waveform from the signal generator memory.

---

**Note:** The signal generator must not be in the Generating state when you call this method.

---

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].delete_waveform(waveform_name_or_handle)
```

**Parameters** `waveform_name_or_handle` (*str or int*) – The name (str) or handle (int) of an arbitrary waveform previously allocated with `nifgen.Session.allocate_named_waveform()`, `nifgen.Session.allocate_waveform()` or `nifgen.Session.create_waveform()`.

## disable

```
nifgen.Session.disable()
```

Places the instrument in a quiescent state where it has minimal or no impact on the system to which it is connected. The analog output and all exported signals are disabled.

## get\_ext\_cal\_last\_date\_and\_time

```
nifgen.Session.get_ext_cal_last_date_and_time()
```

Returns the date and time of the last successful external calibration. The time returned is 24-hour (military) local time; for example, if the device was calibrated at 2:30 PM, this method returns 14 for the **hour** parameter and 30 for the **minute** parameter.

**Return type** `datetime.datetime`

**Returns** Indicates date and time of the last calibration.

## get\_ext\_cal\_last\_temp

```
nifgen.Session.get_ext_cal_last_temp()
```

Returns the temperature at the last successful external calibration. The temperature is returned in degrees Celsius.

**Return type** `float`

**Returns** Specifies the temperature at the last successful calibration in degrees Celsius.

## get\_ext\_cal\_recommended\_interval

```
nifgen.Session.get_ext_cal_recommended_interval()
```

Returns the recommended interval between external calibrations in months.

**Return type** `datetime.timedelta`

**Returns** Specifies the recommended interval between external calibrations in months.

## get\_hardware\_state

```
nifgen.Session.get_hardware_state()
```

Returns the current hardware state of the device and, if the device is in the hardware error state, the current hardware error.



---

**Note:** Hardware states do not necessarily correspond to NI-FGEN states.

---

**Return type** `nifgen.HardwareState`

#### Returns

Returns the hardware state of the signal generator.

#### Defined Values

<code>IDLE</code>	The device is in the Idle state.
<code>WAITING_FOR_START_TRIGGER</code>	The device is waiting for Start Trigger.
<code>RUNNING</code>	The device is in the Running state.
<code>DONE</code>	The generation has completed successfully.
<code>HARDWARE_ERROR</code>	There is a hardware error.

### `get_self_cal_last_date_and_time`

`nifgen.Session.get_self_cal_last_date_and_time()`

Returns the date and time of the last successful self-calibration.

**Return type** `datetime.datetime`

**Returns** Returns the date and time the device was last calibrated.

### `get_self_cal_last_temp`

`nifgen.Session.get_self_cal_last_temp()`

Returns the temperature at the last successful self-calibration. The temperature is returned in degrees Celsius.

**Return type** `float`

**Returns** Specifies the temperature at the last successful calibration in degrees Celsius.

### `get_self_cal_supported`

`nifgen.Session.get_self_cal_supported()`

Returns whether the device supports self-calibration.

**Return type** `bool`

#### Returns

Returns whether the device supports self-calibration.

**\*\*Defined Values\*\***

True	Self-calibration is supported.
False	Self-calibration is not supported.

## is\_done

`nifgen.Session.is_done()`

Determines whether the current generation is complete. This method sets the **done** parameter to True if the session is in the Idle or Committed states.

---

**Note:** NI-FGEN only reports the **done** parameter as True after the current generation is complete in Single trigger mode.

---

**Return type** `bool`

### Returns

Returns information about the completion of waveform generation.

### Defined Values

True	Generation is complete.
False	Generation is not complete.

## lock

`nifgen.Session.lock()`

Obtains a multithread lock on the device session. Before doing so, the software waits until all other execution threads release their locks on the device session.

Other threads may have obtained a lock on this session for the following reasons:

- The application called the `nifgen.Session.lock()` method.
- A call to NI-FGEN locked the session.
- After a call to the `nifgen.Session.lock()` method returns successfully, no other threads can access the device session until you call the `nifgen.Session.unlock()` method or exit out of the with block when using lock context manager.
- Use the `nifgen.Session.lock()` method and the `nifgen.Session.unlock()` method around a sequence of calls to instrument driver methods if you require that the device retain its settings through the end of the sequence.

You can safely make nested calls to the `nifgen.Session.lock()` method within the same thread. To completely unlock the session, you must balance each call to the `nifgen.Session.lock()` method with a call to the `nifgen.Session.unlock()` method.

One method for ensuring there are the same number of unlock method calls as there is lock calls is to use lock as a context manager

```
with nifgen.Session('dev1') as session:
    with session.lock():
        # Calls to session within a single lock context
```

The first *with* block ensures the session is closed regardless of any exceptions raised

The second *with* block ensures that unlock is called regardless of any exceptions raised

**Return type** `context manager`

**Returns** When used in a *with* statement, `nifgen.Session.lock()` acts as a context manager and unlock will be called when the *with* block is exited

## query\_arb\_seq\_capabilities

`nifgen.Session.query_arb_seq_capabilities()`

Returns the properties of the signal generator that are related to creating arbitrary sequences (the `nifgen.Session.max_num_sequences`, `nifgen.Session.min_sequence_length`, `nifgen.Session.max_sequence_length`, and `nifgen.Session.max_loop_count` properties).

### Return type

tuple (maximum\_number\_of\_sequences, minimum\_sequence\_length, maximum\_sequence\_length, maximum\_loop\_count)

### WHERE

maximum\_number\_of\_sequences (int):

Returns the maximum number of arbitrary waveform sequences that the signal generator allows. NI-FGEN obtains this value from the `nifgen.Session.max_num_sequences` property.

minimum\_sequence\_length (int):

Returns the minimum number of arbitrary waveforms the signal generator allows in a sequence. NI-FGEN obtains this value from the `nifgen.Session.min_sequence_length` property.

maximum\_sequence\_length (int):

Returns the maximum number of arbitrary waveforms the signal generator allows in a sequence. NI-FGEN obtains this value from the `nifgen.Session.max_sequence_length` property.

maximum\_loop\_count (int):

Returns the maximum number of times the signal generator can repeat an arbitrary waveform in a sequence. NI-FGEN obtains this value from the `nifgen.Session.max_loop_count` property.

## query\_arb\_wfm\_capabilities

`nifgen.Session.query_arb_wfm_capabilities()`

Returns the properties of the signal generator that are related to creating arbitrary waveforms. These properties are the maximum number of waveforms, waveform quantum, minimum waveform size, and maximum waveform size.

---

**Note:** If you do not want to obtain the waveform quantum, pass a value of VI\_NULL for this parameter.

---

### Return type

tuple (maximum\_number\_of\_waveforms, waveform\_quantum, minimum\_waveform\_size, maximum\_waveform\_size)

## WHERE

maximum\_number\_of\_waveforms (int):

Returns the maximum number of arbitrary waveforms that the signal generator allows. NI-FGEN obtains this value from the `nifgen.Session.max_num_waveforms` property.

waveform\_quantum (int):

The size (number of points) of each waveform must be a multiple of a constant quantum value. This parameter obtains the quantum value that the signal generator uses. NI-FGEN returns this value from the `nifgen.Session.waveform_quantum` property.

For example, when this property returns a value of 8, all waveform sizes must be a multiple of 8.

minimum\_waveform\_size (int):

Returns the minimum number of points that the signal generator allows in a waveform. NI-FGEN obtains this value from the `nifgen.Session.min_waveform_size` property.

maximum\_waveform\_size (int):

Returns the maximum number of points that the signal generator allows in a waveform. NI-FGEN obtains this value from the `nifgen.Session.max_waveform_size` property.

## query\_freq\_list\_capabilities

`nifgen.Session.query_freq_list_capabilities()`

Returns the properties of the signal generator that are related to creating frequency lists. These properties are `nifgen.Session.max_num_freq_lists`, `nifgen.Session.min_freq_list_length`, `nifgen.Session.max_freq_list_length`, `nifgen.Session.min_freq_list_duration`, `nifgen.Session.max_freq_list_duration`, and `nifgen.Session.freq_list_duration_quantum`.

### Return type

tuple (maximum\_number\_of\_freq\_lists, minimum\_frequency\_list\_length, maximum\_frequency\_list\_length, minimum\_frequency\_list\_duration, maximum\_frequency\_list\_duration, frequency\_list\_duration\_quantum)

## WHERE

maximum\_number\_of\_freq\_lists (int):

Returns the maximum number of frequency lists that the signal generator allows. NI-FGEN obtains this value from the `nifgen.Session.max_num_freq_lists` property.

minimum\_frequency\_list\_length (int):

Returns the minimum number of steps that the signal generator allows in a frequency list. NI-FGEN obtains this value from the `nifgen.Session.min_freq_list_length` property.

maximum\_frequency\_list\_length (int):

Returns the maximum number of steps that the signal generator allows in a frequency list. NI-FGEN obtains this value from the `nifgen.Session.max_freq_list_length` property.

`minimum_frequency_list_duration` (float):

Returns the minimum duration that the signal generator allows in a step of a frequency list. NI-FGEN obtains this value from the `nifgen.Session.min_freq_list_duration` property.

`maximum_frequency_list_duration` (float):

Returns the maximum duration that the signal generator allows in a step of a frequency list. NI-FGEN obtains this value from the `nifgen.Session.max_freq_list_duration` property.

`frequency_list_duration_quantum` (float):

Returns the quantum of which all durations must be a multiple in a frequency list. NI-FGEN obtains this value from the `nifgen.Session.freq_list_duration_quantum` property.

## read\_current\_temperature

`nifgen.Session.read_current_temperature()`

Reads the current onboard temperature of the device. The temperature is returned in degrees Celsius.

**Return type** float

**Returns** Returns the current temperature read from onboard temperature sensors, in degrees Celsius.

## reset

`nifgen.Session.reset()`

Resets the instrument to a known state. This method aborts the generation, clears all routes, and resets session properties to the default values. This method does not, however, commit the session properties or configure the device hardware to its default state.

---

**Note:** For the NI 5401/5404/5411/5431, this method exhibits the same behavior as the `nifgen.Session.reset_device()` method.

---

## reset\_device

`nifgen.Session.reset_device()`

Performs a hard reset on the device. Generation is stopped, all routes are released, external bidirectional terminals are tristated, FPGAs are reset, hardware is configured to its default state, and all session properties are reset to their default states.

## reset\_with\_defaults

`nifgen.Session.reset_with_defaults()`

Resets the instrument and reapplies initial user-specified settings from the logical name that was

used to initialize the session. If the session was created without a logical name, this method is equivalent to the `nifgen.Session.reset()` method.

## self\_cal

`nifgen.Session.self_cal()`

Performs a full internal self-calibration on the device. If the calibration is successful, new calibration data and constants are stored in the onboard EEPROM.

## self\_test

`nifgen.Session.self_test()`

Runs the instrument self-test routine and returns the test result(s).

Raises *SelfTestError* on self test failure. Properties on exception object:

- code - failure code from driver
- message - status message from driver

Self-Test Code	Description
0	Passed self-test
1	Self-test failed

---

**Note:** When used on some signal generators, the device is reset after the `nifgen.Session.self_test()` method runs. If you use the `nifgen.Session.self_test()` method, your device may not be in its previously configured state after the method runs.

---

## send\_software\_edge\_trigger

`nifgen.Session.send_software_edge_trigger()`

Sends a command to trigger the signal generator. This VI can act as an override for an external edge trigger.

If called directly on the session, this will send a software start trigger.

..code:: python

```
session.send_software_edge_trigger()
```

If called using the script trigger repeated capability container, this will send a software trigger to the specified script trigger

..code:: python

```
session.script_triggers[1].send_software_edge_trigger()
```

..note:

This method does **not** override external digital edge triggers of the NI\_↪5401/5411/5431.

## set\_next\_write\_position

```
nifgen.Session.set_next_write_position(waveform_name_or_handle, relative_to,
                                       offset)
```

Sets the position in the waveform at which the next waveform data is written. This method allows you to write to arbitrary locations within the waveform. These settings apply only to the next write to the waveform specified by the waveformHandle parameter. Subsequent writes to that waveform begin where the last write left off, unless this method is called again. The waveformHandle passed in must have been created by a call to the `nifgen.Session.allocate_waveform()` method or one of the following `nifgen.Session.create_waveform()` method.

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].set_next_write_position(waveform_name_or_handle,
                                             relative_to, offset)
```

### Parameters

- **waveform\_name\_or\_handle** (*str or int*) – The name (str) or handle (int) of an arbitrary waveform previously allocated with `nifgen.Session.allocate_named_waveform()`, `nifgen.Session.allocate_waveform()` or `nifgen.Session.create_waveform()`.
- **relative\_to** (*nifgen.RelativeTo*) – Specifies the reference position in the waveform. This position and **offset** together determine where to start loading data into the waveform.

**\*\*Defined Values\*\***

<code>START (0)</code>	Use the start of the waveform as the reference position.
<code>CURRENT (1)</code>	Use the current position within the waveform as the reference position.

- **offset** (*int*) – Specifies the offset from **relativeTo** at which to start loading the data into the waveform.

## unlock

```
nifgen.Session.unlock()
```

Releases a lock that you acquired on an device session using `nifgen.Session.lock()`. Refer to `nifgen.Session.unlock()` for additional information on session locks.

## wait\_until\_done

```
nifgen.Session.wait_until_done(max_time=datetime.timedelta(seconds=10.0))
```

Waits until the device is done generating or until the maximum time has expired.

**Parameters** **max\_time** (*float in seconds or datetime.timedelta*) – Specifies the timeout value in milliseconds.

## write\_script

`nifgen.Session.write_script(script)`

Writes a string containing one or more scripts that govern the generation of waveforms.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].write_script(script)
```

---

**Parameters** `script` (*str*) – Contains the text of the script you want to use for your generation operation. Refer to [scripting Instructions](#) for more information about writing scripts.

## write\_waveform

`nifgen.Session.write_waveform(waveform_name_or_handle, data)`

Writes data to the waveform in onboard memory.

By default, subsequent calls to this method continue writing data from the position of the last sample written. You can set the write position and offset by calling the `nifgen.Session.set_next_write_position()` `nifgen.Session.set_next_write_position()` method.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `nifgen.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `nifgen.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].write_waveform(waveform_name_or_handle, data)
```

---

### Parameters

- **waveform\_name\_or\_handle** (*str or int*) – The name (*str*) or handle (*int*) of an arbitrary waveform previously allocated with `nifgen.Session.allocate_named_waveform()`, `nifgen.Session.allocate_waveform()` or `nifgen.Session.create_waveform()`.
- **data** (*list of float*) – Array of data to load into the waveform. This may be an iterable of float, or for best performance a `numpy.ndarray` of dtype `int16` or `float64`.

## Properties



Property	Datatype
<code>nifgen.Session.all_marker_events_latched_status</code>	int
<code>nifgen.Session.all_marker_events_live_status</code>	int
<code>nifgen.Session.analog_data_mask</code>	int
<code>nifgen.Session.analog_filter_enabled</code>	bool
<code>nifgen.Session.analog_path</code>	AnalogPath
<code>nifgen.Session.analog_static_value</code>	int
<code>nifgen.Session.arb_gain</code>	float
<code>nifgen.Session.arb_marker_position</code>	int
<code>nifgen.Session.arb_offset</code>	float
<code>nifgen.Session.arb_repeat_count</code>	int
<code>nifgen.Session.arb_sample_rate</code>	float
<code>nifgen.Session.arb_sequence_handle</code>	int
<code>nifgen.Session.arb_waveform_handle</code>	int
<code>nifgen.Session.aux_power_enabled</code>	bool
<code>nifgen.Session.bus_type</code>	BusType
<code>nifgen.Session.channel_count</code>	int
<code>nifgen.Session.channel_delay</code>	float
<code>nifgen.Session.clock_mode</code>	ClockMode
<code>nifgen.Session.common_mode_offset</code>	float
<code>nifgen.Session.data_marker_events_count</code>	int
<code>nifgen.Session.data_marker_event_data_bit_number</code>	int
<code>nifgen.Session.data_marker_event_level_polarity</code>	DataMarkerEventLevelPola
<code>nifgen.Session.data_marker_event_output_terminal</code>	str
<code>nifgen.Session.data_transfer_block_size</code>	int
<code>nifgen.Session.data_transfer_maximum_bandwidth</code>	float
<code>nifgen.Session.data_transfer_maximum_in_flight_reads</code>	int
<code>nifgen.Session.data_transfer_preferred_packet_size</code>	int
<code>nifgen.Session.digital_data_mask</code>	int
<code>nifgen.Session.digital_edge_script_trigger_edge</code>	ScriptTriggerDigitalEdge
<code>nifgen.Session.digital_edge_script_trigger_source</code>	str
<code>nifgen.Session.digital_edge_start_trigger_edge</code>	StartTriggerDigitalEdgeE
<code>nifgen.Session.digital_edge_start_trigger_source</code>	str
<code>nifgen.Session.digital_filter_enabled</code>	bool
<code>nifgen.Session.digital_filter_interpolation_factor</code>	float
<code>nifgen.Session.digital_gain</code>	float
<code>nifgen.Session.digital_pattern_enabled</code>	bool
<code>nifgen.Session.digital_static_value</code>	int
<code>nifgen.Session.done_event_output_terminal</code>	str
<code>nifgen.Session.driver_setup</code>	str
<code>nifgen.Session.exported_onboard_reference_clock_output_terminal</code>	str
<code>nifgen.Session.exported_reference_clock_output_terminal</code>	str
<code>nifgen.Session.exported_sample_clock_divisor</code>	int
<code>nifgen.Session.exported_sample_clock_output_terminal</code>	str
<code>nifgen.Session.exported_sample_clock_timebase_divisor</code>	int
<code>nifgen.Session.exported_sample_clock_timebase_output_terminal</code>	str
<code>nifgen.Session.exported_script_trigger_output_terminal</code>	str
<code>nifgen.Session.exported_start_trigger_output_terminal</code>	str
<code>nifgen.Session.external_clock_delay_binary_value</code>	int
<code>nifgen.Session.external_sample_clock_multiplier</code>	float
<code>nifgen.Session.file_transfer_block_size</code>	int

Continued on next

Table 9 – continued from previous page

Property	Datatype
<code>nifgen.Session.filter_correction_frequency</code>	float
<code>nifgen.Session.flatness_correction_enabled</code>	bool
<code>nifgen.Session.fpga_bitfile_path</code>	str
<code>nifgen.Session.freq_list_duration_quantum</code>	float
<code>nifgen.Session.freq_list_handle</code>	int
<code>nifgen.Session.func_amplitude</code>	float
<code>nifgen.Session.func_buffer_size</code>	int
<code>nifgen.Session.func_dc_offset</code>	float
<code>nifgen.Session.func_duty_cycle_high</code>	float
<code>nifgen.Session.func_frequency</code>	float
<code>nifgen.Session.func_max_buffer_size</code>	int
<code>nifgen.Session.func_start_phase</code>	float
<code>nifgen.Session.func_waveform</code>	Waveform
<code>nifgen.Session.idle_behavior</code>	IdleBehavior
<code>nifgen.Session.idle_value</code>	int
<code>nifgen.Session.instrument_firmware_revision</code>	str
<code>nifgen.Session.instrument_manufacturer</code>	str
<code>nifgen.Session.instrument_model</code>	str
<code>nifgen.Session.io_resource_descriptor</code>	str
<code>nifgen.Session.load_impedance</code>	float
<code>nifgen.Session.logical_name</code>	str
<code>nifgen.Session.major_version</code>	int
<code>nifgen.Session.marker_events_count</code>	int
<code>nifgen.Session.marker_event_output_terminal</code>	str
<code>nifgen.Session.max_freq_list_duration</code>	float
<code>nifgen.Session.max_freq_list_length</code>	int
<code>nifgen.Session.max_loop_count</code>	int
<code>nifgen.Session.max_num_freq_lists</code>	int
<code>nifgen.Session.max_num_sequences</code>	int
<code>nifgen.Session.max_num_waveforms</code>	int
<code>nifgen.Session.max_sequence_length</code>	int
<code>nifgen.Session.max_waveform_size</code>	int
<code>nifgen.Session.memory_size</code>	int
<code>nifgen.Session.minor_version</code>	int
<code>nifgen.Session.min_freq_list_duration</code>	float
<code>nifgen.Session.min_freq_list_length</code>	int
<code>nifgen.Session.min_sequence_length</code>	int
<code>nifgen.Session.min_waveform_size</code>	int
<code>nifgen.Session.module_revision</code>	str
<code>nifgen.Session.output_enabled</code>	bool
<code>nifgen.Session.output_impedance</code>	float
<code>nifgen.Session.output_mode</code>	OutputMode
<code>nifgen.Session.ready_for_start_event_output_terminal</code>	str
<code>nifgen.Session.reference_clock_source</code>	ReferenceClockSource
<code>nifgen.Session.ref_clock_frequency</code>	float
<code>nifgen.Session.sample_clock_source</code>	SampleClockSource
<code>nifgen.Session.sample_clock_timebase_rate</code>	float
<code>nifgen.Session.sample_clock_timebase_source</code>	SampleClockTimebaseSource
<code>nifgen.Session.script_to_generate</code>	str

Continued on next

Table 9 – continued from previous page

Property	Datatype
<code>nifgen.Session.script_triggers_count</code>	int
<code>nifgen.Session.script_trigger_type</code>	ScriptTriggerType
<code>nifgen.Session.serial_number</code>	str
<code>nifgen.Session.simulate</code>	bool
<code>nifgen.Session.specific_driver_description</code>	str
<code>nifgen.Session.specific_driver_revision</code>	str
<code>nifgen.Session.specific_driver_vendor</code>	str
<code>nifgen.Session.started_event_output_terminal</code>	str
<code>nifgen.Session.start_trigger_type</code>	StartTriggerType
<code>nifgen.Session.streaming_space_available_in_waveform</code>	int
<code>nifgen.Session.streaming_waveform_handle</code>	int
<code>nifgen.Session.streaming_waveform_name</code>	str
<code>nifgen.Session.streaming_write_timeout</code>	float in seconds or datetime.timedelta
<code>nifgen.Session.supported_instrument_models</code>	str
<code>nifgen.Session.terminal_configuration</code>	TerminalConfiguration
<code>nifgen.Session.trigger_mode</code>	TriggerMode
<code>nifgen.Session.wait_behavior</code>	WaitBehavior
<code>nifgen.Session.wait_value</code>	int
<code>nifgen.Session.waveform_quantum</code>	int

## Methods

Method name
<code>nifgen.Session.abort()</code>
<code>nifgen.Session.allocate_named_waveform()</code>
<code>nifgen.Session.allocate_waveform()</code>
<code>nifgen.Session.clear_arb_memory()</code>
<code>nifgen.Session.clear_arb_sequence()</code>
<code>nifgen.Session.clear_freq_list()</code>
<code>nifgen.Session.clear_user_standard_waveform()</code>
<code>nifgen.Session.commit()</code>
<code>nifgen.Session.configure_arb_sequence()</code>
<code>nifgen.Session.configure_arb_waveform()</code>
<code>nifgen.Session.configure_custom_fir_filter_coefficients()</code>
<code>nifgen.Session.configure_freq_list()</code>
<code>nifgen.Session.configure_standard_waveform()</code>
<code>nifgen.Session.create_advanced_arb_sequence()</code>
<code>nifgen.Session.create_arb_sequence()</code>
<code>nifgen.Session.create_freq_list()</code>
<code>nifgen.Session.create_waveform_from_file_f64()</code>
<code>nifgen.Session.create_waveform_from_file_il6()</code>
<code>nifgen.Session.create_waveform_numpy()</code>
<code>nifgen.Session.define_user_standard_waveform()</code>
<code>nifgen.Session.delete_script()</code>
<code>nifgen.Session.delete_waveform()</code>
<code>nifgen.Session.disable()</code>
<code>nifgen.Session.get_ext_cal_last_date_and_time()</code>
<code>nifgen.Session.get_ext_cal_last_temp()</code>

Continued on next page

Table 10 – continued from previous page

Method name
<i>nifgen.Session.get_ext_cal_recommended_interval()</i>
<i>nifgen.Session.get_hardware_state()</i>
<i>nifgen.Session.get_self_cal_last_date_and_time()</i>
<i>nifgen.Session.get_self_cal_last_temp()</i>
<i>nifgen.Session.get_self_cal_supported()</i>
<i>nifgen.Session.is_done()</i>
<i>nifgen.Session.lock()</i>
<i>nifgen.Session.query_arb_seq_capabilities()</i>
<i>nifgen.Session.query_arb_wfm_capabilities()</i>
<i>nifgen.Session.query_freq_list_capabilities()</i>
<i>nifgen.Session.read_current_temperature()</i>
<i>nifgen.Session.reset()</i>
<i>nifgen.Session.reset_device()</i>
<i>nifgen.Session.reset_with_defaults()</i>
<i>nifgen.Session.self_cal()</i>
<i>nifgen.Session.self_test()</i>
<i>nifgen.Session.send_software_edge_trigger()</i>
<i>nifgen.Session.set_next_write_position()</i>
<i>nifgen.Session.unlock()</i>
<i>nifgen.Session.wait_until_done()</i>
<i>nifgen.Session.write_script()</i>
<i>nifgen.Session.write_waveform()</i>

### 7.3.3.2 Enums

Enums used in NI-FGEN

#### AnalogPath

**class** `nifgen.AnalogPath`

**MAIN**

Specifies use of the main path. NI-FGEN chooses the amplifier based on the user-specified gain.

**DIRECT**

Specifies use of the direct path.

**FIXED\_LOW\_GAIN**

Specifies use of the low-gain amplifier in the main path, no matter what value the user specifies for gain. This setting limits the output range.

**FIXED\_HIGH\_GAIN**

Specifies use of the high-gain amplifier in the main path.

#### BusType

**class** `nifgen.BusType`

**INVALID**

Indicates an invalid bus type.

**AT**

Indicates the signal generator is the AT bus type.

**PCI**

Indicates the signal generator is the PCI bus type.

**PXI**

Indicates the signal generator is the PXI bus type.

**VXI**

Indicates the signal generator is the VXI bus type.

**PCMCIA**

Indicates the signal generator is the PCI-CMA bus type.

**PXIE**

Indicates the signal generator is the PXI Express bus type.

## ByteOrder

```
class nifgen.ByteOrder
```

**LITTLE****BIG**

## ClockMode

```
class nifgen.ClockMode
```

**HIGH\_RESOLUTION**

High resolution sampling—Sample rate is generated by a high-resolution clock source.

**DIVIDE\_DOWN**

Divide down sampling—Sample rates are generated by dividing the source frequency.

**AUTOMATIC**

Automatic Selection—NI-FGEN selects between the divide-down and high-resolution clocking modes.

## DataMarkerEventLevelPolarity

```
class nifgen.DataMarkerEventLevelPolarity
```

**HIGH**

When the operation is ready to start, the Ready for Start event level is high.

**LOW**

When the operation is ready to start, the Ready for Start event level is low.

## HardwareState

```
class nifgen.HardwareState
```

**IDLE**  
**WAITING\_FOR\_START\_TRIGGER**  
**RUNNING**  
**DONE**  
**HARDWARE\_ERROR**

## IdleBehavior

**class** nifgen.IdleBehavior

**HOLD\_LAST**  
While in an Idle or Wait state, the output signal remains at the last voltage generated prior to entering the state.

**JUMP\_TO**  
While in an Idle or Wait state, the output signal remains at the value configured in the Idle or Wait value property.

## OutputMode

**class** nifgen.OutputMode

**FUNC**  
Standard Method mode—Generates standard method waveforms such as sine, square, triangle, and so on.

**ARB**  
Arbitrary waveform mode—Generates waveforms from user-created/provided waveform arrays of numeric data.

**SEQ**  
Arbitrary sequence mode — Generates downloaded waveforms in an order your specify.

**FREQ\_LIST**  
Frequency List mode—Generates a standard method using a list of frequencies you define.

**SCRIPT**  
**Script mode**—Allows you to use scripting to link and loop multiple waveforms in complex combinations.

## ReferenceClockSource

**class** nifgen.ReferenceClockSource

**CLOCK\_IN**  
Specifies that the CLK IN input signal from the front panel connector is used as the Reference Clock source.

**NONE**  
Specifies that a Reference Clock is not used.

**ONBOARD\_REFERENCE\_CLOCK**  
Specifies that the onboard Reference Clock is used as the Reference Clock source.

**PXI\_CLOCK**

Specifies the PXI Clock is used as the Reference Clock source.

**RTSI\_7**

Specifies that the RTSI line 7 is used as the Reference Clock source.

**RelativeTo**

```
class nifgen.RelativeTo
```

**START****CURRENT****SampleClockSource**

```
class nifgen.SampleClockSource
```

**CLOCK\_IN**

Specifies that the signal at the CLK IN front panel connector is used as the Sample Clock source.

**DDC\_CLOCK\_IN**

Specifies that the Sample Clock from DDC connector is used as the Sample Clock source.

**ONBOARD\_CLOCK**

Specifies that the onboard clock is used as the Sample Clock source.

**PXI\_STAR\_LINE**

Specifies that the PXI\_STAR trigger line is used as the Sample Clock source.

**PXI\_TRIGGER\_LINE\_0RTSI\_0**

Specifies that the PXI or RTSI line 0 is used as the Sample Clock source.

**PXI\_TRIGGER\_LINE\_1RTSI\_1**

Specifies that the PXI or RTSI line 1 is used as the Sample Clock source.

**PXI\_TRIGGER\_LINE\_2RTSI\_2**

Specifies that the PXI or RTSI line 2 is used as the Sample Clock source.

**PXI\_TRIGGER\_LINE\_3RTSI\_3**

Specifies that the PXI or RTSI line 3 is used as the Sample Clock source.

**PXI\_TRIGGER\_LINE\_4RTSI\_4**

Specifies that the PXI or RTSI line 4 is used as the Sample Clock source.

**PXI\_TRIGGER\_LINE\_5RTSI\_5**

Specifies that the PXI or RTSI line 5 is used as the Sample Clock source.

**PXI\_TRIGGER\_LINE\_6RTSI\_6**

Specifies that the PXI or RTSI line 6 is used as the Sample Clock source.

**PXI\_TRIGGER\_LINE\_7RTSI\_7**

Specifies that the PXI or RTSI line 7 is used as the Sample Clock source.

## SampleClockTimebaseSource

```
class nifgen.SampleClockTimebaseSource
```

### CLOCK\_IN

Specifies that the external signal on the CLK IN front panel connector is used as the source.

### ONBOARD\_CLOCK

Specifies that the onboard Sample Clock timebase is used as the source.

## ScriptTriggerDigitalEdgeEdge

```
class nifgen.ScriptTriggerDigitalEdgeEdge
```

### RISING

Rising Edge

### FALLING

Falling Edge

## ScriptTriggerType

```
class nifgen.ScriptTriggerType
```

### TRIG\_NONE

No trigger is configured. Signal generation starts immediately.

### DIGITAL\_EDGE

Trigger is asserted when a digital edge is detected.

### DIGITAL\_LEVEL

Trigger is asserted when a digital level is detected.

### SOFTWARE\_EDGE

Trigger is asserted when a software edge is detected.

## StartTriggerDigitalEdgeEdge

```
class nifgen.StartTriggerDigitalEdgeEdge
```

### RISING

Rising Edge

### FALLING

Falling Edge

## StartTriggerType

```
class nifgen.StartTriggerType
```



**TRIG\_NONE**

None

**DIGITAL\_EDGE**

Digital Edge

**SOFTWARE\_EDGE**

Software Edge

**P2P\_ENDPOINT\_FULLNESS**

P2P Endpoint Fullness

## TerminalConfiguration

```
class nifgen.TerminalConfiguration
```

**SINGLE\_ENDED**

Single-ended operation

**DIFFERENTIAL**

Differential operation

## TriggerMode

```
class nifgen.TriggerMode
```

**SINGLE**

Single Trigger Mode - The waveform you describe in the sequence list is generated only once by going through the entire staging list. Only one trigger is required to start the waveform generation. You can use Single trigger mode with the output mode in any mode. After a trigger is received, the waveform generation starts from the first stage and continues through to the last stage. Then, the last stage generates repeatedly until you stop the waveform generation.

**CONTINUOUS**

Continuous Trigger Mode - The waveform you describe in the staging list generates infinitely by repeatedly cycling through the staging list. After a trigger is received, the waveform generation starts from the first stage and continues through to the last stage. After the last stage completes, the waveform generation loops back to the start of the first stage and continues until it is stopped. Only one trigger is required to start the waveform generation.

**STEPPED**

Stepped Trigger Mode - After a start trigger is received, the waveform described by the first stage generates. Then, the device waits for the next trigger signal. On the next trigger, the waveform described by the second stage generates, and so on. After the staging list completes, the waveform generation returns to the first stage and continues in a cyclic fashion. After any stage has generated completely, the first eight samples of the next stage are repeated continuously until the next trigger is received. trigger mode.

---

**Note:** In Frequency List mode, Stepped trigger mode is the same as Burst

---

**BURST**

Burst Trigger Mode - After a start trigger is received, the waveform described by the first stage generates until another trigger is received. At the next trigger, the buffer of the previous stage completes, and then the waveform described by the second stage generates. After the staging list completes, the waveform

generation returns to the first stage and continues in a cyclic fashion. In Frequency List mode, the duration instruction is ignored, and the trigger switches the frequency to the next frequency in the list. trigger mode.

---

**Note:** In Frequency List mode, Stepped trigger mode is the same as Burst

---

## WaitBehavior

**class** `nifgen.WaitBehavior`

### **HOLD\_LAST**

While in an Idle or Wait state, the output signal remains at the last voltage generated prior to entering the state.

### **JUMP\_TO**

While in an Idle or Wait state, the output signal remains at the value configured in the Idle or Wait value property.

## Waveform

**class** `nifgen.Waveform`

### **SINE**

Sinusoid waveform

### **SQUARE**

Square waveform

### **TRIANGLE**

Triange waveform

### **RAMP\_UP**

Positive ramp waveform

### **RAMP\_DOWN**

Negative ramp waveform

### **DC**

Constant voltage

### **NOISE**

White noise

### **USER**

User-defined waveform as defined by the `nifgen.Session.define_user_standard_waveform()` method.

### 7.3.3.3 Exceptions and Warnings

#### DriverError

**exception** `nifgen.DriverError`

An error originating from the NI-FGEN driver

### UnsupportedConfigurationError

**exception** `nifgen.UnsupportedConfigurationError`

An error due to using this module in an unsupported platform.

### DriverNotInstalledError

**exception** `nifgen.DriverNotInstalledError`

An error due to using this module without the driver runtime installed.

### InvalidRepeatedCapabilityError

**exception** `nifgen.InvalidRepeatedCapabilityError`

An error due to an invalid character in a repeated capability

### SelfTestError

**exception** `nifgen.SelfTestError`

An error due to a failed self-test

### DriverWarning

**exception** `nifgen.DriverWarning`

A warning originating from the NI-FGEN driver

## 7.3.3.4 Examples

### nifgen\_arb\_waveform.py

Listing 6: (nifgen\_arb\_waveform.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import math
5  import nifgen
6  import sys
7  import time
8
9
10 def create_waveform_data(number_of_samples):
11     waveform_data = []
12     angle_per_sample = (2 * math.pi) / number_of_samples
13     for i in range(number_of_samples):
14         waveform_data.append(math.sin(i * angle_per_sample) * math.sin(i * angle_per_
15         ↪sample * 20))
16     return waveform_data
17

```

(continues on next page)

(continued from previous page)

```

18 def example(resource_name, options, samples, gain, offset, gen_time):
19     waveform_data = create_waveform_data(samples)
20     with nifgen.Session(resource_name=resource_name, options=options) as session:
21         session.output_mode = nifgen.OutputMode.ARB
22         waveform = session.create_waveform(waveform_data_array=waveform_data)
23         session.configure_arb_waveform(waveform_handle=waveform, gain=gain,
↳offset=offset)
24         with session.initiate():
25             time.sleep(gen_time)
26
27
28 def _main(argv):
29     parser = argparse.ArgumentParser(description='Continuously generates an arbitrary_
↳waveform.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)
30     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
↳name of a National Instruments Arbitrary Waveform Generator')
31     parser.add_argument('-s', '--samples', default=100000, type=int, help='Number of_
↳samples')
32     parser.add_argument('-g', '--gain', default=1.0, type=float, help='Gain')
33     parser.add_argument('-o', '--offset', default=0.0, type=float, help='DC offset (V)
↳')
34     parser.add_argument('-t', '--time', default=5.0, type=float, help='Generation_
↳time (s)')
35     parser.add_argument('-op', '--option-string', default='', type=str, help='Option_
↳string')
36     args = parser.parse_args(argv)
37     example(args.resource_name, args.option_string, args.samples, args.gain, args.
↳offset, args.time)
38
39
40 def main():
41     _main(sys.argv[1:])
42
43
44 def test_example():
45     options = {'simulate': True, 'driver_setup': {'Model': '5433 (2CH)', 'BoardType':
↳'PXIe', }, }
46     example('PXI1Slot2', options, 100000, 1.0, 0.0, 5.0)
47
48
49 def test_main():
50     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:5433 (2CH);
↳BoardType:PXIe', ]
51     _main(cmd_line)
52
53
54 if __name__ == '__main__':
55     main()
56
57

```

## nifgen\_standard\_function.py

Listing 7: (nifgen\_standard\_function.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import nifgen
5  import sys
6  import time
7
8
9  def example(resource_name, options, waveform, frequency, amplitude, offset, phase,
    ↪ gen_time):
10     with nifgen.Session(resource_name=resource_name, options=options) as session:
11         session.output_mode = nifgen.OutputMode.FUNC
12         session.configure_standard_waveform(waveform=nifgen.Waveform[waveform],
    ↪ amplitude=amplitude, frequency=frequency, dc_offset=offset, start_phase=phase)
13         with session.initiate():
14             time.sleep(gen_time)
15
16
17  def _main(argv):
18     supported_waveforms = list(nifgen.Waveform.__members__.keys())[:-1] # no support
    ↪ for user-defined waveforms in example
19     parser = argparse.ArgumentParser(description='Generates the standard function.',
    ↪ formatter_class=argparse.ArgumentDefaultsHelpFormatter)
20     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource
    ↪ name of a National Instruments Function Generator')
21     parser.add_argument('-w', '--waveform', default=supported_waveforms[0],
    ↪ choices=supported_waveforms, type=str.upper, help='Standard waveform')
22     parser.add_argument('-f', '--frequency', default=1000, type=float, help=
    ↪ 'Frequency (Hz)')
23     parser.add_argument('-a', '--amplitude', default=1.0, type=float, help='Amplitude
    ↪ (Vpk-pk)')
24     parser.add_argument('-o', '--offset', default=0.0, type=float, help='DC offset (V)
    ↪')
25     parser.add_argument('-p', '--phase', default=0.0, type=float, help='Start phase
    ↪ (deg)')
26     parser.add_argument('-t', '--time', default=5.0, type=float, help='Generation
    ↪ time (s)')
27     parser.add_argument('-op', '--option-string', default='', type=str, help='Option
    ↪ string')
28     args = parser.parse_args(argv)
29     example(args.resource_name, args.option_string, args.waveform, args.frequency,
    ↪ args.amplitude, args.offset, args.phase, args.time)
30
31
32  def main():
33     _main(sys.argv[1:])
34
35
36  def test_example():
37     options = {'simulate': True, 'driver_setup': {'Model': '5433 (2CH)', 'BoardType':
    ↪ 'PXIe', }, }
38     example('PXI1Slot2', options, 'SINE', 1000, 1.0, 0.0, 0.0, 5.0)
39
40
41  def test_main():

```

(continues on next page)

(continued from previous page)

```

42     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:5433 (2CH);
↳BoardType:PXIe', ]
43     _main(cmd_line)
44
45
46 if __name__ == '__main__':
47     main()
48
49
50

```

## 7.4 nscope module

### 7.4.1 Installation

As a prerequisite to using the nscope module, you must install the NI-SCOPE runtime on your system. Visit [ni.com/downloads](http://ni.com/downloads) to download the driver runtime for your devices.

The nimi-python modules (i.e. for NI-SCOPE) can be installed with **pip**:

```
$ python -m pip install nscope~=1.0.0
```

Or **easy\_install** from **setuptools**:

```
$ python -m easy_install nscope
```

### 7.4.2 Usage

The following is a basic example of using the **nscope** module to open a session to a High Speed Digitizer and capture a single record of 1000 points.

```

import nscope
with nscope.Session("Dev1") as session:
    session.channels[0].configure_vertical(range=1.0, coupling=nscope.
↳VerticalCoupling.AC)
    session.channels[1].configure_vertical(range=10.0, coupling=nscope.
↳VerticalCoupling.DC)
    session.configure_horizontal_timing(min_sample_rate=50000000, min_num_pts=1000,
↳ref_position=50.0, num_records=5, enforce_realtime=True)
    with session.initiate():
        waveforms = session.channels[0,1].fetch(num_records=5)
        for wfm in waveforms:
            print('Channel {0}, record {1} samples acquired: {2:,\n'.format(wfm.channel,
↳wfm.record, len(wfm.samples)))

    # Find all channel 1 records (Note channel name is always a sting even if
↳integers used in channel[])
    chan1 = [wfm for wfm in waveforms if wfm.channel == '0']

    # Find all record number 3
    rec3 = [wfm for wfm in waveforms if wfm.record == 3]

```

The waveform returned from **fetch** is a flat list of Python objects

- Attributes:
  - **relative\_initial\_x** (float) the time (in seconds) from the trigger to the first sample in the fetched waveform
  - **absolute\_initial\_x** (float) timestamp (in seconds) of the first fetched sample. This timestamp is comparable between records and acquisitions; devices that do not support this parameter use 0 for this output.
  - **x\_increment** (float) the time between points in the acquired waveform in seconds
  - **channel** (str) channel name this waveform was asquire from
  - **record** (int) record number of this waveform
  - **gain** (float) the gain factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **offset** (float) the offset factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **samples** (array of float) floating point array of samples. Length will be of the actual samples acquired
- Such that all record 0 waveforms are first. For example, with a channel list of 0,1, you would have the following index values:
  - index 0 = record 0, channel 0
  - index 1 = record 0, channel 1
  - index 2 = record 1, channel 0
  - index 3 = record 1, channel 1
  - etc.

If you need more performance or need to work with [SciPy](#), you can use the `fetch_into()` method instead of `fetch()`. This method takes an already allocated [numpy](#) array and puts the acquired samples in it. Data types supported:

- `numpy.float64`
- `numpy.int8`
- `numpy.int16`
- `numpy.int32`

```
voltage_range = 1.0
record_length = 2000
channels = [0, 1]
num_channels = len(channels)
num_records = 5
wfm = numpy.ndarray(num_channels * record_length, dtype=numpy.int8)
session.configure_vertical(voltage_range, niscopes.VerticalCoupling.AC)
session.configure_horizontal_timing(50000000, record_length, 50.0, num_records, True)
with session.initiate():
    waveform_infos = session.channels[channels].fetch_into(wfm=wfm, num_records=num_
↪records)
```

The waveform\_infos returned from `fetch_into` is a 1D list of Python objects

- Attributes:
  - **relative\_initial\_x** (float) the time (in seconds) from the trigger to the first sample in the fetched waveform
  - **absolute\_initial\_x** (float) timestamp (in seconds) of the first fetched sample. This timestamp is comparable between records and acquisitions; devices that do not support this parameter use 0 for this output.
  - **x\_increment** (float) the time between points in the acquired waveform in seconds
  - **channel** (str) channel name this waveform was asquire from
  - **record** (int) record number of this waveform
  - **gain** (float) the gain factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **offset** (float) the offset factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **samples** (numpy array of datatype used) floating point array of samples. Length will be of the actual samples acquired

---

**Note:** Python 3 only

---

- Such that all record 0 waveforms are first. For example, with a channel list of 0,1, you would have the following index values:
  - index 0 = record 0, channel 0
  - index 1 = record 0, channel 1
  - index 2 = record 1, channel 0
  - index 3 = record 1, channel 1
  - etc.

---

**Note:** When using Python 2, the waveform\_infos objects do not include the waveform for that record. Instead, samples are in the waveform passed into the function using the following layout:

- index 0 = record 0, channel 0
  - index  $x$  = record 0, channel 1
  - index  $2x$  = record 1, channel 0
  - index  $3x$  = record 1, channel 1
  - etc.
  - Where  $x$  = the record length
- 

Additional examples for NI-SCOPE are located in `src/niscope/examples/` directory.



## 7.4.3 API Reference

### 7.4.3.1 niscopes.Session

**class** `niscopes.Session` (*self, resource\_name, id\_query=False, reset\_device=False, options={}*)

Performs the following initialization actions:

- Creates a new IVI instrument driver and optionally sets the initial state of the following session properties: Range Check, Cache, Simulate, Record Value Coercions
- Opens a session to the specified device using the interface and address you specify for the **resourceName**
- Resets the digitizer to a known state if **resetDevice** is set to True
- Queries the instrument ID and verifies that it is valid for this instrument driver if the **IDQuery** is set to True
- Returns an instrument handle that you use to identify the instrument in all subsequent instrument driver method calls

#### Parameters

- **resource\_name** (*str*) –

**Caution:** Traditional NI-DAQ and NI-DAQmx device names are not case-sensitive. However, all IVI names, such as logical names, are case-sensitive. If you use logical names, driver session names, or virtual names in your program, you must make sure that the name you use matches the name in the IVI Configuration Store file exactly, without any variations in the case of the characters.

Specifies the resource name of the device to initialize

For Traditional NI-DAQ devices, the syntax is `DAQ::n`, where *n* is the device number assigned by MAX, as shown in Example 1.

For NI-DAQmx devices, the syntax is just the device name specified in MAX, as shown in Example 2. Typical default names for NI-DAQmx devices in MAX are `Dev1` or `PXI1Slot1`. You can rename an NI-DAQmx device by right-clicking on the name in MAX and entering a new name.

An alternate syntax for NI-DAQmx devices consists of `DAQ::NI-DAQmx device name`, as shown in Example 3. This naming convention allows for the use of an NI-DAQmx device in an application that was originally designed for a Traditional NI-DAQ device. For example, if the application expects `DAQ::1`, you can rename the NI-DAQmx device to 1 in MAX and pass in `DAQ::1` for the resource name, as shown in Example 4.

If you use the `DAQ::n` syntax and an NI-DAQmx device name already exists with that same name, the NI-DAQmx device is matched first.

You can also pass in the name of an IVI logical name or an IVI virtual name configured with the IVI Configuration utility, as shown in Example 5. A logical name identifies a particular virtual instrument. A virtual name identifies a specific device and specifies the initial settings for the session.

Example	Device Type	Syntax
1	Traditional NI-DAQ device	DAQ::1 (1 = device number)
2	NI-DAQmx device	myDAQmxDevice (myDAQmxDevice = device name)
3	NI-DAQmx device	DAQ::myDAQmxDevice (myDAQmxDevice = device name)
4	NI-DAQmx device	DAQ::2 (2 = device name)
5	IVI logical name or IVI virtual name	myLogicalName (myLogicalName = name)

- **id\_query** (*bool*) – Specify whether to perform an ID query.

When you set this parameter to True, NI-SCOPE verifies that the device you initialize is a type that it supports.

When you set this parameter to False, the method initializes the device without performing an ID query.

#### Defined Values

True—Perform ID query

False—Skip ID query

**Default Value:** True

- **reset\_device** (*bool*) – Specify whether to reset the device during the initialization process.

Default Value: True

#### Defined Values

True (1)—Reset device

False (0)—Do not reset device

---

**Note:** For the NI 5112, repeatedly resetting the device may cause excessive wear on the electromechanical relays. Refer to [NI 5112 Electromechanical Relays](#) for recommended programming practices.

---

- **options** (*str*) – Specifies the initial value of certain properties for the session. The syntax for **options** is a dictionary of properties with an assigned value. For example:

```
{ 'simulate': False }
```

You do not have to specify a value for all the properties. If you do not specify a value for a property, the default value is used.

Advanced Example: { 'simulate': True, 'driver\_setup': { 'Model': '<model number>', 'BoardType': '<type>' } }

Property	Default
range_check	True
query_instrument_status	False
cache	True
simulate	False
record_value_coersions	False
driver_setup	{}

## Properties

Property	Datatype
<i>absolute_sample_clock_offset</i>	float in seconds or datetime.timedelta
<i>accessory_gain</i>	float
<i>accessory_offset</i>	float
<i>acquisition_start_time</i>	float in seconds or datetime.timedelta
<i>acquisition_type</i>	<i>AcquisitionType</i>
<i>acq_arm_source</i>	str
<i>adv_trig_src</i>	str
<i>allow_more_records_than_memory</i>	bool
<i>arm_ref_trig_src</i>	str
<i>backlog</i>	float
<i>bandpass_filter_enabled</i>	bool
<i>binary_sample_width</i>	int
<i>channel_count</i>	int
<i>channel_enabled</i>	bool
<i>channel_terminal_configuration</i>	<i>TerminalConfiguration</i>
<i>data_transfer_block_size</i>	int
<i>data_transfer_maximum_bandwidth</i>	float
<i>data_transfer_preferred_packet_size</i>	int
<i>device_temperature</i>	float
<i>driver_setup</i>	str
<i>enable_dc_restore</i>	bool
<i>enable_time_interleaved_sampling</i>	bool
<i>end_of_acquisition_event_output_terminal</i>	str
<i>end_of_record_event_output_terminal</i>	str
<i>end_of_record_to_advance_trigger_holdoff</i>	float in seconds or datetime.timedelta
<i>equalization_filter_enabled</i>	bool
<i>equalization_num_coefficients</i>	int
<i>exported_advance_trigger_output_terminal</i>	str
<i>exported_ref_trigger_output_terminal</i>	str
<i>exported_start_trigger_output_terminal</i>	str
<i>flex_fir_antialias_filter_type</i>	<i>FlexFIRAntialiasFilterType</i>
<i>fpga_bitfile_path</i>	str
<i>high_pass_filter_frequency</i>	float
<i>horz_enforce_realtime</i>	bool
<i>horz_min_num_pts</i>	int
<i>horz_num_records</i>	int
<i>horz_record_length</i>	int
<i>horz_record_ref_position</i>	float
<i>horz_sample_rate</i>	float

Continued on next page

Table 11 – continued from previous page

Property	Datatype
<i>horz_time_per_record</i>	float in seconds or datetime.timedelta
<i>input_clock_source</i>	str
<i>input_impedance</i>	float
<i>instrument_firmware_revision</i>	str
<i>instrument_manufacturer</i>	str
<i>instrument_model</i>	str
<i>interleaving_offset_correction_enabled</i>	bool
<i>io_resource_descriptor</i>	str
<i>logical_name</i>	str
<i>master_enable</i>	bool
<i>max_input_frequency</i>	float
<i>max_real_time_sampling_rate</i>	float
<i>max_ris_rate</i>	float
<i>min_sample_rate</i>	float
<i>onboard_memory_size</i>	int
<i>output_clock_source</i>	str
<i>pll_lock_status</i>	bool
<i>points_done</i>	float
<i>poll_interval</i>	int
<i>probe_attenuation</i>	float
<i>ready_for_advance_event_output_terminal</i>	str
<i>ready_for_ref_event_output_terminal</i>	str
<i>ready_for_start_event_output_terminal</i>	str
<i>records_done</i>	int
<i>record_arm_source</i>	str
<i>ref_clk_rate</i>	float
<i>ref_trigger_detector_location</i>	<i>RefTriggerDetectorLocation</i>
<i>ref_trigger_minimum_quiet_time</i>	float in seconds or datetime.timedelta
<i>ref_trig_tdc_enable</i>	bool
<i>resolution</i>	int
<i>ris_in_auto_setup_enable</i>	bool
<i>ris_method</i>	<i>RISMethod</i>
<i>ris_num_averages</i>	int
<i>sample_clock_timebase_multiplier</i>	int
<i>sample_mode</i>	int
<i>samp_clk_timebase_div</i>	int
<i>samp_clk_timebase_rate</i>	float
<i>samp_clk_timebase_src</i>	str
<i>serial_number</i>	str
<i>simulate</i>	bool
<i>specific_driver_description</i>	str
<i>specific_driver_revision</i>	str
<i>specific_driver_vendor</i>	str
<i>start_to_ref_trigger_holdoff</i>	float in seconds or datetime.timedelta
<i>supported_instrument_models</i>	str
<i>trigger_auto_triggered</i>	bool
<i>trigger_coupling</i>	<i>TriggerCoupling</i>
<i>trigger_delay_time</i>	float in seconds or datetime.timedelta
<i>trigger_holdoff</i>	float in seconds or datetime.timedelta

Continued on next page

Table 11 – continued from previous page

Property	Datatype
<i>trigger_hysteresis</i>	float
<i>trigger_impedance</i>	float
<i>trigger_level</i>	float
<i>trigger_modifier</i>	<i>TriggerModifier</i>
<i>trigger_slope</i>	<i>TriggerSlope</i>
<i>trigger_source</i>	str
<i>trigger_type</i>	<i>TriggerType</i>
<i>trigger_window_high_level</i>	float
<i>trigger_window_low_level</i>	float
<i>trigger_window_mode</i>	<i>TriggerWindowMode</i>
<i>tv_trigger_event</i>	<i>VideoTriggerEvent</i>
<i>tv_trigger_line_number</i>	int
<i>tv_trigger_polarity</i>	<i>VideoPolarity</i>
<i>tv_trigger_signal_format</i>	<i>VideoSignalFormat</i>
<i>vertical_coupling</i>	<i>VerticalCoupling</i>
<i>vertical_offset</i>	float
<i>vertical_range</i>	float

**Public methods**

Method name
<i>abort()</i>
<i>acquisition_status()</i>
<i>auto_setup()</i>
<i>commit()</i>
<i>configure_chan_characteristics()</i>
<i>configure_equalization_filter_coefficients()</i>
<i>configure_horizontal_timing()</i>
<i>configure_trigger_digital()</i>
<i>configure_trigger_edge()</i>
<i>configure_trigger_hysteresis()</i>
<i>configure_trigger_immediate()</i>
<i>configure_trigger_software()</i>
<i>configure_trigger_video()</i>
<i>configure_trigger_window()</i>
<i>configure_vertical()</i>
<i>disable()</i>
<i>fetch()</i>
<i>fetch_into()</i>
<i>get_equalization_filter_coefficients()</i>
<i>lock()</i>
<i>probe_compensation_signal_start()</i>
<i>probe_compensation_signal_stop()</i>
<i>read()</i>
<i>reset()</i>
<i>reset_device()</i>
<i>reset_with_defaults()</i>
<i>self_cal()</i>
<i>self_test()</i>

Continued on next page

Table 12 – continued from previous page

Method name
<code>send_software_trigger_edge()</code>
<code>unlock()</code>

## Properties

### absolute\_sample\_clock\_offset

`niscope.Session.absolute_sample_clock_offset`

Gets or sets the absolute time offset of the sample clock relative to the reference clock in terms of seconds.

---

**Note:** Configures the sample clock relationship with respect to the reference clock. This parameter is factored into NI-TClk adjustments and is typically used to improve the repeatability of NI-TClk Synchronization. When this parameter is read, the currently programmed value is returned. The range of the absolute sample clock offset is [-.5 sample clock periods, .5 sample clock periods]. The default absolute sample clock offset is 0s.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:Advanced:Absolute Sample Clock Offset**
  - C Attribute: **NISCOPE\_ATTR\_ABSOLUTE\_SAMPLE\_CLOCK\_OFFSET**
- 

### accessory\_gain

`niscope.Session.accessory_gain`

Returns the calibration gain for the current device configuration. **Related topics:** [NI 5122/5124/5142 Calibration](#)

---

**Note:** This property is only supported by the NI PXI-5900 differential amplifier.

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].accessory_gain
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Device:Accessory:Gain**
- C Attribute: **NISCOPE\_ATTR\_ACCESSORY\_GAIN**

## accessory\_offset

`niscope.Session.accessory_offset`

Returns the calibration offset for the current device configuration. **Related topics:** [NI 5122/5124/5142 Calibration](#)

**Note:** This property is supported only by the NI PXI-5900 differential amplifier.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].accessory_offset
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Device:Accessory:Offset**
- C Attribute: **NISCOPE\_ATTR\_ACCESSORY\_OFFSET**

## acquisition\_start\_time

`niscope.Session.acquisition_start_time`

Specifies the length of time from the trigger event to the first point in the waveform record in seconds. If the value is positive, the first point in the waveform record occurs after the trigger event (same as specifying `niscope.Session.trigger_delay_time`). If the value is negative, the first point in the waveform record occurs before the trigger event (same as specifying `niscope.Session.horz_record_ref_position`).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Advanced:Acquisition Start Time**
  - C Attribute: **NISCOPE\_ATTR\_ACQUISITION\_START\_TIME**
- 

## acquisition\_type

`niscope.Session.acquisition_type`

Specifies how the digitizer acquires data and fills the waveform record.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.AcquisitionType</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Acquisition:Acquisition Type**
  - C Attribute: **NISCOPE\_ATTR\_ACQUISITION\_TYPE**
- 

## acq\_arm\_source

`niscope.Session.acq_arm_source`

Specifies the source the digitizer monitors for a start (acquisition arm) trigger. When the start trigger is received, the digitizer begins acquiring pretrigger samples. Valid Values: `NISCOPE_VAL_IMMEDIATE` ('VAL\_IMMEDIATE') - Triggers immediately `NISCOPE_VAL_RTSL_0` ('VAL\_RTSL\_0') - RTSL 0 `NISCOPE_VAL_RTSL_1` ('VAL\_RTSL\_1')



- RTSI 1 NISCOPE\_VAL\_RTSI\_2 ('VAL\_RTSI\_2') - RTSI 2 NISCOPE\_VAL\_RTSI\_3 ('VAL\_RTSI\_3') - RTSI 3 NISCOPE\_VAL\_RTSI\_4 ('VAL\_RTSI\_4') - RTSI 4 NISCOPE\_VAL\_RTSI\_5 ('VAL\_RTSI\_5') - RTSI 5 NISCOPE\_VAL\_RTSI\_6 ('VAL\_RTSI\_6') - RTSI 6 NISCOPE\_VAL\_PFI\_0 ('VAL\_PFI\_0') - PFI 0 NISCOPE\_VAL\_PFI\_1 ('VAL\_PFI\_1') - PFI 1 NISCOPE\_VAL\_PFI\_2 ('VAL\_PFI\_2') - PFI 2 NISCOPE\_VAL\_PXI\_STAR ('VAL\_PXI\_STAR') - PXI Star Trigger

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Start Trigger (Acq. Arm):Source**
  - C Attribute: **NISCOPE\_ATTR\_ACQ\_ARM\_SOURCE**
- 

## adv\_trig\_src

`niscope.Session.adv_trig_src`

Specifies the source the digitizer monitors for an advance trigger. When the advance trigger is received, the digitizer begins acquiring pretrigger samples.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Advance Trigger:Source**
  - C Attribute: **NISCOPE\_ATTR\_ADV\_TRIG\_SRC**
- 

## allow\_more\_records\_than\_memory

`niscope.Session.allow_more_records_than_memory`

Indicates whether more records can be configured with `niscope.Session.configure_horizontal_timing()` than fit in the onboard memory. If this property

is set to True, it is necessary to fetch records while the acquisition is in progress. Eventually, some of the records will be overwritten. An error is returned from the fetch method if you attempt to fetch a record that has been overwritten.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Enable Records > Memory**
  - C Attribute: **NISCOPE\_ATTR\_ALLOW\_MORE\_RECORDS\_THAN\_MEMORY**
- 

## arm\_ref\_trig\_src

`niscope.Session.arm_ref_trig_src`

Specifies the source the digitizer monitors for an arm reference trigger. When the arm reference trigger is received, the digitizer begins looking for a reference (stop) trigger from the user-configured trigger source.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Arm Reference Trigger:Source**
  - C Attribute: **NISCOPE\_ATTR\_ARM\_REF\_TRIG\_SRC**
- 

## backlog

`niscope.Session.backlog`

Returns the number of samples (`niscope.Session.points_done`) that have been acquired but not fetched for the record specified by `niscope.Session.fetch_record_number`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Fetch:Fetch Backlog**
  - C Attribute: **NISCOPE\_ATTR\_BACKLOG**
- 

## bandpass\_filter\_enabled

`niscope.Session.bandpass_filter_enabled`

Enables the bandpass filter on the specified channel. The default value is FALSE.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].bandpass_filter_enabled = var
var = session.channels[0,1].bandpass_filter_enabled
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Advanced:Bandpass Filter Enabled**
  - C Attribute: **NISCOPE\_ATTR\_BANDPASS\_FILTER\_ENABLED**
- 

## binary\_sample\_width

`niscope.Session.binary_sample_width`

Indicates the bit width of the binary data in the acquired waveform. Useful for determining which Binary Fetch method to use. Compare to `niscope.Session.resolution`. To configure the device to store samples with a lower resolution than the native, set this property to the desired binary width. This can be useful for streaming at faster speeds at the cost of resolution. The least significant bits will be lost with this configuration. Valid Values: 8, 16, 32

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Acquisition:Binary Sample Width**
  - C Attribute: **NISCOPE\_ATTR\_BINARY\_SAMPLE\_WIDTH**
- 

## channel\_count

`niscope.Session.channel_count`

Indicates the number of channels that the specific instrument driver supports. For channel-based properties, the IVI engine maintains a separate cache value for each channel.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Capabilities:Channel Count**
  - C Attribute: **NISCOPE\_ATTR\_CHANNEL\_COUNT**
- 

## channel\_enabled

`niscope.Session.channel_enabled`

Specifies whether the digitizer acquires a waveform for the channel. Valid Values: True (1) - Acquire data on this channel False (0) - Don't acquire data on this channel

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].channel_enabled = var
var = session.channels[0,1].channel_enabled
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Channel Enabled**
- C Attribute: **NISCOPE\_ATTR\_CHANNEL\_ENABLED**

## channel\_terminal\_configuration

`niscope.Session.channel_terminal_configuration`

Specifies the terminal configuration for the channel.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].channel_terminal_configuration = var
var = session.channels[0,1].channel_terminal_configuration
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TerminalConfiguration</code>
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Channel Terminal Configuration**
- C Attribute: **NISCOPE\_ATTR\_CHANNEL\_TERMINAL\_CONFIGURATION**

## data\_transfer\_block\_size

`niscope.Session.data_transfer_block_size`

Specifies the maximum number of samples to transfer at one time from the device to host memory. Increasing this number should result in better fetching performance because the driver does not need

to restart the transfers as often. However, increasing this number may also increase the amount of page-locked memory required from the system.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Fetch>Data Transfer Block Size**
  - C Attribute: **NISCOPE\_ATTR\_DATA\_TRANSFER\_BLOCK\_SIZE**
- 

### **data\_transfer\_maximum\_bandwidth**

`niscope.Session.data_transfer_maximum_bandwidth`

This property specifies the maximum bandwidth that the device is allowed to consume.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Fetch:Advanced:Maximum Bandwidth**
  - C Attribute: **NISCOPE\_ATTR\_DATA\_TRANSFER\_MAXIMUM\_BANDWIDTH**
- 

### **data\_transfer\_preferred\_packet\_size**

`niscope.Session.data_transfer_preferred_packet_size`

This property specifies the size of (read request/memory write) data payload. Due to alignment of the data buffers, the hardware may not always generate a packet of this size.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Fetch:Advanced:Preferred Packet Size**
  - C Attribute: **NISCOPE\_ATTR\_DATA\_TRANSFER\_PREFERRED\_PACKET\_SIZE**
- 

## device\_temperature

`niscope.Session.device_temperature`

Returns the temperature of the device in degrees Celsius from the onboard sensor.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Device:Temperature**
  - C Attribute: **NISCOPE\_ATTR\_DEVICE\_TEMPERATURE**
- 

## driver\_setup

`niscope.Session.driver_setup`

This property indicates the Driver Setup string that the user specified when initializing the driver. Some cases exist where the end-user must specify instrument driver options at initialization. An example of this is specifying a particular instrument model from among a family of instruments that the driver supports. This is useful when using simulation. The end-user can specify driver-specific options through the DriverSetup keyword in the optionsString parameter in `niscope.Session.__init__()`, or through the IVI Configuration Utility. If the user does not specify a Driver Setup string, this property returns an empty string.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	0
Resettable	0

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NISCOPE\_ATTR\_DRIVER\_SETUP**
-

## enable\_dc\_restore

`niscope.Session.enable_dc_restore`

Restores the video-triggered data retrieved by the digitizer to the video signal's zero reference point.

Valid Values: True - Enable DC restore False - Disable DC restore

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Video:Enable DC Restore**
  - C Attribute: **NISCOPE\_ATTR\_ENABLE\_DC\_RESTORE**
- 

## enable\_time\_interleaved\_sampling

`niscope.Session.enable_time_interleaved_sampling`

Specifies whether the digitizer acquires the waveform using multiple ADCs for the channel enabling a higher maximum real-time sampling rate. Valid Values: True (1) - Use multiple interleaved ADCs on this channel False (0) - Use only this channel's ADC to acquire data for this channel

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].enable_time_interleaved_sampling = var
var = session.channels[0,1].enable_time_interleaved_sampling
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Enable Time Interleaved Sampling**
  - C Attribute: **NISCOPE\_ATTR\_ENABLE\_TIME\_INTERLEAVED\_SAMPLING**
-



## end\_of\_acquisition\_event\_output\_terminal

`niscope.Session.end_of_acquisition_event_output_terminal`

Specifies the destination for the End of Acquisition Event. When this event is asserted, the digitizer has completed sampling for all records. Consult your device documentation for a specific list of valid destinations.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:End of Acquisition:Output Terminal**
  - C Attribute: **NISCOPE\_ATTR\_END\_OF\_ACQUISITION\_EVENT\_OUTPUT\_TERMINAL**
- 

## end\_of\_record\_event\_output\_terminal

`niscope.Session.end_of_record_event_output_terminal`

Specifies the destination for the End of Record Event. When this event is asserted, the digitizer has completed sampling for the current record. Consult your device documentation for a specific list of valid destinations.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:End of Record:Output Terminal**
  - C Attribute: **NISCOPE\_ATTR\_END\_OF\_RECORD\_EVENT\_OUTPUT\_TERMINAL**
- 

## end\_of\_record\_to\_advance\_trigger\_holdoff

`niscope.Session.end_of_record_to_advance_trigger_holdoff`

End of Record to Advance Trigger Holdoff is the length of time (in seconds) that a device waits between the completion of one record and the acquisition of pre-trigger samples for the next record. During this time, the acquisition engine state delays the transition to the Wait for Advance Trigger

state, and will not store samples in onboard memory, accept an Advance Trigger, or trigger on the input signal.. **Supported Devices:** NI 5185/5186

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:End of Record to Advance Trigger Holdoff**
  - C Attribute: **NISCOPE\_ATTR\_END\_OF\_RECORD\_TO\_ADVANCE\_TRIGGER\_HOLDOFF**
- 

## equalization\_filter\_enabled

`niscope.Session.equalization_filter_enabled`

Enables the onboard signal processing FIR block. This block is connected directly to the input signal. This filter is designed to compensate the input signal for artifacts introduced to the signal outside of the digitizer. However, since this is a generic FIR filter any coefficients are valid. Coefficients should be between +1 and -1 in value.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].equalization_filter_enabled = var
var = session.channels[0,1].equalization_filter_enabled
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Onboard Signal Processing:Equalization:Equalization Filter Enabled**
  - C Attribute: **NISCOPE\_ATTR\_EQUALIZATION\_FILTER\_ENABLED**
-

## equalization\_num\_coefficients

### `niscope.Session.equalization_num_coefficients`

Returns the number of coefficients that the FIR filter can accept. This filter is designed to compensate the input signal for artifacts introduced to the signal outside of the digitizer. However, since this is a generic FIR filter any coefficients are valid. Coefficients should be between +1 and -1 in value.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].equalization_num_coefficients
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Onboard Signal Processing:Equalization:Equalization Num Coefficients**
- C Attribute: **NISCOPE\_ATTR\_EQUALIZATION\_NUM\_COEFFICIENTS**

## exported\_advance\_trigger\_output\_terminal

### `niscope.Session.exported_advance_trigger_output_terminal`

Specifies the destination to export the advance trigger. When the advance trigger is received, the digitizer begins acquiring samples for the Nth record. Consult your device documentation for a specific list of valid destinations.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Advance Trigger:Output Terminal**
- C Attribute: **NISCOPE\_ATTR\_EXPORTED\_ADVANCE\_TRIGGER\_OUTPUT\_TERMINAL**

### `exported_ref_trigger_output_terminal`

`niscope.Session.exported_ref_trigger_output_terminal`

Specifies the destination export for the reference (stop) trigger. Consult your device documentation for a specific list of valid destinations.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Output Terminal**
  - C Attribute: **NISCOPE\_ATTR\_EXPORTED\_REF\_TRIGGER\_OUTPUT\_TERMINAL**
- 

### `exported_start_trigger_output_terminal`

`niscope.Session.exported_start_trigger_output_terminal`

Specifies the destination to export the Start trigger. When the start trigger is received, the digitizer begins acquiring samples. Consult your device documentation for a specific list of valid destinations.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Start Trigger (Acq. Arm):Output Terminal**
  - C Attribute: **NISCOPE\_ATTR\_EXPORTED\_START\_TRIGGER\_OUTPUT\_TERMINAL**
- 

### `flex_fir_antialias_filter_type`

`niscope.Session.flex_fir_antialias_filter_type`

The NI 5922 flexible-resolution digitizer uses an onboard FIR lowpass antialias filter. Use this property to select from several types of filters to achieve desired filtering characteristics.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify

a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].flex_fir_antialias_filter_type = var
var = session.channels[0,1].flex_fir_antialias_filter_type
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.FlexFIRAntialiasFilterType</code>
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Advanced:Flex FIR Antialias Filter Type**
- C Attribute: **NISCOPE\_ATTR\_FLEX\_FIR\_ANTIALIAS\_FILTER\_TYPE**

## fpga\_bitfile\_path

`niscope.Session.fpga_bitfile_path`

Gets the absolute file path to the bitfile loaded on the FPGA.

**Note:** Gets the absolute file path to the bitfile loaded on the FPGA.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Device:FPGA Bitfile Path**
- C Attribute: **NISCOPE\_ATTR\_FPGA\_BITFILE\_PATH**

## high\_pass\_filter\_frequency

`niscope.Session.high_pass_filter_frequency`

Specifies the frequency for the highpass filter in Hz. The device uses one of the valid values listed below. If an invalid value is specified, no coercion occurs. The default value is 0. **(PXIe-5164)**

**Valid Values:** 0 90 450 **Related topics:** [Digital Filtering](#)

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Advanced:High Pass Filter Frequency**
  - C Attribute: **NISCOPE\_ATTR\_HIGH\_PASS\_FILTER\_FREQUENCY**
- 

## horz\_enforce\_realtime

`niscope.Session.horz_enforce_realtime`

Indicates whether the digitizer enforces real-time measurements or allows equivalent-time measurements.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Enforce Realtime**
  - C Attribute: **NISCOPE\_ATTR\_HORZ\_ENFORCE\_REALTIME**
- 

## horz\_min\_num\_pts

`niscope.Session.horz_min_num_pts`

Specifies the minimum number of points you require in the waveform record for each channel. NI-SCOPE uses the value you specify to configure the record length that the digitizer uses for waveform acquisition. `niscope.Session.horz_record_length` returns the actual record length. Valid Values: 1 - available onboard memory

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Min Number of Points**
  - C Attribute: **NISCOPE\_ATTR\_HORZ\_MIN\_NUM\_PTS**
- 

## horz\_num\_records

`niscope.Session.horz_num_records`

Specifies the number of records to acquire. Can be used for multi-record acquisition and single-record acquisitions. Setting this to 1 indicates a single-record acquisition.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Number of Records**
  - C Attribute: **NISCOPE\_ATTR\_HORZ\_NUM\_RECORDS**
- 

## horz\_record\_length

`niscope.Session.horz_record_length`

Returns the actual number of points the digitizer acquires for each channel. The value is equal to or greater than the minimum number of points you specify with `niscope.Session.horz_min_num_pts`. Allocate a ViReal64 array of this size or greater to pass as the WaveformArray parameter of the Read and Fetch methods. This property is only valid after a call to the one of the Configure Horizontal methods.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Actual Record Length**
  - C Attribute: **NISCOPE\_ATTR\_HORZ\_RECORD\_LENGTH**
-

## horz\_record\_ref\_position

`niscope.Session.horz_record_ref_position`

Specifies the position of the Reference Event in the waveform record. When the digitizer detects a trigger, it waits the length of time the `niscope.Session.trigger_delay_time` property specifies. The event that occurs when the delay time elapses is the Reference Event. The Reference Event is relative to the start of the record and is a percentage of the record length. For example, the value 50.0 corresponds to the center of the waveform record and 0.0 corresponds to the first element in the waveform record. Valid Values: 0.0 - 100.0

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Reference Position**
  - C Attribute: **NISCOPE\_ATTR\_HORZ\_RECORD\_REF\_POSITION**
- 

## horz\_sample\_rate

`niscope.Session.horz_sample_rate`

Returns the effective sample rate using the current configuration. The units are samples per second. This property is only valid after a call to the one of the Configure Horizontal methods. Units: Hertz (Samples / Second)

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Actual Sample Rate**
  - C Attribute: **NISCOPE\_ATTR\_HORZ\_SAMPLE\_RATE**
- 

## horz\_time\_per\_record

`niscope.Session.horz_time_per_record`

Specifies the length of time that corresponds to the record length. Units: Seconds



The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Advanced:Time Per Record**
  - C Attribute: **NISCOPE\_ATTR\_HORZ\_TIME\_PER\_RECORD**
- 

## input\_clock\_source

`niscope.Session.input_clock_source`

Specifies the input source for the PLL reference clock (the 1 MHz to 20 MHz clock on the NI 5122, the 10 MHz clock for the NI 5112/5620/5621/5911) to which the digitizer will be phase-locked; for the NI 5102, this is the source of the board clock.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:Reference (Input) Clock Source**
  - C Attribute: **NISCOPE\_ATTR\_INPUT\_CLOCK\_SOURCE**
- 

## input\_impedance

`niscope.Session.input_impedance`

Specifies the input impedance for the channel in Ohms.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].input_impedance = var
var = session.channels[0,1].input_impedance
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Input Impedance**
  - C Attribute: **NISCOPE\_ATTR\_INPUT\_IMPEDANCE**
- 

## instrument\_firmware\_revision

`niscope.Session.instrument_firmware_revision`

A string that contains the firmware revision information for the instrument you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Firmware Revision**
  - C Attribute: **NISCOPE\_ATTR\_INSTRUMENT\_FIRMWARE\_REVISION**
- 

## instrument\_manufacturer

`niscope.Session.instrument_manufacturer`

A string that contains the name of the instrument manufacturer.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Manufacturer**
- C Attribute: **NISCOPE\_ATTR\_INSTRUMENT\_MANUFACTURER**

## instrument\_model

`niscope.Session.instrument_model`

A string that contains the model number of the current instrument.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Model**
- C Attribute: **NISCOPE\_ATTR\_INSTRUMENT\_MODEL**

## interleaving\_offset\_correction\_enabled

`niscope.Session.interleaving_offset_correction_enabled`

Enables the interleaving offset correction on the specified channel. The default value is TRUE.

**Related topics:** [Timed Interleaved Sampling](#)

**Note:** If disabled, warranted specifications are not guaranteed.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Advanced:Interleaving Offset Correction Enabled**
- C Attribute: **NISCOPE\_ATTR\_INTERLEAVING\_OFFSET\_CORRECTION\_ENABLED**

## io\_resource\_descriptor

### `niscope.Session.io_resource_descriptor`

Indicates the resource descriptor the driver uses to identify the physical device. If you initialize the driver with a logical name, this property contains the resource descriptor that corresponds to the entry in the IVI Configuration utility. If you initialize the instrument driver with the resource descriptor, this property contains that value. You can pass a logical name to `niscope.Session.Init()` or `niscope.Session.__init__()`. The IVI Configuration utility must contain an entry for the logical name. The logical name entry refers to a virtual instrument section in the IVI Configuration file. The virtual instrument section specifies a physical device and initial user options.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:Resource Descriptor**
  - C Attribute: **NISCOPE\_ATTR\_IO\_RESOURCE\_DESCRIPTOR**
- 

## logical\_name

### `niscope.Session.logical_name`

A string containing the logical name you specified when opening the current IVI session. You can pass a logical name to `niscope.Session.Init()` or `niscope.Session.__init__()`. The IVI Configuration utility must contain an entry for the logical name. The logical name entry refers to a virtual instrument section in the IVI Configuration file. The virtual instrument section specifies a physical device and initial user options.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:Logical Name**
- C Attribute: **NISCOPE\_ATTR\_LOGICAL\_NAME**

## master\_enable

`niscope.Session.master_enable`

Specifies whether you want the device to be a master or a slave. The master typically originates the trigger signal and clock sync pulse. For a standalone device, set this property to False.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Master Enable**
- C Attribute: **NISCOPE\_ATTR\_MASTER\_ENABLE**

## max\_input\_frequency

`niscope.Session.max_input_frequency`

Specifies the bandwidth of the channel. Express this value as the frequency at which the input circuitry attenuates the input signal by 3 dB. The units are hertz. Defined Values: NISCOPE\_VAL\_BANDWIDTH\_FULL (-1.0) NISCOPE\_VAL\_BANDWIDTH\_DEVICE\_DEFAULT (0.0) NISCOPE\_VAL\_20MHZ\_BANDWIDTH (20000000.0) NISCOPE\_VAL\_100MHZ\_BANDWIDTH (100000000.0) NISCOPE\_VAL\_20MHZ\_MAX\_INPUT\_FREQUENCY (20000000.0) NISCOPE\_VAL\_100MHZ\_MAX\_INPUT\_FREQUENCY (100000000.0)

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].max_input_frequency = var
var = session.channels[0,1].max_input_frequency
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Maximum Input Frequency**
  - C Attribute: **NISCOPE\_ATTR\_MAX\_INPUT\_FREQUENCY**
- 

### **max\_real\_time\_sampling\_rate**

`niscope.Session.max_real_time_sampling_rate`

Returns the maximum real time sample rate in Hz.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Maximum Real Time Sample Rate**
  - C Attribute: **NISCOPE\_ATTR\_MAX\_REAL\_TIME\_SAMPLING\_RATE**
- 

### **max\_ris\_rate**

`niscope.Session.max_ris_rate`

Returns the maximum sample rate in RIS mode in Hz.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Maximum RIS Rate**
- C Attribute: **NISCOPE\_ATTR\_MAX\_RIS\_RATE**

## min\_sample\_rate

`niscope.Session.min_sample_rate`

Specify the sampling rate for the acquisition in Samples per second. Valid Values: The combination of sampling rate and min record length must allow the digitizer to sample at a valid sampling rate for the acquisition type specified in `niscope.Session.ConfigureAcquisition()` and not require more memory than the onboard memory module allows.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	Yes

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Min Sample Rate**
  - C Attribute: **NISCOPE\_ATTR\_MIN\_SAMPLE\_RATE**
- 

## onboard\_memory\_size

`niscope.Session.onboard_memory_size`

Returns the total combined amount of onboard memory for all channels in bytes.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Memory Size**
  - C Attribute: **NISCOPE\_ATTR\_ONBOARD\_MEMORY\_SIZE**
-

## output\_clock\_source

`niscope.Session.output_clock_source`

Specifies the output source for the 10 MHz clock to which another digitizer's sample clock can be phased-locked.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:Output Clock Source**
  - C Attribute: **NISCOPE\_ATTR\_OUTPUT\_CLOCK\_SOURCE**
- 

## pll\_lock\_status

`niscope.Session.pll_lock_status`

If TRUE, the PLL has remained locked to the external reference clock since it was last checked. If FALSE, the PLL has become unlocked from the external reference clock since it was last checked.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:PLL Lock Status**
  - C Attribute: **NISCOPE\_ATTR\_PLL\_LOCK\_STATUS**
- 

## points\_done

`niscope.Session.points_done`

Actual number of samples acquired in the record specified by `niscope.Session.fetch_record_number` from the `niscope.Session.fetch_relative_to` and `niscope.Session.fetch_offset` properties.

The following table lists the characteristics of this property.



Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Fetch:Points Done**
  - C Attribute: **NISCOPE\_ATTR\_POINTS\_DONE**
- 

## poll\_interval

`niscope.Session.poll_interval`

Specifies the poll interval in milliseconds to use during RIS acquisitions to check whether the acquisition is complete.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	0
Resettable	0

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NISCOPE\_ATTR\_POLL\_INTERVAL**
- 

## probe\_attenuation

`niscope.Session.probe_attenuation`

Specifies the probe attenuation for the input channel. For example, for a 10:1 probe, set this property to 10.0. Valid Values: Any positive real number. Typical values are 1, 10, and 100.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].probe_attenuation = var
var = session.channels[0,1].probe_attenuation
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Probe Attenuation**
  - C Attribute: **NISCOPE\_ATTR\_PROBE\_ATTENUATION**
- 

### **ready\_for\_advance\_event\_output\_terminal**

`niscope.Session.ready_for_advance_event_output_terminal`

Specifies the destination for the Ready for Advance Event. When this event is asserted, the digitizer is ready to receive an advance trigger. Consult your device documentation for a specific list of valid destinations.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Ready for Advance:Output Terminal**
  - C Attribute: **NISCOPE\_ATTR\_READY\_FOR\_ADVANCE\_EVENT\_OUTPUT\_TERMINAL**
- 

### **ready\_for\_ref\_event\_output\_terminal**

`niscope.Session.ready_for_ref_event_output_terminal`

Specifies the destination for the Ready for Reference Event. When this event is asserted, the digitizer is ready to receive a reference trigger. Consult your device documentation for a specific list of valid destinations.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Ready for Reference:Output Terminal**
  - C Attribute: **NISCOPE\_ATTR\_READY\_FOR\_REF\_EVENT\_OUTPUT\_TERMINAL**
- 

## ready\_for\_start\_event\_output\_terminal

`niscope.Session.ready_for_start_event_output_terminal`

Specifies the destination for the Ready for Start Event. When this event is asserted, the digitizer is ready to receive a start trigger. Consult your device documentation for a specific list of valid destinations.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Ready for Start:Output Terminal**
  - C Attribute: **NISCOPE\_ATTR\_READY\_FOR\_START\_EVENT\_OUTPUT\_TERMINAL**
- 

## records\_done

`niscope.Session.records_done`

Specifies the number of records that have been completely acquired.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Fetch:Records Done**
  - C Attribute: **NISCOPE\_ATTR\_RECORDS\_DONE**
-

## record\_arm\_source

`niscope.Session.record_arm_source`

Specifies the record arm source.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Synchronization:Record Arm Source**
  - C Attribute: **NISCOPE\_ATTR\_RECORD\_ARM\_SOURCE**
- 

## ref\_clk\_rate

`niscope.Session.ref_clk_rate`

If `niscope.Session.input_clock_source` is an external source, this property specifies the frequency of the input, or reference clock, to which the internal sample clock timebase is synchronized. The frequency is in hertz.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:Reference Clock Rate**
  - C Attribute: **NISCOPE\_ATTR\_REF\_CLK\_RATE**
- 

## ref\_trigger\_detector\_location

`niscope.Session.ref_trigger_detector_location`

Indicates which analog compare circuitry to use on the device.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.RefTriggerDetectorLocation
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Onboard Signal Processing:Ref Trigger Detection Location**
  - C Attribute: **NISCOPE\_ATTR\_REF\_TRIGGER\_DETECTOR\_LOCATION**
- 

## ref\_trigger\_minimum\_quiet\_time

`niscope.Session.ref_trigger_minimum_quiet_time`

The amount of time the trigger circuit must not detect a signal above the trigger level before the trigger is armed. This property is useful for triggering at the beginning and not in the middle of signal bursts.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Onboard Signal Processing:Ref Trigger Min Quiet Time**
  - C Attribute: **NISCOPE\_ATTR\_REF\_TRIGGER\_MINIMUM\_QUIET\_TIME**
- 

## ref\_trig\_tdc\_enable

`niscope.Session.ref_trig_tdc_enable`

This property controls whether the TDC is used to compute an accurate trigger.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:Advanced:Enable TDC**
  - C Attribute: **NISCOPE\_ATTR\_REF\_TRIG\_TDC\_ENABLE**
- 

## resolution

`niscope.Session.resolution`

Indicates the bit width of valid data (as opposed to padding bits) in the acquired waveform. Compare to `niscope.Session.binary_sample_width`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Acquisition:Resolution**
  - C Attribute: **NISCOPE\_ATTR\_RESOLUTION**
- 

## ris\_in\_auto\_setup\_enable

`niscope.Session.ris_in_auto_setup_enable`

Indicates whether the digitizer should use RIS sample rates when searching for a frequency in autosetup. Valid Values: True (1) - Use RIS sample rates in autosetup False (0) - Do not use RIS sample rates in autosetup

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Acquisition:Advanced:Enable RIS in Auto Setup**
  - C Attribute: **NISCOPE\_ATTR\_RIS\_IN\_AUTO\_SETUP\_ENABLE**
-

## ris\_method

`niscope.Session.ris_method`

Specifies the algorithm for random-interleaved sampling, which is used if the sample rate exceeds the value of `niscope.Session.max_real_time_sampling_rate`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.RISMethod
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:RIS Method**
- C Attribute: **NISCOPE\_ATTR\_RIS\_METHOD**

## ris\_num\_averages

`niscope.Session.ris_num_averages`

The number of averages for each bin in an RIS acquisition. The number of averages times the oversampling factor is the minimum number of real-time acquisitions necessary to reconstruct the RIS waveform. Averaging is useful in RIS because the trigger times are not evenly spaced, so adjacent points in the reconstructed waveform not be accurately spaced. By averaging, the errors in both time and voltage are smoothed.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Horizontal:RIS Num Avg**
- C Attribute: **NISCOPE\_ATTR\_RIS\_NUM\_AVERAGES**

## sample\_clock\_timebase\_multiplier

`niscope.Session.sample_clock_timebase_multiplier`

If *Sample Clock Timebase Source* `<p:py:meth:'niscope.Session.SampleClockTimebaseSource.html'>__` is an external source, this property specifies the ratio between the *Sample Clock Timebase Rate* `<p:py:meth:'niscope.Session.SampleClockTimebaseRate.html'>__` and the actual sample rate,

which can be higher. This property can be used in conjunction with the *Sample Clock Timebase Divisor* Property [<p:py:meth:'niscope.Session.SampleClockTimebaseDivisor.html'>\\_\\_](mailto:niscope.Session.SampleClockTimebaseDivisor.html). Some devices use multiple ADCs to sample the same channel at an effective sample rate that is greater than the specified clock rate. When providing an external sample clock use this property to indicate when you want a higher sample rate. Valid values for this property vary by device and current configuration. **Related topics:** [Sample Clock](#)

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:Sample Clock Timebase Multiplier**
  - C Attribute: **NISCOPE\_ATTR\_SAMPLE\_CLOCK\_TIMEBASE\_MULTIPLIER**
- 

## sample\_mode

`niscope.Session.sample_mode`

Indicates the sample mode the digitizer is currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Acquisition:Sample Mode**
  - C Attribute: **NISCOPE\_ATTR\_SAMPLE\_MODE**
- 

## samp\_clk\_timebase\_div

`niscope.Session.samp_clk_timebase_div`

If `niscope.Session.samp_clk_timebase_src` is an external source, specifies the ratio between the sample clock timebase rate and the actual sample rate, which can be slower.

The following table lists the characteristics of this property.



Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:Sample Clock Timebase Divisor**
  - C Attribute: **NISCOPE\_ATTR\_SAMP\_CLK\_TIMEBASE\_DIV**
- 

### samp\_clk\_timebase\_rate

`niscope.Session.samp_clk_timebase_rate`

If `niscope.Session.samp_clk_timebase_src` is an external source, specifies the frequency in hertz of the external clock used as the timebase source.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:Sample Clock Timebase Rate**
  - C Attribute: **NISCOPE\_ATTR\_SAMP\_CLK\_TIMEBASE\_RATE**
- 

### samp\_clk\_timebase\_src

`niscope.Session.samp_clk_timebase_src`

Specifies the source of the sample clock timebase, which is the timebase used to control waveform sampling. The actual sample rate may be the timebase itself or a divided version of the timebase, depending on the `niscope.Session.min_sample_rate` (for internal sources) or the `niscope.Session.samp_clk_timebase_div` (for external sources).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Clocking:Sample Clock Timebase Source**
  - C Attribute: **NISCOPE\_ATTR\_SAMP\_CLK\_TIMEBASE\_SRC**
- 

## serial\_number

`niscope.Session.serial_number`

Returns the serial number of the device.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Device:Serial Number**
  - C Attribute: **NISCOPE\_ATTR\_SERIAL\_NUMBER**
- 

## simulate

`niscope.Session.simulate`

Specifies whether or not to simulate instrument driver I/O operations. If simulation is enabled, instrument driver methods perform range checking and call `Ivi_GetAttribute` and `Ivi_SetAttribute` methods, but they do not perform instrument I/O. For output parameters that represent instrument data, the instrument driver methods return calculated values. The default value is False. Use the `niscope.Session.__init__()` method to override this value.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:User Options:Simulate**
  - C Attribute: **NISCOPE\_ATTR\_SIMULATE**
-

## specific\_driver\_description

`niscope.Session.specific_driver_description`

A string that contains a brief description of the specific driver

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Description**
  - C Attribute: **NISCOPE\_ATTR\_SPECIFIC\_DRIVER\_DESCRIPTION**
- 

## specific\_driver\_revision

`niscope.Session.specific_driver_revision`

A string that contains additional version information about this instrument driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Revision**
  - C Attribute: **NISCOPE\_ATTR\_SPECIFIC\_DRIVER\_REVISION**
- 

## specific\_driver\_vendor

`niscope.Session.specific_driver_vendor`

A string that contains the name of the vendor that supplies this driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Driver Vendor**
  - C Attribute: **NISCOPE\_ATTR\_SPECIFIC\_DRIVER\_VENDOR**
- 

## start\_to\_ref\_trigger\_holdoff

`niscope.Session.start_to_ref_trigger_holdoff`

Pass the length of time you want the digitizer to wait after it starts acquiring data until the digitizer enables the trigger system to detect a reference (stop) trigger. Units: Seconds Valid Values: 0.0 - 171.8

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].start_to_ref_trigger_holdoff = var
var = session.channels[0,1].start_to_ref_trigger_holdoff
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Start To Ref Trigger Holdoff**
  - C Attribute: **NISCOPE\_ATTR\_START\_TO\_REF\_TRIGGER\_HOLDOFF**
- 

## supported\_instrument\_models

`niscope.Session.supported_instrument_models`

A string that contains a comma-separated list of the instrument model numbers supported by this driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Capabilities:Supported Instrument Models**
  - C Attribute: **NISCOPE\_ATTR\_SUPPORTED\_INSTRUMENT\_MODELS**
- 

## trigger\_auto\_triggered

`niscope.Session.trigger_auto_triggered`

Specifies if the last acquisition was auto triggered. You can use the Auto Triggered property to find out if the last acquisition was triggered.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Auto Triggered**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_AUTO\_TRIGGERED**
- 

## trigger\_coupling

`niscope.Session.trigger_coupling`

Specifies how the digitizer couples the trigger source. This property affects instrument operation only when `niscope.Session.trigger_type` is set to `EDGE`, `HYSTERESIS`, or `WINDOW`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TriggerCoupling</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Coupling**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_COUPLING**
-

## trigger\_delay\_time

`niscope.Session.trigger_delay_time`

Specifies the trigger delay time in seconds. The trigger delay time is the length of time the digitizer waits after it receives the trigger. The event that occurs when the trigger delay elapses is the Reference Event. Valid Values: 0.0 - 171.8

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Delay**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_DELAY\_TIME**
- 

## trigger\_holdoff

`niscope.Session.trigger_holdoff`

Specifies the length of time (in seconds) the digitizer waits after detecting a trigger before enabling the trigger subsystem to detect another trigger. This property affects instrument operation only when the digitizer requires multiple acquisitions to build a complete waveform. The digitizer requires multiple waveform acquisitions when it uses equivalent-time sampling or when the digitizer is configured for a multi-record acquisition through a call to `niscope.Session.configure_horizontal_timing()`. Valid Values: 0.0 - 171.8

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Holdoff**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_HOLDOFF**
- 

## trigger\_hysteresis

`niscope.Session.trigger_hysteresis`

Specifies the size of the hysteresis window on either side of the trigger level. The digitizer triggers

when the trigger signal passes through the threshold you specify with the Trigger Level parameter, has the slope you specify with the Trigger Slope parameter, and passes through the hysteresis window that you specify with this parameter.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Hysteresis**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_HYSTERESIS**
- 

## trigger\_impedance

`niscope.Session.trigger_impedance`

Specifies the input impedance for the external analog trigger channel in Ohms. Valid Values: 50 - 50 ohms 1000000 - 1 mega ohm

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Impedance**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_IMPEDANCE**
- 

## trigger\_level

`niscope.Session.trigger_level`

Specifies the voltage threshold for the trigger subsystem. The units are volts. This property affects instrument behavior only when the `niscope.Session.trigger_type` is set to *EDGE*, *HYSTERESIS*, or *WINDOW*. Valid Values: The values of the range and offset parameters in `niscope.Session.configure_vertical()` determine the valid range for the trigger level on the channel you use as the Trigger Source. The value you pass for this parameter must meet the following conditions:

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Level**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_LEVEL**
- 

## trigger\_modifier

`niscope.Session.trigger_modifier`

Configures the device to automatically complete an acquisition if a trigger has not been received. Valid Values: None (1) - Normal triggering Auto Trigger (2) - Auto trigger acquisition if no trigger arrives

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.TriggerModifier
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Modifier**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_MODIFIER**
- 

## trigger\_slope

`niscope.Session.trigger_slope`

Specifies if a rising or a falling edge triggers the digitizer. This property affects instrument operation only when `niscope.Session.trigger_type` is set to *EDGE*, *HYSTERESIS*, or *WINDOW*.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.TriggerSlope
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:



- LabVIEW Property: **Triggering:Trigger Slope**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_SLOPE**
- 

## trigger\_source

`niscope.Session.trigger_source`

Specifies the source the digitizer monitors for the trigger event.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Source**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_SOURCE**
- 

## trigger\_type

`niscope.Session.trigger_type`

Specifies the type of trigger to use.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TriggerType</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Type**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_TYPE**
- 

## trigger\_window\_high\_level

`niscope.Session.trigger_window_high_level`

Pass the upper voltage threshold you want the digitizer to use for window triggering.

The digitizer triggers when the trigger signal enters or leaves the window you specify with `niscope.Session.trigger_window_low_level` and `niscope.Session.trigger_window_high_level`. Valid Values: The values of the Vertical Range and Vertical Offset parameters in `niscope.Session.configure_vertical()` determine the valid range for the High Window Level on the channel you use as the Trigger Source parameter in `niscope.Session.ConfigureTriggerSource()`. The value you pass for this parameter must meet the following conditions. High Trigger Level  $\leq$  Vertical Range/2 + Vertical Offset High Trigger Level  $\geq$  (-Vertical Range/2) + Vertical Offset High Trigger Level > Low Trigger Level

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Window:High Level**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_WINDOW\_HIGH\_LEVEL**
- 

## trigger\_window\_low\_level

`niscope.Session.trigger_window_low_level`

Pass the lower voltage threshold you want the digitizer to use for window triggering. The digitizer triggers when the trigger signal enters or leaves the window you specify with `niscope.Session.trigger_window_low_level` and `niscope.Session.trigger_window_high_level`. Units: Volts Valid Values: The values of the Vertical Range and Vertical Offset parameters in `niscope.Session.configure_vertical()` determine the valid range for the Low Window Level on the channel you use as the Trigger Source parameter in `niscope.Session.ConfigureTriggerSource()`. The value you pass for this parameter must meet the following conditions. Low Trigger Level  $\leq$  Vertical Range/2 + Vertical Offset Low Trigger Level  $\geq$  (-Vertical Range/2) + Vertical Offset Low Trigger Level < High Trigger Level

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Window:Low Level**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_WINDOW\_LOW\_LEVEL**
- 

## trigger\_window\_mode

`niscope.Session.trigger_window_mode`

Specifies whether you want a trigger to occur when the signal enters or leaves the window specified by `niscope.Session.trigger_window_low_level`, or `niscope.Session.trigger_window_high_level`.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TriggerWindowMode</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Window:Window Mode**
  - C Attribute: **NISCOPE\_ATTR\_TRIGGER\_WINDOW\_MODE**
- 

## tv\_trigger\_event

`niscope.Session.tv_trigger_event`

Specifies the condition in the video signal that causes the digitizer to trigger.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.VideoTriggerEvent</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Video:Event**
  - C Attribute: **NISCOPE\_ATTR\_TV\_TRIGGER\_EVENT**
-

## tv\_trigger\_line\_number

`niscope.Session.tv_trigger_line_number`

Specifies the line on which to trigger, if `niscope.Session.tv_trigger_event` is set to line number. The valid ranges of the property depend on the signal format selected. M-NTSC has a valid range of 1 to 525. B/G-PAL, SECAM, 576i, and 576p have a valid range of 1 to 625. 720p has a valid range of 1 to 750. 1080i and 1080p have a valid range of 1 to 1125.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Video:Line Number**
  - C Attribute: **NISCOPE\_ATTR\_TV\_TRIGGER\_LINE\_NUMBER**
- 

## tv\_trigger\_polarity

`niscope.Session.tv_trigger_polarity`

Specifies whether the video signal sync is positive or negative.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.VideoPolarity
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Video:Polarity**
  - C Attribute: **NISCOPE\_ATTR\_TV\_TRIGGER\_POLARITY**
- 

## tv\_trigger\_signal\_format

`niscope.Session.tv_trigger_signal_format`

Specifies the type of video signal, such as NTSC, PAL, or SECAM.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify

a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].tv_trigger_signal_format = var
var = session.channels[0,1].tv_trigger_signal_format
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.VideoSignalFormat</code>
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Triggering:Trigger Video:Signal Format**
- C Attribute: **NISCOPE\_ATTR\_TV\_TRIGGER\_SIGNAL\_FORMAT**

## vertical\_coupling

### `niscope.Session.vertical_coupling`

Specifies how the digitizer couples the input signal for the channel. When input coupling changes, the input stage takes a finite amount of time to settle.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the `set/get` will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
session.channels[0,1].vertical_coupling = var
var = session.channels[0,1].vertical_coupling
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.VerticalCoupling</code>
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Vertical Coupling**
- C Attribute: **NISCOPE\_ATTR\_VERTICAL\_COUPLING**

## vertical\_offset

### `niscope.Session.vertical_offset`

Specifies the location of the center of the range. The value is with respect to ground and is in volts. For example, to acquire a sine wave that spans between 0.0 and 10.0 V, set this property to 5.0 V.

**Note:** This property is not supported by all digitizers. Refer to the NI High-Speed Digitizers Help for a list of vertical offsets supported for each device.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].vertical_offset = var
var = session.channels[0,1].vertical_offset
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Vertical Offset**
- C Attribute: **NISCOPE\_ATTR\_VERTICAL\_OFFSET**

## vertical\_range

### `niscope.Session.vertical_range`

Specifies the absolute value of the input range for a channel in volts. For example, to acquire a sine wave that spans between -5 and +5 V, set this property to 10.0 V. Refer to the NI High-Speed Digitizers Help for a list of supported vertical ranges for each device. If the specified range is not supported by a device, the value is coerced up to the next valid range.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niscope.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].vertical_range = var
var = session.channels[0,1].vertical_range
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Vertical:Vertical Range**
- C Attribute: **NISCOPE\_ATTR\_VERTICAL\_RANGE**

## Methods

### abort

`niscope.Session.abort()`

Aborts an acquisition and returns the digitizer to the Idle state. Call this method if the digitizer times out waiting for a trigger.

### acquisition\_status

`niscope.Session.acquisition_status()`

Returns status information about the acquisition to the **status** output parameter.

**Return type** `niscope.AcquisitionStatus`

#### Returns

Returns whether the acquisition is complete, in progress, or unknown.

#### Defined Values

`COMPLETE`

`IN_PROGRESS`

`STATUS_UNKNOWN`

### auto\_setup

`niscope.Session.auto_setup()`

Automatically configures the instrument. When you call this method, the digitizer senses the input signal and automatically configures many of the instrument settings. If a signal is detected on a channel, the driver chooses the smallest available vertical range that is larger than the signal range. For example, if the signal is a 1.2 V<sub>pk-pk</sub> sine wave, and the device supports 1 V and 2 V vertical ranges, the driver will choose the 2 V vertical range for that channel.

If no signal is found on any analog input channel, a warning is returned, and all channels are enabled. A channel is considered to have a signal present if the signal is at least 10% of the smallest vertical range available for that channel.

The following settings are changed:

<b>General</b>	
Acquisition mode	Normal
Reference clock	Internal
<b>Vertical</b>	
Vertical coupling	AC (DC for NI 5621)
Vertical bandwidth	Full
Vertical range	Changed by auto setup
Vertical offset	0 V
Probe attenuation	Unchanged by auto setup
Input impedance	Unchanged by auto setup
<b>Horizontal</b>	
Sample rate	Changed by auto setup
Min record length	Changed by auto setup
Enforce realtime	True
Number of Records	Changed to 1
<b>Triggering</b>	
Trigger type	Edge if signal present, otherwise immediate
Trigger channel	Lowest numbered channel with a signal present
Trigger slope	Positive
Trigger coupling	DC
Reference position	50%
Trigger level	50% of signal on trigger channel
Trigger delay	0
Trigger holdoff	0
Trigger output	None

## commit

```
niscope.Session.commit()
```

Commits to hardware all the parameter settings associated with the task. Use this method if you want a parameter change to be immediately reflected in the hardware. This method is not supported for Traditional NI-DAQ (Legacy) devices.

## configure\_chan\_characteristics

```
niscope.Session.configure_chan_characteristics(input_impedance,  
                                              max_input_frequency)
```

Configures the properties that control the electrical characteristics of the channel—the input impedance and the bandwidth.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `niscope.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling this method on the result.:



```
session.channels[0,1].configure_chan_characteristics(input_impedance,
↳max_input_frequency)
```

### Parameters

- **input\_impedance** (*float*) – The input impedance for the channel; NI-SCOPE sets `niscope.Session.input_impedance` to this value.
- **max\_input\_frequency** (*float*) – The bandwidth for the channel; NI-SCOPE sets `niscope.Session.max_input_frequency` to this value. Pass 0 for this value to use the hardware default bandwidth. Pass -1 for this value to achieve full bandwidth.

## configure\_equalization\_filter\_coefficients

`niscope.Session.configure_equalization_filter_coefficients` (*coefficients*)

Configures the custom coefficients for the equalization FIR filter on the device. This filter is designed to compensate the input signal for artifacts introduced to the signal outside of the digitizer. Because this filter is a generic FIR filter, any coefficients are valid. Coefficient values should be between +1 and -1.

**Tip:** This method requires repeated capabilities (channels). If called directly on the `niscope.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].configure_equalization_filter_
↳coefficients(coefficients)
```

**Parameters** **coefficients** (*list of float*) – The custom coefficients for the equalization FIR filter on the device. These coefficients should be between +1 and -1. You can obtain the number of coefficients from the `:py:data:'niscope.Session.equalization_num_coefficients'` `<cvi:py:data:niscope.Session.equalization_num_coefficients.html>` property. The `:py:data:'niscope.Session.equalization_filter_enabled'` `<cvi:py:data:niscope.Session.equalization_filter_enabled.html>` property must be set to TRUE to enable the filter.

## configure\_horizontal\_timing

`niscope.Session.configure_horizontal_timing` (*min\_sample\_rate*, *min\_num\_pts*, *ref\_position*, *num\_records*, *enforce\_realtime*)

Configures the common properties of the horizontal subsystem for a multirecord acquisition in terms of minimum sample rate.

### Parameters

- **min\_sample\_rate** (*float*) – The sampling rate for the acquisition. Refer to `niscope.Session.min_sample_rate` for more information.

- **min\_num\_pts** (*int*) – The minimum number of points you need in the record for each channel; call `niscope.Session.ActualRecordLength()` to obtain the actual record length used.

Valid Values: Greater than 1; limited by available memory

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

- **ref\_position** (*float*) – The position of the Reference Event in the waveform record specified as a percentage.
- **num\_records** (*int*) – The number of records to acquire
- **enforce\_realtime** (*bool*) – Indicates whether the digitizer enforces real-time measurements or allows equivalent-time (RIS) measurements; not all digitizers support RIS—refer to [Features Supported by Device](#) for more information.

Default value: True

#### Defined Values

True—Allow real-time acquisitions only

False—Allow real-time and equivalent-time acquisitions

## configure\_trigger\_digital

```
niscope.Session.configure_trigger_digital(trigger_source,
                                         slope=niscope.TriggerSlope.POSITIVE,
                                         hold-
                                         off=datetime.timedelta(seconds=0.0),
                                         delay=datetime.timedelta(seconds=0.0))
```

Configures the common properties of a digital trigger.

When you initiate an acquisition, the digitizer waits for the start trigger, which is configured through the `niscope.Session.acq_arm_source` (Start Trigger Source) property. The default is immediate. Upon receiving the start trigger the digitizer begins sampling pretrigger points. After the digitizer finishes sampling pretrigger points, the digitizer waits for a reference (stop) trigger that you specify with a method such as this one. Upon receiving the reference trigger the digitizer finishes the acquisition after completing posttrigger sampling. With each Configure Trigger method, you specify configuration parameters such as the trigger source and the amount of trigger delay.

---

**Note:** For multirecord acquisitions, all records after the first record are started by using the Advance Trigger Source. The default is immediate.

You can adjust the amount of pre-trigger and post-trigger samples using the reference position parameter on the `niscope.Session.configure_horizontal_timing()` method. The default is half of the record length.

Some features are not supported by all digitizers. Refer to [Features Supported by Device](#) for more information.

Digital triggering is not supported in RIS mode.

---

#### Parameters

- **trigger\_source** (*str*) – Specifies the trigger source. Refer to `niscope.Session.trigger_source` for defined values.
- **slope** (`niscope.TriggerSlope`) – Specifies whether you want a rising edge or a falling edge to trigger the digitizer. Refer to `niscope.Session.trigger_slope` for more information.
- **holdoff** (*float in seconds or datetime.timedelta*) – The length of time the digitizer waits after detecting a trigger before enabling NI-SCOPE to detect another trigger. Refer to `niscope.Session.trigger_holdoff` for more information.
- **delay** (*float in seconds or datetime.timedelta*) – How long the digitizer waits after receiving the trigger to start acquiring data. Refer to `niscope.Session.trigger_delay_time` for more information.

### configure\_trigger\_edge

```
niscope.Session.configure_trigger_edge(trigger_source, level, trigger_coupling,  
                                       slope=niscope.TriggerSlope.POSITIVE,  
                                       holdoff=datetime.timedelta(seconds=0.0),  
                                       delay=datetime.timedelta(seconds=0.0))
```

Configures common properties for analog edge triggering.

When you initiate an acquisition, the digitizer waits for the start trigger, which is configured through the `niscope.Session.acq_arm_source` (Start Trigger Source) property. The default is immediate. Upon receiving the start trigger the digitizer begins sampling pretrigger points. After the digitizer finishes sampling pretrigger points, the digitizer waits for a reference (stop) trigger that you specify with a method such as this one. Upon receiving the reference trigger the digitizer finishes the acquisition after completing posttrigger sampling. With each Configure Trigger method, you specify configuration parameters such as the trigger source and the amount of trigger delay.

---

**Note:** Some features are not supported by all digitizers. Refer to [Features Supported by Device](#) for more information.

---

#### Parameters

- **trigger\_source** (*str*) – Specifies the trigger source. Refer to `niscope.Session.trigger_source` for defined values.
- **level** (*float*) – The voltage threshold for the trigger. Refer to `niscope.Session.trigger_level` for more information.
- **trigger\_coupling** (`niscope.TriggerCoupling`) – Applies coupling and filtering options to the trigger signal. Refer to `niscope.Session.trigger_coupling` for more information.
- **slope** (`niscope.TriggerSlope`) – Specifies whether you want a rising edge or a falling edge to trigger the digitizer. Refer to `niscope.Session.trigger_slope` for more information.
- **holdoff** (*float in seconds or datetime.timedelta*) – The length of time the digitizer waits after detecting a trigger before enabling NI-SCOPE to detect another trigger. Refer to `niscope.Session.trigger_holdoff` for more information.

- **delay** (*float in seconds or `datetime.timedelta`*) – How long the digitizer waits after receiving the trigger to start acquiring data. Refer to `niscope.Session.trigger_delay_time` for more information.

## configure\_trigger\_hysteresis

```
niscope.Session.configure_trigger_hysteresis(trigger_source, level, hys-  
teresis, trigger_coupling,  
slope=niscope.TriggerSlope.POSITIVE,  
hold-  
off=datetime.timedelta(seconds=0.0),  
de-  
lay=datetime.timedelta(seconds=0.0))
```

Configures common properties for analog hysteresis triggering. This kind of trigger specifies an additional value, specified in the **hysteresis** parameter, that a signal must pass through before a trigger can occur. This additional value acts as a kind of buffer zone that keeps noise from triggering an acquisition.

When you initiate an acquisition, the digitizer waits for the start trigger, which is configured through the `niscope.Session.acq_arm_source`. The default is immediate. Upon receiving the start trigger the digitizer begins sampling pretrigger points. After the digitizer finishes sampling pretrigger points, the digitizer waits for a reference (stop) trigger that you specify with a method such as this one. Upon receiving the reference trigger the digitizer finishes the acquisition after completing posttrigger sampling. With each Configure Trigger method, you specify configuration parameters such as the trigger source and the amount of trigger delay.

---

**Note:** Some features are not supported by all digitizers. Refer to [Features Supported by Device](#) for more information.

---

### Parameters

- **trigger\_source** (*str*) – Specifies the trigger source. Refer to `niscope.Session.trigger_source` for defined values.
- **level** (*float*) – The voltage threshold for the trigger. Refer to `niscope.Session.trigger_level` for more information.
- **hysteresis** (*float*) – The size of the hysteresis window on either side of the **level** in volts; the digitizer triggers when the trigger signal passes through the hysteresis value you specify with this parameter, has the slope you specify with **slope**, and passes through the **level**. Refer to `niscope.Session.trigger_hysteresis` for defined values.
- **trigger\_coupling** (*`niscope.TriggerCoupling`*) – Applies coupling and filtering options to the trigger signal. Refer to `niscope.Session.trigger_coupling` for more information.
- **slope** (*`niscope.TriggerSlope`*) – Specifies whether you want a rising edge or a falling edge to trigger the digitizer. Refer to `niscope.Session.trigger_slope` for more information.
- **holdoff** (*float in seconds or `datetime.timedelta`*) – The length of time the digitizer waits after detecting a trigger before enabling NI-SCOPE to detect another trigger. Refer to `niscope.Session.trigger_holdoff` for more information.

- **delay** (*float in seconds or `datetime.timedelta`*) – How long the digitizer waits after receiving the trigger to start acquiring data. Refer to `niscope.Session.trigger_delay_time` for more information.

### configure\_trigger\_immediate

```
niscope.Session.configure_trigger_immediate()
```

Configures common properties for immediate triggering. Immediate triggering means the digitizer triggers itself.

When you initiate an acquisition, the digitizer waits for a trigger. You specify the type of trigger that the digitizer waits for with a Configure Trigger method, such as `niscope.Session.configure_trigger_immediate()`.

### configure\_trigger\_software

```
niscope.Session.configure_trigger_software(holdoff=datetime.timedelta(seconds=0.0),
                                           de-
                                           lay=datetime.timedelta(seconds=0.0))
```

Configures common properties for software triggering.

When you initiate an acquisition, the digitizer waits for the start trigger, which is configured through the `niscope.Session.acq_arm_source` (Start Trigger Source) property. The default is immediate. Upon receiving the start trigger the digitizer begins sampling pretrigger points. After the digitizer finishes sampling pretrigger points, the digitizer waits for a reference (stop) trigger that you specify with a method such as this one. Upon receiving the reference trigger the digitizer finishes the acquisition after completing posttrigger sampling. With each Configure Trigger method, you specify configuration parameters such as the trigger source and the amount of trigger delay.

To trigger the acquisition, use `niscope.Session.send_software_trigger_edge()`.

---

**Note:** Some features are not supported by all digitizers. Refer to [Features Supported by Device](#) for more information.

---

#### Parameters

- **holdoff** (*float in seconds or `datetime.timedelta`*) – The length of time the digitizer waits after detecting a trigger before enabling NI-SCOPE to detect another trigger. Refer to `niscope.Session.trigger_holdoff` for more information.
- **delay** (*float in seconds or `datetime.timedelta`*) – How long the digitizer waits after receiving the trigger to start acquiring data. Refer to `niscope.Session.trigger_delay_time` for more information.

## configure\_trigger\_video

```
niscope.Session.configure_trigger_video(trigger_source,          signal_format,
                                       event, polarity, trigger_coupling,
                                       enable_dc_restore=False,
                                       line_number=1,             hold-
                                       off=datetime.timedelta(seconds=0.0),
                                       delay=datetime.timedelta(seconds=0.0))
```

Configures the common properties for video triggering, including the signal format, TV event, line number, polarity, and enable DC restore. A video trigger occurs when the digitizer finds a valid video signal sync.

When you initiate an acquisition, the digitizer waits for the start trigger, which is configured through the `niscope.Session.acq_arm_source` (Start Trigger Source) property. The default is immediate. Upon receiving the start trigger the digitizer begins sampling pretrigger points. After the digitizer finishes sampling pretrigger points, the digitizer waits for a reference (stop) trigger that you specify with a method such as this one. Upon receiving the reference trigger the digitizer finishes the acquisition after completing posttrigger sampling. With each Configure Trigger method, you specify configuration parameters such as the trigger source and the amount of trigger delay.

---

**Note:** Some features are not supported by all digitizers. Refer to [Features Supported by Device](#) for more information.

---

### Parameters

- **trigger\_source** (*str*) – Specifies the trigger source. Refer to `niscope.Session.trigger_source` for defined values.
- **signal\_format** (`niscope.VideoSignalFormat`) – Specifies the type of video signal sync the digitizer should look for. Refer to `niscope.Session.tv_trigger_signal_format` for more information.
- **event** (`niscope.VideoTriggerEvent`) – Specifies the TV event you want to trigger on. You can trigger on a specific or on the next coming line or field of the signal.
- **polarity** (`niscope.VideoPolarity`) – Specifies the polarity of the video signal sync.
- **trigger\_coupling** (`niscope.TriggerCoupling`) – Applies coupling and filtering options to the trigger signal. Refer to `niscope.Session.trigger_coupling` for more information.
- **enable\_dc\_restore** (*bool*) – Offsets each video line so the clamping level (the portion of the video line between the end of the color burst and the beginning of the active image) is moved to zero volt. Refer to `niscope.Session.enable_dc_restore` for defined values.
- **line\_number** (*int*) – Selects the line number to trigger on. The line number range covers an entire frame and is referenced as shown on [Vertical Blanking and Synchronization Signal](#). Refer to `niscope.Session.tv_trigger_line_number` for more information.

Default value: 1

- **holdoff** (*float in seconds or datetime.timedelta*) – The length of time the digitizer waits after detecting a trigger before enabling NI-SCOPE to

detect another trigger. Refer to `niscope.Session.trigger_holdoff` for more information.

- **delay** (*float in seconds or `datetime.timedelta`*) – How long the digitizer waits after receiving the trigger to start acquiring data. Refer to `niscope.Session.trigger_delay_time` for more information.

## configure\_trigger\_window

```
niscope.Session.configure_trigger_window(trigger_source, low_level,
                                         high_level,    window_mode,
                                         trigger_coupling, hold-
                                         off=datetime.timedelta(seconds=0.0),
                                         delay=datetime.timedelta(seconds=0.0))
```

Configures common properties for analog window triggering. A window trigger occurs when a signal enters or leaves a window you specify with the **high level** or **low level** parameters.

When you initiate an acquisition, the digitizer waits for the start trigger, which is configured through the `niscope.Session.acq_arm_source` (Start Trigger Source) property. The default is immediate. Upon receiving the start trigger the digitizer begins sampling pretrigger points. After the digitizer finishes sampling pretrigger points, the digitizer waits for a reference (stop) trigger that you specify with a method such as this one. Upon receiving the reference trigger the digitizer finishes the acquisition after completing posttrigger sampling. With each Configure Trigger method, you specify configuration parameters such as the trigger source and the amount of trigger delay.

To trigger the acquisition, use `niscope.Session.send_software_trigger_edge()`.

---

**Note:** Some features are not supported by all digitizers. Refer to [Features Supported by Device](#) for more information.

---

### Parameters

- **trigger\_source** (*str*) – Specifies the trigger source. Refer to `niscope.Session.trigger_source` for defined values.
- **low\_level** (*float*) – Passes the voltage threshold you want the digitizer to use for low triggering.
- **high\_level** (*float*) – Passes the voltage threshold you want the digitizer to use for high triggering.
- **window\_mode** (`niscope.TriggerWindowMode`) – Specifies whether you want the trigger to occur when the signal enters or leaves a window.
- **trigger\_coupling** (`niscope.TriggerCoupling`) – Applies coupling and filtering options to the trigger signal. Refer to `niscope.Session.trigger_coupling` for more information.
- **holdoff** (*float in seconds or `datetime.timedelta`*) – The length of time the digitizer waits after detecting a trigger before enabling NI-SCOPE to detect another trigger. Refer to `niscope.Session.trigger_holdoff` for more information.
- **delay** (*float in seconds or `datetime.timedelta`*) – How long the digitizer waits after receiving the trigger to start acquiring data. Refer to `niscope.Session.trigger_delay_time` for more information.

## configure\_vertical

```
niscope.Session.configure_vertical(range, coupling, offset=0.0,  
                                  probe_attenuation=1.0, enabled=True)
```

Configures the most commonly configured properties of the digitizer vertical subsystem, such as the range, offset, coupling, probe attenuation, and the channel.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `niscope.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].configure_vertical(range, coupling, offset=0.0,  
↪probe_attenuation=1.0, enabled=True)
```

---

### Parameters

- **range** (*float*) – Specifies the vertical range. Refer to `niscope.Session.vertical_range` for more information.
- **coupling** (`niscope.VerticalCoupling`) – Specifies how to couple the input signal. Refer to `niscope.Session.vertical_coupling` for more information.
- **offset** (*float*) – Specifies the vertical offset. Refer to `niscope.Session.vertical_offset` for more information.
- **probe\_attenuation** (*float*) – Specifies the probe attenuation. Refer to `niscope.Session.probe_attenuation` for valid values.
- **enabled** (*bool*) – Specifies whether the channel is enabled for acquisition. Refer to `niscope.Session.channel_enabled` for more information.

## disable

```
niscope.Session.disable()
```

Aborts any current operation, opens data channel relays, and releases RTSI and PFI lines.

## fetch

```
niscope.Session.fetch(num_samples=None, relative_to=niscope.FetchRelativeTo.PRETRIGGER,  
                      offset=0, record_number=0, num_records=None, time-  
                      out=datetime.timedelta(seconds=5.0))
```

Returns the waveform from a previously initiated acquisition that the digitizer acquires for the specified channel. This method returns scaled voltage waveforms.

This method may return multiple waveforms depending on the number of channels, the acquisition type, and the number of records you specify.

---

**Note:** Some functionality, such as time stamping, is not supported in all digitizers.

---



**Tip:** This method requires repeated capabilities (channels). If called directly on the `niscopesession.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscopesession.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].fetch(num_samples=None, relative_to=niscopesession.
    FetchRelativeTo.PRETRIGGER, offset=0, record_number=0, num_
    records=None, timeout=datetime.timedelta(seconds=5.0))
```

### Parameters

- **num\_samples** (*int*) – The maximum number of samples to fetch for each waveform. If the acquisition finishes with fewer points than requested, some devices return partial data if the acquisition finished, was aborted, or a timeout of 0 was used. If it fails to complete within the timeout period, the method raises.
- **relative\_to** (*niscopesession.FetchRelativeTo*) – Position to start fetching within one record.
- **offset** (*int*) – Offset in samples to start fetching data within each record. The offset can be positive or negative.
- **record\_number** (*int*) – Zero-based index of the first record to fetch.
- **num\_records** (*int*) – Number of records to fetch. Use -1 to fetch all configured records.
- **timeout** (*float or datetime.timedelta*) – The time to wait for data to be acquired; using 0 for this parameter tells NI-SCOPE to fetch whatever is currently available. Using -1 seconds for this parameter implies infinite timeout.

**Return type** list of `WaveformInfo`

### Returns

Returns an array of classes with the following timing and scaling information about each waveform:

- **relative\_initial\_x** (*float*) the time (in seconds) from the trigger to the first sample in the fetched waveform
- **absolute\_initial\_x** (*float*) timestamp (in seconds) of the first fetched sample. This timestamp is comparable between records and acquisitions; devices that do not support this parameter use 0 for this output.
- **x\_increment** (*float*) the time between points in the acquired waveform in seconds
- **channel** (*str*) channel name this waveform was asquire from
- **record** (*int*) record number of this waveform
- **gain** (*float*) the gain factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **offset** (*float*) the offset factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **samples** (array of float) floating point array of samples. Length will be of the actual samples acquired

## fetch\_into

```
niscope.Session.fetch_into (waveform, relative_to=niscope.FetchRelativeTo.PRETRIGGER,  
                             offset=0, record_number=0, num_records=None, time-  
                             out=datetime.timedelta(seconds=5.0))
```

Returns the waveform from a previously initiated acquisition that the digitizer acquires for the specified channel. This method returns scaled voltage waveforms.

This method may return multiple waveforms depending on the number of channels, the acquisition type, and the number of records you specify.

---

**Note:** Some functionality, such as time stamping, is not supported in all digitizers.

---

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `niscope.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].fetch(waveform, relative_to=niscope.  
    ↪FetchRelativeTo.PRETRIGGER, offset=0, record_number=0, num_  
    ↪records=None, timeout=datetime.timedelta(seconds=5.0))
```

---

## Parameters

- **waveform** (`array.array("d")`) – numpy array of the appropriate type and size the should be acquired as a 1D array. Size should be **num\_samples** times number of waveforms. Call `niscope.Session._actual_num_wfms()` to determine the number of waveforms.

Types supported are

- `numpy.float64`
- `numpy.int8`
- `numpy.in16`
- `numpy.int32`

Example:

```
waveform = numpy.ndarray(num_samples * session.actual_num_  
    ↪wfms(), dtype=numpy.float64)  
wfm_info = session['0,1'].fetch_into(num_samples, waveform, ↪  
    ↪timeout=5.0)
```

- **relative\_to** (`niscope.FetchRelativeTo`) – Position to start fetching within one record.

- **offset** (*int*) – Offset in samples to start fetching data within each record. The offset can be positive or negative.
- **record\_number** (*int*) – Zero-based index of the first record to fetch.
- **num\_records** (*int*) – Number of records to fetch. Use -1 to fetch all configured records.
- **timeout** (*float*) – The time to wait in seconds for data to be acquired; using 0 for this parameter tells NI-SCOPE to fetch whatever is currently available. Using -1 for this parameter implies infinite timeout.

**Return type** list of WaveformInfo

### Returns

Returns an array of classed with the following timing and scaling information about each waveform:

- **relative\_initial\_x** (float) the time (in seconds) from the trigger to the first sample in the fetched waveform
- **absolute\_initial\_x** (float) timestamp (in seconds) of the first fetched sample. This timestamp is comparable between records and acquisitions; devices that do not support this parameter use 0 for this output.
- **x\_increment** (float) the time between points in the acquired waveform in seconds
- **channel** (str) channel name this waveform was asquire from
- **record** (int) record number of this waveform
- **gain** (float) the gain factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **offset** (float) the offset factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **samples** (array of float) floating point array of samples. Length will be of the actual samples acquired

## get\_equalization\_filter\_coefficients

`niscope.Session.get_equalization_filter_coefficients()`

Retrieves the custom coefficients for the equalization FIR filter on the device. This filter is designed to compensate the input signal for artifacts introduced to the signal outside of the digitizer. Because this filter is a generic FIR filter, any coefficients are valid. Coefficient values should be between +1 and -1.

---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `niscope.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset

of repeated capabilities using the Python index notation on an `niscopes.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].get_equalization_filter_coefficients()
```

## lock

`niscopes.Session.lock()`

Obtains a multithread lock on the device session. Before doing so, the software waits until all other execution threads release their locks on the device session.

Other threads may have obtained a lock on this session for the following reasons:

- The application called the `niscopes.Session.lock()` method.
- A call to NI-SCOPE locked the session.
- After a call to the `niscopes.Session.lock()` method returns successfully, no other threads can access the device session until you call the `niscopes.Session.unlock()` method or exit out of the with block when using lock context manager.
- Use the `niscopes.Session.lock()` method and the `niscopes.Session.unlock()` method around a sequence of calls to instrument driver methods if you require that the device retain its settings through the end of the sequence.

You can safely make nested calls to the `niscopes.Session.lock()` method within the same thread. To completely unlock the session, you must balance each call to the `niscopes.Session.lock()` method with a call to the `niscopes.Session.unlock()` method.

One method for ensuring there are the same number of unlock method calls as there is lock calls is to use lock as a context manager

```
with niscopes.Session('dev1') as session:
    with session.lock():
        # Calls to session within a single lock context
```

The first `with` block ensures the session is closed regardless of any exceptions raised

The second `with` block ensures that `unlock` is called regardless of any exceptions raised

**Return type** context manager

**Returns** When used in a `with` statement, `niscopes.Session.lock()` acts as a context manager and `unlock` will be called when the `with` block is exited

## probe\_compensation\_signal\_start

`niscopes.Session.probe_compensation_signal_start()`

Starts the 1 kHz square wave output on PFI 1 for probe compensation.

## probe\_compensation\_signal\_stop

`niscopes.Session.probe_compensation_signal_stop()`

Stops the 1 kHz square wave output on PFI 1 for probe compensation.

## read

```
niscope.Session.read(num_samples=None, relative_to=niscope.FetchRelativeTo.PRETRIGGER,
                    offset=0, record_number=0, num_records=None, timeout=
                    datetime.timedelta(seconds=5.0))
```

Initiates an acquisition, waits for it to complete, and retrieves the data. The process is similar to calling `niscope.Session._initiate_acquisition()`, `niscope.Session.acquisition_status()`, and `niscope.Session.fetch()`. The only difference is that with `niscope.Session.read()`, you enable all channels specified with **channelList** before the acquisition; in the other method, you enable the channels with `niscope.Session.configure_vertical()`.

This method may return multiple waveforms depending on the number of channels, the acquisition type, and the number of records you specify.

---

**Note:** Some functionality, such as time stamping, is not supported in all digitizers.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `niscope.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling this method on the result.:

---

```
session.channels[0,1].read(num_samples=None, relative_to=niscope.
    ↪FetchRelativeTo.PRETRIGGER, offset=0, record_number=0, num_
    ↪records=None, timeout=datetime.timedelta(seconds=5.0))
```

---

### Parameters

- **num\_samples** (*int*) – The maximum number of samples to fetch for each waveform. If the acquisition finishes with fewer points than requested, some devices return partial data if the acquisition finished, was aborted, or a timeout of 0 was used. If it fails to complete within the timeout period, the method raises.
- **relative\_to** (*niscope.FetchRelativeTo*) – Position to start fetching within one record.
- **offset** (*int*) – Offset in samples to start fetching data within each record. The offset can be positive or negative.
- **record\_number** (*int*) – Zero-based index of the first record to fetch.
- **num\_records** (*int*) – Number of records to fetch. Use -1 to fetch all configured records.
- **timeout** (*float or datetime.timedelta*) – The time to wait for data to be acquired; using 0 for this parameter tells NI-SCOPE to fetch whatever is currently available. Using -1 seconds for this parameter implies infinite timeout.

**Return type** list of WaveformInfo

### Returns

Returns an array of classes with the following timing and scaling information about each waveform:

- **relative\_initial\_x** (float) the time (in seconds) from the trigger to the first sample in the fetched waveform
- **absolute\_initial\_x** (float) timestamp (in seconds) of the first fetched sample. This timestamp is comparable between records and acquisitions; devices that do not support this parameter use 0 for this output.
- **x\_increment** (float) the time between points in the acquired waveform in seconds
- **channel** (str) channel name this waveform was asquire from
- **record** (int) record number of this waveform
- **gain** (float) the gain factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **offset** (float) the offset factor of the given channel; useful for scaling binary data with the following formula:

$$voltage = binarydata * gainfactor + offset$$

- **samples** (array of float) floating point array of samples. Length will be of the actual samples acquired

## reset

```
niscope.Session.reset()
```

Stops the acquisition, releases routes, and all session properties are reset to their [default states](#).

## reset\_device

```
niscope.Session.reset_device()
```

Performs a hard reset of the device. Acquisition stops, all routes are released, RTSI and PFI lines are tristated, hardware is configured to its default state, and all session properties are reset to their default state.

- [Thermal Shutdown](#)

## reset\_with\_defaults

```
niscope.Session.reset_with_defaults()
```

Performs a software reset of the device, returning it to the default state and applying any initial default settings from the IVI Configuration Store.

## self\_cal

`niscope.Session.self_cal (option=niscope.Option.SELF_CALIBRATE_ALL_CHANNELS)`  
 Self-calibrates most NI digitizers, including all SMC-based devices and most Traditional NI-DAQ (Legacy) devices. To verify that your digitizer supports self-calibration, refer to [Features Supported by Device](#).

For SMC-based digitizers, if the self-calibration is performed successfully in a regular session, the calibration constants are immediately stored in the self-calibration area of the EEPROM. If the self-calibration is performed in an external calibration session, the calibration constants take effect immediately for the duration of the session. However, they are not stored in the EEPROM until `niscope.Session.CalEnd()` is called with **action** set to `NISCOPE_VAL_ACTION_STORE` and no errors occur.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---



---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---



---

**Tip:** This method requires repeated capabilities (channels). If called directly on the `niscope.Session` object, then the method will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niscope.Session` repeated capabilities container, and calling this method on the result.:

```
session.channels[0,1].self_cal(option=niscope.Option.SELF_CALIBRATE_ALL_CHANNELS)
```

---

**Parameters** `option` (`niscope.Option`) – The calibration option. Use `VI_NULL` for a normal self-calibration operation or `NISCOPE_VAL_CAL_RESTORE_EXTERNAL_CALIBRATION` to restore the previous calibration.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## self\_test

`niscope.Session.self_test()`  
 Runs the instrument self-test routine and returns the test result(s). Refer to the device-specific help topics for an explanation of the message contents.

Raises *SelfTestError* on self test failure. Properties on exception object:

- code - failure code from driver
- message - status message from driver

Self-Test Code	Description
0	Passed self-test
1	Self-test failed

## send\_software\_trigger\_edge

`niscope.Session.send_software_trigger_edge` (*which\_trigger*)

Sends the selected trigger to the digitizer. Call this method if you called `niscope.Session.configure_trigger_software()` when you want the Reference trigger to occur. You can also call this method to override a misused edge, digital, or hysteresis trigger. If you have configured `niscope.Session.acq_arm_source`, `niscope.Session.arm_ref_trig_src`, or `niscope.Session.adv_trig_src`, call this method when you want to send the corresponding trigger to the digitizer.

**Parameters** `which_trigger` (`niscope.WhichTrigger`) – Specifies the type of trigger to send to the digitizer.

### Defined Values

`START` (0L)

`ARM_REFERENCE` (1L)

`REFERENCE` (2L)

`ADVANCE` (3L)

## unlock

`niscope.Session.unlock()`

Releases a lock that you acquired on an device session using `niscope.Session.lock()`. Refer to `niscope.Session.unlock()` for additional information on session locks.

## Properties

Property	Datatype
<code>niscope.Session.absolute_sample_clock_offset</code>	float in seconds or datetime.timedelta
<code>niscope.Session.accessory_gain</code>	float
<code>niscope.Session.accessory_offset</code>	float
<code>niscope.Session.acquisition_start_time</code>	float in seconds or datetime.timedelta
<code>niscope.Session.acquisition_type</code>	AcquisitionType
<code>niscope.Session.acq_arm_source</code>	str
<code>niscope.Session.adv_trig_src</code>	str
<code>niscope.Session.allow_more_records_than_memory</code>	bool
<code>niscope.Session.arm_ref_trig_src</code>	str
<code>niscope.Session.backlog</code>	float
<code>niscope.Session.bandpass_filter_enabled</code>	bool
<code>niscope.Session.binary_sample_width</code>	int
<code>niscope.Session.channel_count</code>	int
<code>niscope.Session.channel_enabled</code>	bool

Continued on next page



Table 13 – continued from previous page

Property	Datatype
<code>niscope.Session.channel_terminal_configuration</code>	TerminalConfiguration
<code>niscope.Session.data_transfer_block_size</code>	int
<code>niscope.Session.data_transfer_maximum_bandwidth</code>	float
<code>niscope.Session.data_transfer_preferred_packet_size</code>	int
<code>niscope.Session.device_temperature</code>	float
<code>niscope.Session.driver_setup</code>	str
<code>niscope.Session.enable_dc_restore</code>	bool
<code>niscope.Session.enable_time_interleaved_sampling</code>	bool
<code>niscope.Session.end_of_acquisition_event_output_terminal</code>	str
<code>niscope.Session.end_of_record_event_output_terminal</code>	str
<code>niscope.Session.end_of_record_to_advance_trigger_holdoff</code>	float in seconds or datetime.timedelta
<code>niscope.Session.equalization_filter_enabled</code>	bool
<code>niscope.Session.equalization_num_coefficients</code>	int
<code>niscope.Session.exported_advance_trigger_output_terminal</code>	str
<code>niscope.Session.exported_ref_trigger_output_terminal</code>	str
<code>niscope.Session.exported_start_trigger_output_terminal</code>	str
<code>niscope.Session.flex_fir_antialias_filter_type</code>	FlexFIRAntialiasFilterType
<code>niscope.Session.fpga_bitfile_path</code>	str
<code>niscope.Session.high_pass_filter_frequency</code>	float
<code>niscope.Session.horz_enforce_realtime</code>	bool
<code>niscope.Session.horz_min_num_pts</code>	int
<code>niscope.Session.horz_num_records</code>	int
<code>niscope.Session.horz_record_length</code>	int
<code>niscope.Session.horz_record_ref_position</code>	float
<code>niscope.Session.horz_sample_rate</code>	float
<code>niscope.Session.horz_time_per_record</code>	float in seconds or datetime.timedelta
<code>niscope.Session.input_clock_source</code>	str
<code>niscope.Session.input_impedance</code>	float
<code>niscope.Session.instrument_firmware_revision</code>	str
<code>niscope.Session.instrument_manufacturer</code>	str
<code>niscope.Session.instrument_model</code>	str
<code>niscope.Session.interleaving_offset_correction_enabled</code>	bool
<code>niscope.Session.io_resource_descriptor</code>	str
<code>niscope.Session.logical_name</code>	str
<code>niscope.Session.master_enable</code>	bool
<code>niscope.Session.max_input_frequency</code>	float
<code>niscope.Session.max_real_time_sampling_rate</code>	float
<code>niscope.Session.max_ris_rate</code>	float
<code>niscope.Session.min_sample_rate</code>	float
<code>niscope.Session.onboard_memory_size</code>	int
<code>niscope.Session.output_clock_source</code>	str
<code>niscope.Session.pll_lock_status</code>	bool
<code>niscope.Session.points_done</code>	float
<code>niscope.Session.poll_interval</code>	int
<code>niscope.Session.probe_attenuation</code>	float
<code>niscope.Session.ready_for_advance_event_output_terminal</code>	str
<code>niscope.Session.ready_for_ref_event_output_terminal</code>	str
<code>niscope.Session.ready_for_start_event_output_terminal</code>	str
<code>niscope.Session.records_done</code>	int

Continued on next page

Table 13 – continued from previous page

Property	Datatype
<code>niscope.Session.record_arm_source</code>	str
<code>niscope.Session.ref_clk_rate</code>	float
<code>niscope.Session.ref_trigger_detector_location</code>	RefTriggerDetectorLocation
<code>niscope.Session.ref_trigger_minimum_quiet_time</code>	float in seconds or datetime.timedelta
<code>niscope.Session.ref_trig_tdc_enable</code>	bool
<code>niscope.Session.resolution</code>	int
<code>niscope.Session.ris_in_auto_setup_enable</code>	bool
<code>niscope.Session.ris_method</code>	RISMethod
<code>niscope.Session.ris_num_averages</code>	int
<code>niscope.Session.sample_clock_timebase_multiplier</code>	int
<code>niscope.Session.sample_mode</code>	int
<code>niscope.Session.samp_clk_timebase_div</code>	int
<code>niscope.Session.samp_clk_timebase_rate</code>	float
<code>niscope.Session.samp_clk_timebase_src</code>	str
<code>niscope.Session.serial_number</code>	str
<code>niscope.Session.simulate</code>	bool
<code>niscope.Session.specific_driver_description</code>	str
<code>niscope.Session.specific_driver_revision</code>	str
<code>niscope.Session.specific_driver_vendor</code>	str
<code>niscope.Session.start_to_ref_trigger_holdoff</code>	float in seconds or datetime.timedelta
<code>niscope.Session.supported_instrument_models</code>	str
<code>niscope.Session.trigger_auto_triggered</code>	bool
<code>niscope.Session.trigger_coupling</code>	TriggerCoupling
<code>niscope.Session.trigger_delay_time</code>	float in seconds or datetime.timedelta
<code>niscope.Session.trigger_holdoff</code>	float in seconds or datetime.timedelta
<code>niscope.Session.trigger_hysteresis</code>	float
<code>niscope.Session.trigger_impedance</code>	float
<code>niscope.Session.trigger_level</code>	float
<code>niscope.Session.trigger_modifier</code>	TriggerModifier
<code>niscope.Session.trigger_slope</code>	TriggerSlope
<code>niscope.Session.trigger_source</code>	str
<code>niscope.Session.trigger_type</code>	TriggerType
<code>niscope.Session.trigger_window_high_level</code>	float
<code>niscope.Session.trigger_window_low_level</code>	float
<code>niscope.Session.trigger_window_mode</code>	TriggerWindowMode
<code>niscope.Session.tv_trigger_event</code>	VideoTriggerEvent
<code>niscope.Session.tv_trigger_line_number</code>	int
<code>niscope.Session.tv_trigger_polarity</code>	VideoPolarity
<code>niscope.Session.tv_trigger_signal_format</code>	VideoSignalFormat
<code>niscope.Session.vertical_coupling</code>	VerticalCoupling
<code>niscope.Session.vertical_offset</code>	float
<code>niscope.Session.vertical_range</code>	float

## Methods

Method name
<code>niscope.Session.abort()</code>
<code>niscope.Session.acquisition_status()</code>

Continued on next page

Table 14 – continued from previous page

Method name
<i>niscope.Session.auto_setup()</i>
<i>niscope.Session.commit()</i>
<i>niscope.Session.configure_chan_characteristics()</i>
<i>niscope.Session.configure_equalization_filter_coefficients()</i>
<i>niscope.Session.configure_horizontal_timing()</i>
<i>niscope.Session.configure_trigger_digital()</i>
<i>niscope.Session.configure_trigger_edge()</i>
<i>niscope.Session.configure_trigger_hysteresis()</i>
<i>niscope.Session.configure_trigger_immediate()</i>
<i>niscope.Session.configure_trigger_software()</i>
<i>niscope.Session.configure_trigger_video()</i>
<i>niscope.Session.configure_trigger_window()</i>
<i>niscope.Session.configure_vertical()</i>
<i>niscope.Session.disable()</i>
<i>niscope.Session.fetch()</i>
<i>niscope.Session.fetch_into()</i>
<i>niscope.Session.get_equalization_filter_coefficients()</i>
<i>niscope.Session.lock()</i>
<i>niscope.Session.probe_compensation_signal_start()</i>
<i>niscope.Session.probe_compensation_signal_stop()</i>
<i>niscope.Session.read()</i>
<i>niscope.Session.reset()</i>
<i>niscope.Session.reset_device()</i>
<i>niscope.Session.reset_with_defaults()</i>
<i>niscope.Session.self_cal()</i>
<i>niscope.Session.self_test()</i>
<i>niscope.Session.send_software_trigger_edge()</i>
<i>niscope.Session.unlock()</i>

### 7.4.3.2 Enums

Enums used in NI-SCOPE

#### AcquisitionStatus

```
class niscope.AcquisitionStatus
```

```
    COMPLETE
```

```
    IN_PROGRESS
```

```
    STATUS_UNKNOWN
```

#### AcquisitionType

```
class niscope.AcquisitionType
```

**NORMAL**

Sets the digitizer to normal resolution mode. The digitizer can use real-time sampling or equivalent-time sampling.

**FLEXRES**

Sets the digitizer to flexible resolution mode if supported. The digitizer uses different hardware configurations to change the resolution depending on the sampling rate used.

**DDC**

Sets the digitizer to DDC mode on the NI 5620/5621.

## FetchRelativeTo

```
class niscopes.FetchRelativeTo
```

**READ\_POINTER**

The read pointer is set to zero when a new acquisition is initiated. After every fetch the read pointer is incremented to be the sample after the last sample retrieved. Therefore, you can repeatedly fetch relative to the read pointer for a continuous acquisition program.

**PRETRIGGER**

Fetches relative to the first pretrigger point requested with `niscopes.Session.configure_horizontal_timing()`.

**NOW**

Fetch data at the last sample acquired.

**START**

Fetch data starting at the first point sampled by the digitizer.

**TRIGGER**

Fetch at the first posttrigger sample.

## FlexFIRAntialiasFilterType

```
class niscopes.FlexFIRAntialiasFilterType
```

**FOURTYEIGHT\_TAP\_STANDARD**

This filter is optimized for alias protection and frequency-domain flatness

**FOURTYEIGHT\_TAP\_HANNING**

This filter is optimized for the lowest possible bandwidth for a 48 tap filter and maximizes the SNR

**SIXTEEN\_TAP\_HANNING**

This filter is optimized for the lowest possible bandwidth for a 16 tap filter and maximizes the SNR

**EIGHT\_TAP\_HANNING**

This filter is optimized for the lowest possible bandwidth for a 8 tap filter and maximizes the SNR

## Option

```
class niscopes.Option
```

**SELF\_CALIBRATE\_ALL\_CHANNELS**

Self Calibrating all Channels

**RESTORE\_EXTERNAL\_CALIBRATION**

Restore External Calibration.

## RISMethod

```
class niscopes.RISMethod
```

**EXACT\_NUM\_AVERAGES**

Acquires exactly the specified number of records for each bin in the RIS acquisition. An error is returned from the fetch method if the RIS acquisition does not successfully acquire the specified number of waveforms within the timeout period. You may call the fetch method again to allow more time for the acquisition to finish.

**MIN\_NUM\_AVERAGES**

Each RIS sample is the average of a least a minimum number of randomly distributed points.

**INCOMPLETE**

Returns the RIS waveform after the specified timeout even if it is incomplete. If no waveforms have been acquired in certain bins, these bins will have a NaN (when fetching scaled data) or a zero (when fetching binary data). A warning (positive error code) is returned from the fetch method if the RIS acquisition did not finish. The acquisition aborts when data is returned.

**LIMITED\_BIN\_WIDTH**

Limits the waveforms in the various bins to be within 200 ps of the center of the bin.

## RefTriggerDetectorLocation

```
class niscopes.RefTriggerDetectorLocation
```

**ANALOG\_DETECTION\_CIRCUIT**

use the hardware analog circuitry to implement the reference trigger. This option will trigger before any onboard signal processing.

**DDC\_OUTPUT**

use the onboard signal processing logic to implement the reference trigger. This option will trigger based on the onboard signal processed data.

## TerminalConfiguration

```
class niscopes.TerminalConfiguration
```

**SINGLE\_ENDED**

Channel is single ended

**UNBALANCED\_DIFFERENTIAL**

Channel is unbalanced differential

**DIFFERENTIAL**

Channel is differential

## TriggerCoupling

```
class niscopes.TriggerCoupling
```

**AC**  
AC coupling

**DC**  
DC coupling

**HF\_REJECT**  
Highpass filter coupling

**LF\_REJECT**  
Lowpass filter coupling

**AC\_PLUS\_HF\_REJECT**  
Highpass and lowpass filter coupling

## TriggerModifier

```
class niscopes.TriggerModifier
```

**NO\_TRIGGER\_MOD**  
Normal triggering.

**AUTO**  
Software will trigger an acquisition automatically if no trigger arrives after a certain amount of time.

## TriggerSlope

```
class niscopes.TriggerSlope
```

**NEGATIVE**  
Falling edge

**POSITIVE**  
Rising edge

## TriggerType

```
class niscopes.TriggerType
```

**EDGE**  
Configures the digitizer for edge triggering. An edge trigger occurs when the trigger signal crosses the trigger level specified with the set trigger slope. You configure the trigger level and slope with *niscopes.Session.configure\_trigger\_edge()*.

**TV**  
Configures the digitizer for video/TV triggering. You configure the video trigger parameters like signal Format, Line to trigger off of, Polarity, and Enable DC Restore with *niscopes.Session.configure\_trigger\_video()*.

**IMMEDIATE**

Configures the digitizer for immediate triggering. An immediate trigger occurs as soon as the pretrigger samples are acquired.

**HYSTERESIS**

Configures the digitizer for hysteresis triggering. A hysteresis trigger occurs when the trigger signal crosses the trigger level with the specified slope and passes through the hysteresis window you specify. You configure the trigger level, slope, and hysteresis with `niscope.Session.configure_trigger_hysteresis()`.

**DIGITAL**

Configures the digitizer for digital triggering. A digital trigger occurs when the trigger signal has the specified slope. You configure the trigger slope with `niscope.Session.configure_trigger_digital()`.

**WINDOW**

Configures the digitizer for window triggering. A window trigger occurs when the trigger signal enters or leaves the window defined by the values you specify with the Low Window Level, High Window Level, and Window Mode Parameters. You configure the low window level high window level, and window mode with `niscope.Session.configure_trigger_window()`.

**SOFTWARE**

Configures the digitizer for software triggering. A software trigger occurs when `niscope.Session.SendSoftwareTrigger()` is called.

**TriggerWindowMode**

```
class niscope.TriggerWindowMode
```

**ENTERING**

Trigger upon entering the window

**LEAVING**

Trigger upon leaving the window

**VerticalCoupling**

```
class niscope.VerticalCoupling
```

**AC**

AC coupling

**DC**

DC coupling

**GND**

GND coupling

**VideoPolarity**

```
class niscope.VideoPolarity
```

**POSITIVE**

Specifies that the video signal has positive polarity.

**NEGATIVE**

Specifies that the video signal has negative polarity.

## VideoSignalFormat

**class** nscope.VideoSignalFormat

**NTSC**

NTSC signal format supports line numbers from 1 to 525

**PAL**

PAL signal format supports line numbers from 1 to 625

**SECAM**

SECAM signal format supports line numbers from 1 to 625

**M\_PAL**

M-PAL signal format supports line numbers from 1 to 525

**VIDEO\_480I\_59\_94\_FIELDS\_PER\_SECOND**

480 lines, interlaced, 59.94 fields per second

**VIDEO\_480I\_60\_FIELDS\_PER\_SECOND**

480 lines, interlaced, 60 fields per second

**VIDEO\_480P\_59\_94\_FRAMES\_PER\_SECOND**

480 lines, progressive, 59.94 frames per second

**VIDEO\_480P\_60\_FRAMES\_PER\_SECOND**

480 lines, progressive, 60 frames per second

**VIDEO\_576I\_50\_FIELDS\_PER\_SECOND**

576 lines, interlaced, 50 fields per second

**VIDEO\_576P\_50\_FRAMES\_PER\_SECOND**

576 lines, progressive, 50 frames per second

**VIDEO\_720P\_50\_FRAMES\_PER\_SECOND**

720 lines, progressive, 50 frames per second

**VIDEO\_720P\_59\_94\_FRAMES\_PER\_SECOND**

720 lines, progressive, 59.94 frames per second

**VIDEO\_720P\_60\_FRAMES\_PER\_SECOND**

720 lines, progressive, 60 frames per second

**VIDEO\_1080I\_50\_FIELDS\_PER\_SECOND**

1,080 lines, interlaced, 50 fields per second

**VIDEO\_1080I\_59\_94\_FIELDS\_PER\_SECOND**

1,080 lines, interlaced, 59.94 fields per second

**VIDEO\_1080I\_60\_FIELDS\_PER\_SECOND**

1,080 lines, interlaced, 60 fields per second

**VIDEO\_1080P\_24\_FRAMES\_PER\_SECOND**

1,080 lines, progressive, 24 frames per second



## VideoTriggerEvent

```
class niscopes.VideoTriggerEvent
```

### FIELD1

Trigger on field 1 of the signal

### FIELD2

Trigger on field 2 of the signal

### ANY\_FIELD

Trigger on the first field acquired

### ANY\_LINE

Trigger on the first line acquired

### LINE\_NUMBER

Trigger on a specific line of a video signal. Valid values vary depending on the signal format configured.

## WhichTrigger

```
class niscopes.WhichTrigger
```

### START

### ARM\_REFERENCE

### REFERENCE

### ADVANCE

## 7.4.3.3 Exceptions and Warnings

### DriverError

```
exception niscopes.DriverError
```

An error originating from the NI-SCOPE driver

### UnsupportedConfigurationError

```
exception niscopes.UnsupportedConfigurationError
```

An error due to using this module in an unsupported platform.

### DriverNotInstalledError

```
exception niscopes.DriverNotInstalledError
```

An error due to using this module without the driver runtime installed.

### InvalidRepeatedCapabilityError

**exception** `niscope.InvalidRepeatedCapabilityError`

An error due to an invalid character in a repeated capability

### SelfTestError

**exception** `niscope.SelfTestError`

An error due to a failed self-test

### DriverWarning

**exception** `niscope.DriverWarning`

A warning originating from the NI-SCOPE driver

## 7.4.3.4 Examples

### `niscope_fetch.py`

Listing 8: (`niscope_fetch.py`)

```
1  #!/usr/bin/python
2
3  import argparse
4  import niscope
5  import pprint
6  import sys
7
8  pp = pprint.PrettyPrinter(indent=4, width=80)
9
10
11 def example(resource_name, channels, options, length, voltage):
12     with niscope.Session(resource_name=resource_name, options=options) as session:
13         session.configure_vertical(range=voltage, coupling=niscope.VerticalCoupling.
14         ↪AC)
15         session.configure_horizontal_timing(min_sample_rate=50000000, min_num_
16         ↪pts=length, ref_position=50.0, num_records=1, enforce_realtime=True)
17         with session.initiate():
18             waveforms = session.channels[channels].fetch(num_samples=length)
19             for i in range(len(waveforms)):
20                 print('Waveform {0} information:'.format(i))
21                 print(str(waveforms[i]) + '\n\n')
22
23 def _main(argv):
24     parser = argparse.ArgumentParser(description='Acquires one record from the given_
25     ↪channels.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)
26     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
27     ↪name of a National Instruments Digitizer')
28     parser.add_argument('-c', '--channels', default='0', help='Channel(s) to use')
29     parser.add_argument('-l', '--length', default=1000, type=int, help='Measure_
30     ↪record length')
```

(continues on next page)

(continued from previous page)

```

27     parser.add_argument('-v', '--voltage', default=1.0, type=float, help='Voltage_
↪range (V)')
28     parser.add_argument('-op', '--option-string', default='', type=str, help='Option_
↪string')
29     args = parser.parse_args(argv)
30     example(args.resource_name, args.channels, args.option_string, args.length, args.
↪voltage)
31
32
33 def main():
34     _main(sys.argv[1:])
35
36
37 def test_example():
38     options = {'simulate': True, 'driver_setup': {'Model': '5164', 'BoardType': 'PXIe
↪', }, }
39     example('PXI1Slot2', '0', options, 1000, 1.0)
40
41
42 def test_main():
43     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:5164; BoardType:PXIe
↪', ]
44     _main(cmd_line)
45
46
47 if __name__ == '__main__':
48     main()
49

```

## niscope\_fetch\_forever.py

Listing 9: (niscope\_fetch\_forever.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import datetime
5  import niscopes
6  import numpy as np
7  import pprint
8  import sys
9
10
11 pp = pprint.PrettyPrinter(indent=4, width=80)
12
13
14 # We use fetch_into which allows us to allocate a single buffer per channel and
↪"fetch into" it a section at a time without having to
15 # reconstruct the waveform once we are done
16 def example(resource_name, options, total_acquisition_time_in_seconds, voltage,
↪sample_rate_in_hz, samples_per_fetch):
17     total_samples = int(total_acquisition_time_in_seconds * sample_rate_in_hz)
18     # 1. Opening session
19     with niscopes.Session(resource_name=resource_name, options=options) as session:

```

(continues on next page)

(continued from previous page)

```

20     # We will acquire on all channels of the device
21     channel_list = [c for c in range(session.channel_count)] # Need an actual_
↳list and not a range
22
23     # 2. Creating numpy arrays
24     waveforms = [np.ndarray(total_samples, dtype=np.float64) for c in channel_
↳list]
25
26     # 3. Configuring
27     session.configure_horizontal_timing(min_sample_rate=sample_rate_in_hz, min_
↳num_pts=1, ref_position=0.0, num_records=1, enforce_realtime=True)
28     session.channels[channel_list].configure_vertical(voltage, coupling=niscope.
↳VerticalCoupling.DC, enabled=True)
29     # Configure software trigger, but never send the trigger.
30     # This starts an infinite acquisition, until you call session.abort() or_
↳session.close()
31     session.configure_trigger_software()
32     current_pos = 0
33     # 4. initating
34     with session.initiate():
35         while current_pos < total_samples:
36             # We fetch each channel at a time so we don't have to de-interleave_
↳afterwards
37             # We do not keep the wfm_info returned from fetch_into
38             for channel, waveform in zip(channel_list, waveforms):
39                 # 5. fetching - we return the slice of the waveform array that we_
↳want to "fetch into"
40                 session.channels[channel].fetch_into(waveform[current_pos:current_
↳pos + samples_per_fetch], relative_to=niscope.FetchRelativeTo.READ_POINTER,
41                                                         offset=0, record_number=0,
↳num_records=1, timeout=datetime.timedelta(seconds=5.0))
42                 current_pos += samples_per_fetch
43
44
45 def _main(argv):
46     parser = argparse.ArgumentParser(description='Fetch more samples than will fit in_
↳memory.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)
47     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
↳name of a National Instruments Digitizer')
48     parser.add_argument('-t', '--time', default=10, type=int, help='Time to sample (s)
↳')
49     parser.add_argument('-v', '--voltage', default=1.0, type=float, help='Voltage_
↳range (V)')
50     parser.add_argument('-op', '--option-string', default='', type=str, help='Option_
↳string')
51     parser.add_argument('-r', '--sample-rate', default=1000.0, type=float, help=
↳'Sample Rate (Hz)')
52     parser.add_argument('-s', '--samples-per-fetch', default=100, type=int, help=
↳'Samples per fetch')
53     args = parser.parse_args(argv)
54     example(args.resource_name, args.option_string, args.time, args.voltage, args.
↳sample_rate, args.samples_per_fetch)
55
56
57 def main():
58     _main(sys.argv[1:])
59

```

(continues on next page)

(continued from previous page)

```

60
61 def test_example():
62     options = {'simulate': True, 'driver_setup': {'Model': '5164', 'BoardType': 'PXIe
↪', }, }
63     example('PXI1Slot2', options, 10, 1.0, 1000.0, 100)
64
65
66 def test_main():
67     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:5164; BoardType:PXIe
↪', ]
68     _main(cmd_line)
69
70
71 if __name__ == '__main__':
72     main()
73

```

**niscope\_read.py**

Listing 10: (niscope\_read.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import niscope
5  import pprint
6  import sys
7
8  pp = pprint.PrettyPrinter(indent=4, width=80)
9
10
11 def example(resource_name, channels, options, length, voltage):
12     with niscope.Session(resource_name=resource_name, options=options) as session:
13         session.configure_vertical(range=voltage, coupling=niscope.VerticalCoupling.
↪AC)
14         session.configure_horizontal_timing(min_sample_rate=50000000, min_num_
↪pts=length, ref_position=50.0, num_records=1, enforce_realtime=True)
15         waveforms = session.channels[channels].read(num_samples=length)
16         for i in range(len(waveforms)):
17             print('Waveform {0} information:'.format(i))
18             print(str(waveforms[i]) + '\n\n')
19
20
21 def _main(argv):
22     parser = argparse.ArgumentParser(description='Acquires one record from the given_
↪channels.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)
23     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
↪name of a National Instruments Digitizer')
24     parser.add_argument('-c', '--channels', default='0', help='Channel(s) to use')
25     parser.add_argument('-l', '--length', default=1000, type=int, help='Measure_
↪record length')
26     parser.add_argument('-v', '--voltage', default=1.0, type=float, help='Voltage_
↪range (V)')
27     parser.add_argument('-op', '--option-string', default='', type=str, help='Option_
↪string')

```

(continues on next page)

(continued from previous page)

```

28     args = parser.parse_args(argv)
29     example(args.resource_name, args.channels, args.option_string, args.length, args.
↪voltage)
30
31
32 def main():
33     _main(sys.argv[1:])
34
35
36 def test_example():
37     options = {'simulate': True, 'driver_setup': {'Model': '5164', 'BoardType': 'PXIe
↪', }, }
38     example('PXI1Slot2', '0', options, 1000, 1.0)
39
40
41 def test_main():
42     cmd_line = ['--option-string', 'Simulate=1, DriverSetup=Model:5164; BoardType:PXIe
↪', ]
43     _main(cmd_line)
44
45
46 if __name__ == '__main__':
47     main()
48

```

## 7.5 niswitch module

### 7.5.1 Installation

As a prerequisite to using the **niswitch** module, you must install the NI-SWITCH runtime on your system. Visit [ni.com/downloads](http://ni.com/downloads) to download the driver runtime for your devices.

The **nimi-python** modules (i.e. for **NI-SWITCH**) can be installed with **pip**:

```
$ python -m pip install niswitch~=1.0.0
```

Or **easy\_install** from **setuptools**:

```
$ python -m easy_install niswitch
```

### 7.5.2 Usage

The following is a basic example of using the **niswitch** module to open a session to a Switch and connect channels.

```

import niswitch
with niswitch.Session("Dev1") as session:
    session.connect(channel1='r0', channel2='c0')

```

Additional examples for NI-SWITCH are located in `src/niswitch/examples/` directory.

## 7.5.3 API Reference

### 7.5.3.1 niswitch.Session

**class** `niswitch.Session` (*self*, *resource\_name*, *topology*="Configured Topology", *simulate*=False, *reset\_device*=False)

Returns a session handle used to identify the switch in all subsequent instrument driver calls and sets the topology of the switch. `niswitch.Session.__init__()` creates a new IVI instrument driver session for the switch specified in the `resourceName` parameter. The driver uses the topology specified in the `topology` parameter and overrides the topology specified in MAX. Note: When initializing an NI SwitchBlock device with topology, you must specify the topology created when you configured the device in MAX, using either `NISWITCH_TOPOLOGY_CONFIGURED_TOPOLOGY` or the topology string of the device. Refer to the Initializing with Topology for NI SwitchBlock Devices topic in the NI Switches Help for information about determining the topology string of an NI SwitchBlock device. By default, the switch is reset to a known state. Enable simulation by specifying the topology and setting the `simulate` parameter to True.

#### Parameters

- **resource\_name** (*str*) – Resource name of the switch module to initialize. Default value: None Syntax: Optional fields are shown in square brackets ([]). Configured in MAX Under Valid Syntax Devices and Interfaces DeviceName Traditional NI-DAQ Devices SCXI[chassis ID]::slot number PXI System PXI[bus number]::device number TIP: IVI logical names are also valid for the resource name. Default values for optional fields: chassis ID = 1 bus number = 0 Example resource names: Resource Name Description SC1Mod3 NI-DAQmx module in chassis “SC1” slot 3 MySwitch NI-DAQmx module renamed to “MySwitch” SCXI1::3 Traditional NI-DAQ module in chassis 1, slot 3 SCXI::3 Traditional NI-DAQ module in chassis 1, slot 3 PXI0::16 PXI bus 0, device number 16 PXI::16 PXI bus 0, device number 16
- **topology** (*str*) – Pass the topology name you want to use for the switch you specify with Resource Name parameter. You can also pass `NISWITCH_TOPOLOGY_CONFIGURED_TOPOLOGY` to use the last topology that was configured for the device in MAX. Default Value: `NISWITCH_TOPOLOGY_CONFIGURED_TOPOLOGY`  
Valid Values: `NISWITCH_TOPOLOGY_1127_1_WIRE_64X1_MUX`  
`NISWITCH_TOPOLOGY_1127_2_WIRE_32X1_MUX` `NISWITCH_TOPOLOGY_1127_2_WIRE_4X8_MATRIX`  
`NISWITCH_TOPOLOGY_1127_4_WIRE_16X1_MUX` `NISWITCH_TOPOLOGY_1127_INDEPENDENT`  
`NISWITCH_TOPOLOGY_1128_1_WIRE_64X1_MUX` `NISWITCH_TOPOLOGY_1128_2_WIRE_32X1_MUX`  
`NISWITCH_TOPOLOGY_1128_2_WIRE_4X8_MATRIX`  
`NISWITCH_TOPOLOGY_1128_4_WIRE_16X1_MUX` `NISWITCH_TOPOLOGY_1128_INDEPENDENT`  
`NISWITCH_TOPOLOGY_1129_2_WIRE_16X16_MATRIX`  
`NISWITCH_TOPOLOGY_1129_2_WIRE_8X32_MATRIX`  
`NISWITCH_TOPOLOGY_1129_2_WIRE_4X64_MATRIX`  
`NISWITCH_TOPOLOGY_1129_2_WIRE_DUAL_8X16_MATRIX`  
`NISWITCH_TOPOLOGY_1129_2_WIRE_DUAL_4X32_MATRIX`  
`NISWITCH_TOPOLOGY_1129_2_WIRE_QUAD_4X16_MATRIX`  
`NISWITCH_TOPOLOGY_1130_1_WIRE_256X1_MUX` `NISWITCH_TOPOLOGY_1130_1_WIRE_DUAL_128X1_MUX`  
`NISWITCH_TOPOLOGY_1130_1_WIRE_4X64_MATRIX`  
`NISWITCH_TOPOLOGY_1130_1_WIRE_8X32_MATRIX`  
`NISWITCH_TOPOLOGY_1130_1_WIRE_OCTAL_32X1_MUX`  
`NISWITCH_TOPOLOGY_1130_1_WIRE_QUAD_64X1_MUX`  
`NISWITCH_TOPOLOGY_1130_1_WIRE_SIXTEEN_16X1_MUX`  
`NISWITCH_TOPOLOGY_1130_2_WIRE_4X32_MATRIX`  
`NISWITCH_TOPOLOGY_1130_2_WIRE_128X1_MUX` `NISWITCH_TOPOLOGY_1130_2_WIRE_OCTAL_16X1_MUX`  
`NISWITCH_TOPOLOGY_1130_2_WIRE_QUAD_32X1_MUX`

NISWITCH\_TOPOLOGY\_1130\_4\_WIRE\_64X1\_MUX NISWITCH\_TOPOLOGY\_1130\_4\_WIRE\_QUAD\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_1130\_INDEPENDENT NISWITCH\_TOPOLOGY\_1160\_16\_SPDT  
 NISWITCH\_TOPOLOGY\_1161\_8\_SPDT NISWITCH\_TOPOLOGY\_1163R\_OCTAL\_4X1\_MUX  
 NISWITCH\_TOPOLOGY\_1166\_16\_DPDT NISWITCH\_TOPOLOGY\_1166\_32\_SPDT  
 NISWITCH\_TOPOLOGY\_1167\_INDEPENDENT NISWITCH\_TOPOLOGY\_1169\_100\_SPST  
 NISWITCH\_TOPOLOGY\_1169\_50\_DPST NISWITCH\_TOPOLOGY\_1175\_1\_WIRE\_196X1\_MUX  
 NISWITCH\_TOPOLOGY\_1175\_2\_WIRE\_98X1\_MUX NISWITCH\_TOPOLOGY\_1175\_2\_WIRE\_95X1\_MUX  
 NISWITCH\_TOPOLOGY\_1190\_QUAD\_4X1\_MUX NISWITCH\_TOPOLOGY\_1191\_QUAD\_4X1\_MUX  
 NISWITCH\_TOPOLOGY\_1192\_8\_SPDT NISWITCH\_TOPOLOGY\_1193\_32X1\_MUX  
 NISWITCH\_TOPOLOGY\_1193\_16X1\_TERMINATED\_MUX  
 NISWITCH\_TOPOLOGY\_1193\_DUAL\_16X1\_MUX NISWITCH\_TOPOLOGY\_1193\_DUAL\_8X1\_TERMINATED\_MUX  
 NISWITCH\_TOPOLOGY\_1193\_QUAD\_8X1\_MUX NISWITCH\_TOPOLOGY\_1193\_QUAD\_4X1\_TERMINATED\_MUX  
 NISWITCH\_TOPOLOGY\_1193\_INDEPENDENT NISWITCH\_TOPOLOGY\_1194\_QUAD\_4X1\_MUX  
 NISWITCH\_TOPOLOGY\_1195\_QUAD\_4X1\_MUX NISWITCH\_TOPOLOGY\_2501\_1\_WIRE\_48X1\_MUX  
 NISWITCH\_TOPOLOGY\_2501\_1\_WIRE\_48X1\_AMPLIFIED\_MUX  
 NISWITCH\_TOPOLOGY\_2501\_2\_WIRE\_24X1\_MUX NISWITCH\_TOPOLOGY\_2501\_2\_WIRE\_24X1\_AMPLIFIED\_MUX  
 NISWITCH\_TOPOLOGY\_2501\_2\_WIRE\_DUAL\_12X1\_MUX  
 NISWITCH\_TOPOLOGY\_2501\_2\_WIRE\_QUAD\_6X1\_MUX  
 NISWITCH\_TOPOLOGY\_2501\_2\_WIRE\_4X6\_MATRIX  
 NISWITCH\_TOPOLOGY\_2501\_4\_WIRE\_12X1\_MUX NISWITCH\_TOPOLOGY\_2503\_1\_WIRE\_48X1\_MUX  
 NISWITCH\_TOPOLOGY\_2503\_2\_WIRE\_24X1\_MUX NISWITCH\_TOPOLOGY\_2503\_2\_WIRE\_DUAL\_12X1\_MUX  
 NISWITCH\_TOPOLOGY\_2503\_2\_WIRE\_QUAD\_6X1\_MUX  
 NISWITCH\_TOPOLOGY\_2503\_2\_WIRE\_4X6\_MATRIX  
 NISWITCH\_TOPOLOGY\_2503\_4\_WIRE\_12X1\_MUX NISWITCH\_TOPOLOGY\_2510\_INDEPENDENT  
 NISWITCH\_TOPOLOGY\_2512\_INDEPENDENT NISWITCH\_TOPOLOGY\_2514\_INDEPENDENT  
 NISWITCH\_TOPOLOGY\_2515\_INDEPENDENT NISWITCH\_TOPOLOGY\_2520\_80\_SPST  
 NISWITCH\_TOPOLOGY\_2521\_40\_DPST NISWITCH\_TOPOLOGY\_2522\_53\_SPDT  
 NISWITCH\_TOPOLOGY\_2523\_26\_DPDT NISWITCH\_TOPOLOGY\_2524\_1\_WIRE\_128X1\_MUX  
 NISWITCH\_TOPOLOGY\_2524\_1\_WIRE\_DUAL\_64X1\_MUX  
 NISWITCH\_TOPOLOGY\_2524\_1\_WIRE\_QUAD\_32X1\_MUX  
 NISWITCH\_TOPOLOGY\_2524\_1\_WIRE\_OCTAL\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_2524\_1\_WIRE\_SIXTEEN\_8X1\_MUX  
 NISWITCH\_TOPOLOGY\_2525\_2\_WIRE\_64X1\_MUX NISWITCH\_TOPOLOGY\_2525\_2\_WIRE\_DUAL\_32X1\_MUX  
 NISWITCH\_TOPOLOGY\_2525\_2\_WIRE\_QUAD\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_2525\_2\_WIRE\_OCTAL\_8X1\_MUX  
 NISWITCH\_TOPOLOGY\_2525\_2\_WIRE\_SIXTEEN\_4X1\_MUX  
 NISWITCH\_TOPOLOGY\_2526\_1\_WIRE\_158X1\_MUX NISWITCH\_TOPOLOGY\_2526\_2\_WIRE\_79X1\_MUX  
 NISWITCH\_TOPOLOGY\_2527\_1\_WIRE\_64X1\_MUX NISWITCH\_TOPOLOGY\_2527\_1\_WIRE\_DUAL\_32X1\_MUX  
 NISWITCH\_TOPOLOGY\_2527\_2\_WIRE\_32X1\_MUX NISWITCH\_TOPOLOGY\_2527\_2\_WIRE\_DUAL\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_2527\_4\_WIRE\_16X1\_MUX NISWITCH\_TOPOLOGY\_2527\_INDEPENDENT  
 NISWITCH\_TOPOLOGY\_2529\_2\_WIRE\_DUAL\_4X16\_MATRIX  
 NISWITCH\_TOPOLOGY\_2529\_2\_WIRE\_8X16\_MATRIX  
 NISWITCH\_TOPOLOGY\_2529\_2\_WIRE\_4X32\_MATRIX  
 NISWITCH\_TOPOLOGY\_2530\_1\_WIRE\_128X1\_MUX NISWITCH\_TOPOLOGY\_2530\_1\_WIRE\_DUAL\_64X1\_MUX  
 NISWITCH\_TOPOLOGY\_2530\_1\_WIRE\_4x32\_MATRIX  
 NISWITCH\_TOPOLOGY\_2530\_1\_WIRE\_8x16\_MATRIX  
 NISWITCH\_TOPOLOGY\_2530\_1\_WIRE\_OCTAL\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_2530\_1\_WIRE\_QUAD\_32X1\_MUX  
 NISWITCH\_TOPOLOGY\_2530\_2\_WIRE\_4x16\_MATRIX  
 NISWITCH\_TOPOLOGY\_2530\_2\_WIRE\_64X1\_MUX NISWITCH\_TOPOLOGY\_2530\_2\_WIRE\_DUAL\_32X1\_MUX  
 NISWITCH\_TOPOLOGY\_2530\_2\_WIRE\_QUAD\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_2530\_4\_WIRE\_32X1\_MUX NISWITCH\_TOPOLOGY\_2530\_4\_WIRE\_DUAL\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_2530\_INDEPENDENT NISWITCH\_TOPOLOGY\_2531\_1\_WIRE\_4X128\_MATRIX  
 NISWITCH\_TOPOLOGY\_2531\_1\_WIRE\_8X64\_MATRIX



NISWITCH\_TOPOLOGY\_2531\_1\_WIRE\_DUAL\_4X64\_MATRIX  
 NISWITCH\_TOPOLOGY\_2531\_1\_WIRE\_DUAL\_8X32\_MATRIX  
 NISWITCH\_TOPOLOGY\_2531\_2\_WIRE\_4X64\_MATRIX NISWITCH\_TOPOLOGY\_2531\_2\_WIRE\_8X32\_M  
 NISWITCH\_TOPOLOGY\_2532\_1\_WIRE\_16X32\_MATRIX  
 NISWITCH\_TOPOLOGY\_2532\_1\_WIRE\_4X128\_MATRIX NISWITCH\_TOPOLOGY\_2532\_1\_WIRE\_8X64\_M  
 NISWITCH\_TOPOLOGY\_2532\_1\_WIRE\_DUAL\_16X16\_MATRIX NISWITCH\_TOPOLOGY\_2532\_1\_WIRE  
 NISWITCH\_TOPOLOGY\_2532\_1\_WIRE\_DUAL\_8X32\_MATRIX NISWITCH\_TOPOLOGY\_2532\_1\_WIRE\_S  
 NISWITCH\_TOPOLOGY\_2532\_2\_WIRE\_16X16\_MATRIX NISWITCH\_TOPOLOGY\_2532\_2\_WIRE\_4X64\_M  
 NISWITCH\_TOPOLOGY\_2532\_2\_WIRE\_8X32\_MATRIX NISWITCH\_TOPOLOGY\_2532\_2\_WIRE\_DUAL\_4  
 NISWITCH\_TOPOLOGY\_2533\_1\_WIRE\_4X64\_MATRIX NISWITCH\_TOPOLOGY\_2534\_1\_WIRE\_8X32\_M  
 NISWITCH\_TOPOLOGY\_2535\_1\_WIRE\_4X136\_MATRIX NISWITCH\_TOPOLOGY\_2536\_1\_WIRE\_8X68\_M  
 NISWITCH\_TOPOLOGY\_2540\_1\_WIRE\_8X9\_MATRIX NISWITCH\_TOPOLOGY\_2541\_1\_WIRE\_8X12\_MA  
 NISWITCH\_TOPOLOGY\_2542\_QUAD\_2X1\_TERMINATED\_MUX NISWITCH\_TOPOLOGY\_2543\_DUAL\_4  
 NISWITCH\_TOPOLOGY\_2544\_8X1\_TERMINATED\_MUX NISWITCH\_TOPOLOGY\_2545\_4X1\_TERMINAT  
 NISWITCH\_TOPOLOGY\_2546\_DUAL\_4X1\_MUX NISWITCH\_TOPOLOGY\_2547\_8X1\_MUX  
 NISWITCH\_TOPOLOGY\_2548\_4\_SPDT NISWITCH\_TOPOLOGY\_2549\_TERMINATED\_2\_SPDT  
 NISWITCH\_TOPOLOGY\_2554\_4X1\_MUX NISWITCH\_TOPOLOGY\_2555\_4X1\_TERMINATED\_MUX  
 NISWITCH\_TOPOLOGY\_2556\_DUAL\_4X1\_MUX NISWITCH\_TOPOLOGY\_2557\_8X1\_MUX  
 NISWITCH\_TOPOLOGY\_2558\_4\_SPDT NISWITCH\_TOPOLOGY\_2559\_TERMINATED\_2\_SPDT  
 NISWITCH\_TOPOLOGY\_2564\_16\_SPST NISWITCH\_TOPOLOGY\_2564\_8\_DPST  
 NISWITCH\_TOPOLOGY\_2565\_16\_SPST NISWITCH\_TOPOLOGY\_2566\_16\_SPDT  
 NISWITCH\_TOPOLOGY\_2566\_8\_DPDT NISWITCH\_TOPOLOGY\_2567\_INDEPENDENT  
 NISWITCH\_TOPOLOGY\_2568\_15\_DPST NISWITCH\_TOPOLOGY\_2568\_31\_SPST  
 NISWITCH\_TOPOLOGY\_2569\_100\_SPST NISWITCH\_TOPOLOGY\_2569\_50\_DPST  
 NISWITCH\_TOPOLOGY\_2570\_20\_DPDT NISWITCH\_TOPOLOGY\_2570\_40\_SPDT  
 NISWITCH\_TOPOLOGY\_2571\_66\_SPDT NISWITCH\_TOPOLOGY\_2575\_1\_WIRE\_196X1\_MUX  
 NISWITCH\_TOPOLOGY\_2575\_2\_WIRE\_98X1\_MUX NISWITCH\_TOPOLOGY\_2575\_2\_WIRE\_95X1\_MUX  
 NISWITCH\_TOPOLOGY\_2576\_2\_WIRE\_64X1\_MUX NISWITCH\_TOPOLOGY\_2576\_2\_WIRE\_DUAL\_32X  
 NISWITCH\_TOPOLOGY\_2576\_2\_WIRE\_OCTAL\_8X1\_MUX NISWITCH\_TOPOLOGY\_2576\_2\_WIRE\_QUA  
 NISWITCH\_TOPOLOGY\_2576\_2\_WIRE\_SIXTEEN\_4X1\_MUX NISWITCH\_TOPOLOGY\_2576\_INDEPEND  
 NISWITCH\_TOPOLOGY\_2584\_1\_WIRE\_12X1\_MUX NISWITCH\_TOPOLOGY\_2584\_1\_WIRE\_DUAL\_6X1  
 NISWITCH\_TOPOLOGY\_2584\_2\_WIRE\_6X1\_MUX NISWITCH\_TOPOLOGY\_2584\_INDEPENDENT  
 NISWITCH\_TOPOLOGY\_2585\_1\_WIRE\_10X1\_MUX NISWITCH\_TOPOLOGY\_2586\_10\_SPST  
 NISWITCH\_TOPOLOGY\_2586\_5\_DPST NISWITCH\_TOPOLOGY\_2590\_4X1\_MUX  
 NISWITCH\_TOPOLOGY\_2591\_4X1\_MUX NISWITCH\_TOPOLOGY\_2593\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_2593\_8X1\_TERMINATED\_MUX NISWITCH\_TOPOLOGY\_2593\_DUAL\_8X1\_MU  
 NISWITCH\_TOPOLOGY\_2593\_DUAL\_4X1\_TERMINATED\_MUX NISWITCH\_TOPOLOGY\_2593\_INDEPE  
 NISWITCH\_TOPOLOGY\_2594\_4X1\_MUX NISWITCH\_TOPOLOGY\_2595\_4X1\_MUX  
 NISWITCH\_TOPOLOGY\_2596\_DUAL\_6X1\_MUX NISWITCH\_TOPOLOGY\_2597\_6X1\_TERMINATED\_MU  
 NISWITCH\_TOPOLOGY\_2598\_DUAL\_TRANSFER NISWITCH\_TOPOLOGY\_2599\_2\_SPDT  
 NISWITCH\_TOPOLOGY\_2720\_INDEPENDENT NISWITCH\_TOPOLOGY\_2722\_INDEPENDENT  
 NISWITCH\_TOPOLOGY\_2725\_INDEPENDENT NISWITCH\_TOPOLOGY\_2727\_INDEPENDENT  
 NISWITCH\_TOPOLOGY\_2737\_2\_WIRE\_4X64\_MATRIX NISWITCH\_TOPOLOGY\_2738\_2\_WIRE\_8X32\_M  
 NISWITCH\_TOPOLOGY\_2739\_2\_WIRE\_16X16\_MATRIX NISWITCH\_TOPOLOGY\_2746\_QUAD\_4X1\_MU  
 NISWITCH\_TOPOLOGY\_2747\_DUAL\_8X1\_MUX NISWITCH\_TOPOLOGY\_2748\_16X1\_MUX  
 NISWITCH\_TOPOLOGY\_2790\_INDEPENDENT NISWITCH\_TOPOLOGY\_2796\_DUAL\_6X1\_MUX  
 NISWITCH\_TOPOLOGY\_2797\_6X1\_TERMINATED\_MUX NISWITCH\_TOPOLOGY\_2798\_DUAL\_TRANSE  
 NISWITCH\_TOPOLOGY\_2799\_2\_SPDT

- **simulate** (*bool*) – Enables simulation of the switch module specified in the resource name parameter. Valid Values: True - simulate False - Don't simulate (Default Value)
- **reset\_device** (*bool*) – Specifies whether to reset the switch module during the initialization process. Valid Values: True - Reset Device (Default Value) False - Currently unsupported. The device will not reset.

## Properties

Property	Datatype
<i>analog_bus_sharing_enable</i>	bool
<i>bandwidth</i>	float
<i>channel_count</i>	int
<i>characteristic_impedance</i>	float
<i>continuous_scan</i>	bool
<i>digital_filter_enable</i>	bool
<i>driver_setup</i>	str
<i>handshaking_initiation</i>	<i>HandshakingInitiation</i>
<i>instrument_firmware_revision</i>	str
<i>instrument_manufacturer</i>	str
<i>instrument_model</i>	str
<i>io_resource_descriptor</i>	str
<i>is_configuration_channel</i>	bool
<i>is_debounced</i>	bool
<i>is_scanning</i>	bool
<i>is_source_channel</i>	bool
<i>is_waiting_for_trig</i>	bool
<i>logical_name</i>	str
<i>max_ac_voltage</i>	float
<i>max_carry_ac_current</i>	float
<i>max_carry_ac_power</i>	float
<i>max_carry_dc_current</i>	float
<i>max_carry_dc_power</i>	float
<i>max_dc_voltage</i>	float
<i>max_switching_ac_current</i>	float
<i>max_switching_ac_power</i>	float
<i>max_switching_dc_current</i>	float
<i>max_switching_dc_power</i>	float
<i>number_of_relays</i>	int
<i>num_of_columns</i>	int
<i>num_of_rows</i>	int
<i>power_down_latching_relays_after_debounce</i>	bool
<i>scan_advanced_output</i>	<i>ScanAdvancedOutput</i>
<i>scan_advanced_polarity</i>	<i>ScanAdvancedPolarity</i>
<i>scan_delay</i>	float in seconds or <i>datetime.timedelta</i>
<i>scan_list</i>	str
<i>scan_mode</i>	<i>ScanMode</i>
<i>serial_number</i>	str
<i>settling_time</i>	float in seconds or <i>datetime.timedelta</i>
<i>simulate</i>	bool
<i>specific_driver_description</i>	str
<i>specific_driver_revision</i>	str
<i>specific_driver_vendor</i>	str
<i>supported_instrument_models</i>	str
<i>temperature</i>	float
<i>trigger_input</i>	<i>TriggerInput</i>
<i>trigger_input_polarity</i>	<i>TriggerInputPolarity</i>
<i>wire_mode</i>	int

## Public methods

Method name
<i>abort()</i>
<i>can_connect()</i>
<i>commit()</i>
<i>connect()</i>
<i>connect_multiple()</i>
<i>disable()</i>
<i>disconnect()</i>
<i>disconnect_all()</i>
<i>disconnect_multiple()</i>
<i>get_channel_name()</i>
<i>get_path()</i>
<i>get_relay_count()</i>
<i>get_relay_name()</i>
<i>get_relay_position()</i>
<i>lock()</i>
<i>relay_control()</i>
<i>reset()</i>
<i>reset_with_defaults()</i>
<i>route_scan_advanced_output()</i>
<i>route_trigger_input()</i>
<i>self_test()</i>
<i>send_software_trigger()</i>
<i>set_path()</i>
<i>unlock()</i>
<i>wait_for_debounce()</i>
<i>wait_for_scan_complete()</i>

## Properties

### analog\_bus\_sharing\_enable

`niswitch.Session.analog_bus_sharing_enable`

Enables or disables sharing of an analog bus line so that multiple NI SwitchBlock devices may connect to it simultaneously. To enable multiple NI SwitchBlock devices to share an analog bus line, set this property to True for each device on the channel that corresponds with the shared analog bus line. The default value for all devices is False, which disables sharing of the analog bus. Refer to the Using the Analog Bus on an NI SwitchBlock Carrier topic in the NI Switches Help for more information about sharing the analog bus.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].analog_bus_sharing_enable = var
var = session.channels[0,1].analog_bus_sharing_enable
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Channel Configuration:Analog Bus Sharing Enable**
  - C Attribute: **NISWITCH\_ATTR\_ANALOG\_BUS\_SHARING\_ENABLE**
- 

## bandwidth

`niswitch.Session.bandwidth`

This channel-based property returns the bandwidth for the channel. The units are hertz.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].bandwidth
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Bandwidth**
  - C Attribute: **NISWITCH\_ATTR\_BANDWIDTH**
- 

## channel\_count

`niswitch.Session.channel_count`

Indicates the number of channels that the specific instrument driver supports.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Capabilities:Channel Count**
  - C Attribute: **NISWITCH\_ATTR\_CHANNEL\_COUNT**
- 

## characteristic\_impedance

`niswitch.Session.characteristic_impedance`

This channel-based property returns the characteristic impedance for the channel. The units are ohms.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].characteristic_impedance
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Characteristic Impedance**
  - C Attribute: **NISWITCH\_ATTR\_CHARACTERISTIC\_IMPEDANCE**
- 

## continuous\_scan

`niswitch.Session.continuous_scan`

When a switch device is scanning, the switch can either stop scanning when the end of the scan (False) or continue scanning from the top of the scan list again (True). Notice that if you set the scan to continuous (True), the Wait For Scan Complete operation will always time out and you must call Abort to stop the scan.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Continuous Scan**
  - C Attribute: **NISWITCH\_ATTR\_CONTINUOUS\_SCAN**
- 

## digital\_filter\_enable

### `niswitch.Session.digital_filter_enable`

This property specifies whether to apply the pulse width filter to the Trigger Input. Enabling the Digital Filter (True) prevents the switch module from being triggered by pulses that are less than 150 ns on PXI trigger lines 0–7. When Digital Filter is disabled (False), it is possible for the switch module to be triggered by noise on the PXI trigger lines. If the device triggering the switch is capable of sending pulses greater than 150 ns, you should not disable the Digital Filter.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Digital Filter Enable**
  - C Attribute: **NISWITCH\_ATTR\_DIGITAL\_FILTER\_ENABLE**
- 

## driver\_setup

### `niswitch.Session.driver_setup`

This property indicates the Driver Setup string that the user specified when initializing the driver. Some cases exist where the end-user must specify instrument driver options at initialization time. An example of this is specifying a particular instrument model from among a family of instruments that the driver supports. This is useful when using simulation. The end-user can specify driver-specific options through the DriverSetup keyword in the optionsString parameter to the `niswitch.Session.InitWithOptions()` method, or through the IVI Configuration Utility. If the user does not specify a Driver Setup string, this property returns an empty string.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:Driver Setup**
  - C Attribute: **NISWITCH\_ATTR\_DRIVER\_SETUP**
- 

## handshaking\_initiation

`niswitch.Session.handshaking_initiation`

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.HandshakingInitiation</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Handshaking Initiation**
  - C Attribute: **NISWITCH\_ATTR\_HANDSHAKING\_INITIATION**
- 

## instrument\_firmware\_revision

`niswitch.Session.instrument_firmware_revision`

A string that contains the firmware revision information for the instrument you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Firmware Revision**
- C Attribute: **NISWITCH\_ATTR\_INSTRUMENT\_FIRMWARE\_REVISION**

## instrument\_manufacturer

`niswitch.Session.instrument_manufacturer`

A string that contains the name of the instrument manufacturer you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Manufacturer**
  - C Attribute: **NISWITCH\_ATTR\_INSTRUMENT\_MANUFACTURER**
- 

## instrument\_model

`niswitch.Session.instrument_model`

A string that contains the model number or name of the instrument that you are currently using.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Instrument Identification:Model**
  - C Attribute: **NISWITCH\_ATTR\_INSTRUMENT\_MODEL**
- 

## io\_resource\_descriptor

`niswitch.Session.io_resource_descriptor`

Indicates the resource descriptor the driver uses to identify the physical device. If you initialize the driver with a logical name, this property contains the resource descriptor that corresponds to the entry in the IVI Configuration utility. If you initialize the instrument driver with the resource descriptor, this property contains that value.

The following table lists the characteristics of this property.



Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:IO Resource Descriptor**
  - C Attribute: **NISWITCH\_ATTR\_IO\_RESOURCE\_DESCRIPTOR**
- 

## is\_configuration\_channel

### `niswitch.Session.is_configuration_channel`

This channel-based property specifies whether to reserve the channel for internal path creation. A channel that is available for internal path creation is called a configuration channel. The driver may use configuration channels to create paths between two channels you specify in the `niswitch.Session.connect()` method. Configuration channels are not available for external connections. Set this property to True to mark the channel as a configuration channel. Set this property to False to mark the channel as available for external connections. After you identify a channel as a configuration channel, you cannot use that channel for external connections. The `niswitch.Session.connect()` method returns the `NISWITCH_ERROR_IS_CONFIGURATION_CHANNEL` error when you attempt to establish a connection between a configuration channel and any other channel.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].is_configuration_channel = var
var = session.channels[0,1].is_configuration_channel
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Channel Configuration:Is Configuration Channel**
  - C Attribute: **NISWITCH\_ATTR\_IS\_CONFIGURATION\_CHANNEL**
-

## is\_debounced

`niswitch.Session.is_debounced`

This property indicates whether the entire switch device has settled since the last switching command. A value of True indicates that all signals going through the switch device are valid.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Is Debounced**
  - C Attribute: **NISWITCH\_ATTR\_IS\_DEBOUNCED**
- 

## is\_scanning

`niswitch.Session.is_scanning`

If True, the switch module is currently scanning through the scan list (i.e. it is not in the Idle state). If False, the switch module is not currently scanning through the scan list (i.e. it is in the Idle state).

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Is Scanning**
  - C Attribute: **NISWITCH\_ATTR\_IS\_SCANNING**
- 

## is\_source\_channel

`niswitch.Session.is_source_channel`

This channel-based property specifies whether you want to identify the channel as a source channel. Typically, you set this property to True when you attach the channel to a power supply, a method generator, or an active measurement point on the unit under test, and you do not want to connect the channel to another source. The driver prevents source channels from connecting to each other. The `niswitch.Session.connect()` method returns the

NISWITCH\_ERROR\_ATTEMPT\_TO\_CONNECT\_SOURCES when you attempt to connect two channels that you identify as source channels.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].is_source_channel = var
var = session.channels[0,1].is_source_channel
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Channel Configuration:Is Source Channel**
- C Attribute: **NISWITCH\_ATTR\_IS\_SOURCE\_CHANNEL**

## is\_waiting\_for\_trig

### `niswitch.Session.is_waiting_for_trig`

In a scan list, a semi-colon (;) is used to indicate that at that point in the scan list, the scan engine should pause until a trigger is received from the trigger input. If that trigger is user generated through either a hardware pulse or the Send SW Trigger operation, it is necessary for the user to know when the scan engine has reached such a state.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read only
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Is Waiting for Trigger?**
- C Attribute: **NISWITCH\_ATTR\_IS\_WAITING\_FOR\_TRIG**

## logical\_name

### `niswitch.Session.logical_name`

A string containing the logical name you specified when opening the current IVI session. You may pass a logical name to the `niswitch.Session.init()` or `niswitch.Session.InitWithOptions()` methods. The IVI Configuration utility must contain an entry for the logical name. The logical name entry refers to a virtual instrument section in the IVI Configuration file. The virtual instrument section specifies a physical device and initial user options.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Advanced Session Information:Logical Name**
  - C Attribute: **NISWITCH\_ATTR\_LOGICAL\_NAME**
- 

## max\_ac\_voltage

### `niswitch.Session.max_ac_voltage`

This channel-based property returns the maximum AC voltage the channel can switch. The units are volts RMS.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].max_ac_voltage
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum AC Voltage**
- C Attribute: **NISWITCH\_ATTR\_MAX\_AC\_VOLTAGE**

## max\_carry\_ac\_current

`niswitch.Session.max_carry_ac_current`

This channel-based property returns the maximum AC current the channel can carry. The units are amperes RMS.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].max_carry_ac_current
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum Carry AC Current**
- C Attribute: **NISWITCH\_ATTR\_MAX\_CARRY\_AC\_CURRENT**

## max\_carry\_ac\_power

`niswitch.Session.max_carry_ac_power`

This channel-based property returns the maximum AC power the channel can carry. The units are volt-amperes.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].max_carry_ac_power
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum Carry AC Power**
  - C Attribute: **NISWITCH\_ATTR\_MAX\_CARRY\_AC\_POWER**
- 

### **max\_carry\_dc\_current**

`niswitch.Session.max_carry_dc_current`

This channel-based property returns the maximum DC current the channel can carry. The units are amperes.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].max_carry_dc_current
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum Carry DC Current**
  - C Attribute: **NISWITCH\_ATTR\_MAX\_CARRY\_DC\_CURRENT**
- 

### **max\_carry\_dc\_power**

`niswitch.Session.max_carry_dc_power`

This channel-based property returns the maximum DC power the channel can carry. The units are watts.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can

specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
var = session.channels[0,1].max_carry_dc_power
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum Carry DC Power**
- C Attribute: **NISWITCH\_ATTR\_MAX\_CARRY\_DC\_POWER**

## max\_dc\_voltage

`niswitch.Session.max_dc_voltage`

This channel-based property returns the maximum DC voltage the channel can switch. The units are volts.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the `set/get` will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling `set/get` value on the result.:

```
var = session.channels[0,1].max_dc_voltage
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum DC Voltage**
- C Attribute: **NISWITCH\_ATTR\_MAX\_DC\_VOLTAGE**

## max\_switching\_ac\_current

`niswitch.Session.max_switching_ac_current`

This channel-based property returns the maximum AC current the channel can switch. The units are amperes RMS.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].max_switching_ac_current
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum Switching AC Current**
  - C Attribute: **NISWITCH\_ATTR\_MAX\_SWITCHING\_AC\_CURRENT**
- 

## max\_switching\_ac\_power

`niswitch.Session.max_switching_ac_power`

This channel-based property returns the maximum AC power the channel can switch. The units are volt-amperes.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].max_switching_ac_power
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No



---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum Switching AC Power**
  - C Attribute: **NISWITCH\_ATTR\_MAX\_SWITCHING\_AC\_POWER**
- 

## max\_switching\_dc\_current

`niswitch.Session.max_switching_dc_current`

This channel-based property returns the maximum DC current the channel can switch. The units are amperes.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].max_switching_dc_current
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum Switching DC Current**
  - C Attribute: **NISWITCH\_ATTR\_MAX\_SWITCHING\_DC\_CURRENT**
- 

## max\_switching\_dc\_power

`niswitch.Session.max_switching_dc_power`

This channel-based property returns the maximum DC power the channel can switch. The units are watts.

---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].max_switching_dc_power
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Maximum Switching DC Power**
  - C Attribute: **NISWITCH\_ATTR\_MAX\_SWITCHING\_DC\_POWER**
- 

## number\_of\_relays

`niswitch.Session.number_of_relays`

This property returns the number of relays.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Number of Relays**
  - C Attribute: **NISWITCH\_ATTR\_NUMBER\_OF\_RELAYS**
- 

## num\_of\_columns

`niswitch.Session.num_of_columns`

This property returns the number of channels on the column of a matrix or scanner. If the switch device is a scanner, this value is the number of input channels. The `niswitch.Session.wire_mode` property affects the number of available columns. For example, if your device has 8 input lines and you use the four-wire mode, then the number of columns you have available is 2.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Matrix Configuration:Number of Columns**
- C Attribute: **NISWITCH\_ATTR\_NUM\_OF\_COLUMNS**

## num\_of\_rows

`niswitch.Session.num_of_rows`

This property returns the number of channels on the row of a matrix or scanner. If the switch device is a scanner, this value is the number of output channels. The `niswitch.Session.wire_mode` property affects the number of available rows. For example, if your device has 8 input lines and you use the two-wire mode, then the number of columns you have available is 4.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Matrix Configuration:Number of Rows**
- C Attribute: **NISWITCH\_ATTR\_NUM\_OF\_ROWS**

## power\_down\_latching\_relays\_after\_debounce

`niswitch.Session.power_down_latching_relays_after_debounce`

This property specifies whether to power down latching relays after calling Wait For Debounce. When Power Down Latching Relays After Debounce is enabled (True), a call to Wait For Debounce ensures that the relays are settled and the latching relays are powered down.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Power Down Latching Relays After Debounce**
- C Attribute: **NISWITCH\_ATTR\_POWER\_DOWN\_LATCHING\_RELAYS\_AFTER\_DEBOUNCE**

## scan\_advanced\_output

`niswitch.Session.scan_advanced_output`

This property specifies the method you want to use to notify another instrument that all signals going through the switch device have settled following the processing of one entry in the scan list.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.ScanAdvancedOutput</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Scan Advanced Output**
  - C Attribute: **NISWITCH\_ATTR\_SCAN\_ADVANCED\_OUTPUT**
- 

## scan\_advanced\_polarity

`niswitch.Session.scan_advanced_polarity`

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.ScanAdvancedPolarity</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Scan Advanced Polarity**
  - C Attribute: **NISWITCH\_ATTR\_SCAN\_ADVANCED\_POLARITY**
- 

## scan\_delay

`niswitch.Session.scan_delay`

This property specifies the minimum amount of time the switch device waits before it asserts the scan advanced output trigger after opening or closing the switch. The switch device always waits for debounce before asserting the trigger. The units are seconds. the greater value of the settling time and the value you specify as the scan delay.

---

**Note:** NI PXI-2501/2503/2565/2590/2591 Users—the actual delay will always be

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or datetime.timedelta
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Scan Delay**
  - C Attribute: **NISWITCH\_ATTR\_SCAN\_DELAY**
- 

## scan\_list

### `niswitch.Session.scan_list`

This property contains a scan list, which is a string that specifies channel connections and trigger conditions. The `niswitch.Session.initiate()` method makes or breaks connections and waits for triggers according to the instructions in the scan list. The scan list is comprised of channel names that you separate with special characters. These special characters determine the operations the scanner performs on the channels when it executes this scan list. To create a path between two channels, use the following character between the two channel names: `->` (a dash followed by a `>` sign) Example: `'CH1->CH2'` tells the switch to make a path from channel CH1 to channel CH2. To break or clear a path, use the following character as a prefix before the path: `~` (tilde) Example: `'~CH1->CH2'` tells the switch to break the path from channel CH1 to channel CH2. To tell the switch device to wait for a trigger event, use the following character as a separator between paths: `;` (semi-colon) Example: `'CH1->CH2;CH3->CH4'` tells the switch to make the path from channel CH1 to channel CH2, wait for a trigger, and then make the path from CH3 to CH4.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Scan List**
  - C Attribute: **NISWITCH\_ATTR\_SCAN\_LIST**
- 

## scan\_mode

### `niswitch.Session.scan_mode`

This property specifies what happens to existing connections that conflict with the connections you make in a scan list. For example, if CH1 is already connected to CH2 and the scan list instructs the switch device to connect CH1 to CH3, this property specifies what happens to the connection between CH1 and CH2. If the value of this property is `NONE`, the switch device takes no action on

existing paths. If the value is `BREAK_BEFORE_MAKE`, the switch device breaks conflicting paths before making new ones. If the value is `BREAK_AFTER_MAKE`, the switch device breaks conflicting paths after making new ones. Most switch devices support only one of the possible values. In such cases, this property serves as an indicator of the device's behavior.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	enums.ScanMode
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Scan Mode**
  - C Attribute: **NISWITCH\_ATTR\_SCAN\_MODE**
- 

## serial\_number

`niswitch.Session.serial_number`

This read-only property returns the serial number for the switch device controlled by this instrument driver. If the device does not return a serial number, the driver returns the `IVI_ERROR_ATTRIBUTE_NOT_SUPPORTED` error.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Serial Number**
  - C Attribute: **NISWITCH\_ATTR\_SERIAL\_NUMBER**
- 

## settling\_time

`niswitch.Session.settling_time`

This channel-based property returns the maximum length of time from after you make a connection

until the signal flowing through the channel settles. The units are seconds. the greater value of the settling time and the value you specify as the scan delay.

---

**Note:** NI PXI-2501/2503/2565/2590/2591 Users—the actual delay will always be

---



---

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
session.channels[0,1].settling_time = var
var = session.channels[0,1].settling_time
```

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float in seconds or <code>datetime.timedelta</code>
Permissions	read-write
Channel Based	True
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics: Settling Time**
  - C Attribute: **NISWITCH\_ATTR\_SETTLING\_TIME**
- 

## simulate

### `niswitch.Session.simulate`

Specifies whether or not to simulate instrument driver I/O operations. If simulation is enabled, instrument driver methods perform range checking and call `Ivi_GetAttribute` and `Ivi_SetAttribute` methods, but they do not perform instrument I/O. For output parameters that represent instrument data, the instrument driver methods return calculated values. The default value is `False`. Use the `niswitch.Session.InitWithOptions()` method to override this value.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	bool
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:User Options:Simulate**
  - C Attribute: **NISWITCH\_ATTR\_SIMULATE**
- 

### **specific\_driver\_description**

`niswitch.Session.specific_driver_description`

A string that contains a brief description of the specific driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Description**
  - C Attribute: **NISWITCH\_ATTR\_SPECIFIC\_DRIVER\_DESCRIPTION**
- 

### **specific\_driver\_revision**

`niswitch.Session.specific_driver_revision`

A string that contains additional version information about this instrument driver.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Revision**
  - C Attribute: **NISWITCH\_ATTR\_SPECIFIC\_DRIVER\_REVISION**
- 

### **specific\_driver\_vendor**

`niswitch.Session.specific_driver_vendor`

A string that contains the name of the vendor that supplies this driver.



The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Identification:Driver Vendor**
  - C Attribute: **NISWITCH\_ATTR\_SPECIFIC\_DRIVER\_VENDOR**
- 

## supported\_instrument\_models

`niswitch.Session.supported_instrument_models`

Contains a comma-separated list of supported instrument models.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Inherent IVI Attributes:Driver Capabilities:Supported Instrument Models**
  - C Attribute: **NISWITCH\_ATTR\_SUPPORTED\_INSTRUMENT\_MODELS**
- 

## temperature

`niswitch.Session.temperature`

This property returns the temperature as read by the Switch module. The units are degrees Celsius.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	float
Permissions	read only
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Temperature**
  - C Attribute: **NISWITCH\_ATTR\_TEMPERATURE**
- 

## trigger\_input

`niswitch.Session.trigger_input`

This property specifies the source of the trigger for which the switch device can wait when processing a scan list. The switch device waits for a trigger when it encounters a semi-colon in a scan list. When the trigger occurs, the switch device advances to the next entry in the scan list.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TriggerInput</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Trigger Input**
  - C Attribute: **NISWITCH\_ATTR\_TRIGGER\_INPUT**
- 

## trigger\_input\_polarity

`niswitch.Session.trigger_input_polarity`

Determines the behavior of the trigger Input.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	<code>enums.TriggerInputPolarity</code>
Permissions	read-write
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Scanning Configuration:Trigger Input Polarity**
  - C Attribute: **NISWITCH\_ATTR\_TRIGGER\_INPUT\_POLARITY**
- 

## wire\_mode

`niswitch.Session.wire_mode`

This property returns the wire mode of the switch device. This property affects the values of the

`niswitch.Session.num_of_rows` and `niswitch.Session.num_of_columns` properties. The actual number of input and output lines on the switch device is fixed, but the number of channels depends on how many lines constitute each channel.

**Tip:** This property can use repeated capabilities (channels). If set or get directly on the `niswitch.Session` object, then the set/get will use all repeated capabilities in the session. You can specify a subset of repeated capabilities using the Python index notation on an `niswitch.Session` repeated capabilities container, and calling set/get value on the result.:

```
var = session.channels[0,1].wire_mode
```

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read only
Channel Based	True
Resettable	No

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- LabVIEW Property: **Module Characteristics:Wire mode**
- C Attribute: **NISWITCH\_ATTR\_WIRE\_MODE**

## Methods

### abort

`niswitch.Session.abort()`

Aborts the scan in progress. Initiate a scan with `niswitch.Session.initiate()`. If the switch module is not scanning, `NISWITCH_ERROR_NO_SCAN_IN_PROGRESS` error is returned.

### can\_connect

`niswitch.Session.can_connect(channel1, channel2)`

Verifies that a path between channel 1 and channel 2 can be created. If a path is possible in the switch module, the availability of that path is returned given the existing connections. If the path is possible but in use, a `NISWITCH_WARN_IMPLICIT_CONNECTION_EXISTS` warning is returned.

#### Parameters

- **channel1** (*str*) – Input one of the channel names of the desired path. Pass the other channel name as the channel 2 parameter. Refer to Devices Overview for valid channel names for the switch module. Examples of valid channel names: `ch0`, `com0`, `ab0`, `r1`, `c2`, `cjtemp` Default value: ""
- **channel2** (*str*) – Input one of the channel names of the desired path. Pass the other channel name as the channel 1 parameter. Refer to Devices Overview for

valid channel names for the switch module. Examples of valid channel names: ch0, com0, ab0, r1, c2, cjtemp Default value: ""

**Return type** `niswitch.PathCapability`

### Returns

Indicates whether a path is valid. Possible values include:

	NISWITCH_VAL_PATH_AVAILABLE	1
NISWITCH_VAL_PATH_EXISTS	2	NISWITCH_VAL_PATH_UNSUPPORTED
NISWITCH_VAL_RSRC_IN_USE	4	NISWITCH_VAL_SOURCE_CONFLICT
5	NISWITCH_VAL_CHANNEL_NOT_AVAILABLE	6

Notes: (1) NISWITCH\_VAL\_PATH\_AVAILABLE indicates that the driver can create the path at this time. (2) NISWITCH\_VAL\_PATH\_EXISTS indicates that the path already exists. (3) NISWITCH\_VAL\_PATH\_UNSUPPORTED indicates that the instrument is not capable of creating a path between the channels you specify. (4) NISWITCH\_VAL\_RSRC\_IN\_USE indicates that although the path is valid, the driver cannot create the path at this moment because the switch device is currently using one or more of the required channels to create another path. You must destroy the other path before creating this one. (5) NISWITCH\_VAL\_SOURCE\_CONFLICT indicates that the instrument cannot create a path because both channels are connected to a different source channel. (6) NISWITCH\_VAL\_CHANNEL\_NOT\_AVAILABLE indicates that the driver cannot create a path between the two channels because one of the channels is a configuration channel and thus unavailable for external connections.

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## commit

`niswitch.Session.commit()`

Downloads the configured scan list and trigger settings to hardware. Calling `niswitch.Session.commit()` optional as it is implicitly called during `niswitch.Session.initiate()`. Use `niswitch.Session.commit()` to arm triggers in a given order or to control when expensive hardware operations are performed.

## connect

`niswitch.Session.connect(channel1, channel2)`

Creates a path between channel 1 and channel 2. The driver calculates and uses the shortest path between the two channels. Refer to Immediate Operations for information about Channel Usage types. If a path is not available, the method returns one of the following errors:

- NISWITCH\_ERROR\_EXPLICIT\_CONNECTION\_EXISTS, if the two channels are already explicitly connected by calling either the `niswitch.Session.connect()` or `niswitch.Session.set_path()` method.
- NISWITCH\_ERROR\_IS\_CONFIGURATION\_CHANNEL, if a channel is a configuration channel. Error elaboration contains information about which of the two channels is a configuration channel.
- NISWITCH\_ERROR\_ATTEMPT\_TO\_CONNECT\_SOURCES, if both channels are connected to a different source. Error elaboration contains information about sources channel 1 and 2 connect to.
- NISWITCH\_ERROR\_CANNOT\_CONNECT\_TO\_ITSELF, if channels 1 and 2 are one and the same channel.
- NISWITCH\_ERROR\_PATH\_NOT\_FOUND, if the driver cannot

find a path between the two channels. Note: Paths are bidirectional. For example, if a path exists between channels CH1 and CH2, then the path also exists between channels CH2 and CH1.

#### Parameters

- **channel1** (*str*) – Input one of the channel names of the desired path. Pass the other channel name as the channel 2 parameter. Refer to Devices Overview for valid channel names for the switch module. Examples of valid channel names: ch0, com0, ab0, r1, c2, cjtemp Default value: None
- **channel2** (*str*) – Input one of the channel names of the desired path. Pass the other channel name as the channel 1 parameter. Refer to Devices Overview for valid channel names for the switch module. Examples of valid channel names: ch0, com0, ab0, r1, c2, cjtemp Default value: None

### connect\_multiple

`niswitch.Session.connect_multiple(connection_list)`

Creates the connections between channels specified in Connection List. Specify connections with two endpoints only or the explicit path between two endpoints. NI-SWITCH calculates and uses the shortest path between the channels. Refer to Setting Source and Configuration Channels for information about channel usage types. In the event of an error, connecting stops at the point in the list where the error occurred. If a path is not available, the method returns one of the following errors: - NISWITCH\_ERROR\_EXPLICIT\_CONNECTION\_EXISTS, if the two channels are already explicitly connected. - NISWITCH\_ERROR\_IS\_CONFIGURATION\_CHANNEL, if a channel is a configuration channel. Error elaboration contains information about which of the two channels is a configuration channel. - NISWITCH\_ERROR\_ATTEMPT\_TO\_CONNECT\_SOURCES, if both channels are connected to a different source. Error elaboration contains information about sources channel 1 and 2 to connect. - NISWITCH\_ERROR\_CANNOT\_CONNECT\_TO\_ITSELF, if channels 1 and 2 are one and the same channel. - NISWITCH\_ERROR\_PATH\_NOT\_FOUND, if the driver cannot find a path between the two channels. Note: Paths are bidirectional. For example, if a path exists between channels ch1 and ch2, then the path also exists between channels ch1 and ch2.

**Parameters connection\_list** (*str*) – Connection List specifies a list of connections between channels to make. NI-SWITCH validates the connection list, and aborts execution of the list if errors are returned. Refer to Connection and Disconnection List Syntax for valid connection list syntax and examples. Refer to Devices Overview for valid channel names for the switch module. Example of a valid connection list: c0 -> r1, [c2 -> r2 -> c3] In this example, r2 is a configuration channel. Default value: None

### disable

`niswitch.Session.disable()`

Places the switch module in a quiescent state where it has minimal or no impact on the system to which it is connected. All channels are disconnected and any scan in progress is aborted.

### disconnect

`niswitch.Session.disconnect(channel1, channel2)`

This method destroys the path between two channels that you create with the `niswitch.Session.connect()` or `niswitch.Session.set_path()` method. If a path is not connected or not available, the method returns the IVISWITCH\_ERROR\_NO\_SUCH\_PATH error.

### Parameters

- **channel1** (*str*) – Input one of the channel names of the path to break. Pass the other channel name as the channel 2 parameter. Refer to Devices Overview for valid channel names for the switch module. Examples of valid channel names: ch0, com0, ab0, r1, c2, cjtemp Default value: None
- **channel2** (*str*) – Input one of the channel names of the path to break. Pass the other channel name as the channel 1 parameter. Refer to Devices Overview for valid channel names for the switch module. Examples of valid channel names: ch0, com0, ab0, r1, c2, cjtemp Default value: None

### disconnect\_all

```
niswitch.Session.disconnect_all()
```

Breaks all existing paths. If the switch module cannot break all paths, NISWITCH\_WARN\_PATH\_REMAINS warning is returned.

### disconnect\_multiple

```
niswitch.Session.disconnect_multiple(disconnection_list)
```

Breaks the connections between channels specified in Disconnection List. If no connections exist between channels, NI-SWITCH returns an error. In the event of an error, the VI stops at the point in the list where the error occurred.

**Parameters** **disconnection\_list** (*str*) – Disconnection List specifies a list of connections between channels to break. NI-SWITCH validates the disconnection list, and aborts execution of the list if errors are returned. Refer to Connection and Disconnection List Syntax for valid disconnection list syntax and examples. Refer to Devices Overview for valid channel names for the switch module. Example of a valid disconnection list: c0 -> r1, [c2 -> r2 -> c3] In this example, r2 is a configuration channel. Default value: None

### get\_channel\_name

```
niswitch.Session.get_channel_name(index)
```

Returns the channel string that is in the channel table at the specified index. Use `niswitch.Session.get_channel_name()` in a For Loop to get a complete list of valid channel names for the switch module. Use the Channel Count property to determine the number of channels.

**Parameters** **index** (*int*) – A 1-based index into the channel table. Default value: 1  
Maximum value: Value of Channel Count property.

### get\_path

```
niswitch.Session.get_path(channel1, channel2)
```

Returns a string that identifies the explicit path created with `niswitch.Session.connect()`. Pass this string to `niswitch.Session.set_path()` to establish the exact same path in future connections. In some cases, multiple paths are available between two channels. When you call `niswitch.Session.connect()`, the driver selects an available path. With `niswitch.Session.connect()`, there is no guarantee that the driver selected path will always be the same path through the switch module. `niswitch.Session.get_path()` only returns those paths

explicitly created by niSwitch Connect Channels or `niswitch.Session.set_path()`. For example, if you connect channels CH1 and CH3, and then channels CH2 and CH3, an explicit path between channels CH1 and CH2 does not exist an error is returned

#### Parameters

- **channel11** (*str*) – Input one of the channel names of the desired path. Pass the other channel name as the channel 2 parameter. Refer to Devices Overview for valid channel names for the switch module. Examples of valid channel names: ch0, com0, ab0, r1, c2, cjtemp Default value: ""
- **channel12** (*str*) – Input one of the channel names of the desired path. Pass the other channel name as the channel 1 parameter. Refer to Devices Overview for valid channel names for the switch module. Examples of valid channel names: ch0, com0, ab0, r1, c2, cjtemp Default value: ""

### get\_relay\_count

`niswitch.Session.get_relay_count(relay_name)`

Returns the number of times the relay has changed from Closed to Open. Relay count is useful for tracking relay lifetime and usage. Call `niswitch.Session.wait_for_debounce()` before `niswitch.Session.get_relay_count()` to ensure an accurate count. Refer to the Relay Count topic in the NI Switches Help to determine if the switch module supports relay counting.

**Parameters** **relay\_name** (*str*) – Name of the relay. Default value: None Examples of valid relay names: ch0, ab0, 1wire, hlselect Refer to Devices Overview for a list of valid relay names for the switch module.

**Return type** `int`

**Returns** The number of relay cycles.

### get\_relay\_name

`niswitch.Session.get_relay_name(index)`

Returns the relay name string that is in the relay list at the specified index. Use `niswitch.Session.get_relay_name()` in a For Loop to get a complete list of valid relay names for the switch module. Use the Number of Relays property to determine the number of relays.

**Parameters** **index** (*int*) – A 1-based index into the channel table. Default value: 1 Maximum value: Value of Channel Count property.

### get\_relay\_position

`niswitch.Session.get_relay_position(relay_name)`

Returns the relay position for the relay specified in the Relay Name parameter.

**Parameters** **relay\_name** (*str*) – Name of the relay. Default value: None Examples of valid relay names: ch0, ab0, 1wire, hlselect Refer to Devices Overview for a list of valid relay names for the switch module.

**Return type** `niswitch.RelayPosition`

**Returns**

Indicates whether the relay is open or closed. NISWITCH\_VAL\_OPEN 10 NI-WITCH\_VAL\_CLOSED 11

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## lock

`niswitch.Session.lock()`

Obtains a multithread lock on the device session. Before doing so, the software waits until all other execution threads release their locks on the device session.

Other threads may have obtained a lock on this session for the following reasons:

- The application called the `niswitch.Session.lock()` method.
- A call to NI-SWITCH locked the session.
- After a call to the `niswitch.Session.lock()` method returns successfully, no other threads can access the device session until you call the `niswitch.Session.unlock()` method or exit out of the with block when using lock context manager.
- Use the `niswitch.Session.lock()` method and the `niswitch.Session.unlock()` method around a sequence of calls to instrument driver methods if you require that the device retain its settings through the end of the sequence.

You can safely make nested calls to the `niswitch.Session.lock()` method within the same thread. To completely unlock the session, you must balance each call to the `niswitch.Session.lock()` method with a call to the `niswitch.Session.unlock()` method.

One method for ensuring there are the same number of unlock method calls as there is lock calls is to use lock as a context manager

```
with niswitch.Session('dev1') as session:
    with session.lock():
        # Calls to session within a single lock context
```

The first `with` block ensures the session is closed regardless of any exceptions raised

The second `with` block ensures that unlock is called regardless of any exceptions raised

**Return type** context manager

**Returns** When used in a `with` statement, `niswitch.Session.lock()` acts as a context manager and unlock will be called when the `with` block is exited

## relay\_control

`niswitch.Session.relay_control(relay_name, relay_action)`

Controls individual relays of the switch. When controlling individual relays, the protection offered by setting the usage of source channels and configuration channels, and by enabling or disabling analog bus sharing on the NI SwitchBlock, does not apply. Refer to the device book for your switch in the NI Switches Help to determine if the switch supports individual relay control.

### Parameters

- **relay\_name** (*str*) – Name of the relay. Default value: None Examples of valid relay names: ch0, ab0, 1wire, hlselect Refer to Devices Overview for a list of valid relay names for the switch module.



- **relay\_action** (*niswitch.RelayAction*) – Specifies whether to open or close a given relay. Default value: Relay Close Defined values: NISWITCH\_VAL\_OPEN\_RELAY NISWITCH\_VAL\_CLOSE\_RELAY (Default Value)

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

## reset

```
niswitch.Session.reset()
```

Disconnects all created paths and returns the switch module to the state at initialization. Configuration channel and source channel settings remain unchanged.

## reset\_with\_defaults

```
niswitch.Session.reset_with_defaults()
```

Resets the switch module and applies initial user specified settings from the logical name used to initialize the session. If the session was created without a logical name, this method is equivalent to *niswitch.Session.reset()*.

## route\_scan\_advanced\_output

```
niswitch.Session.route_scan_advanced_output(scan_advanced_output_connector,
                                             scan_advanced_output_bus_line,
                                             invert=False)
```

Routes the scan advanced output trigger from a trigger bus line (TTLx) to the front or rear connector.

### Parameters

- **scan\_advanced\_output\_connector** (*niswitch.ScanAdvancedOutput*) – The scan advanced trigger destination. Valid locations are the *FRONTCONNECTOR* and *REARCONNECTOR*. Default value: *FRONTCONNECTOR*

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

- **scan\_advanced\_output\_bus\_line** (*niswitch.ScanAdvancedOutput*) – The trigger line to route the scan advanced output trigger from the front or rear connector. Select *NONE* to break an existing route. Default value: None Valid Values: *NONE TTL0 TTL1 TTL2 TTL3 TTL4 TTL5 TTL6 TTL7*

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

- **invert** (*bool*) – If True, inverts the input trigger signal from falling to rising or vice versa. Default value: False

## route\_trigger\_input

`niswitch.Session.route_trigger_input(trigger_input_connector, trigger_input_bus_line, invert=False)`

Routes the input trigger from the front or rear connector to a trigger bus line (TTLx). To disconnect the route, call this method again and specify None for trigger bus line parameter.

### Parameters

- **trigger\_input\_connector** (*niswitch.TriggerInput*) – The location of the input trigger source on the switch module. Valid locations are the *FRONTCONNECTOR* and *REARCONNECTOR*. Default value: *FRONTCONNECTOR*

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

- **trigger\_input\_bus\_line** (*niswitch.TriggerInput*) – The trigger line to route the input trigger. Select *NISWITCH\_VAL\_NONE* to break an existing route. Default value: None Valid Values: *NISWITCH\_VAL\_NONE TTL0 TTL1 TTL2 TTL3 TTL4 TTL5 TTL6 TTL7*

---

**Note:** One or more of the referenced values are not in the Python API for this driver. Enums that only define values, or represent True/False, have been removed.

---

- **invert** (*bool*) – If True, inverts the input trigger signal from falling to rising or vice versa. Default value: False

## self\_test

`niswitch.Session.self_test()`

Verifies that the driver can communicate with the switch module.

Raises *SelfTestError* on self test failure. Properties on exception object:

- `code` - failure code from driver
- `message` - status message from driver

Self-Test Code	Description
0	Passed self-test
1	Self-test failed

## send\_software\_trigger

`niswitch.Session.send_software_trigger()`

Sends a software trigger to the switch module specified in the NI-SWITCH session. When the trigger input is set to *SOFTWARE\_TRIG* through either the `niswitch.Session.ConfigureScanTrigger()` or the `niswitch.Session.trigger_input` property, the scan does not proceed from a semi-colon (wait for trigger) until `niswitch.Session.send_software_trigger()` is called.

---

**Note:** One or more of the referenced methods are not in the Python API for this driver.

---

## set\_path

```
niswitch.Session.set_path(path_list)
```

Connects two channels by specifying an explicit path in the path list parameter. `niswitch.Session.set_path()` is particularly useful where path repeatability is important, such as in calibrated signal paths. If this is not necessary, use `niswitch.Session.connect()`.

**Parameters** `path_list` (*str*) – A string composed of comma-separated paths between channel 1 and channel 2. The first and last names in the path are the endpoints of the path. Every other channel in the path are configuration channels. Example of a valid path list string: `ch0->com0, com0->ab0`. In this example, `com0` is a configuration channel. Default value: None Obtain the path list for a previously created path with `niswitch.Session.get_path()`.

## unlock

```
niswitch.Session.unlock()
```

Releases a lock that you acquired on an device session using `niswitch.Session.lock()`. Refer to `niswitch.Session.unlock()` for additional information on session locks.

## wait\_for\_debounce

```
niswitch.Session.wait_for_debounce(maximum_time_ms=datetime.timedelta(milliseconds=5000))
```

Pauses until all created paths have settled. If the time you specify with the Maximum Time (ms) parameter elapsed before the switch paths have settled, this method returns the `NISWITCH_ERROR_MAX_TIME_EXCEEDED` error.

**Parameters** `maximum_time_ms` (*float in seconds or datetime.timedelta*) – Specifies the maximum length of time to wait for all relays in the switch module to activate or deactivate. If the specified time elapses before all relays active or deactivate, a timeout error is returned. Default Value:5000 ms

## wait\_for\_scan\_complete

```
niswitch.Session.wait_for_scan_complete(maximum_time_ms=datetime.timedelta(milliseconds=5000))
```

Pauses until the switch module stops scanning or the maximum time has elapsed and returns a timeout error. If the time you specify with the Maximum Time (ms) parameter elapsed before the scanning operation has finished, this method returns the `NISWITCH_ERROR_MAX_TIME_EXCEEDED` error.

**Parameters** `maximum_time_ms` (*float in seconds or datetime.timedelta*) – Specifies the maximum length of time to wait for the switch module to stop scanning. If the specified time elapses before the scan ends, `NISWITCH_ERROR_MAX_TIME_EXCEEDED` error is returned. Default Value:5000 ms

## Properties

Property	Datatype
<code>niswitch.Session.analog_bus_sharing_enable</code>	bool
<code>niswitch.Session.bandwidth</code>	float
<code>niswitch.Session.channel_count</code>	int
<code>niswitch.Session.characteristic_impedance</code>	float
<code>niswitch.Session.continuous_scan</code>	bool
<code>niswitch.Session.digital_filter_enable</code>	bool
<code>niswitch.Session.driver_setup</code>	str
<code>niswitch.Session.handshaking_initiation</code>	HandshakingInitiation
<code>niswitch.Session.instrument_firmware_revision</code>	str
<code>niswitch.Session.instrument_manufacturer</code>	str
<code>niswitch.Session.instrument_model</code>	str
<code>niswitch.Session.io_resource_descriptor</code>	str
<code>niswitch.Session.is_configuration_channel</code>	bool
<code>niswitch.Session.is_debounced</code>	bool
<code>niswitch.Session.is_scanning</code>	bool
<code>niswitch.Session.is_source_channel</code>	bool
<code>niswitch.Session.is_waiting_for_trig</code>	bool
<code>niswitch.Session.logical_name</code>	str
<code>niswitch.Session.max_ac_voltage</code>	float
<code>niswitch.Session.max_carry_ac_current</code>	float
<code>niswitch.Session.max_carry_ac_power</code>	float
<code>niswitch.Session.max_carry_dc_current</code>	float
<code>niswitch.Session.max_carry_dc_power</code>	float
<code>niswitch.Session.max_dc_voltage</code>	float
<code>niswitch.Session.max_switching_ac_current</code>	float
<code>niswitch.Session.max_switching_ac_power</code>	float
<code>niswitch.Session.max_switching_dc_current</code>	float
<code>niswitch.Session.max_switching_dc_power</code>	float
<code>niswitch.Session.number_of_relays</code>	int
<code>niswitch.Session.num_of_columns</code>	int
<code>niswitch.Session.num_of_rows</code>	int
<code>niswitch.Session.power_down_latching_relays_after_debounce</code>	bool
<code>niswitch.Session.scan_advanced_output</code>	ScanAdvancedOutput
<code>niswitch.Session.scan_advanced_polarity</code>	ScanAdvancedPolarity
<code>niswitch.Session.scan_delay</code>	float in seconds or datetime.timedelta
<code>niswitch.Session.scan_list</code>	str
<code>niswitch.Session.scan_mode</code>	ScanMode
<code>niswitch.Session.serial_number</code>	str
<code>niswitch.Session.settling_time</code>	float in seconds or datetime.timedelta
<code>niswitch.Session.simulate</code>	bool
<code>niswitch.Session.specific_driver_description</code>	str
<code>niswitch.Session.specific_driver_revision</code>	str
<code>niswitch.Session.specific_driver_vendor</code>	str
<code>niswitch.Session.supported_instrument_models</code>	str
<code>niswitch.Session.temperature</code>	float
<code>niswitch.Session.trigger_input</code>	TriggerInput
<code>niswitch.Session.trigger_input_polarity</code>	TriggerInputPolarity

Continued on next page

Table 16 – continued from previous page

Property	Datatype
<code>niswitch.Session.wire_mode</code>	int

## Methods

Method name
<code>niswitch.Session.abort()</code>
<code>niswitch.Session.can_connect()</code>
<code>niswitch.Session.commit()</code>
<code>niswitch.Session.connect()</code>
<code>niswitch.Session.connect_multiple()</code>
<code>niswitch.Session.disable()</code>
<code>niswitch.Session.disconnect()</code>
<code>niswitch.Session.disconnect_all()</code>
<code>niswitch.Session.disconnect_multiple()</code>
<code>niswitch.Session.get_channel_name()</code>
<code>niswitch.Session.get_path()</code>
<code>niswitch.Session.get_relay_count()</code>
<code>niswitch.Session.get_relay_name()</code>
<code>niswitch.Session.get_relay_position()</code>
<code>niswitch.Session.lock()</code>
<code>niswitch.Session.relay_control()</code>
<code>niswitch.Session.reset()</code>
<code>niswitch.Session.reset_with_defaults()</code>
<code>niswitch.Session.route_scan_advanced_output()</code>
<code>niswitch.Session.route_trigger_input()</code>
<code>niswitch.Session.self_test()</code>
<code>niswitch.Session.send_software_trigger()</code>
<code>niswitch.Session.set_path()</code>
<code>niswitch.Session.unlock()</code>
<code>niswitch.Session.wait_for_debounce()</code>
<code>niswitch.Session.wait_for_scan_complete()</code>

### 7.5.3.2 Enums

Enums used in NI-SWITCH

## HandshakingInitiation

```
class niswitch.HandshakingInitiation
```

### MEASUREMENT\_DEVICE

The `niSwitch Initiate Scan` [<switchviref.chm::/py:meth:'niswitch.Session.Initiate\\_Scan.html'>\\_\\_VI](#) does not return until the switch hardware is waiting for a trigger input. This ensures that if you initiate the measurement device after calling the `niSwitch Initiate Scan` [<switchviref.chm::/py:meth:'niswitch.Session.Initiate\\_Scan.html'>\\_\\_VI](#), the switch is sure to receive the first measurement complete (MC) signal sent by the measurement device. The measurement

device should be configured to first take a measurement, send MC, then wait for scanner advanced output signal. Thus, the first MC of the measurement device initiates handshaking.

**SWITCH**

The *niSwitch Initiate Scan* <switchviref.chm::/py:meth:'niswitch.Session.Initiate\_Scan.html'>\_\_ VI returns immediately after beginning scan list execution. It is assumed that the measurement device has already been configured and is waiting for the scanner advanced signal. The measurement should be configured to first wait for a trigger, then take a measurement. Thus, the first scanner advanced output signal of the switch module initiates handshaking.

**PathCapability**

```
class niswitch.PathCapability
```

**PATH\_AVAILABLE**

Path Available

**PATH\_EXISTS**

Path Exists

**PATH\_UNSUPPORTED**

Path Unsupported

**RESOURCE\_IN\_USE**

Resource in use

**SOURCE\_CONFLICT**

Source conflict

**CHANNEL\_NOT\_AVAILABLE**

Channel not available

**RelayAction**

```
class niswitch.RelayAction
```

**OPEN**

Open Relay

**CLOSE**

Close Relay

**RelayPosition**

```
class niswitch.RelayPosition
```

**OPEN**

Open

**CLOSED**

Closed

## ScanAdvancedOutput

```
class niswitch.ScanAdvancedOutput
```

**NONE**

The switch device does not produce a Scan Advanced Output trigger.

**EXTERNAL**

External Trigger. The switch device produces the Scan Advanced Output trigger on the external trigger output.

**TTL0**

The switch device produces the Scan Advanced Output on the PXI TRIG0 line.

**TTL1**

The switch device produces the Scan Advanced Output on the PXI TRIG1 line.

**TTL2**

The switch device produces the Scan Advanced Output on the PXI TRIG2 line.

**TTL3**

The switch device produces the Scan Advanced Output on the PXI TRIG3 line.

**TTL4**

The switch device produces the Scan Advanced Output on the PXI TRIG4 line.

**TTL5**

The switch device produces the Scan Advanced Output on the PXI TRIG5 line.

**TTL6**

The switch device produces the Scan Advanced Output on the PXI TRIG6 line.

**TTL7**

The switch device produces the Scan Advanced Output on the PXI TRIG7 line.

**PXI\_STAR**

The switch module produces the Scan Advanced Output Trigger on the PXI Star trigger bus before processing the next entry in the scan list.

**REARCONNECTOR**

The switch device produces the Scan Advanced Output trigger on the rear connector.

**FRONTCONNECTOR**

The switch device produces the Scan Advanced Output trigger on the front connector.

**REARCONNECTOR\_MODULE1**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 1.

**REARCONNECTOR\_MODULE2**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 2.

**REARCONNECTOR\_MODULE3**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 3.

**REARCONNECTOR\_MODULE4**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 4.

**REARCONNECTOR\_MODULE5**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 5.

**REARCONNECTOR\_MODULE6**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 6.

#### **REARCONNECTOR\_MODULE7**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 7.

#### **REARCONNECTOR\_MODULE8**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 8.

#### **REARCONNECTOR\_MODULE9**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 9.

#### **REARCONNECTOR\_MODULE10**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 10.

#### **REARCONNECTOR\_MODULE11**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 11.

#### **REARCONNECTOR\_MODULE12**

The switch module produces the Scan Advanced Output Trigger on the rear connector module 12.

#### **FRONTCONNECTOR\_MODULE1**

The switch module produces the Scan Advanced Output Trigger on the front connector module 1.

#### **FRONTCONNECTOR\_MODULE2**

The switch module produces the Scan Advanced Output Trigger on the front connector module 2.

#### **FRONTCONNECTOR\_MODULE3**

The switch module produces the Scan Advanced Output Trigger on the front connector module 3.

#### **FRONTCONNECTOR\_MODULE4**

The switch module produces the Scan Advanced Output Trigger on the front connector module 4.

#### **FRONTCONNECTOR\_MODULE5**

The switch module produces the Scan Advanced Output Trigger on the front connector module 5.

#### **FRONTCONNECTOR\_MODULE6**

The switch module produces the Scan Advanced Output Trigger on the front connector module 6.

#### **FRONTCONNECTOR\_MODULE7**

The switch module produces the Scan Advanced Output Trigger on the front connector module 7.

#### **FRONTCONNECTOR\_MODULE8**

The switch module produces the Scan Advanced Output Trigger on the front connector module 8.

#### **FRONTCONNECTOR\_MODULE9**

The switch module produces the Scan Advanced Output Trigger on the front connector module 9.

#### **FRONTCONNECTOR\_MODULE10**

The switch module produces the Scan Advanced Output Trigger on the front connector module 10.

#### **FRONTCONNECTOR\_MODULE11**

The switch module produces the Scan Advanced Output Trigger on the front connector module 11.

#### **FRONTCONNECTOR\_MODULE12**

The switch module produces the Scan Advanced Output Trigger on the front connector module 12.

## **ScanAdvancedPolarity**

```
class niswitch.ScanAdvancedPolarity
```

#### **RISING**

The trigger occurs on the rising edge of the signal.



**FALLING**

The trigger occurs on the falling edge of the signal.

**ScanMode**

```
class niswitch.ScanMode
```

**NONE**

No implicit action on connections when scanning.

**BREAK\_BEFORE\_MAKE**

When scanning, the switch device breaks existing connections before making new connections.

**BREAK\_AFTER\_MAKE**

When scanning, the switch device breaks existing connections after making new connections.

**TriggerInput**

```
class niswitch.TriggerInput
```

**IMMEDIATE**

Immediate Trigger. The switch device does not wait for a trigger before processing the next entry in the scan list.

**EXTERNAL**

External Trigger. The switch device waits until it receives a trigger from an external source through the external trigger input before processing the next entry in the scan list.

**SOFTWARE\_TRIG**

The switch device waits until you call the `niswitch.Session.send_software_trigger()` method before processing the next entry in the scan list.

**TTL0**

The switch device waits until it receives a trigger on the PXI TRIG0 line before processing the next entry in the scan list.

**TTL1**

The switch device waits until it receives a trigger on the PXI TRIG1 line before processing the next entry in the scan list.

**TTL2**

The switch device waits until it receives a trigger on the PXI TRIG2 line before processing the next entry in the scan list.

**TTL3**

The switch device waits until it receives a trigger on the PXI TRIG3 line before processing the next entry in the scan list.

**TTL4**

The switch device waits until it receives a trigger on the PXI TRIG4 line before processing the next entry in the scan list.

**TTL5**

The switch device waits until it receives a trigger on the PXI TRIG5 line before processing the next entry in the scan list.

**TTL6**

The switch device waits until it receives a trigger on the PXI TRIG6 line before processing the next entry in the scan list.

**TTL7**

The switch device waits until it receives a trigger on the PXI TRIG7 line before processing the next entry in the scan list.

**PXI\_STAR**

The switch device waits until it receives a trigger on the PXI STAR trigger bus before processing the next entry in the scan list.

**REARCONNECTOR**

The switch device waits until it receives a trigger on the rear connector.

**FRONTCONNECTOR**

The switch device waits until it receives a trigger on the front connector.

**REARCONNECTOR\_MODULE1**

The switch module waits until it receives a trigger on the rear connector module 1.

**REARCONNECTOR\_MODULE2**

The switch module waits until it receives a trigger on the rear connector module 2.

**REARCONNECTOR\_MODULE3**

The switch module waits until it receives a trigger on the rear connector module 3.

**REARCONNECTOR\_MODULE4**

The switch module waits until it receives a trigger on the rear connector module 4.

**REARCONNECTOR\_MODULE5**

The switch module waits until it receives a trigger on the rear connector module 5.

**REARCONNECTOR\_MODULE6**

The switch module waits until it receives a trigger on the rear connector module 6.

**REARCONNECTOR\_MODULE7**

The switch module waits until it receives a trigger on the rear connector module 7.

**REARCONNECTOR\_MODULE8**

The switch module waits until it receives a trigger on the rear connector module 8.

**REARCONNECTOR\_MODULE9**

The switch module waits until it receives a trigger on the rear connector module 9.

**REARCONNECTOR\_MODULE10**

The switch module waits until it receives a trigger on the rear connector module 10.

**REARCONNECTOR\_MODULE11**

The switch module waits until it receives a trigger on the rear connector module 11.

**REARCONNECTOR\_MODULE12**

The switch module waits until it receives a trigger on the rear connector module 12.

**FRONTCONNECTOR\_MODULE1**

The switch module waits until it receives a trigger on the front connector module 1.

**FRONTCONNECTOR\_MODULE2**

The switch module waits until it receives a trigger on the front connector module 2.

**FRONTCONNECTOR\_MODULE3**

The switch module waits until it receives a trigger on the front connector module 3.

#### **FRONTCONNECTOR\_MODULE4**

The switch module waits until it receives a trigger on the front connector module 4.

#### **FRONTCONNECTOR\_MODULE5**

The switch module waits until it receives a trigger on the front connector module 5.

#### **FRONTCONNECTOR\_MODULE6**

The switch module waits until it receives a trigger on the front connector module 6.

#### **FRONTCONNECTOR\_MODULE7**

The switch module waits until it receives a trigger on the front connector module 7.

#### **FRONTCONNECTOR\_MODULE8**

The switch module waits until it receives a trigger on the front connector module 8.

#### **FRONTCONNECTOR\_MODULE9**

The switch module waits until it receives a trigger on the front connector module 9.

#### **FRONTCONNECTOR\_MODULE10**

The switch module waits until it receives a trigger on the front connector module 10.

#### **FRONTCONNECTOR\_MODULE11**

The switch module waits until it receives a trigger on the front connector module 11.

#### **FRONTCONNECTOR\_MODULE12**

The switch module waits until it receives a trigger on the front connector module 12.

### TriggerInputPolarity

```
class niswitch.TriggerInputPolarity
```

#### **RISING**

The trigger occurs on the rising edge of the signal.

#### **FALLING**

The trigger occurs on the falling edge of the signal.

### 7.5.3.3 Exceptions and Warnings

#### DriverError

```
exception niswitch.DriverError
```

An error originating from the NI-SWITCH driver

#### UnsupportedConfigurationError

```
exception niswitch.UnsupportedConfigurationError
```

An error due to using this module in an unsupported platform.

#### DriverNotInstalledError

```
exception niswitch.DriverNotInstalledError
```

An error due to using this module without the driver runtime installed.

## InvalidRepeatedCapabilityError

**exception** `niswitch.InvalidRepeatedCapabilityError`

An error due to an invalid character in a repeated capability

## SelfTestError

**exception** `niswitch.SelfTestError`

An error due to a failed self-test

## DriverWarning

**exception** `niswitch.DriverWarning`

A warning originating from the NI-SWITCH driver

## 7.5.3.4 Examples

### `niswitch_connect_channels.py`

Listing 11: (`niswitch_connect_channels.py`)

```

1  #!/usr/bin/python
2
3  import argparse
4  import niswitch
5  import sys
6
7
8  def example(resource_name, channel1, channel2, topology, simulate):
9      # if we are simulating resource name must be blank
10     resource_name = '' if simulate else resource_name
11
12     with niswitch.Session(resource_name=resource_name, topology=topology,
13 ↪ simulate=simulate) as session:
14         session.connect(channel1=channel1, channel2=channel2)
15         print('Channel ', channel1, ' and ', channel2, ' are now connected.')
16         session.disconnect(channel1=channel1, channel2=channel2)
17         print('Channel ', channel1, ' and ', channel2, ' are now disconnected.')
18
19 def _main(argv):
20     parser = argparse.ArgumentParser(description='Performs a connection with NI-
21 ↪ SWITCH Channels.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)
22     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource
23 ↪ name of a National Instruments Switch.')
24     parser.add_argument('-ch1', '--channel1', default='c0', help='Channel One.')
25     parser.add_argument('-ch2', '--channel2', default='r0', help='Channel Two.')
26     parser.add_argument('-t', '--topology', default='Configured Topology', help=
27 ↪ 'Topology.')
28     parser.add_argument('-s', '--simulate', default=False, action='store_true', help=
29 ↪ 'Simulate device.')
30     args = parser.parse_args(argv)

```

(continues on next page)

(continued from previous page)

```

27     example(args.resource_name, args.channel1, args.channel2, args.topology, args.
    ↪simulate)
28
29
30 def test_example():
31     example('', 'c0', 'r0', '2737/2-Wire 4x64 Matrix', True)
32
33
34 def test_main():
35     cmd_line = ['--topology', '2737/2-Wire 4x64 Matrix', '--simulate']
36     _main(cmd_line)
37
38
39 def main():
40     _main(sys.argv[1:])
41
42
43 if __name__ == '__main__':
44     main()
45
46

```

## niswitch\_get\_device\_info.py

Listing 12: (niswitch\_get\_device\_info.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import niswitch
5  import sys
6
7
8  def example(resource_name, topology, simulate, device, channel, relay):
9      # if we are simulating resource name must be blank
10     resource_name = '' if simulate else resource_name
11
12     with niswitch.Session(resource_name=resource_name, topology=topology,
    ↪simulate=simulate) as session:
13         if device:
14             print('Device Info:')
15             row_format = '{:<18}' * (2)
16             print(row_format.format('Device Name: ', session.io_resource_descriptor))
17             print(row_format.format('Device Model: ', session.instrument_model))
18             print(row_format.format('Driver Revision: ', session.specific_driver_
    ↪revision))
19             print(row_format.format('Channel count: ', session.channel_count))
20             print(row_format.format('Relay count: ', session.number_of_relays))
21         if channel:
22             print('Channel Info:')
23             row_format = '{:6}' + ' ' * 12 + '{:<15}{:<22}{:6}'
24             print(row_format.format('Number', 'Name', 'Is Configuration', 'Is Source
    ↪'))
25             for i in range(1, session.channel_count + 1):

```

(continues on next page)

(continued from previous page)

```

26         channel_name = session.get_channel_name(index=i)
27         channel = session.channels[channel_name]
28         print(row_format.format(i, channel_name, str(channel.is_configuration_
↪channel), str(channel.is_source_channel)))
29     if relay:
30         print('Realy Info:')
31         row_format = '{:6}' + ' ' * 12 + '{:<15}{:<22}{:6}'
32         print(row_format.format('Number', 'Name', 'Position', 'Count'))
33         for i in range(1, session.number_of_relays + 1):
34             relay_name = session.get_relay_name(index=i)
35             print(row_format.format(i, relay_name, session.get_relay_
↪position(relay_name=relay_name), session.get_relay_count(relay_name=relay_name)))
36
37
38 def _main(argv):
39     parser = argparse.ArgumentParser(description='Prints information for the_
↪specified National Instruments Switch module.', formatter_class=argparse.
↪ArgumentDefaultsHelpFormatter)
40     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
↪name of a National Instruments Switch.')
41     parser.add_argument('-d', '--device', default=False, action='store_true', help=
↪'Prints information for the device')
42     parser.add_argument('-c', '--channel', default=False, action='store_true', help=
↪'Prints information for all relays on the device')
43     parser.add_argument('-r', '--relay', default=False, action='store_true', help=
↪'Prints information for all channels on the device')
44     parser.add_argument('-t', '--topology', default='Configured Topology', help=
↪'Topology.')
45     parser.add_argument('-s', '--simulate', default=False, action='store_true', help=
↪'Simulate device.')
46     args = parser.parse_args(argv)
47
48     if not (args.device or args.channel or args.relay):
49         parser.print_help()
50         sys.exit(1)
51
52     example(args.resource_name, args.topology, args.simulate, args.device, args.
↪channel, args.relay)
53
54
55 def test_example():
56     example('', '2737/2-Wire 4x64 Matrix', True, True, True, True)
57
58
59 def test_main():
60     cmd_line = ['--topology', '2737/2-Wire 4x64 Matrix', '--simulate', '--device', '--
↪channel', '--relay', ]
61     _main(cmd_line)
62
63
64 def main():
65     _main(sys.argv[1:])
66
67
68 if __name__ == '__main__':
69     main()
70

```

(continues on next page)

(continued from previous page)

## niswitch\_relay\_control.py

Listing 13: (niswitch\_relay\_control.py)

```

1  #!/usr/bin/python
2
3  import argparse
4  import niswitch
5  import sys
6
7
8  def example(resource_name, topology, simulate, relay, action):
9      # if we are simulating resource name must be blank
10     resource_name = '' if simulate else resource_name
11
12     with niswitch.Session(resource_name=resource_name, topology=topology,
13 ↪ simulate=simulate) as session:
14         session.relay_control(relay_name=relay, relay_action=niswitch.
15 ↪ RelayAction[action])
16         print('Relay ', relay, ' has had the action ', action, ' performed.')
17
18 def _main(argv):
19     parser = argparse.ArgumentParser(description='Performs relay control with NI-
20 ↪ SWITCH relays.', formatter_class=argparse.ArgumentDefaultsHelpFormatter)
21     parser.add_argument('-n', '--resource-name', default='PXI1Slot2', help='Resource_
22 ↪ name of a National Instruments Switch.')
23     parser.add_argument('-r', '--relay', default='k0', help='Relay Name.')
24     parser.add_argument('-a', '--action', default='OPEN', choices=niswitch.
25 ↪ RelayAction.__members__.keys(), type=str.upper, help='Relay Action.')
26     parser.add_argument('-t', '--topology', default='Configured Topology', help=
27 ↪ 'Topology.')
28     parser.add_argument('-s', '--simulate', default=False, action='store_true', help=
29 ↪ 'Simulate device.')
30     args = parser.parse_args(argv)
31     example(args.resource_name, args.topology, args.simulate, args.relay, args.action)
32
33 def test_example():
34     example('', '2737/2-Wire 4x64 Matrix', True, 'kr0c0', 'OPEN')
35
36 def test_main():
37     cmd_line = ['--topology', '2737/2-Wire 4x64 Matrix', '--simulate', '--relay',
38 ↪ 'kr0c0']
39     _main(cmd_line)
40
41 def main():
42     _main(sys.argv[1:])

```

(continues on next page)

(continued from previous page)

```

41 if __name__ == '__main__':
42     main()
43
44

```

## 7.6 nimodinst module

### 7.6.1 Installation

As a prerequisite to using the nimodinst module, you must install the NI-ModInst runtime on your system. Visit [ni.com/downloads](http://ni.com/downloads) to download the driver runtime for your devices.

The nimi-python modules (i.e. for **NI-ModInst**) can be installed with [pip](#):

```
$ python -m pip install nimodinst~=1.0.0
```

Or `easy_install` from [setuptools](#):

```
$ python -m easy_install nimodinst
```

### 7.6.2 Usage

The following is a basic example of using the **nimodinst** module to retrieve information on all High Speed Digitizers currently in the system.

```

import nimodinst
with nimodinst.Session("niscope") as session:
    for device in session:
        print("{: >20} {: >15} {: >10}".format(device.device_name, device.device_
↵model, device.serial_number))

```

Additional examples for NI-ModInst are located in `src/nimodinst/examples/` directory.

### 7.6.3 API Reference

#### 7.6.3.1 nimodinst.Session

**class** `nimodinst.Session`(*self*, *driver*)

Creates a handle to a list of installed devices supported by the specified driver. Call this method and pass in the name of a National Instruments instrument driver, such as “NI-SCOPE”. This method searches the system and constructs a list of all the installed devices that are supported by that driver, and then returns both a handle to this list and the number of devices found. The handle is used with other methods to query for properties such as device name and model, and to safely discard the list when finished. Note This handle reflects the system state when the handle is created (that is, when you call this method. If you remove devices from the system or rename them in Measurement & Automation Explorer (MAX), this handle may not refer to an accurate list of devices. You should destroy the handle using `nimodinst.Session._close_installed_devices_session()` and create a new handle using this method.

**Parameters** **driver** (*str*) – A string specifying the driver whose supported devices you want to find. This string is not case-sensitive. Some examples are: NI-SCOPE niScope NI-FGEN niFgen



NI-HSDIO niHSDIO NI-DMM niDMM NI-SWITCH niSwitch Note If you use the empty string for this parameter, NI-ModInst creates a list of all Modular Instruments devices installed in the system.

## Properties

Property	Datatype
<i>bus_number</i>	int
<i>chassis_number</i>	int
<i>device_model</i>	str
<i>device_name</i>	str
<i>max_pciexpress_link_width</i>	int
<i>pciexpress_link_width</i>	int
<i>serial_number</i>	str
<i>slot_number</i>	int
<i>socket_number</i>	int

## Public methods

Method name
Method name

## Properties

### bus\_number

`nimodinst.Session.bus_number`

The bus on which the device has been enumerated.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_BUS\_NUMBER**
- 

### chassis\_number

`nimodinst.Session.chassis_number`

The number of the chassis in which the device is installed. This property can only be queried for PXI devices installed in a chassis that has been properly identified in MAX.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_CHASSIS\_NUMBER**
- 

## device\_model

`nimodinst.Session.device_model`

The model of the device (for example, NI PXI-5122)

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_DEVICE\_MODEL**
- 

## device\_name

`nimodinst.Session.device_name`

The name of the device, which can be used to open an instrument driver session for that device

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_DEVICE\_NAME**
-

## max\_pciexpress\_link\_width

```
nimodinst.Session.max_pciexpress_link_width
```

**MAX\_PCIEXPRESS\_LINK\_WIDTH**

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_MAX\_PCIEXPRESS\_LINK\_WIDTH**
- 

## pciexpress\_link\_width

```
nimodinst.Session.pciexpress_link_width
```

**PCIEXPRESS\_LINK\_WIDTH**

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_PCIEXPRESS\_LINK\_WIDTH**
- 

## serial\_number

```
nimodinst.Session.serial_number
```

The serial number of the device

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	str
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_SERIAL\_NUMBER**
- 

## slot\_number

`nimodinst.Session.slot_number`

The slot (for example, in a PXI chassis) in which the device is installed. This property can only be queried for PXI devices installed in a chassis that has been properly identified in MAX.

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_SLOT\_NUMBER**
- 

## socket\_number

`nimodinst.Session.socket_number`

The socket number on which the device has been enumerated

The following table lists the characteristics of this property.

Characteristic	Value
Datatype	int
Permissions	read
Channel Based	False
Resettable	No

---

**Tip:** This property corresponds to the following LabVIEW Property or C Attribute:

- C Attribute: **NIMODINST\_ATTR\_SOCKET\_NUMBER**
-

## Methods

## Properties

Property	Datatype
<code>nimodinst.Session.bus_number</code>	int
<code>nimodinst.Session.chassis_number</code>	int
<code>nimodinst.Session.device_model</code>	str
<code>nimodinst.Session.device_name</code>	str
<code>nimodinst.Session.max_pciexpress_link_width</code>	int
<code>nimodinst.Session.pciexpress_link_width</code>	int
<code>nimodinst.Session.serial_number</code>	str
<code>nimodinst.Session.slot_number</code>	int
<code>nimodinst.Session.socket_number</code>	int

## Methods

Method name
Method name

### 7.6.3.2 Exceptions and Warnings

#### DriverError

**exception** `nimodinst.DriverError`  
An error originating from the NI-ModInst driver

#### UnsupportedConfigurationError

**exception** `nimodinst.UnsupportedConfigurationError`  
An error due to using this module in an unsupported platform.

#### DriverNotInstalledError

**exception** `nimodinst.DriverNotInstalledError`  
An error due to using this module without the driver runtime installed.

#### InvalidRepeatedCapabilityError

**exception** `nimodinst.InvalidRepeatedCapabilityError`  
An error due to an invalid character in a repeated capability

## SelfTestError

**exception** `nimodinst.SelfTestError`  
An error due to a failed self-test

## DriverWarning

**exception** `nimodinst.DriverWarning`  
A warning originating from the NI-ModInst driver

### 7.6.3.3 Examples

#### `nimodinst_all_devices.py`

Listing 14: (`nimodinst_all_devices.py`)

```
1  #!/usr/bin/python
2
3  import nimodinst
4
5
6  def example():
7      with nimodinst.Session('') as session:
8          if len(session) > 0:
9              print("%d items" % len(session))
10             print("{: >20} {: >15} {: >10}".format('Name', 'Model', 'S/N'))
11             for d in session:
12                 print("{: >20} {: >15} {: >10}".format(d.device_name, d.device_model, d.
13                 ↪serial_number))
14
15  def _main():
16      example()
17
18
19  def test_example():
20      example()
21
22
23  if __name__ == '__main__':
24      _main()
25
26
```

## CHAPTER 8

---

### Indices and tables

---

- `genindex`
- `modindex`
- `search`





### n

- nidcpower, [14](#)
- nidmm, [123](#)
- nifgen, [191](#)
- nimodinst, [428](#)
- niscopes, [293](#)
- niswitch, [379](#)



## A

- abort() (in module nidcpower.Session), 98
- abort() (in module nidmm.Session), 159
- abort() (in module nifgen.Session), 251
- abort() (in module niscopes.Session), 347
- abort() (in module niswitch.Session), 407
- absolute\_sample\_clock\_offset (in module niscopes.Session), 298
- AC (nidmm.WaveformCoupling attribute), 186
- AC (niscopes.TriggerCoupling attribute), 370
- AC (niscopes.VerticalCoupling attribute), 371
- AC\_CURRENT (nidmm.Function attribute), 181
- ac\_max\_freq (in module nidmm.Session), 127
- ac\_min\_freq (in module nidmm.Session), 128
- AC\_PLUS\_HF\_REJECT (niscopes.TriggerCoupling attribute), 370
- AC\_VOLTS (nidmm.Function attribute), 181
- AC\_VOLTS\_DC\_COUPLED (nidmm.Function attribute), 181
- accessory\_gain (in module niscopes.Session), 298
- accessory\_offset (in module niscopes.Session), 299
- acq\_arm\_source (in module niscopes.Session), 300
- acquisition\_start\_time (in module niscopes.Session), 300
- acquisition\_status() (in module niscopes.Session), 347
- acquisition\_type (in module niscopes.Session), 300
- AcquisitionStatus (class in nidmm), 179
- AcquisitionStatus (class in niscopes), 367
- AcquisitionType (class in niscopes), 367
- adc\_calibration (in module nidmm.Session), 128
- ADCCalibration (class in nidmm), 179
- adv\_trig\_src (in module niscopes.Session), 301
- ADVANCE (niscopes.WhichTrigger attribute), 373
- all\_marker\_events\_latched\_status (in module nifgen.Session), 196
- all\_marker\_events\_live\_status (in module nifgen.Session), 197
- allocate\_named\_waveform() (in module nifgen.Session), 251
- allocate\_waveform() (in module nifgen.Session), 251
- allow\_more\_records\_than\_memory (in module niscopes.Session), 301
- analog\_bus\_sharing\_enable (in module niswitch.Session), 383
- analog\_data\_mask (in module nifgen.Session), 197
- ANALOG\_DETECTION\_CIRCUIT (niscopes.RefTriggerDetectorLocation attribute), 369
- analog\_filter\_enabled (in module nifgen.Session), 198
- analog\_path (in module nifgen.Session), 198
- analog\_static\_value (in module nifgen.Session), 198
- AnalogPath (class in nifgen), 280
- ANY\_FIELD (niscopes.VideoTriggerEvent attribute), 373
- ANY\_LINE (niscopes.VideoTriggerEvent attribute), 373
- aperture\_time (in module nidcpower.Session), 18
- aperture\_time (in module nidmm.Session), 128
- aperture\_time\_units (in module nidcpower.Session), 19
- aperture\_time\_units (in module nidmm.Session), 129
- ApertureTimeUnits (class in nidcpower), 115
- ApertureTimeUnits (class in nidmm), 180
- ARB (nifgen.OutputMode attribute), 282
- arb\_gain (in module nifgen.Session), 199
- arb\_marker\_position (in module nifgen.Session), 199
- arb\_offset (in module nifgen.Session), 200
- arb\_repeat\_count (in module nifgen.Session), 201
- arb\_sample\_rate (in module nifgen.Session), 201
- arb\_sequence\_handle (in module nifgen.Session), 201
- arb\_waveform\_handle (in module nifgen.Session), 202
- arm\_ref\_trig\_src (in module niscopes.Session), 302
- ARM\_REFERENCE (niscopes.WhichTrigger attribute), 373
- ASYMMETRIC (nidcpower.ComplianceLimitSymmetry attribute), 115
- AT (nifgen.BusType attribute), 281
- AUTO (nidmm.ADCCalibration attribute), 179
- AUTO (nidmm.AutoZero attribute), 180
- AUTO (nidmm.DCNoiseRejection attribute), 181
- AUTO (nidmm.LCCalculationModel attribute), 182
- AUTO (niscopes.TriggerModifier attribute), 370
- auto\_range\_value (in module nidmm.Session), 130

[auto\\_setup\(\)](#) (in module `niscopes.Session`), 347  
[auto\\_zero](#) (in module `nidcpower.Session`), 20  
[auto\\_zero](#) (in module `nidmm.Session`), 130  
[AUTOMATIC](#) (`nidcpower.PowerSource` attribute), 117  
[AUTOMATIC](#) (`nifgen.ClockMode` attribute), 281  
[AUTOMATICALLY\\_AFTER\\_SOURCE\\_COMPLETE](#) (`nidcpower.MeasureWhen` attribute), 116  
[AutoZero](#) (class in `nidcpower`), 115  
[AutoZero](#) (class in `nidmm`), 180  
[aux\\_power\\_enabled](#) (in module `nifgen.Session`), 203  
[AUX\\_TRIG1](#) (`nidmm.SampleTrigger` attribute), 184  
[AUX\\_TRIG1](#) (`nidmm.TriggerSource` attribute), 186  
[AUXILIARY](#) (`nidcpower.PowerSource` attribute), 117  
[AUXILIARY](#) (`nidcpower.PowerSourceInUse` attribute), 117  
[auxiliary\\_power\\_source\\_available](#) (in module `nidcpower.Session`), 20

## B

[B](#) (`nidmm.ThermocoupleType` attribute), 184  
[backlog](#) (in module `niscopes.Session`), 302  
[bandpass\\_filter\\_enabled](#) (in module `niscopes.Session`), 303  
[bandwidth](#) (in module `niswitch.Session`), 384  
[BIG](#) (`nifgen.ByteOrder` attribute), 281  
[binary\\_sample\\_width](#) (in module `niscopes.Session`), 303  
[BREAK\\_AFTER\\_MAKE](#) (`niswitch.ScanMode` attribute), 421  
[BREAK\\_BEFORE\\_MAKE](#) (`niswitch.ScanMode` attribute), 421  
[buffer\\_size](#) (in module `nidmm.Session`), 130  
[BURST](#) (`nifgen.TriggerMode` attribute), 285  
[bus\\_number](#) (in module `nimodinst.Session`), 429  
[bus\\_type](#) (in module `nifgen.Session`), 203  
[BusType](#) (class in `nifgen`), 280  
[ByteOrder](#) (class in `nifgen`), 281

## C

[cable\\_comp\\_type](#) (in module `nidmm.Session`), 131  
[CableCompensationType](#) (class in `nidmm`), 180  
[can\\_connect\(\)](#) (in module `niswitch.Session`), 407  
[CAPACITANCE](#) (`nidmm.Function` attribute), 182  
[channel\\_count](#) (in module `nidcpower.Session`), 21  
[channel\\_count](#) (in module `nidmm.Session`), 131  
[channel\\_count](#) (in module `nifgen.Session`), 203  
[channel\\_count](#) (in module `niscopes.Session`), 304  
[channel\\_count](#) (in module `niswitch.Session`), 384  
[channel\\_delay](#) (in module `nifgen.Session`), 204  
[channel\\_enabled](#) (in module `niscopes.Session`), 304  
[CHANNEL\\_NOT\\_AVAILABLE](#) (`niswitch.PathCapability` attribute), 418  
[channel\\_terminal\\_configuration](#) (in module `niscopes.Session`), 305

[characteristic\\_impedance](#) (in module `niswitch.Session`), 385  
[chassis\\_number](#) (in module `nimodinst.Session`), 429  
[clear\\_arb\\_memory\(\)](#) (in module `nifgen.Session`), 252  
[clear\\_arb\\_sequence\(\)](#) (in module `nifgen.Session`), 252  
[clear\\_freq\\_list\(\)](#) (in module `nifgen.Session`), 252  
[clear\\_user\\_standard\\_waveform\(\)](#) (in module `nifgen.Session`), 253  
[CLOCK\\_IN](#) (`nifgen.ReferenceClockSource` attribute), 282  
[CLOCK\\_IN](#) (`nifgen.SampleClockSource` attribute), 283  
[CLOCK\\_IN](#) (`nifgen.SampleClockTimebaseSource` attribute), 284  
[clock\\_mode](#) (in module `nifgen.Session`), 204  
[ClockMode](#) (class in `nifgen`), 281  
[CLOSE](#) (`niswitch.RelayAction` attribute), 418  
[CLOSED](#) (`niswitch.RelayPosition` attribute), 418  
[commit\(\)](#) (in module `nidcpower.Session`), 99  
[commit\(\)](#) (in module `nifgen.Session`), 253  
[commit\(\)](#) (in module `niscopes.Session`), 348  
[commit\(\)](#) (in module `niswitch.Session`), 408  
[common\\_mode\\_offset](#) (in module `nifgen.Session`), 205  
[COMPLETE](#) (`niscopes.AcquisitionStatus` attribute), 367  
[compliance\\_limit\\_symmetry](#) (in module `nidcpower.Session`), 21  
[ComplianceLimitSymmetry](#) (class in `nidcpower`), 115  
[configure\\_aperture\\_time\(\)](#) (in module `nidcpower.Session`), 99  
[configure\\_arb\\_sequence\(\)](#) (in module `nifgen.Session`), 254  
[configure\\_arb\\_waveform\(\)](#) (in module `nifgen.Session`), 255  
[configure\\_chan\\_characteristics\(\)](#) (in module `niscopes.Session`), 348  
[configure\\_custom\\_fir\\_filter\\_coefficients\(\)](#) (in module `nifgen.Session`), 256  
[configure\\_equalization\\_filter\\_coefficients\(\)](#) (in module `niscopes.Session`), 349  
[configure\\_freq\\_list\(\)](#) (in module `nifgen.Session`), 256  
[configure\\_horizontal\\_timing\(\)](#) (in module `niscopes.Session`), 349  
[configure\\_measurement\\_absolute\(\)](#) (in module `nidmm.Session`), 159  
[configure\\_measurement\\_digits\(\)](#) (in module `nidmm.Session`), 160  
[configure\\_multi\\_point\(\)](#) (in module `nidmm.Session`), 161  
[configure\\_rtd\\_custom\(\)](#) (in module `nidmm.Session`), 162  
[configure\\_rtd\\_type\(\)](#) (in module `nidmm.Session`), 162  
[configure\\_standard\\_waveform\(\)](#) (in module `nifgen.Session`), 258  
[configure\\_thermistor\\_custom\(\)](#) (in module `nidmm.Session`), 164  
[configure\\_thermocouple\(\)](#) (in module `nidmm.Session`), 164

- `configure_trigger()` (in module `nidmm.Session`), 165
  - `configure_trigger_digital()` (in module `niscopes.Session`), 350
  - `configure_trigger_edge()` (in module `niscopes.Session`), 351
  - `configure_trigger_hysteresis()` (in module `niscopes.Session`), 352
  - `configure_trigger_immediate()` (in module `niscopes.Session`), 353
  - `configure_trigger_software()` (in module `niscopes.Session`), 353
  - `configure_trigger_video()` (in module `niscopes.Session`), 354
  - `configure_trigger_window()` (in module `niscopes.Session`), 355
  - `configure_vertical()` (in module `niscopes.Session`), 356
  - `configure_waveform_acquisition()` (in module `nidmm.Session`), 165
  - `connect()` (in module `niswitch.Session`), 408
  - `connect_multiple()` (in module `niswitch.Session`), 409
  - CONTINUOUS (`nifgen.TriggerMode` attribute), 285
  - `continuous_scan` (in module `niswitch.Session`), 385
  - `create_advanced_arb_sequence()` (in module `nifgen.Session`), 260
  - `create_arb_sequence()` (in module `nifgen.Session`), 262
  - `create_freq_list()` (in module `nifgen.Session`), 263
  - `create_waveform_from_file_f64()` (in module `nifgen.Session`), 264
  - `create_waveform_from_file_i16()` (in module `nifgen.Session`), 265
  - `create_waveform_numpy()` (in module `nifgen.Session`), 266
  - CURRENT (`nidcpower.MeasurementTypes` attribute), 116
  - CURRENT (`nidcpower.OutputStates` attribute), 117
  - CURRENT (`nifgen.RelativeTo` attribute), 283
  - `current_compensation_frequency` (in module `nidcpower.Session`), 22
  - `current_gain_bandwidth` (in module `nidcpower.Session`), 23
  - `current_level` (in module `nidcpower.Session`), 23
  - `current_level_autorange` (in module `nidcpower.Session`), 24
  - `current_level_range` (in module `nidcpower.Session`), 25
  - `current_limit` (in module `nidcpower.Session`), 26
  - `current_limit_autorange` (in module `nidcpower.Session`), 26
  - `current_limit_high` (in module `nidcpower.Session`), 27
  - `current_limit_low` (in module `nidcpower.Session`), 28
  - `current_limit_range` (in module `nidcpower.Session`), 29
  - `current_pole_zero_ratio` (in module `nidcpower.Session`), 30
  - `current_source` (in module `nidmm.Session`), 132
  - CUSTOM (`nidcpower.TransientResponse` attribute), 119
  - CUSTOM (`nidmm.RTDType` attribute), 183
  - CUSTOM (`nidmm.ThermistorType` attribute), 184
- ## D
- `data_marker_event_data_bit_number` (in module `nifgen.Session`), 206
  - `data_marker_event_level_polarity` (in module `nifgen.Session`), 206
  - `data_marker_event_output_terminal` (in module `nifgen.Session`), 207
  - `data_marker_events_count` (in module `nifgen.Session`), 205
  - `data_transfer_block_size` (in module `nifgen.Session`), 207
  - `data_transfer_block_size` (in module `niscopes.Session`), 305
  - `data_transfer_maximum_bandwidth` (in module `nifgen.Session`), 208
  - `data_transfer_maximum_bandwidth` (in module `niscopes.Session`), 306
  - `data_transfer_maximum_in_flight_reads` (in module `nifgen.Session`), 208
  - `data_transfer_preferred_packet_size` (in module `nifgen.Session`), 209
  - `data_transfer_preferred_packet_size` (in module `niscopes.Session`), 306
  - DataMarkerEventLevelPolarity (class in `nifgen`), 281
  - DC (`nidmm.WaveformCoupling` attribute), 186
  - DC (`nifgen.Waveform` attribute), 286
  - DC (`niscopes.TriggerCoupling` attribute), 370
  - DC (`niscopes.VerticalCoupling` attribute), 371
  - `dc_bias` (in module `nidmm.Session`), 132
  - DC\_CURRENT (`nidcpower.OutputFunction` attribute), 116
  - DC\_CURRENT (`nidmm.Function` attribute), 181
  - `dc_noise_rejection` (in module `nidcpower.Session`), 31
  - `dc_noise_rejection` (in module `nidmm.Session`), 133
  - DC\_VOLTAGE (`nidcpower.OutputFunction` attribute), 116
  - DC\_VOLTS (`nidmm.Function` attribute), 181
  - DCNoiseRejection (class in `nidcpower`), 115
  - DCNoiseRejection (class in `nidmm`), 181
  - DDC (`niscopes.AcquisitionType` attribute), 368
  - DDC\_CLOCK\_IN (`nifgen.SampleClockSource` attribute), 283
  - DDC\_OUTPUT (`niscopes.RefTriggerDetectorLocation` attribute), 369
  - `define_user_standard_waveform()` (in module `nifgen.Session`), 266
  - `delete_script()` (in module `nifgen.Session`), 267
  - `delete_waveform()` (in module `nifgen.Session`), 267
  - `device_model` (in module `nimodinst.Session`), 430
  - `device_name` (in module `nimodinst.Session`), 430
  - `device_temperature` (in module `niscopes.Session`), 307

DIFFERENTIAL (nifgen.TerminalConfiguration attribute), 285  
 DIFFERENTIAL (niscope.TerminalConfiguration attribute), 369  
 DIGITAL (niscope.TriggerType attribute), 371  
 digital\_data\_mask (in module nifgen.Session), 209  
 DIGITAL\_EDGE (nidcpower.TriggerType attribute), 119  
 DIGITAL\_EDGE (nifgen.ScriptTriggerType attribute), 284  
 DIGITAL\_EDGE (nifgen.StartTriggerType attribute), 285  
 digital\_edge\_measure\_trigger\_input\_terminal (in module nidcpower.Session), 31  
 digital\_edge\_pulse\_trigger\_input\_terminal (in module nidcpower.Session), 32  
 digital\_edge\_script\_trigger\_edge (in module nifgen.Session), 210  
 digital\_edge\_script\_trigger\_source (in module nifgen.Session), 210  
 digital\_edge\_sequence\_advance\_trigger\_input\_terminal (in module nidcpower.Session), 32  
 digital\_edge\_source\_trigger\_input\_terminal (in module nidcpower.Session), 33  
 digital\_edge\_start\_trigger\_edge (in module nifgen.Session), 211  
 digital\_edge\_start\_trigger\_input\_terminal (in module nidcpower.Session), 33  
 digital\_edge\_start\_trigger\_source (in module nifgen.Session), 211  
 digital\_filter\_enable (in module niswitch.Session), 386  
 digital\_filter\_enabled (in module nifgen.Session), 212  
 digital\_filter\_interpolation\_factor (in module nifgen.Session), 212  
 digital\_gain (in module nifgen.Session), 213  
 DIGITAL\_LEVEL (nifgen.ScriptTriggerType attribute), 284  
 digital\_pattern\_enabled (in module nifgen.Session), 213  
 digital\_static\_value (in module nifgen.Session), 214  
 DIODE (nidmm.Function attribute), 181  
 DIRECT (nifgen.AnalogPath attribute), 280  
 disable() (in module nidcpower.Session), 100  
 disable() (in module nidmm.Session), 166  
 disable() (in module nifgen.Session), 268  
 disable() (in module niscope.Session), 356  
 disable() (in module niswitch.Session), 409  
 disconnect() (in module niswitch.Session), 409  
 disconnect\_all() (in module niswitch.Session), 410  
 disconnect\_multiple() (in module niswitch.Session), 410  
 DIVIDE\_DOWN (nifgen.ClockMode attribute), 281  
 DONE (nifgen.HardwareState attribute), 282  
 done\_event\_output\_terminal (in module nifgen.Session), 214  
 driver\_setup (in module nidcpower.Session), 34  
 driver\_setup (in module nidmm.Session), 133

driver\_setup (in module nifgen.Session), 214  
 driver\_setup (in module niscope.Session), 307  
 driver\_setup (in module niswitch.Session), 386  
 DriverError, 119, 186, 286, 373, 423, 433  
 DriverNotInstalledError, 119, 186, 287, 373, 423, 433  
 DriverWarning, 120, 187, 287, 374, 424, 434

## E

E (nidmm.ThermocoupleType attribute), 185  
 EDGE (niscope.TriggerType attribute), 370  
 EIGHT\_TAP\_HANNING (niscope.FlexFIRAntialiasFilterType attribute), 368  
 enable\_dc\_restore (in module niscope.Session), 308  
 enable\_time\_interleaved\_sampling (in module niscope.Session), 308  
 end\_of\_acquisition\_event\_output\_terminal (in module niscope.Session), 309  
 end\_of\_record\_event\_output\_terminal (in module niscope.Session), 309  
 end\_of\_record\_to\_advance\_trigger\_holdoff (in module niscope.Session), 309  
 ENTERING (niscope.TriggerWindowMode attribute), 371  
 equalization\_filter\_enabled (in module niscope.Session), 310  
 equalization\_num\_coefficients (in module niscope.Session), 311  
 Event (class in nidcpower), 115  
 EXACT\_NUM\_AVERAGES (niscope.RISMethod attribute), 369  
 exported\_advance\_trigger\_output\_terminal (in module niscope.Session), 311  
 exported\_measure\_trigger\_output\_terminal (in module nidcpower.Session), 35  
 exported\_onboard\_reference\_clock\_output\_terminal (in module nifgen.Session), 215  
 exported\_pulse\_trigger\_output\_terminal (in module nidcpower.Session), 35  
 exported\_ref\_trigger\_output\_terminal (in module niscope.Session), 312  
 exported\_reference\_clock\_output\_terminal (in module nifgen.Session), 215  
 exported\_sample\_clock\_divisor (in module nifgen.Session), 216  
 exported\_sample\_clock\_output\_terminal (in module nifgen.Session), 216  
 exported\_sample\_clock\_timebase\_divisor (in module nifgen.Session), 217  
 exported\_sample\_clock\_timebase\_output\_terminal (in module nifgen.Session), 217  
 exported\_script\_trigger\_output\_terminal (in module nifgen.Session), 218



- p>
exported\_sequence\_advance\_trigger\_output\_terminal (in module nidcpower.Session), 36
- 
- exported\_source\_trigger\_output\_terminal (in module nidcpower.Session), 36
- 
- exported\_start\_trigger\_output\_terminal (in module nidcpower.Session), 37
- 
- exported\_start\_trigger\_output\_terminal (in module nifgen.Session), 218
- 
- exported\_start\_trigger\_output\_terminal (in module niscopes.Session), 312
- 
- EXTERNAL (nidmm.MeasurementCompleteDest attribute), 182
- 
- EXTERNAL (nidmm.SampleTrigger attribute), 183
- 
- EXTERNAL (nidmm.TriggerSource attribute), 185
- 
- EXTERNAL (niswitch.ScanAdvancedOutput attribute), 419
- 
- EXTERNAL (niswitch.TriggerInput attribute), 421
- 
- external\_clock\_delay\_binary\_value (in module nifgen.Session), 219
- 
- external\_sample\_clock\_multiplier (in module nifgen.Session), 219
- 
- ## F
- FALLING (nifgen.ScriptTriggerDigitalEdgeEdge attribute), 284  
FALLING (nifgen.StartTriggerDigitalEdgeEdge attribute), 284  
FALLING (niswitch.ScanAdvancedPolarity attribute), 420  
FALLING (niswitch.TriggerInputPolarity attribute), 423  
FAST (nidcpower.TransientResponse attribute), 119  
fetch() (in module nidmm.Session), 166  
fetch() (in module niscopes.Session), 356  
fetch\_backlog (in module nidcpower.Session), 37  
fetch\_into() (in module niscopes.Session), 358  
fetch\_multi\_point() (in module nidmm.Session), 167  
fetch\_multiple() (in module nidcpower.Session), 100  
fetch\_waveform() (in module nidmm.Session), 168  
fetch\_waveform\_into() (in module nidmm.Session), 168  
FetchRelativeTo (class in niscopes), 368  
FIELD1 (niscopes.VideoTriggerEvent attribute), 373  
FIELD2 (niscopes.VideoTriggerEvent attribute), 373  
file\_transfer\_block\_size (in module nifgen.Session), 220  
filter\_correction\_frequency (in module nifgen.Session), 220  
FINISHED\_WITH\_BACKLOG (nidmm.AcquisitionStatus attribute), 179  
FINISHED\_WITH\_NO\_BACKLOG (nidmm.AcquisitionStatus attribute), 180  
FIXED (nidmm.ThermocoupleReferenceJunctionType attribute), 184  
FIXED\_HIGH\_GAIN (nifgen.AnalogPath attribute), 280  
FIXED\_LOW\_GAIN (nifgen.AnalogPath attribute), 280  
flatness\_correction\_enabled (in module nifgen.Session), 220  
flex\_fir\_antialias\_filter\_type (in module niscopes.Session), 312  
FlexFIRAntialiasFilterType (class in niscopes), 368  
FLEXRES (niscopes.AcquisitionType attribute), 368  
FOUR\_WIRE\_RES (nidmm.Function attribute), 181  
FOUR\_WIRE\_RTD (nidmm.TransducerType attribute), 185  
FOURTYEIGHT\_TAP\_HANNING (niscopes.FlexFIRAntialiasFilterType attribute), 368  
FOURTYEIGHT\_TAP\_STANDARD (niscopes.FlexFIRAntialiasFilterType attribute), 368  
fpga\_bitfile\_path (in module nifgen.Session), 221  
fpga\_bitfile\_path (in module niscopes.Session), 313  
FREQ (nidmm.Function attribute), 181  
FREQ\_LIST (nifgen.OutputMode attribute), 282  
freq\_list\_duration\_quantum (in module nifgen.Session), 221  
freq\_list\_handle (in module nifgen.Session), 222  
freq\_voltage\_auto\_range (in module nidmm.Session), 134  
freq\_voltage\_range (in module nidmm.Session), 134  
FRONTCONNECTOR (niswitch.ScanAdvancedOutput attribute), 419  
FRONTCONNECTOR (niswitch.TriggerInput attribute), 422  
FRONTCONNECTOR\_MODULE1 (niswitch.ScanAdvancedOutput attribute), 420  
FRONTCONNECTOR\_MODULE1 (niswitch.TriggerInput attribute), 422  
FRONTCONNECTOR\_MODULE10 (niswitch.ScanAdvancedOutput attribute), 420  
FRONTCONNECTOR\_MODULE10 (niswitch.TriggerInput attribute), 423  
FRONTCONNECTOR\_MODULE11 (niswitch.ScanAdvancedOutput attribute), 420  
FRONTCONNECTOR\_MODULE11 (niswitch.TriggerInput attribute), 423  
FRONTCONNECTOR\_MODULE12 (niswitch.ScanAdvancedOutput attribute), 420  
FRONTCONNECTOR\_MODULE12 (niswitch.TriggerInput attribute), 423  
FRONTCONNECTOR\_MODULE2 (niswitch.ScanAdvancedOutput attribute), 420  
FRONTCONNECTOR\_MODULE2 (niswitch.TriggerInput attribute), 422

FRONTCONNECTOR\_MODULE3  
(niswitch.ScanAdvancedOutput attribute),  
420

FRONTCONNECTOR\_MODULE3  
(niswitch.TriggerInput attribute), 422

FRONTCONNECTOR\_MODULE4  
(niswitch.ScanAdvancedOutput attribute),  
420

FRONTCONNECTOR\_MODULE4  
(niswitch.TriggerInput attribute), 422

FRONTCONNECTOR\_MODULE5  
(niswitch.ScanAdvancedOutput attribute),  
420

FRONTCONNECTOR\_MODULE5  
(niswitch.TriggerInput attribute), 423

FRONTCONNECTOR\_MODULE6  
(niswitch.ScanAdvancedOutput attribute),  
420

FRONTCONNECTOR\_MODULE6  
(niswitch.TriggerInput attribute), 423

FRONTCONNECTOR\_MODULE7  
(niswitch.ScanAdvancedOutput attribute),  
420

FRONTCONNECTOR\_MODULE7  
(niswitch.TriggerInput attribute), 423

FRONTCONNECTOR\_MODULE8  
(niswitch.ScanAdvancedOutput attribute),  
420

FRONTCONNECTOR\_MODULE8  
(niswitch.TriggerInput attribute), 423

FRONTCONNECTOR\_MODULE9  
(niswitch.ScanAdvancedOutput attribute),  
420

FRONTCONNECTOR\_MODULE9  
(niswitch.TriggerInput attribute), 423

FUNC (nifgen.OutputMode attribute), 282

func\_amplitude (in module nifgen.Session), 222

func\_buffer\_size (in module nifgen.Session), 223

func\_dc\_offset (in module nifgen.Session), 223

func\_duty\_cycle\_high (in module nifgen.Session), 224

func\_frequency (in module nifgen.Session), 224

func\_max\_buffer\_size (in module nifgen.Session), 225

func\_start\_phase (in module nifgen.Session), 225

func\_waveform (in module nifgen.Session), 226

Function (class in nidmm), 181

function (in module nidmm.Session), 134

## G

get\_cal\_date\_and\_time() (in module nidmm.Session),  
169

get\_channel\_name() (in module nidcpower.Session), 101

get\_channel\_name() (in module niswitch.Session), 410

get\_dev\_temp() (in module nidmm.Session), 170

get\_equalization\_filter\_coefficients() (in module niscope.Session), 359

get\_ext\_cal\_last\_date\_and\_time() (in module nidcpower.Session), 101

get\_ext\_cal\_last\_date\_and\_time() (in module nifgen.Session), 268

get\_ext\_cal\_last\_temp() (in module nidcpower.Session),  
101

get\_ext\_cal\_last\_temp() (in module nifgen.Session), 268

get\_ext\_cal\_recommended\_interval() (in module nidcpower.Session), 102

get\_ext\_cal\_recommended\_interval() (in module nidmm.Session), 170

get\_ext\_cal\_recommended\_interval() (in module nifgen.Session), 268

get\_hardware\_state() (in module nifgen.Session), 268

get\_last\_cal\_temp() (in module nidmm.Session), 170

get\_path() (in module niswitch.Session), 410

get\_relay\_count() (in module niswitch.Session), 411

get\_relay\_name() (in module niswitch.Session), 411

get\_relay\_position() (in module niswitch.Session), 411

get\_self\_cal\_last\_date\_and\_time() (in module nidcpower.Session), 102

get\_self\_cal\_last\_date\_and\_time() (in module nifgen.Session), 269

get\_self\_cal\_last\_temp() (in module nidcpower.Session),  
102

get\_self\_cal\_last\_temp() (in module nifgen.Session), 269

get\_self\_cal\_supported() (in module nidmm.Session),  
171

get\_self\_cal\_supported() (in module nifgen.Session), 269

GND (niscope.VerticalCoupling attribute), 371

## H

handshaking\_initiation (in module niswitch.Session), 387

HandshakingInitiation (class in niswitch), 417

HARDWARE\_ERROR (nifgen.HardwareState attribute),  
282

HardwareState (class in nifgen), 281

HF\_REJECT (niscope.TriggerCoupling attribute), 370

HIGH (nidcpower.OutputCapacitance attribute), 116

HIGH (nidcpower.Polarity attribute), 117

HIGH (nifgen.DataMarkerEventLevelPolarity attribute),  
281

HIGH\_ORDER (nidmm.DCNoiseRejection attribute),  
181

high\_pass\_filter\_frequency (in module niscope.Session),  
313

HIGH\_RESOLUTION (nifgen.ClockMode attribute),  
281

HOLD\_LAST (nifgen.IdleBehavior attribute), 282

HOLD\_LAST (nifgen.WaitBehavior attribute), 286

horz\_enforce\_realtime (in module niscope.Session), 314

horz\_min\_num\_pts (in module niscope.Session), 314



[horz\\_num\\_records](#) (in module [niscopes.Session](#)), 315  
[horz\\_record\\_length](#) (in module [niscopes.Session](#)), 315  
[horz\\_record\\_ref\\_position](#) (in module [niscopes.Session](#)), 316  
[horz\\_sample\\_rate](#) (in module [niscopes.Session](#)), 316  
[horz\\_time\\_per\\_record](#) (in module [niscopes.Session](#)), 316  
[HYSTERESIS](#) ([niscopes.TriggerType](#) attribute), 371

## I

[IDLE](#) ([nifgen.HardwareState](#) attribute), 281  
[idle\\_behavior](#) (in module [nifgen.Session](#)), 226  
[idle\\_value](#) (in module [nifgen.Session](#)), 226  
[IdleBehavior](#) (class in [nifgen](#)), 282  
[IMMEDIATE](#) ([nidmm.SampleTrigger](#) attribute), 183  
[IMMEDIATE](#) ([nidmm.TriggerSource](#) attribute), 185  
[IMMEDIATE](#) ([niscopes.TriggerType](#) attribute), 370  
[IMMEDIATE](#) ([niswitch.TriggerInput](#) attribute), 421  
[IN\\_PROGRESS](#) ([niscopes.AcquisitionStatus](#) attribute), 367  
[INCOMPLETE](#) ([niscopes.RISMethod](#) attribute), 369  
[INDUCTANCE](#) ([nidmm.Function](#) attribute), 182  
[input\\_clock\\_source](#) (in module [niscopes.Session](#)), 317  
[input\\_impedance](#) (in module [niscopes.Session](#)), 317  
[input\\_resistance](#) (in module [nidmm.Session](#)), 135  
[instrument\\_firmware\\_revision](#) (in module [nidcpower.Session](#)), 38  
[instrument\\_firmware\\_revision](#) (in module [nidmm.Session](#)), 135  
[instrument\\_firmware\\_revision](#) (in module [nifgen.Session](#)), 227  
[instrument\\_firmware\\_revision](#) (in module [niscopes.Session](#)), 318  
[instrument\\_firmware\\_revision](#) (in module [niswitch.Session](#)), 387  
[instrument\\_manufacturer](#) (in module [nidcpower.Session](#)), 38  
[instrument\\_manufacturer](#) (in module [nidmm.Session](#)), 136  
[instrument\\_manufacturer](#) (in module [nifgen.Session](#)), 227  
[instrument\\_manufacturer](#) (in module [niscopes.Session](#)), 318  
[instrument\\_manufacturer](#) (in module [niswitch.Session](#)), 388  
[instrument\\_model](#) (in module [nidcpower.Session](#)), 38  
[instrument\\_model](#) (in module [nidmm.Session](#)), 136  
[instrument\\_model](#) (in module [nifgen.Session](#)), 228  
[instrument\\_model](#) (in module [niscopes.Session](#)), 319  
[instrument\\_model](#) (in module [niswitch.Session](#)), 388  
[instrument\\_product\\_id](#) (in module [nidmm.Session](#)), 137  
[interleaving\\_offset\\_correction\\_enabled](#) (in module [niscopes.Session](#)), 319  
[interlock\\_input\\_open](#) (in module [nidcpower.Session](#)), 39  
[INTERNAL](#) ([nidcpower.PowerSource](#) attribute), 117

[INTERNAL](#) ([nidcpower.PowerSourceInUse](#) attribute), 117  
[INTERVAL](#) ([nidmm.SampleTrigger](#) attribute), 183  
[INVALID](#) ([nifgen.BusType](#) attribute), 280  
[InvalidRepeatedCapabilityError](#), 119, 187, 287, 374, 424, 433  
[io\\_resource\\_descriptor](#) (in module [nidcpower.Session](#)), 39  
[io\\_resource\\_descriptor](#) (in module [nidmm.Session](#)), 137  
[io\\_resource\\_descriptor](#) (in module [nifgen.Session](#)), 228  
[io\\_resource\\_descriptor](#) (in module [niscopes.Session](#)), 320  
[io\\_resource\\_descriptor](#) (in module [niswitch.Session](#)), 388  
[is\\_configuration\\_channel](#) (in module [niswitch.Session](#)), 389  
[is\\_debounced](#) (in module [niswitch.Session](#)), 390  
[is\\_done\(\)](#) (in module [nifgen.Session](#)), 270  
[is\\_scanning](#) (in module [niswitch.Session](#)), 390  
[is\\_source\\_channel](#) (in module [niswitch.Session](#)), 390  
[is\\_waiting\\_for\\_trig](#) (in module [niswitch.Session](#)), 391  
[IVIDMM](#) ([nidmm.OperationMode](#) attribute), 183

## J

[J](#) ([nidmm.ThermocoupleType](#) attribute), 185  
[JUMP\\_TO](#) ([nifgen.IdleBehavior](#) attribute), 282  
[JUMP\\_TO](#) ([nifgen.WaitBehavior](#) attribute), 286

## K

[K](#) ([nidmm.ThermocoupleType](#) attribute), 185  
[KEEP\\_IN\\_MEMORY](#) ([nidcpower.SelfCalibrationPersistence](#) attribute), 118

## L

[LBR\\_TRIG0](#) ([nidmm.MeasurementCompleteDest](#) attribute), 182  
[LBR\\_TRIG1](#) ([nidmm.SampleTrigger](#) attribute), 184  
[LBR\\_TRIG1](#) ([nidmm.TriggerSource](#) attribute), 186  
[lc\\_calculation\\_model](#) (in module [nidmm.Session](#)), 137  
[lc\\_number\\_meas\\_to\\_average](#) (in module [nidmm.Session](#)), 138  
[LCCalculationModel](#) (class in [nidmm](#)), 182  
[LEAVING](#) ([niscopes.TriggerWindowMode](#) attribute), 371  
[LF\\_REJECT](#) ([niscopes.TriggerCoupling](#) attribute), 370  
[LIMITED\\_BIN\\_WIDTH](#) ([niscopes.RISMethod](#) attribute), 369  
[LINE\\_NUMBER](#) ([niscopes.VideoTriggerEvent](#) attribute), 373  
[LITTLE](#) ([nifgen.ByteOrder](#) attribute), 281  
[load\\_impedance](#) (in module [nifgen.Session](#)), 229  
[LOCAL](#) ([nidcpower.Sense](#) attribute), 118  
[lock\(\)](#) (in module [nidcpower.Session](#)), 103  
[lock\(\)](#) (in module [nidmm.Session](#)), 171  
[lock\(\)](#) (in module [nifgen.Session](#)), 270  
[lock\(\)](#) (in module [niscopes.Session](#)), 360

lock() (in module niswitch.Session), 412  
logical\_name (in module nidcpower.Session), 40  
logical\_name (in module nidmm.Session), 138  
logical\_name (in module nifgen.Session), 229  
logical\_name (in module niscopes.Session), 320  
logical\_name (in module niswitch.Session), 392  
LOW (nidcpower.OutputCapacitance attribute), 116  
LOW (nidcpower.Polarity attribute), 117  
LOW (nifgen.DataMarkerEventLevelPolarity attribute), 281

## M

M\_PAL (niscopes.VideoSignalFormat attribute), 372  
MAIN (nifgen.AnalogPath attribute), 280  
major\_version (in module nifgen.Session), 230  
marker\_event\_output\_terminal (in module nifgen.Session), 230  
marker\_events\_count (in module nifgen.Session), 230  
master\_enable (in module niscopes.Session), 321  
max\_ac\_voltage (in module niswitch.Session), 392  
max\_carry\_ac\_current (in module niswitch.Session), 393  
max\_carry\_ac\_power (in module niswitch.Session), 393  
max\_carry\_dc\_current (in module niswitch.Session), 394  
max\_carry\_dc\_power (in module niswitch.Session), 394  
max\_dc\_voltage (in module niswitch.Session), 395  
max\_freq\_list\_duration (in module nifgen.Session), 231  
max\_freq\_list\_length (in module nifgen.Session), 231  
max\_input\_frequency (in module niscopes.Session), 321  
max\_loop\_count (in module nifgen.Session), 232  
max\_num\_freq\_lists (in module nifgen.Session), 232  
max\_num\_sequences (in module nifgen.Session), 233  
max\_num\_waveforms (in module nifgen.Session), 233  
max\_pciexpress\_link\_width (in module nimodinst.Session), 431  
max\_real\_time\_sampling\_rate (in module niscopes.Session), 322  
max\_ris\_rate (in module niscopes.Session), 322  
max\_sequence\_length (in module nifgen.Session), 234  
max\_switching\_ac\_current (in module niswitch.Session), 396  
max\_switching\_ac\_power (in module niswitch.Session), 396  
max\_switching\_dc\_current (in module niswitch.Session), 397  
max\_switching\_dc\_power (in module niswitch.Session), 397  
max\_waveform\_size (in module nifgen.Session), 234  
meas\_complete\_dest (in module nidmm.Session), 139  
MEASURE (nidcpower.SendSoftwareEdgeTriggerType attribute), 118  
measure() (in module nidcpower.Session), 103  
measure\_buffer\_size (in module nidcpower.Session), 40  
MEASURE\_COMPLETE (nidcpower.Event attribute), 115

measure\_complete\_event\_delay (in module nidcpower.Session), 41  
measure\_complete\_event\_output\_terminal (in module nidcpower.Session), 41  
measure\_complete\_event\_pulse\_polarity (in module nidcpower.Session), 42  
measure\_complete\_event\_pulse\_width (in module nidcpower.Session), 42  
measure\_multiple() (in module nidcpower.Session), 104  
measure\_record\_delta\_time (in module nidcpower.Session), 43  
measure\_record\_length (in module nidcpower.Session), 43  
measure\_record\_length\_is\_finite (in module nidcpower.Session), 44  
measure\_trigger\_type (in module nidcpower.Session), 45  
measure\_when (in module nidcpower.Session), 45  
MEASUREMENT\_DEVICE (niswitch.HandshakingInitiation attribute), 417  
MeasurementCompleteDest (class in nidmm), 182  
MeasurementTypes (class in nidcpower), 116  
MeasureWhen (class in nidcpower), 116  
memory\_size (in module nifgen.Session), 234  
min\_freq\_list\_duration (in module nifgen.Session), 235  
min\_freq\_list\_length (in module nifgen.Session), 236  
MIN\_NUM\_AVERAGES (niscopes.RISMethod attribute), 369  
min\_sample\_rate (in module niscopes.Session), 323  
min\_sequence\_length (in module nifgen.Session), 236  
min\_waveform\_size (in module nifgen.Session), 236  
minor\_version (in module nifgen.Session), 235  
module\_revision (in module nifgen.Session), 237

## N

N (nidmm.ThermocoupleType attribute), 185  
NEGATIVE (niscopes.TriggerSlope attribute), 370  
NEGATIVE (niscopes.VideoPolarity attribute), 372  
nidcpower (module), 14  
nidmm (module), 123  
nifgen (module), 191  
nimodinst (module), 428  
niscopes (module), 293  
niswitch (module), 379  
NO\_ACQUISITION\_IN\_PROGRESS (nidmm.AcquisitionStatus attribute), 180  
NO\_TRIGGER\_MOD (niscopes.TriggerModifier attribute), 370  
NOISE (nifgen.Waveform attribute), 286  
NONE (nidcpower.TriggerType attribute), 119  
NONE (nidmm.CableCompensationType attribute), 180  
NONE (nidmm.MeasurementCompleteDest attribute), 182  
NONE (nifgen.ReferenceClockSource attribute), 282

NONE (niswitch.ScanAdvancedOutput attribute), 419  
NONE (niswitch.ScanMode attribute), 421  
NORMAL (nidcpower.DCNoiseRejection attribute), 115  
NORMAL (nidcpower.TransientResponse attribute), 119  
NORMAL (nidmm.DCNoiseRejection attribute), 181  
NORMAL (niscopes.AcquisitionType attribute), 367  
NOW (niscopes.FetchRelativeTo attribute), 368  
NTSC (niscopes.VideoSignalFormat attribute), 372  
num\_of\_columns (in module niswitch.Session), 398  
num\_of\_rows (in module niswitch.Session), 399  
number\_of\_averages (in module nidmm.Session), 139  
number\_of\_relays (in module niswitch.Session), 398

## O

OFF (nidcpower.AutoZero attribute), 115  
OFF (nidmm.ADCCalibration attribute), 179  
OFF (nidmm.AutoZero attribute), 180  
offset\_comp\_ohms (in module nidmm.Session), 140  
ON (nidcpower.AutoZero attribute), 115  
ON (nidmm.ADCCalibration attribute), 179  
ON (nidmm.AutoZero attribute), 180  
ON\_DEMAND (nidcpower.MeasureWhen attribute), 116  
ON\_MEASURE\_TRIGGER (nidcpower.MeasureWhen attribute), 116  
ONBOARD\_CLOCK (nifgen.SampleClockSource attribute), 283  
ONBOARD\_CLOCK (nifgen.SampleClockTimebaseSource attribute), 284  
onboard\_memory\_size (in module niscopes.Session), 323  
ONBOARD\_REFERENCE\_CLOCK (nifgen.ReferenceClockSource attribute), 282  
ONCE (nidcpower.AutoZero attribute), 115  
ONCE (nidmm.AutoZero attribute), 180  
OPEN (nidmm.CableCompensationType attribute), 180  
OPEN (niswitch.RelayAction attribute), 418  
OPEN (niswitch.RelayPosition attribute), 418  
OPEN\_AND\_SHORT (nidmm.CableCompensationType attribute), 180  
open\_cable\_comp\_conductance (in module nidmm.Session), 140  
open\_cable\_comp\_susceptance (in module nidmm.Session), 140  
operation\_mode (in module nidmm.Session), 141  
OperationMode (class in nidmm), 183  
Option (class in niscopes), 368  
output\_capacitance (in module nidcpower.Session), 46  
output\_clock\_source (in module niscopes.Session), 324  
output\_connected (in module nidcpower.Session), 46  
output\_enabled (in module nidcpower.Session), 47  
output\_enabled (in module nifgen.Session), 237  
output\_function (in module nidcpower.Session), 48  
output\_impedance (in module nifgen.Session), 238  
output\_mode (in module nifgen.Session), 238

output\_resistance (in module nidcpower.Session), 49  
OutputCapacitance (class in nidcpower), 116  
OutputFunction (class in nidcpower), 116  
OutputMode (class in nifgen), 282  
OutputStates (class in nidcpower), 117  
overranging\_enabled (in module nidcpower.Session), 49  
ovp\_enabled (in module nidcpower.Session), 50  
ovp\_limit (in module nidcpower.Session), 50

## P

P2P\_ENDPOINT\_FULLNESS (nifgen.StartTriggerType attribute), 285  
PAL (niscopes.VideoSignalFormat attribute), 372  
PARALLEL (nidmm.LCCalculationModel attribute), 182  
PATH\_AVAILABLE (niswitch.PathCapability attribute), 418  
PATH\_EXISTS (niswitch.PathCapability attribute), 418  
PATH\_UNSUPPORTED (niswitch.PathCapability attribute), 418  
PathCapability (class in niswitch), 418  
PAUSED (nidmm.AcquisitionStatus attribute), 180  
PCI (nifgen.BusType attribute), 281  
pciexpress\_link\_width (in module nimodinst.Session), 431  
PCMCIA (nifgen.BusType attribute), 281  
perform\_open\_cable\_comp() (in module nidmm.Session), 172  
perform\_short\_cable\_comp() (in module nidmm.Session), 172  
PERIOD (nidmm.Function attribute), 181  
pll\_lock\_status (in module niscopes.Session), 324  
points\_done (in module niscopes.Session), 324  
Polarity (class in nidcpower), 117  
poll\_interval (in module niscopes.Session), 325  
POSITIVE (niscopes.TriggerSlope attribute), 370  
POSITIVE (niscopes.VideoPolarity attribute), 371  
power\_down\_latching\_relays\_after\_debounce (in module niswitch.Session), 399  
POWER\_LINE\_CYCLES (nidcpower.ApertureTimeUnits attribute), 115  
POWER\_LINE\_CYCLES (nidmm.ApertureTimeUnits attribute), 180  
power\_line\_frequency (in module nidcpower.Session), 51  
power\_source (in module nidcpower.Session), 52  
power\_source\_in\_use (in module nidcpower.Session), 52  
powerline\_freq (in module nidmm.Session), 141  
PowerSource (class in nidcpower), 117  
PowerSourceInUse (class in nidcpower), 117  
PRETRIGGER (niscopes.FetchRelativeTo attribute), 368  
probe\_attenuation (in module niscopes.Session), 325  
probe\_compensation\_signal\_start() (in module niscopes.Session), 360  
probe\_compensation\_signal\_stop() (in module niscopes.Session), 360

PT3750 (nidmm.RTDType attribute), 183  
PT3851 (nidmm.RTDType attribute), 183  
PT3911 (nidmm.RTDType attribute), 183  
PT3916 (nidmm.RTDType attribute), 183  
PT3920 (nidmm.RTDType attribute), 183  
PT3928 (nidmm.RTDType attribute), 183  
PULSE (nidcpower.SendSoftwareEdgeTriggerType attribute), 118  
pulse\_bias\_current\_level (in module nidcpower.Session), 53  
pulse\_bias\_current\_limit (in module nidcpower.Session), 53  
pulse\_bias\_current\_limit\_high (in module nidcpower.Session), 54  
pulse\_bias\_current\_limit\_low (in module nidcpower.Session), 55  
pulse\_bias\_delay (in module nidcpower.Session), 56  
pulse\_bias\_voltage\_level (in module nidcpower.Session), 57  
pulse\_bias\_voltage\_limit (in module nidcpower.Session), 57  
pulse\_bias\_voltage\_limit\_high (in module nidcpower.Session), 58  
pulse\_bias\_voltage\_limit\_low (in module nidcpower.Session), 59  
PULSE\_COMPLETE (nidcpower.Event attribute), 116  
pulse\_complete\_event\_output\_terminal (in module nidcpower.Session), 60  
pulse\_complete\_event\_pulse\_polarity (in module nidcpower.Session), 61  
pulse\_complete\_event\_pulse\_width (in module nidcpower.Session), 61  
PULSE\_CURRENT (nidcpower.OutputFunction attribute), 117  
pulse\_current\_level (in module nidcpower.Session), 62  
pulse\_current\_level\_range (in module nidcpower.Session), 62  
pulse\_current\_limit (in module nidcpower.Session), 63  
pulse\_current\_limit\_high (in module nidcpower.Session), 64  
pulse\_current\_limit\_low (in module nidcpower.Session), 65  
pulse\_current\_limit\_range (in module nidcpower.Session), 66  
pulse\_off\_time (in module nidcpower.Session), 67  
pulse\_on\_time (in module nidcpower.Session), 67  
pulse\_trigger\_type (in module nidcpower.Session), 68  
PULSE\_VOLTAGE (nidcpower.OutputFunction attribute), 117  
pulse\_voltage\_level (in module nidcpower.Session), 69  
pulse\_voltage\_level\_range (in module nidcpower.Session), 69  
pulse\_voltage\_limit (in module nidcpower.Session), 70  
pulse\_voltage\_limit\_high (in module nidcpower.Session), 71  
pulse\_voltage\_limit\_low (in module nidcpower.Session), 72  
pulse\_voltage\_limit\_range (in module nidcpower.Session), 73  
PXI (nifgen.BusType attribute), 281  
PXI\_CLOCK (nifgen.ReferenceClockSource attribute), 282  
PXI\_STAR (nidmm.SampleTrigger attribute), 184  
PXI\_STAR (nidmm.TriggerSource attribute), 186  
PXI\_STAR (niswitch.ScanAdvancedOutput attribute), 419  
PXI\_STAR (niswitch.TriggerInput attribute), 422  
PXI\_STAR\_LINE (nifgen.SampleClockSource attribute), 283  
PXI\_TRIG0 (nidmm.MeasurementCompleteDest attribute), 182  
PXI\_TRIG0 (nidmm.SampleTrigger attribute), 183  
PXI\_TRIG0 (nidmm.TriggerSource attribute), 185  
PXI\_TRIG1 (nidmm.MeasurementCompleteDest attribute), 182  
PXI\_TRIG1 (nidmm.SampleTrigger attribute), 183  
PXI\_TRIG1 (nidmm.TriggerSource attribute), 185  
PXI\_TRIG2 (nidmm.MeasurementCompleteDest attribute), 182  
PXI\_TRIG2 (nidmm.SampleTrigger attribute), 183  
PXI\_TRIG2 (nidmm.TriggerSource attribute), 185  
PXI\_TRIG3 (nidmm.MeasurementCompleteDest attribute), 182  
PXI\_TRIG3 (nidmm.SampleTrigger attribute), 184  
PXI\_TRIG3 (nidmm.TriggerSource attribute), 186  
PXI\_TRIG4 (nidmm.MeasurementCompleteDest attribute), 182  
PXI\_TRIG4 (nidmm.SampleTrigger attribute), 184  
PXI\_TRIG4 (nidmm.TriggerSource attribute), 186  
PXI\_TRIG5 (nidmm.MeasurementCompleteDest attribute), 182  
PXI\_TRIG5 (nidmm.SampleTrigger attribute), 184  
PXI\_TRIG5 (nidmm.TriggerSource attribute), 186  
PXI\_TRIG6 (nidmm.MeasurementCompleteDest attribute), 182  
PXI\_TRIG6 (nidmm.SampleTrigger attribute), 184  
PXI\_TRIG6 (nidmm.TriggerSource attribute), 186  
PXI\_TRIG7 (nidmm.MeasurementCompleteDest attribute), 182  
PXI\_TRIG7 (nidmm.SampleTrigger attribute), 184  
PXI\_TRIG7 (nidmm.TriggerSource attribute), 186  
PXI\_TRIGGER\_LINE\_0RTSI\_0 (nifgen.SampleClockSource attribute), 283  
PXI\_TRIGGER\_LINE\_1RTSI\_1 (nifgen.SampleClockSource attribute), 283  
PXI\_TRIGGER\_LINE\_2RTSI\_2 (nifgen.SampleClockSource attribute), 283



PXI\_TRIGGER\_LINE\_3RTSI\_3  
(nifgen.SampleClockSource attribute), 283

PXI\_TRIGGER\_LINE\_4RTSI\_4  
(nifgen.SampleClockSource attribute), 283

PXI\_TRIGGER\_LINE\_5RTSI\_5  
(nifgen.SampleClockSource attribute), 283

PXI\_TRIGGER\_LINE\_6RTSI\_6  
(nifgen.SampleClockSource attribute), 283

PXI\_TRIGGER\_LINE\_7RTSI\_7  
(nifgen.SampleClockSource attribute), 283

PXIE (nifgen.BusType attribute), 281

## Q

query\_arb\_seq\_capabilities() (in module nifgen.Session), 271

query\_arb\_wfm\_capabilities() (in module nifgen.Session), 271

query\_freq\_list\_capabilities() (in module nifgen.Session), 272

query\_in\_compliance() (in module nidcpower.Session), 104

query\_instrument\_status (in module nidcpower.Session), 74

query\_max\_current\_limit() (in module nidcpower.Session), 105

query\_max\_voltage\_level() (in module nidcpower.Session), 106

query\_min\_current\_limit() (in module nidcpower.Session), 106

query\_output\_state() (in module nidcpower.Session), 106

## R

R (nidmm.ThermocoupleType attribute), 185

RAMP\_DOWN (nifgen.Waveform attribute), 286

RAMP\_UP (nifgen.Waveform attribute), 286

range (in module nidmm.Session), 142

read() (in module nidmm.Session), 173

read() (in module niscopes.Session), 361

read\_current\_temperature() (in module nidcpower.Session), 107

read\_current\_temperature() (in module nifgen.Session), 273

read\_multi\_point() (in module nidmm.Session), 173

READ\_POINTER (niscopes.FetchRelativeTo attribute), 368

read\_status() (in module nidmm.Session), 174

read\_waveform() (in module nidmm.Session), 175

ready\_for\_advance\_event\_output\_terminal (in module niscopes.Session), 326

READY\_FOR\_PULSE\_TRIGGER (nidcpower.Event attribute), 116

ready\_for\_pulse\_trigger\_event\_output\_terminal (in module nidcpower.Session), 74

ready\_for\_pulse\_trigger\_event\_pulse\_polarity (in module nidcpower.Session), 75

ready\_for\_pulse\_trigger\_event\_pulse\_width (in module nidcpower.Session), 75

ready\_for\_ref\_event\_output\_terminal (in module niscopes.Session), 326

ready\_for\_start\_event\_output\_terminal (in module nifgen.Session), 239

ready\_for\_start\_event\_output\_terminal (in module niscopes.Session), 327

REARCONNECTOR (niswitch.ScanAdvancedOutput attribute), 419

REARCONNECTOR (niswitch.TriggerInput attribute), 422

REARCONNECTOR\_MODULE1 (niswitch.ScanAdvancedOutput attribute), 419

REARCONNECTOR\_MODULE1 (niswitch.TriggerInput attribute), 422

REARCONNECTOR\_MODULE10 (niswitch.ScanAdvancedOutput attribute), 420

REARCONNECTOR\_MODULE10 (niswitch.TriggerInput attribute), 422

REARCONNECTOR\_MODULE11 (niswitch.ScanAdvancedOutput attribute), 420

REARCONNECTOR\_MODULE11 (niswitch.TriggerInput attribute), 422

REARCONNECTOR\_MODULE12 (niswitch.ScanAdvancedOutput attribute), 420

REARCONNECTOR\_MODULE12 (niswitch.TriggerInput attribute), 422

REARCONNECTOR\_MODULE2 (niswitch.ScanAdvancedOutput attribute), 419

REARCONNECTOR\_MODULE2 (niswitch.TriggerInput attribute), 422

REARCONNECTOR\_MODULE3 (niswitch.ScanAdvancedOutput attribute), 419

REARCONNECTOR\_MODULE3 (niswitch.TriggerInput attribute), 422

REARCONNECTOR\_MODULE4 (niswitch.ScanAdvancedOutput attribute), 419

REARCONNECTOR\_MODULE4 (niswitch.TriggerInput attribute), 422

REARCONNECTOR\_MODULE5 (niswitch.ScanAdvancedOutput attribute), 419

REARCONNECTOR\_MODULE5 (niswitch.TriggerInput attribute), 422

**REARCONNECTOR\_MODULE6**  
 (niswitch.ScanAdvancedOutput attribute), 419  
**REARCONNECTOR\_MODULE6**  
 (niswitch.TriggerInput attribute), 422  
**REARCONNECTOR\_MODULE7**  
 (niswitch.ScanAdvancedOutput attribute), 419  
**REARCONNECTOR\_MODULE7**  
 (niswitch.TriggerInput attribute), 422  
**REARCONNECTOR\_MODULE8**  
 (niswitch.ScanAdvancedOutput attribute), 420  
**REARCONNECTOR\_MODULE8**  
 (niswitch.TriggerInput attribute), 422  
**REARCONNECTOR\_MODULE9**  
 (niswitch.ScanAdvancedOutput attribute), 420  
**REARCONNECTOR\_MODULE9**  
 (niswitch.TriggerInput attribute), 422  
 record\_arm\_source (in module niscopes.Session), 328  
 records\_done (in module niscopes.Session), 327  
 ref\_clk\_rate (in module niscopes.Session), 328  
 ref\_clock\_frequency (in module nifgen.Session), 240  
 ref\_trig\_tdc\_enable (in module niscopes.Session), 329  
 ref\_trigger\_detector\_location (in module niscopes.Session), 328  
 ref\_trigger\_minimum\_quiet\_time (in module niscopes.Session), 329  
**REFERENCE** (niscopes.WhichTrigger attribute), 373  
 reference\_clock\_source (in module nifgen.Session), 239  
 ReferenceClockSource (class in nifgen), 282  
 RefTriggerDetectorLocation (class in niscopes), 369  
 RelativeTo (class in nifgen), 283  
 relay\_control() (in module niswitch.Session), 412  
 RelayAction (class in niswitch), 418  
 RelayPosition (class in niswitch), 418  
**REMOTE** (nidcpower.Sense attribute), 118  
 reset() (in module nidcpower.Session), 107  
 reset() (in module nidmm.Session), 175  
 reset() (in module nifgen.Session), 273  
 reset() (in module niscopes.Session), 362  
 reset() (in module niswitch.Session), 413  
 reset\_average\_before\_measurement (in module nidcpower.Session), 76  
 reset\_device() (in module nidcpower.Session), 107  
 reset\_device() (in module nifgen.Session), 273  
 reset\_device() (in module niscopes.Session), 362  
 reset\_with\_defaults() (in module nidcpower.Session), 108  
 reset\_with\_defaults() (in module nidmm.Session), 176  
 reset\_with\_defaults() (in module nifgen.Session), 273  
 reset\_with\_defaults() (in module niscopes.Session), 362  
 reset\_with\_defaults() (in module niswitch.Session), 413  
 resolution (in module niscopes.Session), 330  
 resolution\_absolute (in module nidmm.Session), 143  
 resolution\_digits (in module nidmm.Session), 143  
**RESOURCE\_IN\_USE** (niswitch.PathCapability attribute), 418  
**RESTORE\_EXTERNAL\_CALIBRATION** (niscopes.Option attribute), 369  
 ris\_in\_auto\_setup\_enable (in module niscopes.Session), 330  
 ris\_method (in module niscopes.Session), 331  
 ris\_num\_averages (in module niscopes.Session), 331  
**RISING** (nifgen.ScriptTriggerDigitalEdgeEdge attribute), 284  
**RISING** (nifgen.StartTriggerDigitalEdgeEdge attribute), 284  
**RISING** (niswitch.ScanAdvancedPolarity attribute), 420  
**RISING** (niswitch.TriggerInputPolarity attribute), 423  
 RISMmethod (class in niscopes), 369  
 route\_scan\_advanced\_output() (in module niswitch.Session), 413  
 route\_trigger\_input() (in module niswitch.Session), 414  
**RTDType** (class in nidmm), 183  
**RTSI\_7** (nifgen.ReferenceClockSource attribute), 283  
**RUNNING** (nidmm.AcquisitionStatus attribute), 179  
**RUNNING** (nifgen.HardwareState attribute), 282

## S

**S** (nidmm.ThermocoupleType attribute), 185  
 samp\_clk\_timebase\_div (in module niscopes.Session), 332  
 samp\_clk\_timebase\_rate (in module niscopes.Session), 333  
 samp\_clk\_timebase\_src (in module niscopes.Session), 333  
 sample\_clock\_source (in module nifgen.Session), 240  
 sample\_clock\_timebase\_multiplier (in module niscopes.Session), 331  
 sample\_clock\_timebase\_rate (in module nifgen.Session), 241  
 sample\_clock\_timebase\_source (in module nifgen.Session), 241  
 sample\_count (in module nidmm.Session), 144  
 sample\_interval (in module nidmm.Session), 144  
 sample\_mode (in module niscopes.Session), 332  
 sample\_trigger (in module nidmm.Session), 144  
 SampleClockSource (class in nifgen), 283  
 SampleClockTimebaseSource (class in nifgen), 284  
 samples\_to\_average (in module nidcpower.Session), 76  
 SampleTrigger (class in nidmm), 183  
 scan\_advanced\_output (in module niswitch.Session), 400  
 scan\_advanced\_polarity (in module niswitch.Session), 400  
 scan\_delay (in module niswitch.Session), 400  
 scan\_list (in module niswitch.Session), 401  
 scan\_mode (in module niswitch.Session), 401  
 ScanAdvancedOutput (class in niswitch), 419  
 ScanAdvancedPolarity (class in niswitch), 420

- ScanMode (class in niswitch), 421  
SCRIPT (nifgen.OutputMode attribute), 282  
script\_to\_generate (in module nifgen.Session), 242  
script\_trigger\_type (in module nifgen.Session), 243  
script\_triggers\_count (in module nifgen.Session), 242  
ScriptTriggerDigitalEdgeEdge (class in nifgen), 284  
ScriptTriggerType (class in nifgen), 284  
SECAM (niscope.VideoSignalFormat attribute), 372  
SECOND\_ORDER (nidcpower.DCNoiseRejection attribute), 115  
SECOND\_ORDER (nidmm.DCNoiseRejection attribute), 181  
SECONDS (nidcpower.ApertureTimeUnits attribute), 115  
SECONDS (nidmm.ApertureTimeUnits attribute), 180  
self\_cal() (in module nidcpower.Session), 108  
self\_cal() (in module nidmm.Session), 176  
self\_cal() (in module nifgen.Session), 274  
self\_cal() (in module niscopes.Session), 363  
SELF\_CALIBRATE\_ALL\_CHANNELS (niscope.Option attribute), 368  
self\_calibration\_persistence (in module nidcpower.Session), 77  
self\_test() (in module nidcpower.Session), 108  
self\_test() (in module nidmm.Session), 176  
self\_test() (in module nifgen.Session), 274  
self\_test() (in module niscopes.Session), 363  
self\_test() (in module niswitch.Session), 414  
SelfCalibrationPersistence (class in nidcpower), 118  
SelfTestError, 120, 187, 287, 374, 424, 434  
send\_software\_edge\_trigger() (in module nidcpower.Session), 109  
send\_software\_edge\_trigger() (in module nifgen.Session), 274  
send\_software\_trigger() (in module nidmm.Session), 176  
send\_software\_trigger() (in module niswitch.Session), 414  
send\_software\_trigger\_edge() (in module niscopes.Session), 364  
SendSoftwareEdgeTriggerType (class in nidcpower), 118  
Sense (class in nidcpower), 118  
sense (in module nidcpower.Session), 78  
SEQ (nifgen.OutputMode attribute), 282  
SEQUENCE (nidcpower.SourceMode attribute), 118  
SEQUENCE\_ADVANCE (nidcpower.SendSoftwareEdgeTriggerType attribute), 118  
sequence\_advance\_trigger\_type (in module nidcpower.Session), 78  
SEQUENCE\_ENGINE\_DONE (nidcpower.Event attribute), 116  
sequence\_engine\_done\_event\_output\_terminal (in module nidcpower.Session), 79  
sequence\_engine\_done\_event\_pulse\_polarity (in module nidcpower.Session), 79  
sequence\_engine\_done\_event\_pulse\_width (in module nidcpower.Session), 80  
SEQUENCE\_ITERATION\_COMPLETE (nidcpower.Event attribute), 116  
sequence\_iteration\_complete\_event\_output\_terminal (in module nidcpower.Session), 80  
sequence\_iteration\_complete\_event\_pulse\_polarity (in module nidcpower.Session), 81  
sequence\_iteration\_complete\_event\_pulse\_width (in module nidcpower.Session), 81  
sequence\_loop\_count (in module nidcpower.Session), 82  
sequence\_loop\_count\_is\_finite (in module nidcpower.Session), 83  
serial\_number (in module nidmm.Session), 145  
serial\_number (in module nifgen.Session), 243  
serial\_number (in module nimodinst.Session), 431  
serial\_number (in module niscopes.Session), 334  
serial\_number (in module niswitch.Session), 402  
SERIES (nidmm.LCCalculationModel attribute), 182  
Session (class in nidcpower), 14  
Session (class in nidmm), 123  
Session (class in nifgen), 191  
Session (class in nimodinst), 428  
Session (class in niscopes), 293  
Session (class in niswitch), 379  
set\_next\_write\_position() (in module nifgen.Session), 275  
set\_path() (in module niswitch.Session), 415  
set\_sequence() (in module nidcpower.Session), 109  
settle\_time (in module nidmm.Session), 145  
settling\_time (in module niswitch.Session), 402  
SHORT (nidmm.CableCompensationType attribute), 180  
short\_cable\_comp\_reactance (in module nidmm.Session), 146  
short\_cable\_comp\_resistance (in module nidmm.Session), 146  
simulate (in module nidcpower.Session), 83  
simulate (in module nidmm.Session), 147  
simulate (in module nifgen.Session), 244  
simulate (in module niscopes.Session), 334  
simulate (in module niswitch.Session), 403  
SINE (nifgen.Waveform attribute), 286  
SINGLE (nifgen.TriggerMode attribute), 285  
SINGLE\_ENDED (nifgen.TerminalConfiguration attribute), 285  
SINGLE\_ENDED (niscopes.TerminalConfiguration attribute), 369  
SINGLE\_POINT (nidcpower.SourceMode attribute), 118  
SIXTEEN\_TAP\_HANNING (niscopes.FlexFIRAntialiasFilterType attribute), 368  
slot\_number (in module nimodinst.Session), 432

- SLOW (nidcpower.TransientResponse attribute), [119](#)
  - socket\_number (in module nimodinst.Session), [432](#)
  - SOFTWARE (niscope.TriggerType attribute), [371](#)
  - SOFTWARE\_EDGE (nidcpower.TriggerType attribute), [119](#)
  - SOFTWARE\_EDGE (nifgen.ScriptTriggerType attribute), [284](#)
  - SOFTWARE\_EDGE (nifgen.StartTriggerType attribute), [285](#)
  - SOFTWARE\_TRIG (nidmm.SampleTrigger attribute), [183](#)
  - SOFTWARE\_TRIG (nidmm.TriggerSource attribute), [185](#)
  - SOFTWARE\_TRIG (niswitch.TriggerInput attribute), [421](#)
  - SOURCE (nidcpower.SendSoftwareEdgeTriggerType attribute), [118](#)
  - SOURCE\_COMPLETE (nidcpower.Event attribute), [115](#)
  - source\_complete\_event\_output\_terminal (in module nidcpower.Session), [83](#)
  - source\_complete\_event\_pulse\_polarity (in module nidcpower.Session), [84](#)
  - source\_complete\_event\_pulse\_width (in module nidcpower.Session), [84](#)
  - SOURCE\_CONFLICT (niswitch.PathCapability attribute), [418](#)
  - source\_delay (in module nidcpower.Session), [85](#)
  - source\_mode (in module nidcpower.Session), [86](#)
  - source\_trigger\_type (in module nidcpower.Session), [86](#)
  - SourceMode (class in nidcpower), [118](#)
  - specific\_driver\_description (in module nidcpower.Session), [87](#)
  - specific\_driver\_description (in module nidmm.Session), [147](#)
  - specific\_driver\_description (in module nifgen.Session), [244](#)
  - specific\_driver\_description (in module niscope.Session), [335](#)
  - specific\_driver\_description (in module niswitch.Session), [404](#)
  - specific\_driver\_major\_version (in module nidmm.Session), [148](#)
  - specific\_driver\_minor\_version (in module nidmm.Session), [148](#)
  - specific\_driver\_prefix (in module nidcpower.Session), [87](#)
  - specific\_driver\_revision (in module nidcpower.Session), [87](#)
  - specific\_driver\_revision (in module nidmm.Session), [149](#)
  - specific\_driver\_revision (in module nifgen.Session), [244](#)
  - specific\_driver\_revision (in module niscope.Session), [335](#)
  - specific\_driver\_revision (in module niswitch.Session), [404](#)
  - specific\_driver\_vendor (in module nidcpower.Session), [88](#)
  - specific\_driver\_vendor (in module nidmm.Session), [149](#)
  - specific\_driver\_vendor (in module nifgen.Session), [245](#)
  - specific\_driver\_vendor (in module niscope.Session), [335](#)
  - specific\_driver\_vendor (in module niswitch.Session), [404](#)
  - SQUARE (nifgen.Waveform attribute), [286](#)
  - START (nidcpower.SendSoftwareEdgeTriggerType attribute), [118](#)
  - START (nifgen.RelativeTo attribute), [283](#)
  - START (niscope.FetchRelativeTo attribute), [368](#)
  - START (niscope.WhichTrigger attribute), [373](#)
  - start\_to\_ref\_trigger\_holdoff (in module niscope.Session), [336](#)
  - start\_trigger\_type (in module nidcpower.Session), [88](#)
  - start\_trigger\_type (in module nifgen.Session), [246](#)
  - started\_event\_output\_terminal (in module nifgen.Session), [245](#)
  - StartTriggerDigitalEdgeEdge (class in nifgen), [284](#)
  - StartTriggerType (class in nifgen), [284](#)
  - STATUS\_UNKNOWN (niscope.AcquisitionStatus attribute), [367](#)
  - STEPPED (nifgen.TriggerMode attribute), [285](#)
  - streaming\_space\_available\_in\_waveform (in module nifgen.Session), [246](#)
  - streaming\_waveform\_handle (in module nifgen.Session), [247](#)
  - streaming\_waveform\_name (in module nifgen.Session), [247](#)
  - streaming\_write\_timeout (in module nifgen.Session), [248](#)
  - supported\_instrument\_models (in module nidcpower.Session), [89](#)
  - supported\_instrument\_models (in module nidmm.Session), [149](#)
  - supported\_instrument\_models (in module nifgen.Session), [248](#)
  - supported\_instrument\_models (in module niscope.Session), [336](#)
  - supported\_instrument\_models (in module niswitch.Session), [405](#)
  - SWITCH (niswitch.HandshakingInitiation attribute), [418](#)
  - SYMMETRIC (nidcpower.ComplianceLimitSymmetry attribute), [115](#)
- ## T
- T (nidmm.ThermocoupleType attribute), [185](#)
  - temp\_rtd\_a (in module nidmm.Session), [150](#)
  - temp\_rtd\_b (in module nidmm.Session), [150](#)
  - temp\_rtd\_c (in module nidmm.Session), [151](#)
  - temp\_rtd\_res (in module nidmm.Session), [151](#)
  - temp\_rtd\_type (in module nidmm.Session), [152](#)
  - temp\_tc\_fixed\_ref\_junc (in module nidmm.Session), [152](#)
  - temp\_tc\_ref\_junc\_type (in module nidmm.Session), [152](#)
  - temp\_tc\_type (in module nidmm.Session), [153](#)
  - temp\_thermistor\_a (in module nidmm.Session), [153](#)
  - temp\_thermistor\_b (in module nidmm.Session), [154](#)



- ul style="list-style-type: none; padding-left: 0;">
- temp\_thermistor\_c (in module nidmm.Session), 154
- temp\_thermistor\_type (in module nidmm.Session), 155
- temp\_transducer\_type (in module nidmm.Session), 155
- temperature (in module niswitch.Session), 405
- TEMPERATURE (nidmm.Function attribute), 181
- terminal\_configuration (in module nifgen.Session), 248
- TerminalConfiguration (class in nifgen), 285
- TerminalConfiguration (class in niscopes), 369
- THERMISTOR (nidmm.TransducerType attribute), 185
- THERMISTOR\_44004 (nidmm.ThermistorType attribute), 184
- THERMISTOR\_44006 (nidmm.ThermistorType attribute), 184
- THERMISTOR\_44007 (nidmm.ThermistorType attribute), 184
- ThermistorType (class in nidmm), 184
- THERMOCOUPLE (nidmm.TransducerType attribute), 185
- ThermocoupleReferenceJunctionType (class in nidmm), 184
- ThermocoupleType (class in nidmm), 184
- TransducerType (class in nidmm), 185
- transient\_response (in module nidcpower.Session), 89
- TransientResponse (class in nidcpower), 119
- TRIANGLE (nifgen.Waveform attribute), 286
- TRIG\_NONE (nifgen.ScriptTriggerType attribute), 284
- TRIG\_NONE (nifgen.StartTriggerType attribute), 284
- TRIGGER (niscopes.FetchRelativeTo attribute), 368
- trigger\_auto\_triggered (in module niscopes.Session), 337
- trigger\_count (in module nidmm.Session), 156
- trigger\_coupling (in module niscopes.Session), 337
- trigger\_delay (in module nidmm.Session), 156
- trigger\_delay\_time (in module niscopes.Session), 338
- trigger\_holdoff (in module niscopes.Session), 338
- trigger\_hysteresis (in module niscopes.Session), 338
- trigger\_impedance (in module niscopes.Session), 339
- trigger\_input (in module niswitch.Session), 406
- trigger\_input\_polarity (in module niswitch.Session), 406
- trigger\_level (in module niscopes.Session), 339
- trigger\_mode (in module nifgen.Session), 249
- trigger\_modifier (in module niscopes.Session), 340
- trigger\_slope (in module niscopes.Session), 340
- trigger\_source (in module nidmm.Session), 157
- trigger\_source (in module niscopes.Session), 341
- trigger\_type (in module niscopes.Session), 341
- trigger\_window\_high\_level (in module niscopes.Session), 341
- trigger\_window\_low\_level (in module niscopes.Session), 342
- trigger\_window\_mode (in module niscopes.Session), 343
- TriggerCoupling (class in niscopes), 370
- TriggerInput (class in niswitch), 421
- TriggerInputPolarity (class in niswitch), 423
- TriggerMode (class in nifgen), 285
- TriggerModifier (class in niscopes), 370
- TriggerSlope (class in niscopes), 370
- TriggerSource (class in nidmm), 185
- TriggerType (class in nidcpower), 119
- TriggerType (class in niscopes), 370
- TriggerWindowMode (class in niscopes), 371
- TTL0 (niswitch.ScanAdvancedOutput attribute), 419
- TTL0 (niswitch.TriggerInput attribute), 421
- TTL1 (niswitch.ScanAdvancedOutput attribute), 419
- TTL1 (niswitch.TriggerInput attribute), 421
- TTL2 (niswitch.ScanAdvancedOutput attribute), 419
- TTL2 (niswitch.TriggerInput attribute), 421
- TTL3 (niswitch.ScanAdvancedOutput attribute), 419
- TTL3 (niswitch.TriggerInput attribute), 421
- TTL4 (niswitch.ScanAdvancedOutput attribute), 419
- TTL4 (niswitch.TriggerInput attribute), 421
- TTL5 (niswitch.ScanAdvancedOutput attribute), 419
- TTL5 (niswitch.TriggerInput attribute), 421
- TTL6 (niswitch.ScanAdvancedOutput attribute), 419
- TTL6 (niswitch.TriggerInput attribute), 421
- TTL7 (niswitch.ScanAdvancedOutput attribute), 419
- TTL7 (niswitch.TriggerInput attribute), 422
- TV (niscopes.TriggerType attribute), 370
- tv\_trigger\_event (in module niscopes.Session), 343
- tv\_trigger\_line\_number (in module niscopes.Session), 344
- tv\_trigger\_polarity (in module niscopes.Session), 344
- tv\_trigger\_signal\_format (in module niscopes.Session), 344
- TWO\_WIRE\_RES (nidmm.Function attribute), 181
- TWO\_WIRE\_RTD (nidmm.TransducerType attribute), 185
- ## U
- UNBALANCED\_DIFFERENTIAL (niscopes.TerminalConfiguration attribute), 369
  - unlock() (in module nidcpower.Session), 110
  - unlock() (in module nidmm.Session), 177
  - unlock() (in module nifgen.Session), 275
  - unlock() (in module niscopes.Session), 364
  - unlock() (in module niswitch.Session), 415
  - UnsupportedConfigurationError, 119, 186, 287, 373, 423, 433
  - USER (nifgen.Waveform attribute), 286
- ## V
- vertical\_coupling (in module niscopes.Session), 345
  - vertical\_offset (in module niscopes.Session), 346
  - vertical\_range (in module niscopes.Session), 346
  - VerticalCoupling (class in niscopes), 371
  - VIDEO\_1080I\_50\_FIELDS\_PER\_SECOND (niscopes.VideoSignalFormat attribute), 372
  - VIDEO\_1080I\_59\_94\_FIELDS\_PER\_SECOND (niscopes.VideoSignalFormat attribute), 372

[VIDEO\\_1080I\\_60\\_FIELDS\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_1080P\\_24\\_FRAMES\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_480I\\_59\\_94\\_FIELDS\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_480I\\_60\\_FIELDS\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_480P\\_59\\_94\\_FRAMES\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_480P\\_60\\_FRAMES\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_576I\\_50\\_FIELDS\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_576P\\_50\\_FRAMES\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_720P\\_50\\_FRAMES\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_720P\\_59\\_94\\_FRAMES\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VIDEO\\_720P\\_60\\_FRAMES\\_PER\\_SECOND](#) (niscope.VideoSignalFormat attribute), [372](#)  
[VideoPolarity](#) (class in niscopescope), [371](#)  
[VideoSignalFormat](#) (class in niscopescope), [372](#)  
[VideoTriggerEvent](#) (class in niscopescope), [373](#)  
[VOLTAGE](#) (nidcpower.MeasurementTypes attribute), [116](#)  
[VOLTAGE](#) (nidcpower.OutputStates attribute), [117](#)  
[voltage\\_compensation\\_frequency](#) (in module nidcpower.Session), [90](#)  
[voltage\\_gain\\_bandwidth](#) (in module nidcpower.Session), [91](#)  
[voltage\\_level](#) (in module nidcpower.Session), [91](#)  
[voltage\\_level\\_autorange](#) (in module nidcpower.Session), [92](#)  
[voltage\\_level\\_range](#) (in module nidcpower.Session), [93](#)  
[voltage\\_limit](#) (in module nidcpower.Session), [93](#)  
[voltage\\_limit\\_autorange](#) (in module nidcpower.Session), [94](#)  
[voltage\\_limit\\_high](#) (in module nidcpower.Session), [95](#)  
[voltage\\_limit\\_low](#) (in module nidcpower.Session), [96](#)  
[voltage\\_limit\\_range](#) (in module nidcpower.Session), [97](#)  
[voltage\\_pole\\_zero\\_ratio](#) (in module nidcpower.Session), [98](#)  
[VXI](#) (nifgen.BusType attribute), [281](#)

## W

[wait\\_behavior](#) (in module nifgen.Session), [249](#)  
[wait\\_for\\_debounce\(\)](#) (in module niswitch.Session), [415](#)  
[wait\\_for\\_event\(\)](#) (in module nidcpower.Session), [110](#)  
[wait\\_for\\_scan\\_complete\(\)](#) (in module niswitch.Session), [415](#)  
[wait\\_until\\_done\(\)](#) (in module nifgen.Session), [275](#)  
[wait\\_value](#) (in module nifgen.Session), [250](#)  
[WaitBehavior](#) (class in nifgen), [286](#)

[WAITING\\_FOR\\_START\\_TRIGGER](#) (nifgen.HardwareState attribute), [282](#)  
[Waveform](#) (class in nifgen), [286](#)  
[WAVEFORM](#) (nidmm.OperationMode attribute), [183](#)  
[waveform\\_coupling](#) (in module nidmm.Session), [157](#)  
[WAVEFORM\\_CURRENT](#) (nidmm.Function attribute), [181](#)  
[waveform\\_points](#) (in module nidmm.Session), [158](#)  
[waveform\\_quantum](#) (in module nifgen.Session), [250](#)  
[waveform\\_rate](#) (in module nidmm.Session), [158](#)  
[WAVEFORM\\_VOLTAGE](#) (nidmm.Function attribute), [181](#)  
[WaveformCoupling](#) (class in nidmm), [186](#)  
[WhichTrigger](#) (class in niscopescope), [373](#)  
[WINDOW](#) (niscopescope.TriggerType attribute), [371](#)  
[wire\\_mode](#) (in module niswitch.Session), [406](#)  
[write\\_script\(\)](#) (in module nifgen.Session), [276](#)  
[WRITE\\_TO\\_EEPROM](#) (nidcpower.SelfCalibrationPersistence attribute), [118](#)  
[write\\_waveform\(\)](#) (in module nifgen.Session), [276](#)